



Meltdown and Spectre side channel attacks security vulnerability fix add-on

Release Notes

Software releases are created to correct defects, make enhancements, or add new features. These releases are tested on all current, actively shipping platforms and operating systems as applicable. This release notes contain details on the supported platforms, any changes in the configuration settings and licensing details as well. The bug fixes along with the workarounds are documented in the release notes. Any changes in the feature functionality from an end-user perspective are listed with the description of each feature at a high level.

Release Date: Feb 2018

Contents

Release type and definition	1
Supported platforms.....	1
Add-on package information.....	2
Known issues.....	2
Support matrix.....	2
Installing add-on using Wyse Management Suite.....	3
Installing add-on manually using ThinLinux.....	3
Installing add-on manually using ThinLinux INI parameter.....	4
Installing add-on using Wyse Device Manager	4

Release type and definition

Dell Wyse Device Manager (WDM) software is the premier enterprise solution for managing Dell Wyse thin and zero clients simply, remotely, and securely. It enables IT professionals to easily organize, upgrade, control, and support thousands of Windows Embedded, ThinLinux, Wyse ThinOS, Wyse ThinOs Lite, and P-Class devices across any LAN, WAN, or wireless network.

The software uses industry standard communication protocols and a component-based architecture to efficiently manage your network devices. Its intuitive, simple and powerful user interface using WEB UI. Dell Wyse Device Manager (WDM) includes an easy-to-use console that enables you to easily perform all the device management functions that are required to run and maintain your WDM Environment. The Web UI is user friendly and enables you to perform all the device management functions easily.

Supported platforms

The add-on contains the operating system updates from SUSE to address the Meltdown and Spectre security vulnerabilities for the following platforms:

- Wyse 5060 thin client with ThinLinux

- Wyse 5020 thin client with ThinLinux—D50Q
- Wyse 7020 thin client with ThinLinux—Z50Q
- Wyse 3030 LT thin client with ThinLinux
- Wyse 3040 thin client with ThinLinux

After Installing the Intel Side Channel add-on, the kernel firmware package is updated to `Kernel-firmware-20170530-21.16.1.noarch`, and the kernel default package is updated to `kernel-default-4.4.103-92.56.1.x86_64` to support the fixes for the following security vulnerabilities:

- CVE-2017-5753
- CVE-2017-5715
- CVE-2017-5754

For more information about the security vulnerabilities, see Access.redhat.com

Add-on package information

Table 1. RPM add-on details

Build file name	<code>unified-addon-1.0.0-00.03.x86_64.rpm</code>
Size	81239359 bytes

Table 2. RSP add-on details

Build file name	<code>unified-addon-1.0.0-00.03.x86_64.zip</code>
Size	81242214 bytes

Known issues

Table 3. Known issues

Known issues	Workaround
LS-399 [Intel_SideChannel]—The installed kernel version is not updated on the system information page.	There is no workaround for the issue in this release.

Support matrix

Table 4. Support matrix

Platform name	Memory configuration (Flash/RAM)	Supported BIOS version	Supported build version for ThinLinux 1.0.x (English)	Build version after installing the add-on
Wyse 5060 thin client with ThinLinux	16 GB/4 GB	1.0G	1.0.6.2	1.0.6.3
Wyse 5020 thin client with ThinLinux—D50Q	8 GB/2 GB	2.0F	1.0.6.2	1.0.6.3
Wyse 7020 thin client with ThinLinux—Z50Q	8 GB/2 GB	2.0F	1.0.6.2	1.0.6.3

Platform name	Memory configuration (Flash/RAM)	Supported BIOS version	Supported build version for ThinLinux 1.0.x (English)	Build version after installing the add-on
Wyse 3030 LT thin client with ThinLinux	4 GB/2 GB	1.0F	1.0.6.2	1.0.6.3
Wyse 3040 thin client with ThinLinux	16 GB/2 GB	1.2.3	1.0.4.1/1.0.4.2	1.0.4.3/1.0.4.4

Installing add-on using Wyse Management Suite

- 1 Go to [Dell Wyse support](#).
- 2 Expand **Download Wyse Software and Driver**.
- 3 Click **Wyse Support Download**.
- 4 From the **Active** drop-down list, select your thin client model, and click **Search**.
The **Downloads** page is displayed.
- 5 Download the respective RPM or RSP file, and copy the files to the following path:
 - RPM file—C:\WMS\LocalRepo\repository\thinClientApps.
 - RSP file—C:\WMS\Local Repo\repository\rspPackages\zipped. The compress folder is extracted automatically, and the extracted files are copied to C:\WMS\LocalRepo\repository\rspPackages\valid path.
- 6 Log in to Wyse Management Suite.
- 7 Click **Portal Administration**, and then click **File Repository** under **Console Settings**.
- 8 Select the **Local Repository** check box.
- 9 Click **Sync Files**.
Wait for the synchronization process to complete. The synchronization process copies the package from the repository to **Apps and Data**.
- 10 Click **Apps and Data**.
The **Apps and Data** page is displayed.
- 11 Verify the copied package in the applications list.
- 12 To create a group in the Wyse Management Suite server, click **Groups & Configs**.
The **Groups & Configs** page is displayed.
- 13 Click the **Plus sign (+)** button, and register your client in the same group.
- 14 Click **Apps and Data**.
The **Apps and Data** page is displayed.
- 15 Click **Thin Clients** under **App Policies**.
- 16 Click **Add Policy** to add the policy to the required group.
- 17 Update the required fields, and then click **Save**.
The policy is added to the required group.
- 18 Click **Jobs**.
The **Jobs** page is displayed.
- 19 Click **Schedule App Policy** and update the required fields to schedule the policy.
- 20 Monitor the status in the **Jobs** page to ensure that the package installation is successful.

NOTE: The lock screen is displayed during the package installation process on all the thin clients.

Installing add-on manually using ThinLinux

- 1 Copy the add-on and the directory file to the <root path>\add-ons folder.
- 2 Log in to the thin client.

- 3 To enter into the **Admin mode**, click the **Switch to Admin** button.
- 4 Enter the default password.
The default password is admin.
- 5 Click the **Settings** icon on the desktop.
The **System Settings** page is displayed.
- 6 Click the **System** icon.
- 7 Click **Update settings**.
- 8 To enable the **Set update server manually** option, click the **ON/OFF** button.
- 9 Enter the URL address of the specified server in the **Update Server URL** box.
You can also enter the user name and password of the specified server in the **Update Server User Name** and **Update Server Password** box.
- 10 Click **Addons**.
- 11 Click the **Plus sign (+)** button, to install the add-ons.
- 12 Select the add-ons.
- 13 Click **Save**.
The add-on is installed on the thin client.

Installing add-on manually using ThinLinux INI parameter

- 1 Copy the add-on and the directory file to the <root path>\add-ons folder.
- 2 To install the add-on add the following INI parameter:
`InstallAddons=unified_addon-1.0.0-00.03.x86_64.rpm` in `wlx.ini`.
- 3 Log in to the thin client.
- 4 To enter into the **Admin mode**, click the **Switch to Admin** button.
- 5 Enter the default password.
The default password is admin.
- 6 Click the **Settings** icon on the desktop.
The **System Settings** page is displayed.
- 7 Click the **Management** icon.
- 8 Click **INI**.
The **Manage INI Configuration** page is displayed.
- 9 From the drop-down list, select the configuration source and provide the server details.
- 10 Click **Save**.
The following message is displayed:
System Upgradation complete. Machine will reboot now. Count down timer starts with 10 sec.
- 11 Click **OK**.
The add-on is installed on the thin client and the system restarts.

Installing add-on using Wyse Device Manager

NOTE: Copy the <name of the add-on>.rsp file to the Wyse Device Manager server. The copied RSP file is included in the .zip file.

- 1 Launch Wyse Device Manager and login using valid credentials.
- 2 Click **Applications** in the **Dell Wyse Device Manager dashboard** page.
The options **Images**, **Other Packages**, **Agent Update**, **Device Configuration**, and **PCoIP Device Configuration** are displayed.
- 3 Select one of the options except **Device Configuration**, and **PCoIP Device Configuration**.
- 4 Click **Create Package Plus (+)**.
- 4 Meltdown and Spectre side channel attacks security vulnerability fix add-on
Release Notes

The application prompts to download the Package Register utility.

- 5 Click **Allow**.
The **Create Package** window is displayed.
- 6 Download the .zip file on your local repository.
- 7 Navigate to the folder, and run the **Package Register** utility file.
The **WDM Package Registration Utility** window is displayed.
- 8 Enter WDM server address and user credentials in the respective fields.
- 9 Select **RSP** to register, and click **Browse**.
The **WDM Package Uploader** window is displayed.
- 10 Click **Open**.
The list of selected packages is displayed.
- 11 Select the packages that you want to register, and click **Upload**.
The status is displayed as **Success**.
- 12 Click **Devices** and select the **Device ID** check box.
- 13 Click **Update**, and select the preferred package.
- 14 Click **Save**.
The add-ons installation is scheduled to the device and the add-on is installed to the thin client.