


53-1002749-01  
14 December 2012



# Fabric OS

---

## Message Reference

Supporting Fabric OS v7.1.0

**BROCADE**

Copyright © 2002-2012 Brocade Communications Systems, Inc. All Rights Reserved.

Brocade, Brocade Assurance, the B-wing symbol, BigIron, DCX, Fabric OS, FastIron, MLX, NetIron, SAN Health, ServerIron, TurboIron, VCS, and VDX are registered trademarks, and AnyIO, Brocade One, CloudPlex, Effortless Networking, ICX, NET Health, OpenScript, and The Effortless Network are trademarks of Brocade Communications Systems, Inc., in the United States and/or in other countries. Other brands, products, or service names mentioned may be trademarks of their respective owners.

Notice: This document is for informational purposes only and does not set forth any warranty, expressed or implied, concerning any equipment, equipment feature, or service offered or to be offered by Brocade. Brocade reserves the right to make changes to this document at any time, without notice, and assumes no responsibility for its use. This informational document describes features that may not be currently available. Contact a Brocade sales office for information on feature and product availability. Export of technical data contained in this document may require an export license from the United States government.

The authors and Brocade Communications Systems, Inc. shall have no liability or responsibility to any person or entity with respect to any loss, cost, liability, or damages arising from the information contained in this book or the computer programs that accompany it.

The product described by this document may contain "open source" software covered by the GNU General Public License or other open source license agreements. To find-out which open source software is included in Brocade products, view the licensing terms applicable to the open source software, and obtain a copy of the programming source code, please visit <http://www.brocade.com/support/oscd>.

## Brocade Communications Systems, Incorporated

Corporate and Latin American Headquarters  
Brocade Communications Systems, Inc.  
130 Holger Way  
San Jose, CA 95134  
Tel: 1-408-333-8000  
Fax: 1-408-333-8101  
E-mail: [info@brocade.com](mailto:info@brocade.com)

Asia-Pacific Headquarters  
Brocade Communications Systems China HK, Ltd.  
No. 1 Guanghua Road  
Chao Yang District  
Units 2718 and 2818  
Beijing 100020, China  
Tel: +8610 6588 8888  
Fax: +8610 6588 9999  
E-mail: [china-info@brocade.com](mailto:china-info@brocade.com)

European Headquarters  
Brocade Communications Switzerland Sàrl  
Centre Swissair  
Tour B - 4ème étage  
29, Route de l'Aéroport  
Case Postale 105  
CH-1215 Genève 15  
Switzerland  
Tel: +41 22 799 5640  
Fax: +41 22 799 5641  
E-mail: [emea-info@brocade.com](mailto:emea-info@brocade.com)

Asia-Pacific Headquarters  
Brocade Communications Systems Co., Ltd. (Shenzhen WFOE)  
Citic Plaza  
No. 233 Tian He Road North  
Unit 1308 - 13th Floor  
Guangzhou, China  
Tel: +8620 3891 2000  
Fax: +8620 3891 2111  
E-mail: [china-info@brocade.com](mailto:china-info@brocade.com)

## Document History

Title	Publication number	Summary of changes	Date
Diagnostic and System Error Message Reference v3.0, v4.0	53-0000210-02	First release	March 2002
Diagnostic and System Error Message Reference v3.1.0	53-0000511-04	Major content reorganization	June 2003
Diagnostic and System Error Message Reference v4.1.0	54-0000515-02	Major content reorganization	June 2003
Diagnostic and System Error Message Reference v4.1.2	53-0000515-06	Minor editorial changes	October 2003
Diagnostic and System Error Message Reference v4.2.0	53-0000515-07	Added FW and PLATFORM messages	December 2003
Diagnostic and System Error Message Reference v4.2.0	53-0000515-08	Updated software and hardware support	March 2004

Title	Publication number	Summary of changes	Date
Fabric OS System Error Message Reference Manual	53-0000515-09	Updated for v4.4.0, First RASLog release	August 2004
Fabric OS System Error Message Reference Manual	53-0000515-10	Added 22 ZONE messages	April 2005
Fabric OS System Error Message Reference Manual	53-0000515-11	Added FICU-1010, HAMK-1004, and PLAT-1001	July 2005
Fabric OS System Error Message Reference Manual	53-1000046-01	Added BM, FCR, IPS, FCIP, SEC, and ZONE messages	January 2006
Fabric OS System Error Message Reference Manual	53-1000046-02	Minor updates to a few messages.	June 2006
Fabric OS Message Reference	53-1000242-01	Updated for Fabric OS v5.2.0: -Changed doc title and number -Added the following new modules: IBPD, ICPD, ISCSI, ISNSCD. Added Audit messages: AUTH, CONF, HTTP, SEC, SNMP, SULB, ZONE. -Updated Introduction chapter with AUDIT log information. -Updated chapter titles.	September 2006
Fabric OS Message Reference	53-1000437-01	Updated for Fabric OS v5.3.0: -Added new chapters: AG, BKSW, IBD, IPAD, SAS. Revised and added new messages to: AUTH, CDR, CONF, EM, FABR, HAM, ISNS, ISW, PDM, SEC, TS, KTRC, SEC, TS. Revised/updated BL, BLL, FCPD, FICU, FW, HIL, LOG, SNMP, SULB, SWCH, SYSM, TRCE, ZOLB, ZONE. -Deleted USWD chapter. -Updated Introductory chapters. -Updated throughout: rebranding, supported hardware, CLI changes.	June 2007
Fabric OS Message Reference	53-1000600-01	Updated for Fabric OS v6.0.0: -Added new chapters: C2, ESS, FICON -Added new messages to: AG, BL, BM, C2, FCIP, ISW, NS, PLAT, SS, HIL. -Added Audit messages: SEC, SULB -Updated Introductory chapters.	October 2007
Fabric OS Message Reference	53-1000600-02	Updated for Fabric OS v6.1.0: -Revised and added new messages to: AG, BL, C2, EM, FABR, FCR, FCIP, FW, SEC, NS, PDM, PLAT, SULB, SWCH, ZONE, WEBD. -Added new Audit chapter: FW. -Added new Audit messages to: SEC. -Updated Introductory chapters.	Jun 2008
Fabric OS Message Reference	53-1001116-01	Updated for Fabric OS v6.1.1_enc: -Revised and added new messages to AG -Added new chapters: CNM, CTAP, CVLC, CVLM, KAC, RKD, SPC, SPM. -Added new Audit chapters: AG, FCIP, FICU, IPAD, PORT, SWCH, UCST. -Updated Introductory chapters.	Aug 2008

Title	Publication number	Summary of changes	Date
Fabric OS Message Reference	53-1001157-01	Updated for Fabric OS v6.2.0: -Revised and added new messages to FSS, KSWD, CTAP, CNM, CVLM, EM, FABR, FCIP, FW, HIL, FCR, SEC, SWCH, UCST, ZONE. -Added new chapters: CHASSIS, LFM, PMGR, TAPE. -Updated Introductory chapters.	November 2008
Fabric OS Message Reference	53-1001338-01	Updated for Fabric OS v6.3.0: -Modified a message to BKSW, BL, BKSW, BLL, CDR, CEE CONFIG, CONF, EM, FCOE, FCPD, FCPH, FCR, FICON, FICU, FLOD, FSPF, FSSM, FW, HAM,,HAMK, HIL, IPS, ISNS, L2SYS, MFIC, PDM, PLAT, PORT, RCS, RPCD, RTWR, SEC, SNMP, SWCH, TRCE, TRCK, WEBD, ZONE. -Added new messages to AG, AN, AUTH, BLS, C2, CDR, CEE, CONFIG, CHASSIS, CNM, CONF, CTAP, CVLC, CVLM, DAUTH, EM, FABR, FCIP, FCPH, FCR, FICON, FICU, FSPF, FSS, FW, HAM, HSL, KAC, KSWD, LANCE, LFM, MS, NS, NSM, PMGR, PORT, PSWP, RKD, SEC, SPC, SPM, SS, SULB, SWCH, TAPE, UCST, UPTH, XTUN, ZONE. -Added new chapters for LANCE, BLS, AN, CVLM, DAUTH, XTUN. -Updated Introductory chapters.	July 2009
Fabric OS Message Reference	53-1001338-02	Updated for Fabric OS v6.3.0 patch: -Modified a message to BL. -Added new messages to AG, BL, and FCOE. -Added new chapters for Audit CNM, Audit CVLM, and Audit SPM.	November 2009
Fabric OS Message Reference	53-1001767-01	Updated for Fabric OS v6.4.0: -Modified messages to FICU and FW. -Deleted messages to BL, FCOE and FW. -Added new messages to AG, AN, AUTH, BL, C2, CNM, CONF, CVLC, CVLM, FABR, FICU, FW, HAM, HIL, MQ, MS, MSTP, NS, NSM, ONM, PS, PSWP, RKD, SEC, SPM, SS, SSM, SULB, SWCH and ZONE. -Updated Introductory chapters.	March 2010



Title	Publication number	Summary of changes	Date
Fabric OS Message Reference	53-1002149-01	<p>Updated for Fabric OS v7.0.0:</p> <ul style="list-style-type: none"> <li>-Added new chapters: C3, CAL, MCAST_SS, RTE, and VS.</li> <li>-Added new messages: AG, AN, ANV, BL, C2, CDR, CCFG, ECC, EM, ESS, FABR, FCOE, FCPH, FICN, FICU, FSPF, FW, HIL, IPAD, IPS, KAC, L2SYS, LACP, LOG, MS, NS, NSM, ONM, PDM, PS, RAS, RCS, SCN, SEC, SNMP, SPM, SS, SSM, SULB, SWCH, XTUN, ZEUS, and ZONE.</li> <li>-Modified messages: CDR, EM, FABR, FCOE, FICU, FW, HIL, L2SYS, PMGR, SEC, SPM, SS, and XTUN.</li> <li>-Deleted messages: C2, FCOE, FICU, and NSM.</li> <li>-Added new Audit chapters: ESS, MS, PMGR, and RAS.</li> <li>-Updated Introductory chapter.</li> </ul>	April 2011
Fabric OS Message Reference	53-1002448-01	<p>Updated for Fabric OS v7.0.1:</p> <ul style="list-style-type: none"> <li>-Added new messages: BL, CVLC, FICON, FSPF, and PS</li> <li>-Modified messages: AG, AN, C2, C3, CDR, FABR, FSPF, L2SYS, NSM, RTE, and ZONE.</li> <li>-Deleted messages: EM, FABR, ISCS, SAS, and ZOLB.</li> <li>-Updated Introductory chapter.</li> </ul>	December 2011
Fabric OS Message Reference	53-1002749-01	<p>Updated for Fabric OS v7.1.0:</p> <ul style="list-style-type: none"> <li>- Added new chapters: MM and VDR.</li> <li>- Added new messages: AG, ANV, BL, C2, C3, CDR, CONF, CVLM, EM, FABR, FCR, FSPF, FW, HAM, HIL, KAC, LOG, MS, NBFS, PLAT, PS, RAS, SEC, SS, SWCH, TRCE, VDR, XTUN, ZEUS, and ZONE.</li> <li>- Modified messages: AN, AUTH, BL, C2, C3, CDR, CAL, CNM, DOT1, FABR, FCOE, FCPD, FCR, FICU, FSPF, FSS, HIL, HSL, HTTP, IPS, KTRC, L2SS, LFM, PMGR, PS, RCS, RTWR, SEC, ZONE.</li> <li>- Deleted messages: EM, FCOE, HAM, SNMP, SYSC, UCST, ZONE.</li> <li>- Deleted modules: BLL, CER, FCIP, IBPD, and ICPD.</li> <li>- Updated Introductory chapter.</li> </ul>	December 2012



# Contents

---

## About This Document

How this document is organized .....	xiii
Supported hardware and software .....	xiii
What's new in this document.....	xv
Document conventions.....	xvii
Text formatting.....	xvii
Command syntax conventions .....	xvii
Command examples .....	xviii
Notes, cautions, and warnings .....	xviii
Key terms .....	xix
Notice to the reader .....	xix
Additional information.....	xix
Brocade resources.....	xix
Other industry resources.....	xix
Getting technical help.....	xx
Document feedback .....	xxi

## Chapter 1 Introduction to System Messages

Overview of system messages .....	1
System message types .....	1
Message severity levels.....	3
System error message logging .....	4
Configuring the syslog message destinations.....	5
System logging daemon .....	5
System console .....	5
SNMP trap recipient.....	6
SNMP inform recipient.....	9
Port logs .....	11
Changing the severity level of swEventTrap .....	11
Commands for displaying and configuring the system message logs.....	13
Displaying message content on switch .....	14

Configuring system messages and attributes . . . . .	15
Configuring event auditing . . . . .	15
Disabling a RASLog message or module . . . . .	16
Enabling a RASLog message or module . . . . .	17
Setting the severity level of a RASLog message . . . . .	17
Displaying system message logs and attributes . . . . .	17
Displaying RASLog messages . . . . .	18
Displaying RASLog messages one message at a time . . . . .	18
Displaying Audit messages . . . . .	19
Displaying FFDC messages . . . . .	19
Displaying status of the system messages . . . . .	20
Displaying the severity level of RASLog messages . . . . .	20
Displaying RASLog messages by severity level . . . . .	21
Displaying RASLog messages by message ID . . . . .	21
Displaying messages on a slot . . . . .	21
Viewing RASLog messages from Web Tools . . . . .	22
Clearing the system message logs . . . . .	22
Clearing the system message log . . . . .	22
Clearing the Audit message log . . . . .	23
Reading the system messages . . . . .	23
Reading a RAS system message . . . . .	23
Reading an Audit message . . . . .	24
Responding to a system message . . . . .	26
Looking up a system message . . . . .	26
Gathering information about the problem . . . . .	26
Support . . . . .	27
System module descriptions . . . . .	28
<b>Chapter 2</b>	<b>Log Messages</b>
<b>Chapter 3</b>	<b>Audit Messages</b>
<b>Chapter 4</b>	<b>FFDC Messages</b>
<b>Chapter 5</b>	<b>Fabric OS System Messages</b>
AG Messages . . . . .	121
AN Messages . . . . .	136
ANV Messages . . . . .	140

AUTH Messages	144
BKSW Messages	162
BL Messages	163
BLS Messages	180
BM Messages	182
C2 Messages	187
C3 Messages	194
CAL Messages	202
CCFG Messages	203
CDR Messages	207
CHS Messages	214
CNM Messages	216
CONF Messages	239
CTAP Messages	244
CVLC Messages	245
CVLM Messages	258
DOT1 Messages	273
ECC Messages	277
EM Messages	278
ESS Messages	297
ESW Messages	300
EVMD Messages	303
FABR Messages	304
FABS Messages	321
FBC Messages	326
FCMC Messages	327
FCOE Messages	328
FCPD Messages	341
FCPH Messages	343
FCR Messages	345
FICN Messages	374
FICU Messages	418
FKLB Messages	425
FLOD Messages	426
FSPF Messages	428
FSS Messages	432
FSSM Messages	436

FW Messages .....	438
HAM Messages .....	541
HAMK Messages .....	546
HIL Messages .....	548
HLO Messages .....	565
HMON Messages .....	567
HSL Messages .....	568
HTTP Messages .....	571
IBD Messages .....	572
IPAD Messages .....	573
IPS Messages .....	575
ISNS Messages .....	578
KAC Messages .....	582
KSWD Messages .....	587
KTRC Messages .....	588
L2SS Messages .....	590
L3SS Messages .....	593
LACP Messages .....	594
LANCE Messages .....	595
LFM Messages .....	596
LOG Messages .....	598
LSDB Messages .....	602
MCAST_SS Messages .....	604
MFIC Messages .....	611
MM Messages .....	613
MPTH Messages .....	614
MQ Messages .....	615
MS Messages .....	617
MSTP Messages .....	624
NBFS Messages .....	627
NS Messages .....	629
NSM Messages .....	633
ONMD Messages .....	640
PDM Messages .....	642
PDTR Messages .....	650
PLAT Messages .....	651
PMGR Messages .....	653

PORT Messages .....	657
PS Messages .....	660
PSWP Messages .....	664
RAS Messages .....	667
RCS Messages .....	672
RKD Messages .....	677
RMON Messages .....	679
RPCD Messages .....	680
RTE Messages .....	683
RTWR Messages .....	684
SCN Messages .....	686
SEC Messages .....	688
SFLO Messages .....	771
SNMP Messages .....	774
SPC Messages .....	777
SPM Messages .....	790
SS Messages .....	805
SSMD Messages .....	810
SULB Messages .....	825
SWCH Messages .....	843
SYSC Messages .....	852
SYSM Messages .....	854
TAPE Messages .....	857
TRCE Messages .....	858
TRCK Messages .....	863
TS Messages .....	865
UCST Messages .....	868
UPTH Messages .....	871
VDR Messages .....	872
VS Messages .....	873
WEBD Messages .....	876
XTUN Messages .....	879
ZEUS Messages .....	889
ZONE Messages .....	892





# About This Document

---

## In this chapter

• How this document is organized .....	xiii
• Supported hardware and software.....	xiii
• What's new in this document.....	xv
• Document conventions .....	xvii
• Notice to the reader .....	xix
• Additional information.....	xix
• Getting technical help.....	xx
• Document feedback .....	xxi

## How this document is organized

This document is organized to help you find the information that you want as quickly and easily as possible.

The document contains the following components:

- [Chapter 1, “Introduction to System Messages”](#) provides basic information on system messages.
- [Chapter 2, “Log Messages”](#) includes a lookup list for LOG messages.
- [Chapter 3, “Audit Messages”](#) includes a lookup list for Audit messages.
- [Chapter 4, “FFDC Messages”](#) includes a lookup list for FFDC messages.
- [Chapter 5, “Fabric OS System Messages”](#) provides message text, probable cause, recommended action, and severity for each of the messages.

## Supported hardware and software

In those instances in which procedures or parts of procedures documented here apply to some switches but not to others, this guide identifies exactly which switches are supported and which are not.

Although many different software and hardware configurations are tested and supported by Brocade Communications Systems, Inc. for Fabric OS v7.1.0, documenting all possible configurations and scenarios is beyond the scope of this document.

The following hardware platforms are supported by this release of Fabric OS:

- Brocade 300
- Brocade 5100
- Brocade 5300
- Brocade 5410
- Brocade 5424
- Brocade 5430
- Brocade 5450
- Brocade 5460
- Brocade 5470
- Brocade 5480
- Brocade 6505
- Brocade 6510
- Brocade 6520
- Brocade 7800
- Brocade 8000
- Brocade Encryption Switch
- Brocade DCX Backbone and Brocade DCX-4S Backbone
  - FC8-16 port blade
  - FC8-32 port blade
  - FC8-48 port blade
  - FC8-64 port blade
  - FCOE10-24 DCX Blade
  - FS8-18 Encryption Blade
  - FX8-24 DCX Extension Blade
- Brocade DCX 8510-8 Backbone and Brocade DCX 8510-4 Backbone
  - FC8-32E port blade
  - FC8-48E port blade
  - FC8-64 port blade
  - FC16-32 port blade
  - FC16-48 port blade
  - FS8-18 Encryption Blade
  - FX8-24 DCX Extension Blade
- Brocade VA-40FC

# What's new in this document

The following changes have been made since this document was last released:

- The lookup lists in [Chapter 2](#) through [Chapter 4](#) provide hyperlinks to messages by type (LOG, Audit, and FFDC).
- Information that was added:
  - [AG Messages](#)
  - [ANV Messages](#)
  - [BL Messages](#)
  - [C2 Messages](#)
  - [C3 Messages](#)
  - [CDR Messages](#)
  - [CONF Messages](#)
  - [CVLM Messages](#)
  - [EM Messages](#)
  - [FABR Messages](#)
  - [FCR Messages](#)
  - [FSPF Messages](#)
  - [FW Messages](#)
  - [HAM Messages](#)
  - [HIL Messages](#)
  - [KAC Messages](#)
  - [LOG Messages](#)
  - [MM Messages](#)
  - [MS Messages](#)
  - [NBFS Messages](#)
  - [PLAT Messages](#)
  - [PS Messages](#)
  - [RAS Messages](#)
  - [SEC Messages](#)
  - [SS Messages](#)
  - [SWCH Messages](#)
  - [TRCE Messages](#)
  - [VDR Messages](#)
  - [XTUN Messages](#)
  - [ZEUS Messages](#)
  - [ZONE Messages](#)

- Information that was changed:
  - AN Messages
  - AUTH Messages
  - BL Messages
  - C2 Messages
  - C3 Messages
  - CDR Messages
  - CAL Messages
  - CNM Messages
  - DOT1 Messages
  - FABR Messages
  - FCOE Messages
  - FCPD Messages
  - FCR Messages
  - FICU Messages
  - FSPF Messages
  - FSS Messages
  - HIL Messages
  - HSL Messages
  - HTTP Messages
  - IPS Messages
  - KAC Messages
  - KTRC Messages
  - L2SS Messages
  - LFM Messages
  - PMGR Messages
  - PS Messages
  - RCS Messages
  - RTWR Messages
  - SEC Messages
  - ZONE Messages

- Information that was deleted:
  - BLL System Messages
  - CER System Messages
  - [EM Messages](#)
  - FCIP System Messages
  - [FCOE Messages](#)
  - [HAM Messages](#)
  - IBPD System Messages
  - ICPD System Messages
  - [SNMP Messages](#)
  - [SYSC Messages](#)
  - [UCST Messages](#)
  - [ZONE Messages](#)

For further information about new features and documentation updates for this release, refer to the release notes.

## Document conventions

This section describes text formatting conventions and important notice formats used in this document.

### Text formatting

The narrative-text formatting conventions that are used are as follows:

<b>bold text</b>	<ul style="list-style-type: none"> <li>Identifies command names</li> <li>Identifies the names of user-manipulated GUI elements</li> <li>Identifies keywords and operands</li> <li>Identifies text to enter at the GUI or CLI</li> </ul>
<i>italic text</i>	<ul style="list-style-type: none"> <li>Provides emphasis</li> <li>Identifies variables</li> <li>Identifies paths and Internet addresses</li> <li>Identifies document titles</li> </ul>
<code>code text</code>	<ul style="list-style-type: none"> <li>Identifies CLI output</li> <li>Identifies command syntax examples</li> </ul>

For readability, command names in the narrative portions of this guide are presented in mixed lettercase: for example, **switchShow**. In actual examples, command lettercase is all lowercase.

### Command syntax conventions

Command syntax in this manual follows these conventions:

<b>command</b>	Commands are printed in bold.
<b>--option, option</b>	Command options are printed in bold.
<b>-argument, arg</b>	Arguments.
[ ]	Optional element.
<i>variable</i>	Variables are printed in italics. In the help pages, values are <u>underlined</u> or enclosed in angled brackets < >.
...	Repeat the previous element, for example “member[;member...]”
value	Fixed values following arguments are printed in plain font. For example, <b>--show WWN</b>
	Boolean. Elements are exclusive. Example: <b>--show -mode egress   ingress</b>

## Command examples

This book describes how to perform configuration tasks using the Fabric OS command line interface, but does not describe the commands in detail. For complete descriptions of all Fabric OS commands, including syntax, operand description, and sample output, see the *Fabric OS Command Reference*.

## Notes, cautions, and warnings

The following notices and statements are used in this manual. They are listed below in order of increasing severity of potential hazards.

---

### NOTE

A note provides a tip, guidance, or advice, emphasizes important information, or provides a reference to related information.

---



---

### ATTENTION

An Attention statement indicates potential damage to hardware or data.

---



### CAUTION

A Caution statement alerts you to situations that can be potentially hazardous to you or cause damage to hardware, firmware, software, or data.

---



### DANGER

A Danger statement indicates conditions or situations that can be potentially lethal or extremely hazardous to you. Safety labels are also attached directly to products to warn of these conditions or situations.

---

## Key terms

For definitions specific to Brocade and Fibre Channel, see the technical glossaries on MyBrocade. See “[Brocade resources](#)” on page xix for instructions on accessing MyBrocade.

For definitions of SAN-specific terms, visit the Storage Networking Industry Association online dictionary at:

<http://www.snia.org/education/dictionary>

## Notice to the reader

This document may contain references to the trademarks of the following corporations. These trademarks are the properties of their respective companies and corporations.

These references are made for informational purposes only.

Corporation	Referenced Trademarks and Products
Red Hat, Inc.	Red Hat, Red Hat Network, Maximum RPM, Linux Undercover

## Additional information

This section lists additional Brocade and industry-specific documentation that you might find helpful.

### Brocade resources

To get up-to-the-minute information, go to <http://my.brocade.com> to register at no cost for a user ID and password.

White papers, online demonstrations, and data sheets are available through the Brocade website at:

<http://www.brocade.com/products-solutions/products/index.page>

For additional Brocade documentation, visit the Brocade website:

<http://www.brocade.com>

Release notes are available on the MyBrocade website.

### Other industry resources

For additional resource information, visit the Technical Committee T11 website. This website provides interface standards for high-performance and mass storage applications for Fibre Channel, storage management, and other applications:

<http://www.t11.org>

For information about the Fibre Channel industry, visit the Fibre Channel Industry Association website:

<http://www.fibrechannel.org>

## Getting technical help


Contact your switch support supplier for hardware, firmware, and software support, including product repairs and part ordering. To expedite your call, have the following information available:

### 1. General Information

- Switch model
- Switch operating system version
- Software name and software version, if applicable
- Error numbers and messages received
- **supportSave** command output
- Detailed description of the problem, including the switch or fabric behavior immediately following the problem, and specific questions
- Description of any troubleshooting steps already performed and the results
- Serial console and Telnet session logs
- syslog message logs

### 2. Switch Serial Number

The switch serial number and corresponding bar code are provided on the serial number label, as illustrated below.



The serial number label is located as follows:

- *Brocade 300, 5100, 5300, 6505, 6510, 6520, 7800, 8000, VA-40FC, and Brocade Encryption Switch*—On the switch ID pull-out tab located inside the chassis on the port side on the left.
- *Brocade 5410, 5424, 5430, 5450, 5460, 5470, 5480*—Serial number label attached to the module.
- *Brocade DCX and DCX 8510-8*—On the port side of the chassis, on the lower right side and directly above the cable management comb.
- *Brocade DCX-4S and DCX 8510-4*—On the non-port side of the chassis, on the lower left side.

### 3. World Wide Name (WWN)

Use the **licenseldShow** command to display the WWN of the chassis.



If you cannot use the **licenseIdShow** command because the switch is inoperable, you can get the WWN from the same place as the serial number, except for the Brocade DCX. For the Brocade DCX, access the numbers on the WWN cards by removing the Brocade logo plate at the top of the non-port side of the chassis.

## Document feedback

Quality is our first concern at Brocade and we have made every effort to ensure the accuracy and completeness of this document. However, if you find an error or an omission, or you think that a topic needs further development, we want to hear from you. Forward your feedback to:

[documentation@brocade.com](mailto:documentation@brocade.com)

Provide the title and version number of the document and as much detail as possible about your comment, including the topic heading and page number and your suggestions for improvement.



# Introduction to System Messages

---

## In this chapter

- [Overview of system messages](#) . . . . . 1
- [Configuring the syslog message destinations](#) . . . . . 5
- [Changing the severity level of swEventTrap](#) . . . . . 11
- [Commands for displaying and configuring the system message logs](#) . . . . . 13
- [Displaying message content on switch](#) . . . . . 14
- [Configuring system messages and attributes](#) . . . . . 15
- [Displaying system message logs and attributes](#) . . . . . 17
- [Clearing the system message logs](#) . . . . . 22
- [Reading the system messages](#) . . . . . 23
- [Responding to a system message](#) . . . . . 26
- [System module descriptions](#) . . . . . 28

## Overview of system messages

This guide supports Fabric OS v7.1.0 and documents system messages that can help you diagnose and fix problems with a switch or fabric. The messages are organized alphabetically by module name. A *module* is a subsystem in the Fabric OS. Each module generates a set of numbered messages. For each message, this guide provides message text, probable cause, recommended action, and severity level. There may be more than one cause and more than one recommended action for any given message. This guide discusses the most probable cause and typical action recommended.

### System message types

Fabric OS supports three types of system messages. A system message can be of one or more of the following types:

- [RASLog messages](#)
- [Audit log messages](#)
- [FFDC messages](#)

Fabric OS supports a different methodology for storing and accessing each type of message.

## *RASLog messages*

RASLog messages report significant system events (failure, error, or critical conditions) or information and are also used to show the status of the high-level user-initiated actions. RASLog messages are forwarded to the console, to the configured syslog servers, and to the SNMP management station through the Simple Network Management Protocol (SNMP) traps or informs.

The following is an example of a RASLog system message.

```
2012/10/25-17:51:05, [C3-1001], 937, CHASSIS, ERROR, switch, Port 18 failed due to SFP validation failure. Check if the SFP is valid for the configuration.
```

For information on displaying and clearing the RASLog messages, refer to [“Displaying system message logs and attributes”](#) on page 17.

## *Audit log messages*

Event auditing is designed to support post-event audits and problem determination based on high-frequency events of certain types such as security violations, zoning configuration changes, firmware downloads, and certain types of fabric events. Audit messages flagged as AUDIT are not saved in the switch error logs. The switch can be configured to stream Audit messages to the switch console and to forward the messages to specified syslog servers. The Audit log messages are not forwarded to an SNMP management station. There is no limit to the number of audit events.

The following is an example of an Audit message.

```
0 AUDIT, 2012/10/14-06:07:33 (UTC), [SULB-1003], INFO, FIRMWARE, admin/admin/192.0.2.2/telnet/CLI ad_0/switch, , Firmwarecommit has started.
```

For any given event, Audit messages capture the following information:

- User Name - The name of the user who triggered the action.
- User Role - The access level of the user, such as root or admin.
- Event Name - The name of the event that occurred.
- Event Information - Information about the event.

The seven event classes described in [Table 1](#) can be audited.

**TABLE 1** Event classes

Operand	Event class	Description
1	Zone	You can audit zone event configuration changes, but not the actual values that were changed. For example, you may receive a message that states “Zone configuration has changed,” but the message does not display the actual values that were changed.
2	Security	You can audit any user-initiated security event for all management interfaces. For events that have an impact on the entire fabric, an audit is only generated for the switch from which the event was initiated.
3	Configuration	You can audit configuration downloads of existing SNMP configuration parameters. Configuration uploads are not audited.
4	Firmware	You can audit configuration downloads of existing SNMP configuration parameters. Configuration uploads are not audited.
5	Fabric	You can audit Administration Domain-related changes.

**TABLE 1** Event classes (Continued)

Operand	Event class	Description
6	FW	You can audit Fabric Watch (FW)-related changes.
7	LS	You can audit Virtual Fabric (Logical Switch)-related changes.
8	CLI	You can audit the CLI commands executed on the switch.
N/A	RAS	Used to audit or track the RASLog messages or modules that are enabled or disabled using the <b>rasAdmin</b> command. <b>NOTE:</b> The RAS class is not configurable, and it is always enabled internally.

Fabric OS v7.1.0 generates component-specific Audit messages.

Event auditing is a configurable feature, which is by default disabled. You must enable event auditing using the **auditCfg --enable** command to send the events to a configured remote host. Syslogd must be configured for logging audit messages. You can set up filters to screen out particular classes of events using the **auditCfg** command. The defined set of Audit messages is sent to the configured remote host in the Audit message format, so that they are easily distinguishable from other syslog events that may occur in the network. For details on how to configure event auditing, refer to “[Configuring event auditing](#)” on page 15.

### *FFDC messages*

First Failure Data Capture (FFDC) is used to capture failure-specific data when a problem or failure is noted for the first time and before the switch reboots, or trace and log buffer get wrapped. All subsequent iterations of the same error are ignored. This critical debug information is saved in nonvolatile storage and can be retrieved using the **supportSave** command. The FFDC data is used for debugging or analyzing the problem. FFDC is intended for use by Brocade technical support.

FFDC is enabled by default. Execute the **supportFfdc** command to enable or disable FFDC. If FFDC is disabled, the FFDC daemon does not capture any data, even when a message with an FFDC attribute is logged.

The following is an example of the FFDC message.

```
2000/12/17-08:30:13, [SS-1000], 88, SLOT 6 | FFDC | CHASSIS, INFO, DCX,
supportSave has uploaded support information to the host with IP address
192.0.2.2.
```

## Message severity levels

[Table 2](#) shows the four levels of severity for system messages, ranging from CRITICAL (1) to INFO (4). In general, the definitions are wide ranging and are to be used as general guidelines for troubleshooting. For all cases, you must look at each specific error message description thoroughly before taking action.

# 1 Overview of system messages

**TABLE 2** Severity levels of a message

Severity level	Description
1 = CRITICAL	Critical-level messages indicate that the software has detected serious problems that will cause a partial or complete failure of a subsystem if not corrected immediately; for example, a power supply failure or rise in temperature must receive immediate attention.
2 = ERROR	Error-level messages represent an error condition that does not impact overall system functionality significantly. For example, error-level messages might indicate time-outs on certain operations, failures of certain operations after retries, invalid parameters, or failure to perform a requested operation.
3 = WARNING	Warning-level messages highlight a current operating condition that should be checked or it may lead to a failure in the future. For example, a power supply failure in a redundant system relays a warning that the system is no longer operating in redundant mode unless the failed power supply is replaced or fixed.
4 = INFO	Info-level messages report the current non-error status of the system components: for example, detecting online and offline status of a fabric port.

## System error message logging

The RASLog service generates and stores messages related to abnormal or erroneous system behavior. It includes the following features:

- All RASLog error messages are saved to nonvolatile storage by default.
- The system error message log can save a maximum of 1024 messages in random access memory (RAM).
- The system message log is implemented as a circular buffer. When more than the maximum entries are added to the log file, old entries are overwritten by new entries.
- Messages are numbered sequentially from 1 to 2,147,483,647 (0x7fffffff). The sequence number will continue to increase beyond the storage limit of 1024 messages. The sequence number can be reset to 1 using the **errClear** command. The sequence number is persistent across power cycles and switch reboots.
- Trace dump, FFDC, and core dump files can be uploaded to the FTP server using the **supportSave** command.
- Brocade recommends that you configure the syslogd facility as a management tool for error logs. This is particularly important for dual-domain switches because the syslogd facility saves messages from two logical switches as a single file and in sequential order. For more information, refer to “[System logging daemon](#)” on page 5.
- RASLog messages are streamed to the console, and are forwarded to the configured syslog servers and to the SNMP management station through the SNMP traps (in SNMPv1 and SNMPv3) or informs (in SNMPv3). Use the **snmpConfig** command to configure the SNMPv1 and SNMPv3 hosts and their configurations.
- Audit messages are streamed to the switch console, and are forwarded to the configured syslog servers. The Audit log messages are not forwarded to an SNMP management station.

# Configuring the syslog message destinations

You can configure the Fabric OS to send the syslog messages to the following output locations: syslog daemon, system console, and SNMP management station.

## System logging daemon

The system logging daemon (syslogd) is a process on UNIX, Linux, and some Windows systems that reads and logs messages as specified by the system administrator.

Fabric OS can be configured to use a UNIX-style syslogd process to forward system events and error messages to log files on a remote host system. The host system can be running UNIX, Linux, or any other operating system that supports the standard syslogd functionality. Configuring for syslogd involves configuring the host, enabling syslogd on the Brocade model, and, optionally, setting the facility level.

For the Brocade DCX family of switches, each control processor (CP) has a unique error log, depending on which CP was active when that message was reported. To fully understand message logging, you should enable the syslogd, because the logs on the host computer are maintained in a single merged file for both CPs and are in sequential order. Otherwise, you must examine the error logs in both CPs, particularly for events such as **firmwareDownload** or **haFailover**, for which the active CP changes.

For the Brocade DCX family of switches, any security violations that occur through Telnet, HTTP, or serial connections are not propagated between CPs. Security violations on the active CP are not propagated to the standby CP counters in the event of a failover, nor do security violations on the standby CP get propagated to the active CP counters.

## Configuring a syslog server

To configure the switch to forward all system events and error messages to the syslog of one or more servers, perform the following steps.

1. Log in to the switch as admin.
2. Execute the **syslogdIpAdd** *IP address* command to add a server to which system messages are forwarded.

```
switch:admin> syslogdipadd 192.0.2.2
```

You can configure up to six syslog servers to receive the syslog messages.

3. Execute the **syslogdIpShow** command to verify the syslog configuration on the switch.

```
switch:admin> syslogdipshow  
syslog.1 192.0.2.2
```

You can remove a configured syslog server using the **syslogdIpRemove** *IP address* command.

## System console

The system console displays RASLog messages, Audit messages (if enabled), and panic dump messages. These messages are mirrored to the system console; they are always saved in one of the system logs.

# 1 Configuring the syslog message destinations

The system console displays messages only through the serial port. If you log in to a switch through the Ethernet port or modem port, you will not receive system console messages.

You can filter messages that display on the system console by severity using the **errFilterSet** command. All messages are still sent to the system message log and syslogd (if configured).

## *Setting the system console severity level*

You can limit the types of messages that are logged to the console using the **errFilterSet** command. The system messages displayed on the console are filtered up to and include the configured severity level. You can choose one of the following severity levels: INFO, WARNING, ERROR, or CRITICAL.

To set the severity levels for the system console, perform the following steps.

1. Log in to the switch as admin.
2. Execute the **errFilterSet [-d console -v severity]** command to set the console severity level. The *severity* can be one of the following: INFO, WARNING, ERROR, or CRITICAL. The *severity* values are not case-sensitive.

For example, to set the filter severity level for the console to ERROR, enter the following command.

```
switch:admin> errfilterset -d console -v error
```

3. Execute the **errFilterSet** command to verify the configured filter settings.

```
switch:admin> errfilterset  
console: filter severity = ERROR
```

## SNMP trap recipient

An unsolicited message that comes to the management station from the SNMP agent on the device is called a *trap*. When an event occurs and if the event severity level is at or below the set severity level, the SNMP trap, `swEventTrap`, is sent to the configured trap recipients. The `VarBind` in the Trap Data Unit contains the corresponding instance of the event index, time information, event severity level, the repeat count, and description. The following are the possible severity levels:

- None (0)
- Critical (1)
- Error (2)
- Warning (3)
- Informational (4)
- Debug (5)

By default, the severity level is set to None, implying all traps are filtered and therefore no event traps are received. When the severity level is set to Informational, all traps with the severity level of Informational, Warning, Error, and Critical are received. For more information on changing the severity level of `swEventTrap`, refer to [“Changing the severity level of swEventTrap”](#) on page 11.

---

### NOTE

The Audit messages are not converted into `swEventTrap`.

---



The SNMP traps are unreliable because the trap recipient does not send any acknowledgment when it receives a trap. Therefore, the SNMP agent cannot determine if the trap was received.

Brocade switches send traps out on UDP port 162. To receive traps, the management station IP address must be configured on the switch. You can configure the SNMPv1 and SNMPv3 hosts to receive the traps.

For more information on the swEventTrap, refer to the *Fabric OS MIB Reference*.

### ***Configuring the SNMPv1 trap recipient***

Use the **snmpConfig --set snmpv1** command to specify the recipient of the SNMP trap. To configure the SNMPv1 host to receive the trap, perform the following steps.

1. Log in to the switch as admin.
2. Execute the **snmpConfig --set snmpv1** command to configure the SNMP trap recipient.

```
switch:admin> snmpconfig --set snmpv1

SNMP community and trap recipient configuration:
Community (rw): [Secret C0de]
Trap Recipient's IP address : [192.0.2.2]
Trap recipient Severity level : (0..5) [4]
Trap recipient Port : (0..65535) [162]
Community (rw): [OrigEquipMfr]
Trap Recipient's IP address : [fec0:60:22bc:200:313:72ff:fe64:78b2]
```

---

#### **NOTE**

To receive the traps, the management station IP address must be configured on the switch.

---

3. Execute the **snmpConfig --show snmpv1** command to verify the SNMPv1 agent configuration.

```
switch:admin> snmpconfig --show snmpv1

SNMPv1 community and trap recipient configuration:
Community 1: Secret C0de (rw)
  Trap recipient: 192.0.2.2
  Trap port: 162
  Trap recipient Severity level: 5
Community 2: OrigEquipMfr (rw)
  Trap recipient: fec0:60:22bc:200:313:72ff:fe64:78b2
  Trap port: 162
  Trap recipient Severity level: 5
Community 3: private (rw)
  Trap recipient: tools.lab.brocade.com
  Trap port: 162
  Trap recipient Severity level: 5
Community 4: public (ro)
  Trap recipient: 192.0.10.10
  Trap port: 65530
  Trap recipient Severity level: 1
Community 5: common (ro)
  Trap recipient: fec0:60:69bc:200:213:72ff:fe64:069f
  Trap port: 11
  Trap recipient Severity level: 2
Community 6: FibreChannel (ro)
  Trap recipient: WT.org.brocade.com
  Trap port: 65521
```

# 1 Configuring the syslog message destinations

```
Trap recipient Severity level: 2
SNMPv1:Enabled
```

## *Configuring the SNMPv3 trap recipient*

To configure the SNMPv3 host to receive the trap, perform the following steps.

1. Log in to the switch as admin.
2. Execute the **snmpConfig --set snmpv3** command to configure the SNMP trap recipient. Ignore the step to enable the SNMP informs “SNMP Informs Enabled”.

```
switch:admin> snmpconfig --set snmpv3

SNMP Informs Enabled (true, t, false, f): [false]

SNMPv3 user configuration(snmp user not configured in FOS user database will
have physical AD and admin role as the default):
User (rw): [snmpadmin1]
Auth Protocol [MD5(1)/SHA(2)/noAuth(3)]: (1..3) [3]
Priv Protocol [DES(1)/noPriv(2)/3DES(3)/AES128(4)/AES192(5)/AES256(6)]:
(2..2) [2]
User (rw): [snmpadmin2]
Auth Protocol [MD5(1)/SHA(2)/noAuth(3)]: (1..3) [3]
Priv Protocol [DES(1)/noPriv(2)/3DES(3)/AES128(4)/AES192(5)/AES256(6)]:
(2..2) [2]
User (rw): [snmpadmin3]
Auth Protocol [MD5(1)/SHA(2)/noAuth(3)]: (1..3) [3]
Priv Protocol [DES(1)/noPriv(2)/3DES(3)/AES128(4)/AES192(5)/AES256(6)]:
(2..2) [2]
User (ro): [snmpuser1]
Auth Protocol [MD5(1)/SHA(2)/noAuth(3)]: (1..3) [3]
Priv Protocol [DES(1)/noPriv(2)/3DES(3)/AES128(4)/AES192(5)/AES256(6)]:
(2..2) [2]
User (ro): [snmpuser2]
Auth Protocol [MD5(1)/SHA(2)/noAuth(3)]: (1..3) [3]
Priv Protocol [DES(1)/noPriv(2)/3DES(3)/AES128(4)/AES192(5)/AES256(6)]:
(2..2) [2]
User (ro): [snmpuser3]
Auth Protocol [MD5(1)/SHA(2)/noAuth(3)]: (1..3) [3]
Priv Protocol [DES(1)/noPriv(2)/3DES(3)/AES128(4)/AES192(5)/AES256(6)]:
(2..2) [2]

SNMPv3 trap recipient configuration:
Trap Recipient's IP address : [192.0.2.2]
UserIndex: (1..6) [1]
Trap recipient Severity level : (0..5) [1]
Trap recipient Port : (0..65535) [35432]
Trap Recipient's IP address : [192.0.10.10]
UserIndex: (1..6) [2]
Trap recipient Severity level : (0..5) [5]
Trap recipient Port : (0..65535) [162]
Trap Recipient's IP address : [192.0.20.20]
[...]
```

---

### **NOTE**

To receive the SNMP traps, the username, the authentication protocol, the UDP port number, and the privacy protocol must match between the switch and the management station.

---

3. Execute the `snmpConfig --show snmpv3` command to verify the SNMP agent configuration.

```
switch:admin> snmpconfig --show snmpv3
SNMP Informs = 0 (OFF)
SNMPv3 USM configuration:
User 1 (rw): snmpadmin1
Auth Protocol: noAuth
Priv Protocol: noPriv
User 2 (rw): snmpadmin2
Auth Protocol: MD5
Priv Protocol: noPriv
User 3 (rw): snmpadmin3
Auth Protocol: MD5
Priv Protocol: DES
User 4 (ro): snmpuser1
Auth Protocol: noAuth
Priv Protocol: noPriv
User 5 (ro): snmpuser2
Auth Protocol: noAuth
Priv Protocol: noPriv
User 6 (ro): snmpuser3
Auth Protocol: noAuth
Priv Protocol: noPriv
SNMPv3 Trap configuration:
Trap Entry 1: 192.0.2.2
Trap Port: 162
Trap User: snmpadmin1
Trap recipient Severity level: 1
Trap Entry 2: fe80::224:1dff:fef6:0f21
Trap Port: 162
[...]
```

## SNMP inform recipient

An SNMP inform is similar to the SNMP trap except that the management station that receives an SNMP inform acknowledges the system message with an SNMP response packet data unit (PDU). If the sender does not receive the SNMP response PDU, the inform request can be sent again. An SNMP inform request is saved in the switch memory until a response is received or the request times out. The informs are more reliable and they consume more resources in the device and in the network. Use SNMP informs only if it is important that the management station receives all event notifications. Otherwise, use the SNMP traps. Brocade devices support SNMPv3 informs.

### *Configuring the SNMPv3 inform recipient*

To configure the SNMPv3 host to receive the SNMP informs, perform the following steps.

1. Log in to the switch as admin.
2. Execute the `snmpConfig --set snmpv3` command to configure the inform recipient. When prompted to enable the SNMP informs, enter **true** or **t**. Informs are disabled by default.

```
switch:admin> snmpconfig --set snmpv3

SNMP Informs Enabled (true, t, false, f): [false] t

SNMPv3 user configuration(snmp user not configured in FOS user database will
have physical AD and admin role as the default):
User (rw): [snmpadmin1]
Auth Protocol [MD5(1)/SHA(2)/noAuth(3)]: (1..3) [3]
```

# 1 Configuring the syslog message destinations

```
Priv Protocol [DES(1)/noPriv(2)/3DES(3)/AES128(4)/AES192(5)/AES256(6)]:
(2..2) [2]
Engine ID: [0:0:0:0:0:0:0:0]
User (rw): [snmpadmin2]
Auth Protocol [MD5(1)/SHA(2)/noAuth(3)]: (1..3) [3] 1
New Auth Passwd:
Verify Auth Passwd:
Priv Protocol [DES(1)/noPriv(2)/3DES(3)/AES128(4)/AES192(5)/AES256(6)]:
(1..6) [2] 1
New Priv Passwd:
Verify Priv Passwd:
Engine ID: [0:0:0:0:0:0:0:0] 80:00:05:23:01:0A:23:34:1B
User (rw): [snmpadmin3]
Auth Protocol [MD5(1)/SHA(2)/noAuth(3)]: (1..3) [3]
Priv Protocol [DES(1)/noPriv(2)/3DES(3)/AES128(4)/AES192(5)/AES256(6)]:
(2..2) [2]
Engine ID: [0:0:0:0:0:0:0:0]
User (ro): [snmpuser1]
Auth Protocol [MD5(1)/SHA(2)/noAuth(3)]: (1..3) [3]
Priv Protocol [DES(1)/noPriv(2)/3DES(3)/AES128(4)/AES192(5)/AES256(6)]:
(2..2) [2]
Engine ID: [0:0:0:0:0:0:0:0]
User (ro): [snmpuser2]
Auth Protocol [MD5(1)/SHA(2)/noAuth(3)]: (1..3) [3]
Priv Protocol [DES(1)/noPriv(2)/3DES(3)/AES128(4)/AES192(5)/AES256(6)]:
(2..2) [2]
Engine ID: [0:0:0:0:0:0:0:0]
User (ro): [snmpuser3]
Auth Protocol [MD5(1)/SHA(2)/noAuth(3)]: (1..3) [3]
Priv Protocol [DES(1)/noPriv(2)/3DES(3)/AES128(4)/AES192(5)/AES256(6)]:
(2..2) [2]
Engine ID: [0:0:0:0:0:0:0:0]
SNMPv3 trap recipient configuration:
Trap Recipient's IP address : [0.0.0.0] 192.0.2.2
UserIndex: (1..6) [1]
Trap recipient Severity level : (0..5) [0] 4
Trap recipient Port : (0..65535) [162]
Trap Recipient's IP address : [0.0.0.0] 192.0.10.10
UserIndex: (1..6) [2]
Trap recipient Severity level : (0..5) [0] 4
Trap recipient Port : (0..65535) [162]
Trap Recipient's IP address : [0.0.0.0]
Trap Recipient's IP address : [0.0.0.0]
Trap Recipient's IP address : [0.0.0.0]
Trap Recipient's IP address : [0.0.0.0]
Committing configuration.....done.
```

---

## NOTE

To receive the SNMP informs, the username, the authentication protocol, the privacy protocol, the UDP port number, and the engine ID must match between the switch and the management station.

---

3. Execute the `snmpConfig --show snmpv3` command to verify the SNMP agent configuration.

```
switch:admin> snmpconfig --show snmpv3
SNMP Informs = 1 (ON)
SNMPv3 USM configuration:
User 1 (rw): snmpadmin1
Auth Protocol: noAuth
```

```

Priv Protocol: noPriv
Engine ID: 80:00:05:23:01:0a:23:34:21
User 2 (rw): snmpadmin2
Auth Protocol: MD5
Priv Protocol: DES
Engine ID: 80:00:05:23:01:0a:23:34:1b
User 3 (rw): snmpadmin3
Auth Protocol: noAuth
Priv Protocol: noPriv
Engine ID: 00:00:00:00:00:00:00:00:00
User 4 (ro): snmpuser1
Auth Protocol: noAuth
Priv Protocol: noPriv
Engine ID: 00:00:00:00:00:00:00:00:00
User 5 (ro): snmpuser2
Auth Protocol: noAuth
Priv Protocol: noPriv
Engine ID: 00:00:00:00:00:00:00:00:00
User 6 (ro): snmpuser3
Auth Protocol: noAuth
Priv Protocol: noPriv
Engine ID: 00:00:00:00:00:00:00:00:00
SNMPv3 Trap configuration:
Trap Entry 1: 192.0.2.2
Trap Port: 162
Trap User: snmpadmin1
Trap recipient Severity level: 4
Trap Entry 2: 192.0.10.10
Trap Port: 162
Trap User: snmpadmin2
Trap recipient Severity level: 4
Trap Entry 3: No trap recipient configured yet
Trap Entry 4: No trap recipient configured yet
Trap Entry 5: No trap recipient configured yet

```

## Port logs

The Fabric OS maintains an internal log of all port activity. Each switch or logical switch maintains a log file for each port. Port logs are circular buffers that can save up to 8000 entries per logical switch. When the log is full, the newest log entries overwrite the oldest log entries. Port logs capture switch-to-device, device-to-switch, switch-to-switch, some device A-to-device B, and control information. Port logs are not persistent and are lost over power cycles and reboots.

Execute the **portLogShow** command to display the port logs for a particular port.

Execute the **portLogEventShow** command to display the specific events reported for each port.

Port log functionality is completely separate from the system message log. Port logs are typically used to troubleshoot device connections.

## Changing the severity level of swEventTrap

When an event occurs and if the event severity level is at or below the set severity level, the SNMP trap, swEventTrap, is sent to the configured trap recipients. By default, the severity level is set at 0 (None), implying that all the event traps are sent. Use the **snmpConfig --set mibCapability** command to modify the severity level of swEventTrap.

# 1 Changing the severity level of swEventTrap

To change the severity level of swEventTrap, perform the following steps.

1. Log in to the switch as admin.
2. Execute the **snmpConfig --set mibCapability** command to configure MIBs interactively. All the supported MIBs and associated traps are displayed. You can change the DesiredSeverity for swEventTrap to 1 (Critical), 2 (Error), 3 (Warning), or 4 (Informational). The default value is 0.

```
switch:admin> snmpconfig --set mibcapability
FE-MIB: YES
SW-MIB: YES
FA-MIB: YES
FICON-MIB: YES
HA-MIB: YES
FCIP-MIB: YES
ISCSI-MIB: YES
IF-MIB: YES
BD-MIB: YES
SW-TRAP: YES

swFault: YES
swSensorScn: YES
swFCPortScn: YES
swEventTrap: YES
DesiredSeverity:Informational
swFabricWatchTrap: YES
DesiredSeverity:None
swTrackChangesTrap: YES
swIPv6ChangeTrap: YES
swPmgrEventTrap: YES
swFabricReconfigTrap: YES
swFabricSegmentTrap: YES
swExtTrap: NO
swStateChangeTrap: NO
swPortMoveTrap: NO
swBrccdGenericTrap: YES

... <lines omitted for brevity>
SW-TRAP (yes, y, no, n): [yes]
swFault (yes, y, no, n): [yes]
swSensorScn (yes, y, no, n): [yes]
swFCPortScn (yes, y, no, n): [yes]
swEventTrap (yes, y, no, n): [yes]
DesiredSeverity: (0..4) [4] 3
swFabricWatchTrap (yes, y, no, n): [yes]
DesiredSeverity: (0..4) [0] 2
swTrackChangesTrap (yes, y, no, n): [yes]
swIPv6ChangeTrap (yes, y, no, n): [yes]
swPmgrEventTrap (yes, y, no, n): [yes]

[...]
```

3. Execute the **snmpConfig --show mibCapability** command to verify the severity level of swEventTrap.

```
switch:admin> snmpconfig --show mibcapability
FE-MIB: YES
SW-MIB: YES
FA-MIB: YES
FICON-MIB: YES
HA-MIB: YES
FCIP-MIB: YES
ISCSI-MIB: YES
```

```

IF-MIB: YES
BD-MIB: YES
SW-TRAP: YES
    swFault: YES
    swSensorScn: YES
    swFCPortScn: YES
    swEventTrap: YES
        DesiredSeverity: Informational
    swFabricWatchTrap: YES
        DesiredSeverity: Critical
    swTrackChangesTrap: YES
    swIPv6ChangeTrap: YES
    swPmgrEventTrap: YES
    swFabricReconfigTrap: YES
[...]
```

## Commands for displaying and configuring the system message logs

[Table 3](#) describes commands that you can use to view or configure the system message logs. Most commands require the admin access level. For detailed information on required access levels and commands, refer to the *Fabric OS Command Reference*.

**TABLE 3** Commands for viewing or configuring the system parameters and message logs

Command	Description
<b>auditCfg</b>	Configures the audit message log.
<b>auditDump</b>	Displays or clears the audit log.
<b>errClear</b>	Clears all error log messages for all switch instances on this control processor (CP).
<b>errDelimiterSet</b>	Sets the error log start and end delimiter for messages pushed to the console.
<b>errDump</b>	Displays the entire error log, without page breaks. Use the <b>-r</b> option to show the messages in reverse order, from newest to oldest.
<b>errFilterSet</b>	Sets an error severity filter for the system console.
<b>errModuleShow</b>	Displays all the defined error log modules.
<b>errShow</b>	Displays the entire error log, with page breaks. Use the <b>-r</b> option to show the messages in reverse order, from newest to oldest.
<b>pdShow</b>	Displays the contents of the panic dump and core dump files.
<b>portErrShow</b>	Displays the port error summary.
<b>portLogClear</b>	Clears the port log. If the port log is disabled, this command enables it.
<b>portLogDisable</b>	Disables the port log facility.
<b>portLogDump</b>	Displays the port log, without page breaks.
<b>portLogDumpPort</b>	Displays the port log of the specified port, without page breaks.
<b>portLogEnable</b>	Enables the port log facility.
<b>portLogEventShow</b>	Displays which port log events are currently being reported.
<b>portLoginShow</b>	Displays port logins.
<b>portLogPdisc</b>	Sets or clears the debug pdisc_flag.
<b>portLogReset</b>	Enables the port log facility.

# 1 Displaying message content on switch

**TABLE 3** Commands for viewing or configuring the system parameters and message logs (Continued)

Command	Description
<b>portLogResize</b>	Resizes the port log to the specified number of entries.
<b>portLogShow</b>	Displays the port log, with page breaks.
<b>portLogShowPort</b>	Displays the port log of the specified port, with page breaks.
<b>portLogTypeDisable</b>	Disables an event from reporting to the port log. Port log events are described by the <b>portLogEventShow</b> command.
<b>portLogTypeEnable</b>	Enables an event to report to the port log. Port log events are described by the <b>portLogEventShow</b> command.
<b>rasAdmin</b>	Used to enable or disable logging for selected messages or modules, to change the default severity level for a specified message, and to display configured RASLog message settings.
<b>rasMan</b>	Displays message documentation on switch.
<b>setVerbose</b>	Sets the verbose level of a particular module within the Fabric OS.
<b>snmpConfig</b>	Manages the SNMP agent configuration.
<b>supportFfdc</b>	Enables and disables FFDC.
<b>supportFtp</b>	Sets, clears, or displays support FTP parameters or a time interval to check the FTP server.
<b>supportSave</b>	Collects RASLog, trace files, and <b>supportShow</b> (active CP only) information for the local CP and then transfers the files to an FTP server. The operation can take several minutes.
<b>supportShow</b>	Executes a list of diagnostic and error display commands. This output is used by your switch service provider to diagnose and correct problems with the switch. The output from this command is very long.
<b>syslogdFacility</b>	Changes the syslogd facility.
<b>syslogdIpAdd</b>	Adds an IP address as a recipient of system messages.
<b>syslogdIpRemove</b>	Removes an IP address as a recipient of system messages.
<b>syslogdIpShow</b>	Views the currently configured IP addresses that are recipients of system messages.
<b>traceDump</b>	Displays, initiates, or removes a Fabric OS module trace dump.

## Displaying message content on switch

Beginning with Fabric OS v7.1.0, you can view the message documentation such as the message text, message type, class (for audit messages), message severity, cause, and action on the switch console by using the **rasMan message\_ID** command.

To display the message documentation on switch, perform the following steps.

1. Log in to the switch as admin.
2. Use the **rasMan message\_ID** command to display the documentation of a message. The *message\_ID* values are case-sensitive.



For example, execute the following command to display the documentation for PS-1007.

```
switch:admin> rasman PS-1007
Log Messages                                     PS-1007 (7m)

MESSAGE
  PS-1007 - Failed to add Fabricmode Top Talker on
  domain=<domain id>. <function name>.

MESSAGE TYPE
  LOG

SEVERITY
  WARNING

PROBABLE CAUSE
  Indicates that FC Routing (FCR) is enabled on the specified
  fabric.

RECOMMENDED ACTION
  Top Talker cannot be installed on a fabric with FCR service
  enabled. In case Top Talker must be installed on a fabric,
  disable FCR using the fosconfig --disable fcr command.
```

## Configuring system messages and attributes

This section provides information on configuring the system message logs and its attributes. All admin-level commands mentioned in this section are used to enable or disable only the external messages.

### Configuring event auditing

To configure event auditing, perform the following steps.

1. Log in to the switch as admin.
2. Execute the **auditCfg --enable** command to enable the audit feature.
3. Execute the **auditCfg --class** command to configure the event classes you want to audit.

```
switch:admin> auditcfg --enable
Audit filter is enabled.

switch:admin> auditcfg --class 1,2,3,4,5,6,7,8
Audit filter is configured.
```

---

#### NOTE

The class option **9** (MAPS) is for internal use only. The RAS class is not configurable, and it is always enabled internally.

---

4. Execute the **auditCfg --severity severity level** command if you want to set the Audit severity level. By default, all messages are logged. When the severity is set, only messages with the configured severity and higher are displayed. Valid values for *severity level* are INFO, WARNING, ERROR, and CRITICAL

```
switch:admin> auditcfg --severity ERROR
```

# 1 Configuring system messages and attributes

5. Execute the **auditCfg --show** command to verify the configuration.

```
switch:admin> auditCfg --show
Audit filter is enabled.
1-ZONE
2-SECURITY
3-CONFIGURATION
4-FIRMWARE
5-FABRIC
6-FW
7-LS
8-CLI
Severity level: ERROR
```

You must configure the syslog daemon to send the Audit events to a configured remote host using the **syslogdIpAdd** command. For more information on configuring the syslog server, refer to [“Configuring a syslog server”](#) on page 5.

## Disabling a RASLog message or module

To disable a single RASLog message or all messages in a module, perform the following steps.

1. Log in to the switch as admin.
2. Use the following commands to disable a single RASLog message or all messages that belong to a module:
  - Execute the **rasadmin --disable -log message\_ID** command to disable a RASLog message. For example, execute the following command to disable the BL-1001 message.

```
switch:admin> rasadmin --disable -log BL-1001
2012/07/20-13:30:41, [LOG-1005], 378, SLOT 4 | CHASSIS, INFO, switch, Log
message NSM-1009 has been disabled.
```

Use the **rasadmin --show -log message\_ID** command to verify the status of the message.

- Execute the **rasadmin --disable -module module\_ID** command to disable all messages in a module. For example, execute the following command to disable all messages that belong to the BL module.

```
switch:admin> rasadmin --disable -module BL
2012/07/20-13:28:37, [LOG-1007], 375, SLOT 4 | CHASSIS, INFO, switch, Log
Module BL has been disabled.
```

Use the **rasadmin --show -module module\_ID** command to verify the status of the messages that belong to a module.

---

### NOTE

You cannot disable Audit and FFDC messages using the **rasAdmin** command.

---

## Enabling a RASLog message or module

To enable a single RASLog message or all messages in a module that were previously disabled, perform the following steps.

1. Log in to the switch as admin.
2. Use the following commands to enable a single RASLog message or all messages that belong to a module:

- Execute the **rasadmin --enable -log message\_ID** command to enable a single RASLog message that has been disabled.

For example, execute the following command to enable BL-1001 message that was previously disabled.

```
switch:admin> rasadmin --enable -log BL-1001
2012/10/15-13:24:30, [LOG-1006], 373, SLOT 4 | CHASSIS, INFO, switch, Log
message BL-1001 has been enabled.
```

Use the **rasadmin --show -log message\_ID** command to verify the status of the message.

- Execute the **rasadmin --enable -module module\_ID** command to enable all messages in a module. For example, execute the following command to enable to all previously disabled BL messages.

```
switch:admin> rasadmin --enable -module BL
2012/10/15-13:28:37, [LOG-1007], 375, SLOT 4 | CHASSIS, INFO, switch, Log
Module BL has been enabled.
```

Use the **rasadmin --show -module module\_ID** command to verify the status of the messages that belong to a module.

## Setting the severity level of a RASLog message

To change the default severity level of a RASLog message, perform the following steps.

1. Log in to the switch as admin.
2. Use the **rasadmin --set -log message\_ID -severity [DEFAULT | INFO | WARNING | ERROR | CRITICAL]** to change the severity level of a message. For example, execute the following command to change the severity level of C2-1004 message to WARNING.

```
switch:admin> rasadmin --set -log C2-1004 -severity WARNING
```

3. Use the **rasadmin --show -severity message\_ID** command to verify the severity of the message.

```
switch:admin> rasadmin --show -severity C2-1004
Message          Severity
C2-1004 :        WARNING
```

## Displaying system message logs and attributes

This section provides information on displaying the system message logs. These procedures are valid for all the supported platforms.

# 1 Displaying system message logs and attributes

## Displaying RASLog messages

To display the system message log on a switch with no page breaks, perform the following steps. You can display the messages in reverse order using the **reverse** option. To display message logs in all switches (logical switches), use the **all** option.

1. Log in to the switch as admin.
2. Enter the **errDump** command at the command line.

```
switch:admin> errdump
Version: v7.1.0

2000/12/17-05:54:30, [HAM-1004], 1, CHASSIS, INFO, switch, Processor rebooted
- Reset

2000/12/17-05:55:04, [ZONE-1034], 2, FID 128, INFO, switch, A new zone
database file is created.

2000/12/17-05:55:04, [FCR-1069], 3, FID 128, INFO, switch, The FC Routing
service is enabled.

2000/12/17-05:55:04, [FCR-1068], 4, FID 128, INFO, switch, The FC Routing
service is disabled.

2000/12/17-05:55:11, [EM-1034], 5, CHASSIS, ERROR, switch, PS 2 set to faulty,
rc=2000e.
[...]
```

## Displaying RASLog messages one message at a time

To display the system message log one message at a time, perform the following steps.

1. Log in to the switch as admin.
2. Enter the **errShow** command at the command line.

```
switch:admin> errshow
Version: v7.1.0

2011/11/11-05:54:30, [HAM-1004], 1, CHASSIS, INFO, switch, Processor rebooted
- Reset

Type <CR> to continue, Q<CR> to stop:

2011/11/11-05:55:04, [ZONE-1034], 2, FID 128, INFO, switch, A new zone
database file is created.

Type <CR> to continue, Q<CR> to stop:

2011/11/11-05:55:04, [FCR-1069], 3, FID 128, INFO, switch, The FC Routing
service is enabled.

Type <CR> to continue, Q<CR> to stop:
[...]
```

## Displaying Audit messages

To display the Audit messages, perform the following steps. Beginning with Fabric OS v7.1.0 release, the RAS-3005 message is generated for each CLI command executed on switch and is saved in the Audit message log.

1. Log in to the switch as admin.
2. Enter the **auditDump -s** command at the command line.

```
switch:admin> auditdump -s

0 AUDIT, 2011/01/14-06:06:49 (UTC), [RAS-2001], INFO, SYSTEM,
admin/admin/192.0.2.2/telnet/CLI, ad_0/switch/FID 128, , Audit message log is
enabled.

2 AUDIT, 2011/01/14-06:07:03 (UTC), [SEC-3020], INFO, SECURITY,
admin/admin/192.0.2.2/telnet/CLI ad_0/switch, , Event: login, Status: success,
Info: Successful login attempt via SERIAL.

3 AUDIT, 2011/01/14-06:07:33 (UTC), [SULB-1003], INFO, FIRMWARE,
admin/admin/192.0.2.2/telnet/CLI ad_0/switch, , Firmwarecommit has started.

4 AUDIT, 2011/12/11-10:08:58 (UTC), [SULB-1004], INFO, FIRMWARE,
admin/admin/192.0.2.2/telnet/CLI ad_0/switch, , Firmwarecommit has completed.

5 AUDIT, 2012/05/23-03:45:15 (UTC), [RAS-3005], INFO, CLI,
admin/admin/NONE/console/CLI, ad_0/switch/CHASSIS, , CLI: clihistory --all

6 AUDIT, 2012/05/23-04:12:04 (UTC), [RAS-3005], INFO, CLI,
admin/admin/NONE/console/CLI, ad_0/switch/CHASSIS, , CLI: auditdump -s
[...]
```

## Displaying FFDC messages

To display the saved FFDC messages, perform the following steps.

1. Log in to the switch as admin.
2. Enter the **errDump --attribute FFDC** command at the command line.

```
switch:admin> errDump --attribute FFDC
Fabric OS: v7.1.0

2012/10/15-10:39:02, [LOG-1002], 4496, FFDC, WARNING, switch, A log
message was not recorded.

2012/10/15-10:39:18, [RAS-1001], 4496, FFDC, WARNING, switch, First
failure data capture (FFDC) event occurred.
[...]
```

## Displaying status of the system messages

To display the status of the system message, perform the following steps.

1. Log in to the switch as admin.
2. Use the following commands to display the status of all messages in the log, a single message, or all messages that belong to a module:

- Execute the **rasadmin -show -all** command to the status of all RASLog messages in the system log.

```
switch:admin> rasadmin --show -all
Message      Status      Default Severity      Current Severity
FCIP-1000    ENABLED     CRITICAL              CRITICAL
FCIP-1001    ENABLED     INFO                  ERROR
FCIP-1002    ENABLED     INFO                  INFO
[...]
```

- Execute the **rasadmin -show -log message\_ID** command to display the status of a single RASLog message.

```
switch:admin> rasadmin --show -log IPAD-1002
Message      Status      Default Severity      Current Severity
IPAD-1002    DISABLED    INFO                  INFO
```

- Execute the **rasadmin -show -module module\_ID** command to display the status of all messages that belong to the module.

```
switch:admin> rasadmin --show -module ECC
Message      Status      Default Severity      Current Severity
ECC-1000     ENABLED     ERROR                 ERROR
ECC-1001     DISABLED    ERROR                 WARNING
```

- Execute the **rasadmin -show -disabled** command to display the list of all RASLog messages that are disabled.

```
switch:admin> rasadmin --show -disabled
Message      Status
CDR-1001     :      DISABLED
CDR-1003     :      DISABLED
CDR-1004     :      DISABLED
ECC-1001     :      DISABLED
IPAD-1002    :      DISABLED
```

## Displaying the severity level of RASLog messages

To display the severity level of a RASLog message, perform the following steps.

1. Log in to the switch as admin.
2. Use the **rasadmin -show -severity message\_ID** command to display the severity level of a RASLog message. For example, execute the following command to display the status of the SEC-1203 message.

```
switch:admin> rasadmin --show -severity SEC-1203
Message      Severity
SEC-1203 :    WARNING
```

## Displaying RASLog messages by severity level

To display the RASLog messages based on the severity level, perform the following steps.

1. Log in to the switch as admin.
2. Execute the **errdump --severity [DEFAULT | INFO | WARNING | ERROR | CRITICAL]** command. For more information on message severity levels, refer to “[Message severity levels](#)” on page 3. You can set the count of messages to display using the **count** option. The following example filters messages by severity level of ERROR.

```
switch:admin> errdump --count 4 --severity ERROR
Fabric OS: v7.1.0
2012/10/24-11:23:24, [C3-1001], 12, CHASSIS, ERROR, switch, Port 4 failed due
to SFP validation failure. Check if the SFP is valid for the configuration.

2012/10/24-11:23:24, [C3-1001], 13, CHASSIS, ERROR, switch, Port 5 failed due
to SFP validation failure. Check if the SFP is valid for the configuration.

2012/10/24-11:23:25, [C3-1001], 14, CHASSIS, ERROR, switch, Port 18 failed due
to SFP validation failure. Check if the SFP is valid for the configuration.

2012/10/24-11:46:14, [C3-1001], 27, CHASSIS, ERROR, switch, Port 4 failed due
to SFP validation failure. Check if the SFP is valid for the configuration.
```

## Displaying RASLog messages by message ID

To display the RASLog messages based on the message ID, perform the following steps.

1. Log in to the switch as admin.
2. Execute the **errdump --message message\_ID** command. The following example displays all instances of the message HAM-1004.

```
switch:admin> errdump --message HAM-1004
Fabric OS: v7.1.0
2012/11/27-16:18:38, [HAM-1004], 1, CHASSIS, INFO, switch, Processor rebooted
- Reset.

2012/11/27-17:26:44, [HAM-1004], 90, CHASSIS, INFO, switch, Processor rebooted
- FirmwareDownload.

2012/11/27-21:06:25, [HAM-1004], 201, CHASSIS, INFO, switch, Processor
rebooted - FirmwareDownload.
[...]
```

## Displaying messages on a slot

To display the saved messages for a specific slot, perform the following steps.

1. Log in to the switch as admin.
2. Execute the **errdump --slot slot\_num** command.

```
switch:admin> errdump --slot 4
Fabric OS: v7.1.0

2012/06/19-03:26:44, [HAM-1004], 31, SLOT 4 | CHASSIS, INFO, switch, Processor
rebooted - Reboot.
```

# 1 Clearing the system message logs

```
2012/06/19-03:26:44, [SULB-1003], 32, SLOT 4 | CHASSIS, INFO, switch,
Firmwarecommit has started.

2012/06/19-03:26:44, [IPAD-1001], 33, SLOT 4 | CHASSIS, INFO, switch, CP/1
IPv6 manual fe80::224:38ff:fe1b:4400 DHCP Off.

2012/06/19-03:29:15, [IPAD-1000], 48, SLOT 4 | CHASSIS, INFO, switch, CP/0
Ether/0 IPv6 autoconf fd00:60:69bc:816:205:1eff:fe84:3f49/64 tentative DHCP
Off.
[...]
```

---

**NOTE**

The **slot** option is not supported on the non-bladed systems.

---

## Viewing RASLog messages from Web Tools

To view the system message log for a switch from Web Tools, perform the following steps.

1. Launch Web Tools.
2. Select the desired switch from the Fabric Tree. The Switch View displays.
3. Click the **Switch Events** tab. You can view the switch events and messages in the Switch Events Report displayed.

In dual-domain switches, an **Event** button exists for each logical switch. Only messages relating to that switch (and chassis) will be displayed.

## Clearing the system message logs

This section provides information on clearing the system message logs. These procedures are valid for all the supported platforms.

### Clearing the system message log

To clear the system message log for a particular switch instance, perform the following steps.

1. Log in to the switch as admin.
2. Execute the **errClear** command to clear all messages from memory.

---

**NOTE**

For products that have a single processor, all error log messages are cleared. For products that have multiple processors, this command only clears the error logs of the processor from which it is executed.

---



## Clearing the Audit message log

To clear the Audit message log for a particular switch instance, perform the following steps.

1. Log in to the switch as admin.
2. Execute the **auditDump -c** command to clear all Audit messages from memory.

## Reading the system messages

This section provides information about reading the RASLog and Audit messages.

### Reading a RAS system message

This section provides information about reading system messages.

The following example shows the format of a RAS system error message.

```
<timestamp>, [<Event ID>], <Sequence Number>, <Flags>, <Severity>, <Switch name>,
<Event-specific information>
```

The following example shows a sample message from the error log.

```
2011/02/10-14:18:04, [SS-1000], 88, SLOT 6 | FFDC | CHASSIS, INFO, ESNSVT_DCX,
supportSave has uploaded support information to the host with IP address
192.0.2.2.
```

```
2011/02/10-14:13:34, [SS-1001], 87, SLOT 6/1 | FFDC | CHASSIS, WARNING,
ESNSVT_DCX, supportSave's upload operation to host IP address aborted.
```

```
2011/02/10-15:44:51, [SEC-1203], 89, SLOT 6 | FFDC | FID 128, INFO, ESNSVT_DCX,
Login information: Login successful via TELNET/SSH/RSH. IP Addr:192.0.2.2.
```

---

#### NOTE

Any reference to slot 0 in a system message is a reference to the blade within the switch platform, for example, Brocade DCX contains FC8-48 blade, FC8-32 blade, FC8-16 blade, and so on.

---

The fields in the error message are described in [Table 4](#).

**TABLE 4** System message field description

Variable name	Description
Time Stamp	The system time (UTC) when the message was generated on the switch. The RASLog subsystem supports an internationalized time stamp format based on the "LOCAL" setting.
Event ID	The message module and number. These values uniquely identify each message in the Fabric OS and reference the cause and actions recommended in this manual. Note that not all message numbers are used; there can be gaps in the numeric message sequence.

# 1 Reading the system messages

**TABLE 4** System message field description (Continued)

Variable name	Description
Sequence Number	<p>The error message position in the log. When a new message is added to the log, this number is incremented by 1.</p> <p>The message sequence number starts at 1 after a <b>firmwareDownload</b> and will increase up to a value of 2,147,483,647 (0x7fffffff).</p> <p>The sequence number continues to increase after the message log wraps around, i.e. the oldest message in the log is deleted when a new message is added. The sequence number can be reset to 1 using the <b>errClear</b> command. The sequence number is persistent across power cycles and switch reboots.</p>
Flags	<p>For most messages, this field contains a space character (null value) indicating that the message is neither an AUDIT or FFDC message. Messages may contain the following values:</p> <ul style="list-style-type: none"><li>• FFDC – Indicates that additional first failure data capture information has also been generated for this event.</li><li>• FID – The Fabric ID that can range from 0 to 128. FID 128 means the message was generated by the default switch instance.</li><li>• CHASSIS – The message that was generated by the chassis instance.</li><li>• SLOT number – Indicates the message was generated from slot # blade main CPU.</li><li>• SLOT #/1 – Indicates the message was generated from slot # blade Co-CPU.</li></ul>
Severity Level	<p>The severity of the error, which can be one of the following:</p> <ul style="list-style-type: none"><li>• 1 – CRITICAL</li><li>• 2 – ERROR</li><li>• 3 – WARNING</li><li>• 4 – INFO</li></ul>
Switch name	<p>The defined switch name or the chassis name of the switch depending on the action; for example, high availability (HA) messages typically show the chassis name, and login failures show the logical switch name.</p> <p>This value is truncated if it exceeds 16 characters in length. Run either the <b>chassisName</b> command to name the chassis or the <b>switchName</b> command to rename the logical switch.</p>
Event-specific information	<p>A text string explaining the error encountered and providing parameters supplied by the software at runtime.</p>

## Reading an Audit message

Compared to RASLog error messages, messages flagged as AUDIT provide additional user and system-related information of interest for post-event auditing and troubleshooting the problem.

The following example shows the format of the Audit event message.

```
<Sequence Number> AUDIT, <timestamp>, [<Event ID>], <Severity>, <Event Class>,
<User ID>/<Role>/<IP address>/<Interface>/<Application Name>, <Admin
Domain>/<Switch name>, <Reserved field for future expansion>, <Event-specific
information>
```

The following is a sample Audit event message.

```
0 AUDIT, 2005/12/10-09:54:03, [SEC-1000], WARNING, SECURITY,
JohnSmith/root/192.0.2.2/Telnet/CLI, Domain A/JohnsSwitch, , Incorrect password
during login attempt.
```

The fields in the error message are described in [Table 5](#).

**TABLE 5** Audit message field description

Variable name	Description
Sequence Number	The error message position in the log.
Audit flag	Identifies the message as an Audit message.
Time Stamp	The system time (UTC) when the message was generated on the switch. The RASLog subsystem will support an internationalized time stamp format based on the "LOCAL" setting.
Event ID	The message module and number. These values uniquely identify each message in the Fabric OS and reference the cause and actions recommended in this manual. Note that not all message numbers are used; there can be gaps in the numeric message sequence.
Severity	The severity of the error, which can be one of the following: <ul style="list-style-type: none"> <li>• 1 – CRITICAL</li> <li>• 2 – ERROR</li> <li>• 3 – WARNING</li> <li>• 4 – INFO</li> </ul>
Event Class	The event class, which can be one of the following: <ul style="list-style-type: none"> <li>• CFG</li> <li>• CLI</li> <li>• FABRIC</li> <li>• FIRMWARE</li> <li>• FW</li> <li>• LS</li> <li>• MAPS (internal use only)</li> <li>• RAS</li> <li>• SECURITY</li> <li>• ZONE</li> </ul>
User ID	The user ID.
Role	The role of the user ID.
IP address	The IP address.
Interface	The interface being used.
Application Name	The application name being used on the interface.
Admin Domain	The Admin Domain, if there is one.
Switch name	The defined switch name or the chassis name of the switch depending on the action; for example, HA messages typically show the chassis name and login failures show the logical switch name. This value is truncated if it is over 16 characters in length. Execute the <b>chassisName</b> command to name the chassis or the <b>switchName</b> command to rename the logical switch.
Reserved field for future expansion	This field is reserved for future use and contains a space character (null value).
Event-specific information	A text string explaining the error encountered and providing parameters supplied by the software at runtime.

## Responding to a system message

This section provides procedures on gathering information on system messages.

### Looking up a system message

Messages in this manual are arranged alphabetically by Module ID, and then numerically within a given module. To look up a message, copy down the module (see Table 6 on page 28) and the error code and compare this with the Table of Contents or look up lists to determine the location of the information for that message.

The following information is provided for each message:

- Module and code name for the error
- Message text
- Message type
- Class (for Audit messages only)
- Message severity
- Probable cause
- Recommended action

### Gathering information about the problem

Questions to ask yourself when troubleshooting a system message are as follows:

- What is the current Fabric OS level?
- What is the switch hardware version?
- Is the switch operational?
- Assess impact and urgency:
  - Is the switch down?
  - Is it a standalone switch?
  - How large is the fabric?
  - Is the fabric redundant?
- Execute the **errDump** command on each logical switch.
- Execute the **supportFtp** command (as needed) to set up automatic FTP transfers, and then run the **supportSave** command.
- Document the sequence of events by answering the following questions:
  - What happened just prior to the problem?
  - Is the problem repeatable?
  - If so, what are the steps to produce the problem?
  - What configuration was in place when the problem occurred?
- Did a failover occur?
- Was security enabled?
- Was POST enabled?

- Are serial port (console) logs available?
- Which CP was master?
- What and when were the last actions or changes made to the system?

Common steps to be followed when troubleshooting a system message are as follows:

- Execute the **errDump** command on each logical switch.
- Execute the **supportFtp** command (as needed) to set up automatic FTP transfers, and then execute the **supportSave** command.

## Support

Fabric OS creates a number of files that can help support personnel troubleshoot and diagnose a problem. This section describes those files and how to access or save the information for support personnel.

### *Panic dump and core dump files*

The Fabric OS creates panic dump files and core files when there are problems in the Fabric OS kernel. You can view panic dump files using the **pdShow** command. These files can build up in the kernel partition (typically because of failovers) and might need to be periodically deleted or downloaded using the **supportSave** command.

The software watchdog process (SWD) is responsible for monitoring daemons critical to the function of a healthy switch. The SWD holds a list of critical daemons that ping the SWD periodically at a predetermined interval defined for each daemon. The ping interval is set at 133 seconds, with the exception of the Fabric Watch daemon and the IP storage demon, which ping the SWD every 333 seconds. (For a complete listing of daemons, refer to the KSWD entry in [Table 6](#).)

If a daemon fails to ping the SWD within the defined interval, or if the daemon terminates unexpectedly, then the SWD dumps information to the panic dump files, which helps to diagnose the root cause of the unexpected failure.

Execute the **pdShow** command to view these files or the **supportSave** command to send them to a host workstation using FTP. The panic dump files and core files are intended for support personnel use only.

### *Trace dumps*

The Fabric OS produces trace dumps when problems are encountered within Fabric OS modules. The Fabric OS trace dump files are intended for support personnel use only. You can use the **supportSave** or **supportFTP** commands to collect trace dump files to a specified remote location to provide to support when requested.

### *supportSave command*

The **supportSave** command can be used to send the output of the system messages (RASLog), the trace files, and the output of the **supportShow** command to an off-switch storage location through FTP. Prior to running the **supportSave** command, you can optionally set up the FTP parameters using the **supportFtp** command. The **supportShow** command runs a large number of dump and show commands to provide a global output of the status of the switch. Refer to the *Fabric OS Command Reference* for more information on these commands.

## System module descriptions

Table 6 provides a summary of the system modules for which messages are documented in this guide; the system modules are listed alphabetically by name. A module is a subsystem in the Fabric OS. Each module generates a set of numbered messages.

**TABLE 6** System module descriptions

System module	Description
AG	Access Gateway (AG) allows multiple hosts (or HBAs) to access the fabric using fewer physical ports. Access Gateway mode transforms the Brocade switches as well as embedded switches into a device management tool that is compatible with different types of fabrics, including Brocade-, Cisco-, and McDATA-based fabrics.
AN	Error or warning messages from the Bottleneck Detection module, including notification of detected bottlenecks.
ANV	ANV error messages indicate problems with the driver that deal with the ENET application-specific integrated circuits (ASICs) on the Fabric OS. They can be software- or hardware-related errors.
AUTH	Authentication error messages indicate problems with the authentication module of the Fabric OS.
BKSW	BKSW messages are generated by the Fabric OS blade kernel software watchdog module.
BL	BL error messages are a result of faulty hardware, transient out-of-memory conditions, ASIC errors, or inconsistencies in the software state between a blade and the environment monitor (EM) module.
BLS	Fibre Channel over IP port configuration messages over the Brocade 7800 and FX8-24 blade.
BM	Blade management error messages are a result of autoleveling firmware upgrades performed by the control processor (CP).
C2	C2 error messages indicate problems with the 8 Gbps-capable FC module of the Fabric OS.
C3	C3 error messages indicate problems with the 16 Gbps-capable FC module of the Fabric OS.
CAL	Common Access Layer (CAL) provides XML interface for configuring switch parameters in an object model.
CCFG	CCFG error messages indicate problems with the Converged Enhanced Ethernet (CEE) configuration module of the Fabric OS.
CDR	Driver error messages.
CHS	Error messages reporting the problems in the management of the blades in the different slots of the chassis.
CNM	Cluster Node Manager (CNM) is a software daemon module of the Fabric OS. The messages from CNM are problems encountered by CNM, warnings, or information to the user of events.
CONF	Status messages for <b>configUpload</b> and <b>configDownload</b> operations.
CTAP	A user-space daemon that forwards non-performance-critical messages from the TAPE driver to the Crypto Virtual LUN Controller (CVLC) and Security Processor (SP), and vice versa. This module also maintains a cache of recently acquired keys, reducing requests to the key vault itself.
CVLC	Crypto Virtual LUN Controller (CVLC) is a software module running on blade FOS (BFOS). The messages of CVLC are problems encountered by CVLC, warnings to alert the user, or information to the user.
CVLM	Crypto Virtual LUN Manager (CVLM) is a software module of the Fabric OS. The messages of CVLM are problems encountered by CVLM, warnings to alert the user, or information to the user.
DOT1	DOT1 error messages indicate problems with the 802.1x authentication module of the Fabric OS.

**TABLE 6** System module descriptions (Continued)

System module	Description
ECC	Error Checking and Correction (ECC) error messages indicate single-bit and multiple-bit errors in the Dynamic Random Access Memory (DRAM) devices. ECC is a technology that helps to correct memory errors.
EM	The environmental monitor (EM) manages and monitors the various field-replaceable units (FRUs), including the port cards, control processor (CP) blades, blower assemblies, power supplies, and World Wide Name (WWN) cards. EM controls the state of the FRUs during system startup, hot-plug sequences, and fault recovery. EM provides access to and monitors the sensor and status data from the FRUs and maintains the integrity of the system using the environmental and power policies. EM reflects system status by CLI commands, system light emitting diodes (LEDs), and status and alarm messages. EM also manages some component-related data.
ESS	Exchange Switch Support (ESS) error messages indicate problems with the ESS module of the Fabric OS. ESS is an SW_ILS mechanism utilized by switches to exchange vendor and support information.
ESW	ESW error messages indicate problems with the Ethernet switch module of Fabric OS.
EVMD	EVMD is the event management module.
FABR	FABRIC refers to a network of Fibre Channel switches. The FABR error messages come from the fabric daemon. The fabric daemon follows the FC-SW-3 standard for the fabric initialization process, such as determining the E_Ports, assigning unique domain IDs to switches, creating a spanning tree, throttling the trunking process, and distributing the domain and alias lists to all switches in the fabric.
FABS	Fabric OS system driver module.
FBC	Firmware blade compatibility errors with the control processor (CP).
FCMC	Fibre Channel miscellaneous messages relate to problems with the physical layer used to send Fibre Channel traffic to and from the switch.
FCOE	FCoE error messages indicate problems with the FCoE module of the Fabric OS.
FCPD	The Fibre Channel Protocol daemon is responsible for probing the devices attached to the loop port. Probing is a process the switch uses to find the devices attached to the loop ports and to update the Name Server with the information.
FCPH	The Fibre Channel Physical Layer is used to send Fibre Channel traffic to and from the switch.
FCR	Fibre Channel router-related traffic and activity on the fabric or back-end fabric.
FICN	The FICN messages are generated during FICON emulation processing on an FCIP Tunnel.
FICU	The FICON-CUP daemon handles communication with fibre connectivity (FICON) on IBM FICON storage devices. Errors to this module are usually initiation errors or indications that FICON-CUP prerequisites have not been met, such as a license key, core process ID (PID), and secure mode on the fabric.
FKLB	Fabric OS I/O kernel library module.
FLOD	FLOD is a part of the Fabric Shortest Path First (FSPF) protocol that handles synchronization of the link state database (LSDB) and propagation of the link state records (LSRs).
FSPF	Fabric Shortest Path First (FSPF) is a link state routing protocol that is used to determine how frames should be routed. These messages are about protocol errors.

# 1 System module descriptions

**TABLE 6** System module descriptions (Continued)

System module	Description
FSS	The Fabric OS state synchronization framework provides facilities by which the active control processor (CP) can synchronize with the standby CP, enabling the standby CP to take control of the switch nondisruptively during failures and software upgrades. These facilities include version negotiation, state information transfer, and internal synchronization functions, enabling the transition from standby to active operation. FSS is defined both as a component and a service. A <i>component</i> is a module in the Fabric OS, implementing a related set of functionality. A <i>service</i> is a collection of components grouped together to achieve a modular software architecture.
FSSM	The Fabric OS state synchronization management module is defined both as a component and a service. A <i>component</i> is a module in Fabric OS, implementing a related set of functionality. A <i>service</i> is a collection of components grouped together to achieve a modular software architecture.
FW	FW is the Fabric Watch module. This module monitors thresholds for many switch subsystems; for example, temperature, voltage, fan speed, and switch status. Any changes that cross a specified threshold are reported to the system message log.
HAM	HAM is a user-space daemon responsible for high availability management.
HAMK	This is the kernel module for the high availability management (HAM) daemon.
HIL	Hardware independent layer.
HLO	HLO is a part of the Fabric Shortest Path First (FSPF) protocol that handles the HELLO protocol between adjacent switches. The HELLO protocol is used to establish connectivity with a neighbor switch, to establish the identity of the neighbor switch, and to exchange FSPF parameters and capabilities.
HMON	Health monitor.
HSL	HSL error messages indicate problems with the Hardware Subsystem Layer of the Fabric OS.
HTTP	HTTP error messages.
IBD	IBD generates messages related to port restart failure.
IPAD	System messages generated by the IP admin demon.
IPS	Fibre Channel over IP license, tunneling, and port-related messages.
ISNS	ISNS server and client status messages.
KAC	KAC error messages indicate problems associated with Fabric OS and the external key vaults.
KSWD	The kernel software watchdog (KSWD) watches daemons for unexpected terminations and “hang” conditions and informs the HAM module to take corrective actions such as failover or reboot. The following daemons are monitored by KSWD: <ul style="list-style-type: none"> <li>• Access Gateway daemon (agd)</li> <li>• Alias Server daemon (asd)</li> <li>• ARR daemon (arrd)</li> <li>• Authentication daemon (authd)</li> <li>• Blade Manager daemon (bmd)</li> <li>• Cluster Node Manager daemon (cnmd)</li> <li>• Common Access Layer daemon (cald)</li> <li>• DAUTH daemon (dauthd)</li> <li>• Diagnostics daemon (diagd)</li> <li>• Environment Monitor daemon (emd)</li> <li>• Event Manager daemon (evmd)</li> <li>• Exchange Switch Support daemon (essd)</li> <li>• FA-API rpc daemon (rpcd)</li> </ul>



**TABLE 6** System module descriptions (Continued)

System module	Description
KSWD (continued)	<ul style="list-style-type: none"> <li>• Fabric daemon (fabricd)</li> <li>• Fabric Device Management Interface daemon (fdmid)</li> <li>• Fabric Watch daemon (fwd)</li> <li>• FCoE daemon (fcoed)</li> <li>• Fibre Channel Protocol daemon (fcpd)</li> <li>• FICON CUP daemon (ficud)</li> <li>• FSPF daemon (fspfd)</li> <li>• IGMP daemon (igmpd)</li> <li>• IMI daemon (imid)</li> <li>• Inter-fabric Routing daemon (iswitchd)</li> <li>• IP Storage daemon (ipsd)</li> <li>• ISNS client daemon on CP (isnscd)</li> <li>• KAC daemon (kacd)</li> <li>• Layer 2 System daemon (l2sysd)</li> <li>• LFM daemon (lfmd)</li> <li>• Link Aggregation Control Protocol daemon (lacpd)</li> <li>• Management Server daemon (msd)</li> <li>• MM daemon (mmd)</li> <li>• Multicast Sub-System daemon (mcast_ssd)</li> <li>• Multiple Spanning Tree Protocol daemon (mstpd)</li> <li>• Name Server daemon (nsd)</li> <li>• NSM daemon (nsm)</li> <li>• ONM daemon (onmd)</li> <li>• Parity data manager daemon (pdmd)</li> <li>• Proxy daemon (proxyd)</li> <li>• PS daemon (psd)</li> <li>• RASLOG daemon (raslogd)</li> <li>• RCS daemon (rcsd)</li> <li>• RM daemon (rmd)</li> <li>• RMON daemon (rmond)</li> <li>• Security daemon (secd)</li> <li>• Sigma daemon (sigmad)</li> <li>• SNMP daemon (snmpd)</li> <li>• SP management daemon (spmd)</li> <li>• SVP daemon (svpd)</li> <li>• System services module daemon (ssmd)</li> <li>• Time Service daemon (tsd)</li> <li>• TRACE daemon (traced)</li> <li>• Traffic daemon (trafd)</li> <li>• VS daemon (vsd)</li> <li>• Web linker daemon (weblinkerd)</li> <li>• Web Tools daemon (webd)</li> <li>• ZONE daemon (zoned)</li> </ul>
KTRC	Kernel RAS trace module.
L2SS	L2SYS error messages indicate problems with the Layer 2 System manager that controls the Layer 2 forwarding engine and controls the learning/aging/forwarding functionality.
LACP	LACP error messages indicate problems with the Link Aggregation Control Protocol module of the Fabric OS.
LANCE	LANCE error messages indicate problems with the LANCE module of the Fabric OS.

# 1 System module descriptions

**TABLE 6** System module descriptions (Continued)

System module	Description
LFM	LFM error messages indicate problems with the logical fabric manager module that is responsible for making a logical switch use XISLs. This involves creating and managing LISLs in a logical fabric.
LOG	RASLog subsystem.
LSDB	The link state database is a part of the FSPF protocol that maintains records on the status of port links. This database is used to route frames.
MCAST_SS	The Multicast Sub-System messages indicate any problems associated with the Layer 2 and Layer 3 Multicast platform support, including allocation of global platform resources such as MGIDs, hardware acceleration resources for Multicast, and route programming into the hardware (Layer 2 EXM for IGMP Snooping).
MFIC	MS-FICON messages relate to Fibre Connection (FICON) installations. Fibre Connection control unit port (FICON-CUP) messages are displayed under the FICU module.
MM	MM message indicate problems with the management modules.
MPTH	Multicast path uses the shortest path first (SPF) algorithm to dynamically compute a broadcast tree.
MQ	Message queues are used for interprocess communication. Message queues allow many messages, each of variable length, to be queued. Any process or interrupt service routine (ISR) can write messages to a message queue. Any process can read messages from a message queue.
MS	The Management Service enables the user to obtain information about the Fibre Channel fabric topology and attributes by providing a single management access point. MS provides for both monitoring and control of the following areas: <ul style="list-style-type: none"> <li>• <b>Fabric Configuration Server:</b> Provides for the configuration management of the fabric.</li> <li>• <b>Unzoned Name Server:</b> Provides access to Name Server information that is not subject to zone constraints.</li> <li>• <b>Fabric Zone Server:</b> Provides access to and control of zone information.</li> </ul>
MSTP	MSTP error messages indicate problems with Multiple Spanning Tree Protocol modules of the Fabric OS.
NBFSM	NBFSM is a part of the Fabric Shortest Path First (FSPF) protocol that handles a neighboring or adjacent switch's finite state machine (FSM). Input to the FSM changes the local switch from one state to another, based on specific events. For example, when two switches are connected to each other using an interswitch link (ISL) cable, they are in the Init state. After both switches receive HELLO messages, they move to the Database Exchange state, and so on. NBFSM states are Down (0), Init (1), Database Exchange (2), Database Acknowledge Wait (3), Database Wait (4), and Full (5).
NS	Indicates problems with the simple Name Server module.
NSM	NSM error messages indicate problems with the Interface Management and VLAN Management module of the Fabric OS.
ONMD	ONMD error messages indicate problems with the Operation, Administration and Maintenance module of the Fabric OS.
PDM	Parity data manager (PDM) is a user-space daemon responsible for the replication of persistent configuration files from the primary partition to the secondary partition and from the active CP blade to the standby CP blade.
PDTR	PDTR messages indicate panic dump trace files have been created.
PLAT	PLAT messages indicate hardware problems.
PMGR	A group of messages relating to logical switch creation, deletion, and configuration.

**TABLE 6** System module descriptions (Continued)

System module	Description
PORT	PORT error messages refer to the front-end user ports on the switch. Front-end user ports are directly accessible by users to connect end devices or connect to other switches.
PS	The performance server daemon measures the amount of traffic between endpoints or traffic with particular frame formats, such as SCSI frames, IP frames, and customer-defined frames.
PSWP	The portswap feature and associated commands generate these error messages.
RAS	Informational messages when first failure data capture (FFDC) events are logged to the FFDC log and size or roll-over warning.
RCS	The reliable commit service daemon generates log entries when it receives a request from the zoning, security, or management server for passing data messages to switches in the fabric. RCS then requests reliable transport write and read (RTWR) to deliver the message. RCS also acts as a gatekeeper, limiting the number of outstanding requests for the Zoning, Security, or Management Server modules.
RKD	These messages are either error or informational messages pertaining to the re-key daemon of the Fabric OS.
RMON	RMON messages are error or informational messages pertaining to the RMOND daemon.
RPCD	The remote procedure call daemon (RPCD) is used by Fabric Access for API-related tasks.
RTE	RTE is responsible for determining the correct paths for each ingress frame and populating the routing tables in the ASICs with this information. The ASIC then uses the information available in the routing tables to determine the path a particular ingress frame needs to take before it exits the switch.
RTWR	The reliable transport write and read daemon helps deliver data messages either to specific switches in the fabric or to all of the switches in the fabric. For example, if some of the switches are not reachable or are offline, RTWR returns an "unreachable" message to the caller, allowing the caller to take the appropriate action. If a switch is not responding, RTWR retries 100 times.
SCN	The internal state change notification daemon is used for state change notifications from the kernel to the daemons within Fabric OS.
SEC	The security daemon generates security errors, warnings, or information during security-related data management or fabric merge operations. Administrators should watch for these messages to distinguish between internal switch and fabric operation errors and external attacks.
SFLO	sFlow is a standard-based sampling technology embedded within switches and routers, which is used to monitor high-speed network traffic for Data Center Ethernet (DCE) and Converged Enhanced Ethernet (CEE) platforms. sFlow uses two types of sampling: <ul style="list-style-type: none"> <li>• Statistical packet-based sampling of switched or routed packet flows.</li> <li>• Time-based sampling of interface counters.</li> </ul> SFLO messages indicate errors or information related to the sflowd daemon.
SNMP	Simple Network Management Protocol (SNMP) is a universally supported low-level protocol that allows simple get, get next, and set requests to go to the switch (acting as an SNMP agent). It also allows the switch to send traps to the defined and configured management station. Brocade switches support six management entities that can be configured to receive these traps.
SPC	SPC messages indicate problems and informational updates associated with the security processor. These messages could be triggered by the following three modules: Security processor controller, SP system controller, and SP Keyapp.
SPM	Error messages indicating problems either with key or SP management.
SS	The <b>supportSave</b> command generates these error messages if problems are encountered.

# 1 System module descriptions

**TABLE 6** System module descriptions (Continued)

System module	Description
SSMD	SSMD error messages indicate problems with the System Services Module of the Fabric OS.
SULB	The software upgrade library provides the <b>firmwareDownload</b> command capability, which enables firmware upgrades to both CP blades with a single command, as well as nondisruptive code load to all Fabric OS switches. These messages might display if there are any problems during the <b>firmwareDownload</b> procedure. Most messages are informational only and are generated even during successful firmware download. For additional information, refer to the <i>Fabric OS Administrator's Guide</i> .
SWCH	These messages are generated by the switch driver module that manages a Fibre Channel switch instance.
SYSC	System controller is a daemon that starts up and shuts down all Fabric OS modules in the proper sequence.
SYSM	General system messages.
TAPE	A kernel-space driver that handles all I/O operations aimed at Tape containers.
TRCE	RAS TRACE error messages.
TRCK	<p>The track change feature tracks the following events:</p> <ul style="list-style-type: none"> <li>• Turning on or off the track change feature</li> <li>• CONFIG_CHANGE</li> <li>• LOGIN</li> <li>• LOGOUT</li> <li>• FAILED_LOGIN</li> </ul> <p>If any of these events occur, a message is sent to the system message log. Additionally, if the SNMP trap option is enabled, an SNMP trap is also sent.</p> <p>For information on configuring the track change feature, refer to the <i>Fabric OS Command Reference</i> or the <i>Fabric OS Administrator's Guide</i>.</p>
TS	Time Service provides fabric time-synchronization by synchronizing all clocks in the fabric to the clock time on the principal switch.
UCST	UCST is a part of the Fabric Shortest Path First (FSPF) protocol that manages the Unicast routing table.
UPATH	UPATH is a part of the FSPF protocol that uses the SPF algorithm to dynamically compute a Unicast tree.
VDR	VDR messages indicate Field-Programmable Gate Array (FPGA) parity errors.
VS	The VS module messages indicate any problems or information associated with the Dynamic Fabric Provisioning feature, including commands associated with the <b>fapwnn</b> command and configurations.
WEBD	Indicates problems with the Web Tools module.
XTUN	XTUN messages are generated by the FCIP Tunnel implementation. These messages indicate status of FCIP tunnels, FCIP emulation events for FCP traffic, or FCIP debug information (FTRACE buffer status changes).
ZEUS	Zeus error messages indicate problems with the Zeus driver module.
ZONE	The zone module messages indicate any problems associated with the zoning features, including commands associated with aliases, zones, and configurations.

# Log Messages

---

## AG Messages

[AG-1001](#)

[AG-1002](#)

[AG-1003](#)

[AG-1004](#)

[AG-1005](#)

[AG-1006](#)

[AG-1007](#)

[AG-1008](#)

[AG-1009](#)

[AG-1010](#)

[AG-1011](#)

[AG-1012](#)

[AG-1013](#)

[AG-1014](#)

[AG-1015](#)

[AG-1016](#)

[AG-1017](#)

[AG-1018](#)

[AG-1019](#)

[AG-1020](#)

[AG-1021](#)

[AG-1022](#)

[AG-1023](#)

[AG-1024](#)

[AG-1025](#)

[AG-1026](#)

[AG-1027](#)

[AG-1028](#)

## 2 AN Messages

AG-1029  
AG-1030  
AG-1031  
AG-1032  
AG-1033  
AG-1034  
AG-1035  
AG-1036  
AG-1037  
AG-1038  
AG-1039  
AG-1040  
AG-1041  
AG-1042  
AG-1043  
AG-1044

### AN Messages

AN-1001  
AN-1002  
AN-1003  
AN-1004  
AN-1005  
AN-1010  
AN-1011  
AN-1012  
AN-1013

### ANV Messages

ANV-1001  
ANV-1002  
ANV-1003  
ANV-1004  
ANV-1005

ANV-1006

ANV-1007

ANV-1008

ANV-1015

ANV-1016

ANV-1028

## AUTH Messages

AUTH-1001

AUTH-1002

AUTH-1003

AUTH-1004

AUTH-1005

AUTH-1006

AUTH-1007

AUTH-1008

AUTH-1010

AUTH-1011

AUTH-1012

AUTH-1013

AUTH-1014

AUTH-1016

AUTH-1017

AUTH-1018

AUTH-1020

AUTH-1022

AUTH-1023

AUTH-1025

AUTH-1026

AUTH-1027

AUTH-1028

AUTH-1029

AUTH-1030

AUTH-1031

AUTH-1032

## 2 BKSW Messages

AUTH-1033  
AUTH-1034  
AUTH-1035  
AUTH-1036  
AUTH-1037  
AUTH-1038  
AUTH-1039  
AUTH-1040  
AUTH-1041  
AUTH-1042  
AUTH-1043  
AUTH-1044  
AUTH-1045  
AUTH-1046  
AUTH-1047

### **BKSW Messages**

BKSW-1003

### **BL Messages**

BL-1000  
BL-1001  
BL-1002  
BL-1003  
BL-1004  
BL-1006  
BL-1007  
BL-1008  
BL-1009  
BL-1010  
BL-1011  
BL-1012  
BL-1013  
BL-1014



BL-1015

BL-1016

BL-1017

BL-1018

BL-1019

BL-1020

BL-1021

BL-1022

BL-1023

BL-1024

BL-1025

BL-1026

BL-1027

BL-1028

BL-1029

BL-1030

BL-1031

BL-1032

BL-1033

BL-1034

BL-1035

BL-1036

BL-1037

BL-1038

BL-1039

BL-1041

BL-1045

BL-1046

BL-1047

BL-1048

BL-1049

BL-1050

BL-1051

BL-1052

## **BLS Messages**

BLS-1000  
BLS-1001  
BLS-1002  
BLS-1003  
BLS-1004  
BLS-1005

## **BM Messages**

BM-1001  
BM-1002  
BM-1003  
BM-1004  
BM-1005  
BM-1006  
BM-1007  
BM-1008  
BM-1009  
BM-1010  
BM-1053  
BM-1054  
BM-1055  
BM-1056  
BM-1058

## **C2 Messages**

C2-1001  
C2-1002  
C2-1004  
C2-1006  
C2-1007  
C2-1008  
C2-1009  
C2-1010

C2-1012  
C2-1013  
C2-1014  
C2-1015  
C2-1016  
C2-1017  
C2-1018  
C2-1019  
C2-1025  
C2-1026  
C2-1027  
C2-1028

## C3 Messages

C3-1001  
C3-1002  
C3-1004  
C3-1006  
C3-1007  
C3-1008  
C3-1009  
C3-1010  
C3-1011  
C3-1012  
C3-1013  
C3-1014  
C3-1015  
C3-1016  
C3-1017  
C3-1018  
C3-1019  
C3-1020  
C3-1021  
C3-1023  
C3-1025

## 2 CAL Messages

[C3-1026](#)

[C3-1027](#)

[C3-1028](#)

### CAL Messages

[CAL-1001](#)

### CCFG Messages

[CCFG-1001](#)

[CCFG-1002](#)

[CCFG-1003](#)

[CCFG-1004](#)

[CCFG-1005](#)

[CCFG-1006](#)

[CCFG-1007](#)

[CCFG-1008](#)

[CCFG-1009](#)

[CCFG-1010](#)

[CCFG-1011](#)

[CCFG-1012](#)

### CDR Messages

[CDR-1001](#)

[CDR-1002](#)

[CDR-1003](#)

[CDR-1004](#)

[CDR-1005](#)

[CDR-1006](#)

[CDR-1007](#)

[CDR-1008](#)

[CDR-1009](#)

[CDR-1010](#)

[CDR-1011](#)

[CDR-1012](#)

CDR-1014

CDR-1015

CDR-1016

CDR-1017

CDR-1018

CDR-1019

CDR-1022

CDR-1028

## CHS Messages

CHS-1002

CHS-1003

CHS-1004

CHS-1005

## CNM Messages

CNM-1001

CNM-1002

CNM-1003

CNM-1004

CNM-1005

CNM-1006

CNM-1007

CNM-1008

CNM-1009

CNM-1010

CNM-1011

CNM-1012

CNM-1013

CNM-1014

CNM-1015

CNM-1016

CNM-1017

CNM-1018

## 2 CNM Messages

CNM-1019  
CNM-1020  
CNM-1021  
CNM-1022  
CNM-1023  
CNM-1024  
CNM-1025  
CNM-1026  
CNM-1027  
CNM-1028  
CNM-1029  
CNM-1030  
CNM-1031  
CNM-1032  
CNM-1033  
CNM-1034  
CNM-1035  
CNM-1036  
CNM-1037  
CNM-1038  
CNM-1039  
CNM-1040  
CNM-1041  
CNM-1042  
CNM-1043  
CNM-1044  
CNM-1045  
CNM-1046  
CNM-1047  
CNM-1048  
CNM-1049  
CNM-1050  
CNM-1051  
CNM-1052  
CNM-1053

CNM-1054  
CNM-1055  
CNM-1056  
CNM-1057  
CNM-1058  
CNM-1059  
CNM-1060  
CNM-1061  
CNM-1062  
CNM-3001  
CNM-3002  
CNM-3003  
CNM-3004  
CNM-3005  
CNM-3006  
CNM-3007  
CNM-3008  
CNM-3009  
CNM-3010  
CNM-3011  
CNM-3012

## CONF Messages

CONF-1000  
CONF-1001  
CONF-1021  
CONF-1023  
CONF-1024  
CONF-1030  
CONF-1031  
CONF-1032  
CONF-1040  
CONF-1041  
CONF-1042  
CONF-1043

## 2 CTAP Messages

[CONF-1044](#)

### CTAP Messages

[CTAP-1001](#)

### CVLC Messages

[CVLC-1001](#)

[CVLC-1002](#)

[CVLC-1003](#)

[CVLC-1004](#)

[CVLC-1005](#)

[CVLC-1006](#)

[CVLC-1007](#)

[CVLC-1008](#)

[CVLC-1009](#)

[CVLC-1010](#)

[CVLC-1011](#)

[CVLC-1012](#)

[CVLC-1013](#)

[CVLC-1014](#)

[CVLC-1015](#)

[CVLC-1016](#)

[CVLC-1017](#)

[CVLC-1018](#)

[CVLC-1019](#)

[CVLC-1020](#)

[CVLC-1021](#)

[CVLC-1022](#)

[CVLC-1023](#)

[CVLC-1024](#)

[CVLC-1025](#)

[CVLC-1026](#)

[CVLC-1027](#)

[CVLC-1028](#)



CVLC-1029  
CVLC-1030  
CVLC-1031  
CVLC-1032  
CVLC-1033  
CVLC-1034  
CVLC-1035  
CVLC-1039  
CVLC-1041

## CVLM Messages

CVLM-1001  
CVLM-1002  
CVLM-1003  
CVLM-1004  
CVLM-1005  
CVLM-1006  
CVLM-1007  
CVLM-1008  
CVLM-1009  
CVLM-1010  
CVLM-1011  
CVLM-1012  
CVLM-1013  
CVLM-1014  
CVLM-1015  
CVLM-1016  
CVLM-3001  
CVLM-3002  
CVLM-3003  
CVLM-3004  
CVLM-3005  
CVLM-3006  
CVLM-3007  
CVLM-3008

## 2 DOT1 Messages

CVLM-3009  
CVLM-3010  
CVLM-3011  
CVLM-3012  
CVLM-3013  
CVLM-3014  
CVLM-3015  
CVLM-3016  
CVLM-3017  
CVLM-3018  
CVLM-3019  
CVLM-3020  
CVLM-3021  
CVLM-3022  
CVLM-3023  
CVLM-3024  
CVLM-3025  
CVLM-3026  
CVLM-3027  
CVLM-3028

### DOT1 Messages

DOT1-1001  
DOT1-1002  
DOT1-1003  
DOT1-1004  
DOT1-1005  
DOT1-1006  
DOT1-1007  
DOT1-1008  
DOT1-1009  
DOT1-1010

## ECC Messages

[ECC-1000](#)

[ECC-1001](#)

## EM Messages

[EM-1001](#)

[EM-1002](#)

[EM-1003](#)

[EM-1004](#)

[EM-1005](#)

[EM-1006](#)

[EM-1008](#)

[EM-1009](#)

[EM-1010](#)

[EM-1011](#)

[EM-1012](#)

[EM-1013](#)

[EM-1014](#)

[EM-1015](#)

[EM-1016](#)

[EM-1017](#)

[EM-1018](#)

[EM-1019](#)

[EM-1020](#)

[EM-1028](#)

[EM-1029](#)

[EM-1031](#)

[EM-1033](#)

[EM-1034](#)

[EM-1035](#)

[EM-1036](#)

[EM-1037](#)

[EM-1042](#)

[EM-1043](#)

## 2 ESS Messages

EM-1044  
EM-1045  
EM-1046  
EM-1047  
EM-1048  
EM-1049  
EM-1050  
EM-1051  
EM-1057  
EM-1058  
EM-1059  
EM-1060  
EM-1061  
EM-1062  
EM-1063  
EM-1064  
EM-1065  
EM-1066  
EM-1067  
EM-1068  
EM-1069  
EM-1070  
EM-1071  
EM-1072  
EM-2003

### ESS Messages

ESS-1001  
ESS-1002  
ESS-1003  
ESS-1004  
ESS-1005  
ESS-1008  
ESS-1009  
ESS-1010

## ESW Messages

ESW-1001  
ESW-1002  
ESW-1003  
ESW-1004  
ESW-1005  
ESW-1006  
ESW-1007  
ESW-1008

## EVMD Messages

EVMD-1001

## FABR Messages

FABR-1001  
FABR-1002  
FABR-1003  
FABR-1004  
FABR-1005  
FABR-1006  
FABR-1007  
FABR-1008  
FABR-1009  
FABR-1010  
FABR-1011  
FABR-1012  
FABR-1013  
FABR-1014  
FABR-1015  
FABR-1016  
FABR-1017  
FABR-1018  
FABR-1019  
FABR-1020

## 2 FABS Messages

FABR-1021  
FABR-1022  
FABR-1023  
FABR-1024  
FABR-1029  
FABR-1030  
FABR-1031  
FABR-1032  
FABR-1034  
FABR-1035  
FABR-1036  
FABR-1037  
FABR-1038  
FABR-1039  
FABR-1040  
FABR-1041  
FABR-1043  
FABR-1044  
FABR-1045  
FABR-1046  
FABR-1047  
FABR-1048  
FABR-1049  
FABR-1050  
FABR-1051  
FABR-1052  
FABR-1053  
FABR-1054  
FABR-1055

### FABS Messages

FABS-1001  
FABS-1002  
FABS-1004  
FABS-1005

FABS-1006

FABS-1007

FABS-1008

FABS-1009

FABS-1010

FABS-1011

FABS-1013

FABS-1014

FABS-1015

## FBC Messages

FBC-1001

## FCCM Messages

FCCM-1001

## FCOE Messages

FCOE-1001

FCOE-1002

FCOE-1003

FCOE-1004

FCOE-1005

FCOE-1006

FCOE-1007

FCOE-1009

FCOE-1010

FCOE-1012

FCOE-1014

FCOE-1015

FCOE-1016

FCOE-1017

FCOE-1019

FCOE-1021

FCOE-1022

## 2 FCPD Messages

[FCOE-1023](#)

[FCOE-1024](#)

[FCOE-1025](#)

[FCOE-1026](#)

[FCOE-1027](#)

[FCOE-1028](#)

[FCOE-1029](#)

[FCOE-1030](#)

[FCOE-1031](#)

[FCOE-1032](#)

[FCOE-1033](#)

[FCOE-1034](#)

[FCOE-1037](#)

[FCOE-1038](#)

[FCOE-1039](#)

[FCOE-1040](#)

[FCOE-1041](#)

[FCOE-1042](#)

[FCOE-1043](#)

[FCOE-1044](#)

[FCOE-1045](#)

[FCOE-1046](#)

[FCOE-1047](#)

[FCOE-1048](#)

### FCPD Messages

[FCPD-1001](#)

[FCPD-1002](#)

[FCPD-1003](#)

### FCPH Messages

[FCPH-1001](#)

[FCPH-1002](#)

[FCPH-1003](#)



FCPH-1004

FCPH-1005

## FCR Messages

FCR-1001

FCR-1002

FCR-1003

FCR-1004

FCR-1005

FCR-1006

FCR-1007

FCR-1008

FCR-1009

FCR-1010

FCR-1011

FCR-1012

FCR-1013

FCR-1015

FCR-1016

FCR-1018

FCR-1019

FCR-1020

FCR-1021

FCR-1022

FCR-1023

FCR-1024

FCR-1025

FCR-1026

FCR-1027

FCR-1028

FCR-1029

FCR-1030

FCR-1031

FCR-1032

FCR-1033

## 2 FCR Messages

FCR-1034  
FCR-1035  
FCR-1036  
FCR-1037  
FCR-1038  
FCR-1039  
FCR-1040  
FCR-1041  
FCR-1042  
FCR-1043  
FCR-1048  
FCR-1049  
FCR-1053  
FCR-1054  
FCR-1055  
FCR-1056  
FCR-1057  
FCR-1058  
FCR-1059  
FCR-1060  
FCR-1061  
FCR-1062  
FCR-1063  
FCR-1064  
FCR-1065  
FCR-1066  
FCR-1067  
FCR-1068  
FCR-1069  
FCR-1070  
FCR-1071  
FCR-1072  
FCR-1073  
FCR-1074  
FCR-1075

FCR-1076  
FCR-1077  
FCR-1078  
FCR-1079  
FCR-1080  
FCR-1081  
FCR-1082  
FCR-1083  
FCR-1084  
FCR-1085  
FCR-1086  
FCR-1087  
FCR-1088  
FCR-1089  
FCR-1091  
FCR-1092  
FCR-1093  
FCR-1094  
FCR-1095  
FCR-1096  
FCR-1097  
FCR-1098

## FICN Messages

FICN-1003  
FICN-1004  
FICN-1005  
FICN-1006  
FICN-1007  
FICN-1008  
FICN-1009  
FICN-1010  
FICN-1011  
FICN-1012  
FICN-1013

## 2 FICN Messages

FICN-1014  
FICN-1015  
FICN-1016  
FICN-1017  
FICN-1018  
FICN-1019  
FICN-1020  
FICN-1021  
FICN-1022  
FICN-1023  
FICN-1024  
FICN-1025  
FICN-1026  
FICN-1027  
FICN-1028  
FICN-1029  
FICN-1030  
FICN-1031  
FICN-1032  
FICN-1033  
FICN-1034  
FICN-1035  
FICN-1036  
FICN-1037  
FICN-1038  
FICN-1039  
FICN-1040  
FICN-1041  
FICN-1042  
FICN-1043  
FICN-1044  
FICN-1045  
FICN-1046  
FICN-1047  
FICN-1048

FICN-1049  
FICN-1050  
FICN-1051  
FICN-1052  
FICN-1053  
FICN-1054  
FICN-1055  
FICN-1056  
FICN-1057  
FICN-1058  
FICN-1059  
FICN-1060  
FICN-1061  
FICN-1062  
FICN-1063  
FICN-1064  
FICN-1065  
FICN-1066  
FICN-1067  
FICN-1068  
FICN-1069  
FICN-1070  
FICN-1071  
FICN-1072  
FICN-1073  
FICN-1074  
FICN-1075  
FICN-1076  
FICN-1077  
FICN-1078  
FICN-1079  
FICN-1080  
FICN-1081  
FICN-1082  
FICN-1083

## 2 FICN Messages

FICN-1084

FICN-1085

FICN-1086

FICN-1087

FICN-1088

FICN-1089

FICN-1090

FICN-1091

FICN-1092

FICN-1093

FICN-1094

FICN-1095

FICN-1096

FICN-1097

FICN-1098

FICN-1099

FICN-1100

FICN-1101

FICN-1102

FICN-1103

FICN-1104

FICN-1105

FICN-1106

FICN-1107

FICN-1108

FICN-1109

FICN-1110

FICN-1111

FICN-1112

FICN-1113

FICN-1114

FICN-1115

FICN-1116

FICN-1117

FICN-1118

FICN-1119  
FICN-1120  
FICN-1121  
FICN-1122  
FICN-2005  
FICN-2006  
FICN-2064  
FICN-2065  
FICN-2066  
FICN-2082  
FICN-2083  
FICN-2085  
FICN-2086  
FICN-2087

## FICU Messages

FICU-1001  
FICU-1002  
FICU-1003  
FICU-1004  
FICU-1005  
FICU-1006  
FICU-1007  
FICU-1008  
FICU-1009  
FICU-1010  
FICU-1011  
FICU-1012  
FICU-1013  
FICU-1017  
FICU-1018  
FICU-1019  
FICU-1020  
FICU-1021  
FICU-1022

## 2 FKLB Messages

[FICU-1023](#)

[FICU-1024](#)

### FKLB Messages

[FKLB-1001](#)

### FLOD Messages

[FLOD-1001](#)

[FLOD-1003](#)

[FLOD-1004](#)

[FLOD-1005](#)

[FLOD-1006](#)

### FSPF Messages

[FSPF-1001](#)

[FSPF-1002](#)

[FSPF-1003](#)

[FSPF-1005](#)

[FSPF-1006](#)

[FSPF-1007](#)

[FSPF-1008](#)

[FSPF-1009](#)

[FSPF-1010](#)

[FSPF-1011](#)

[FSPF-1012](#)

### FSS Messages

[FSS-1001](#)

[FSS-1002](#)

[FSS-1003](#)

[FSS-1004](#)

[FSS-1005](#)

[FSS-1006](#)

[FSS-1007](#)



FSS-1008

FSS-1009

FSS-1010

FSS-1011

## FSSM Messages

FSSM-1002

FSSM-1003

FSSM-1004

## FW Messages

FW-1001

FW-1002

FW-1003

FW-1004

FW-1005

FW-1006

FW-1007

FW-1008

FW-1009

FW-1010

FW-1011

FW-1012

FW-1033

FW-1034

FW-1035

FW-1036

FW-1037

FW-1038

FW-1039

FW-1040

FW-1041

FW-1042

FW-1043

## 2 FW Messages

FW-1044  
FW-1045  
FW-1046  
FW-1047  
FW-1048  
FW-1049  
FW-1050  
FW-1051  
FW-1052  
FW-1053  
FW-1054  
FW-1113  
FW-1114  
FW-1115  
FW-1116  
FW-1117  
FW-1118  
FW-1119  
FW-1120  
FW-1121  
FW-1122  
FW-1123  
FW-1124  
FW-1125  
FW-1126  
FW-1127  
FW-1128  
FW-1129  
FW-1130  
FW-1131  
FW-1132  
FW-1133  
FW-1134  
FW-1135  
FW-1136

FW-1137  
FW-1138  
FW-1139  
FW-1140  
FW-1160  
FW-1161  
FW-1162  
FW-1163  
FW-1164  
FW-1165  
FW-1166  
FW-1167  
FW-1168  
FW-1169  
FW-1170  
FW-1171  
FW-1172  
FW-1173  
FW-1174  
FW-1175  
FW-1176  
FW-1177  
FW-1178  
FW-1179  
FW-1180  
FW-1181  
FW-1182  
FW-1183  
FW-1184  
FW-1185  
FW-1186  
FW-1187  
FW-1188  
FW-1189  
FW-1190

## 2 FW Messages

FW-1191  
FW-1192  
FW-1193  
FW-1194  
FW-1195  
FW-1196  
FW-1197  
FW-1198  
FW-1199  
FW-1200  
FW-1201  
FW-1202  
FW-1203  
FW-1204  
FW-1205  
FW-1206  
FW-1207  
FW-1216  
FW-1217  
FW-1218  
FW-1219  
FW-1240  
FW-1241  
FW-1242  
FW-1243  
FW-1244  
FW-1245  
FW-1246  
FW-1247  
FW-1248  
FW-1249  
FW-1250  
FW-1251  
FW-1272  
FW-1273

FW-1274  
FW-1275  
FW-1296  
FW-1297  
FW-1298  
FW-1299  
FW-1300  
FW-1301  
FW-1302  
FW-1303  
FW-1304  
FW-1305  
FW-1306  
FW-1307  
FW-1308  
FW-1309  
FW-1310  
FW-1311  
FW-1312  
FW-1313  
FW-1314  
FW-1315  
FW-1316  
FW-1317  
FW-1318  
FW-1319  
FW-1320  
FW-1321  
FW-1322  
FW-1323  
FW-1324  
FW-1325  
FW-1326  
FW-1327  
FW-1328

## 2 FW Messages

FW-1329  
FW-1330  
FW-1331  
FW-1332  
FW-1333  
FW-1334  
FW-1335  
FW-1336  
FW-1337  
FW-1338  
FW-1339  
FW-1340  
FW-1341  
FW-1342  
FW-1343  
FW-1344  
FW-1345  
FW-1346  
FW-1347  
FW-1348  
FW-1349  
FW-1350  
FW-1351  
FW-1352  
FW-1353  
FW-1354  
FW-1355  
FW-1356  
FW-1357  
FW-1358  
FW-1359  
FW-1360  
FW-1361  
FW-1362  
FW-1363

FW-1364  
FW-1365  
FW-1366  
FW-1367  
FW-1368  
FW-1369  
FW-1370  
FW-1371  
FW-1372  
FW-1373  
FW-1374  
FW-1375  
FW-1376  
FW-1377  
FW-1378  
FW-1379  
FW-1400  
FW-1401  
FW-1402  
FW-1403  
FW-1404  
FW-1405  
FW-1406  
FW-1407  
FW-1408  
FW-1424  
FW-1425  
FW-1426  
FW-1427  
FW-1428  
FW-1429  
FW-1430  
FW-1431  
FW-1432  
FW-1433

## 2 FW Messages

FW-1434  
FW-1435  
FW-1436  
FW-1437  
FW-1438  
FW-1439  
FW-1440  
FW-1441  
FW-1442  
FW-1443  
FW-1444  
FW-1445  
FW-1446  
FW-1447  
FW-1448  
FW-1500  
FW-1501  
FW-1502  
FW-1510  
FW-1511  
FW-1512  
FW-1513  
FW-1514  
FW-1515  
FW-1516  
FW-1517  
FW-1518  
FW-1519  
FW-1520  
FW-1521  
FW-1522  
FW-1523  
FW-1524  
FW-1525  
FW-1526



FW-1527  
FW-1528  
FW-1529  
FW-1530  
FW-1531  
FW-1532  
FW-1533  
FW-1534  
FW-1535  
FW-2000  
FW-3010  
FW-3011  
FW-3012  
FW-3013  
FW-3014  
FW-3015  
FW-3016  
FW-3017  
FW-3018  
FW-3019  
FW-3020  
FW-3021  
FW-3022

## **HAM Messages**

HAM-1001  
HAM-1002  
HAM-1004  
HAM-1005  
HAM-1006  
HAM-1007  
HAM-1008  
HAM-1009  
HAM-1010  
HAM-1011

## 2 HAMK Messages

[HAM-1013](#)

[HAM-1014](#)

### HAMK Messages

[HAMK-1001](#)

[HAMK-1002](#)

[HAMK-1003](#)

[HAMK-1004](#)

### HIL Messages

[HIL-1101](#)

[HIL-1102](#)

[HIL-1103](#)

[HIL-1104](#)

[HIL-1105](#)

[HIL-1106](#)

[HIL-1107](#)

[HIL-1108](#)

[HIL-1201](#)

[HIL-1202](#)

[HIL-1203](#)

[HIL-1204](#)

[HIL-1206](#)

[HIL-1207](#)

[HIL-1208](#)

[HIL-1301](#)

[HIL-1302](#)

[HIL-1303](#)

[HIL-1304](#)

[HIL-1305](#)

[HIL-1306](#)

[HIL-1307](#)

[HIL-1308](#)

[HIL-1309](#)

HIL-1310  
HIL-1311  
HIL-1401  
HIL-1402  
HIL-1403  
HIL-1404  
HIL-1501  
HIL-1502  
HIL-1503  
HIL-1504  
HIL-1505  
HIL-1506  
HIL-1507  
HIL-1508  
HIL-1509  
HIL-1510  
HIL-1511  
HIL-1601  
HIL-1602  
HIL-1603  
HIL-1605  
HIL-1610  
HIL-1611  
HIL-1612  
HIL-1613  
HIL-1650

## HLO Messages

HLO-1001  
HLO-1002  
HLO-1003

## HMON Messages

HMON-1001

## HSL Messages

[HSL-1000](#)  
[HSL-1001](#)  
[HSL-1002](#)  
[HSL-1003](#)  
[HSL-1004](#)  
[HSL-1005](#)  
[HSL-1006](#)  
[HSL-1007](#)

## HTTP Messages

[HTTP-1001](#)  
[HTTP-1002](#)  
[HTTP-1003](#)

## IBD Messages

[IBD-1000](#)

## IPAD Messages

[IPAD-1000](#)  
[IPAD-1001](#)  
[IPAD-1002](#)  
[IPAD-1003](#)  
[IPAD-1004](#)

## IPS Messages

[IPS-1001](#)  
[IPS-1002](#)  
[IPS-1003](#)  
[IPS-1004](#)  
[IPS-1005](#)  
[IPS-1006](#)  
[IPS-1007](#)

## ISNS Messages

ISNS-1001  
ISNS-1002  
ISNS-1003  
ISNS-1004  
ISNS-1005  
ISNS-1006  
ISNS-1008  
ISNS-1009  
ISNS-1010  
ISNS-1011  
ISNS-1013  
ISNS-1014

## KAC Messages

KAC-1002  
KAC-1004  
KAC-1006  
KAC-1007  
KAC-1008  
KAC-1009  
KAC-1010  
KAC-1011  
KAC-1012  
KAC-1013  
KAC-1014  
KAC-1015  
KAC-1016  
KAC-1017

## KSWD Messages

KSWD-1001  
KSWD-1002

## 2 KTRC Messages

### KTRC Messages

[KTRC-1001](#)

[KTRC-1002](#)

[KTRC-1003](#)

[KTRC-1004](#)

[KTRC-1005](#)

### L2SS Messages

[L2SS-1001](#)

[L2SS-1002](#)

[L2SS-1003](#)

[L2SS-1004](#)

[L2SS-1005](#)

[L2SS-1006](#)

[L2SS-1007](#)

[L2SS-1008](#)

### L3SS Messages

[L3SS-1004](#)

### LACP Messages

[LACP-1001](#)

[LACP-1002](#)

### LANCE Messages

[LANCE-1000](#)

### LFM Messages

[LFM-1001](#)

[LFM-1002](#)

[LFM-1003](#)

[LFM-1004](#)

[LFM-1005](#)

LFM-1006

## LOG Messages

LOG-1000

LOG-1001

LOG-1002

LOG-1003

LOG-1004

LOG-1005

LOG-1006

LOG-1007

LOG-1008

LOG-1009

LOG-1010

LOG-1011

## LSDB Messages

LSDB-1001

LSDB-1002

LSDB-1003

LSDB-1004

## MCAST\_SS Messages

MCAST\_SS-1001

MCAST\_SS-1002

MCAST\_SS-1003

MCAST\_SS-1004

MCAST\_SS-1005

MCAST\_SS-1006

MCAST\_SS-1007

MCAST\_SS-1008

MCAST\_SS-1009

MCAST\_SS-1010

MCAST\_SS-1011

## 2 MFIC Messages

[MCAST\\_SS-1012](#)

[MCAST\\_SS-1013](#)

[MCAST\\_SS-1014](#)

[MCAST\\_SS-1015](#)

[MCAST\\_SS-1016](#)

[MCAST\\_SS-1017](#)

[MCAST\\_SS-1018](#)

[MCAST\\_SS-1019](#)

[MCAST\\_SS-1020](#)

### MFIC Messages

[MFIC-1001](#)

[MFIC-1002](#)

[MFIC-1003](#)

### MM Messages

[MM-1001](#)

### MPTH Messages

[MPTH-1001](#)

[MPTH-1002](#)

[MPTH-1003](#)

### MQ Messages

[MQ-1004](#)

[MQ-1005](#)

[MQ-1006](#)

### MS Messages

[MS-1001](#)

[MS-1002](#)

[MS-1003](#)

[MS-1004](#)

[MS-1005](#)



MS-1006

MS-1008

MS-1009

MS-1021

MS-1022

MS-1023

MS-1024

MS-1025

MS-1026

MS-1027

MS-1028

MS-1029

MS-1030

## MSTP Messages

MSTP-1001

MSTP-1002

MSTP-1003

MSTP-2001

MSTP-2002

MSTP-2003

MSTP-2004

MSTP-2005

MSTP-2006

## NBFS Messages

NBFS-1001

NBFS-1002

NBFS-1003

NBFS-1004

## NS Messages

NS-1001

NS-1002

## 2 NSM Messages

[NS-1003](#)  
[NS-1004](#)  
[NS-1005](#)  
[NS-1006](#)  
[NS-1007](#)  
[NS-1008](#)  
[NS-1009](#)  
[NS-1010](#)  
[NS-1011](#)  
[NS-1012](#)

### NSM Messages

[NSM-1001](#)  
[NSM-1002](#)  
[NSM-1003](#)  
[NSM-1004](#)  
[NSM-1005](#)  
[NSM-1006](#)  
[NSM-1007](#)  
[NSM-1008](#)  
[NSM-1009](#)  
[NSM-1010](#)  
[NSM-1011](#)  
[NSM-1012](#)  
[NSM-1013](#)  
[NSM-1014](#)  
[NSM-1015](#)  
[NSM-1016](#)  
[NSM-1017](#)  
[NSM-1018](#)  
[NSM-1019](#)  
[NSM-1020](#)

## ONMD Messages

ONMD-1000

ONMD-1001

ONMD-1002

ONMD-1003

ONMD-1004

ONMD-1005

## PDM Messages

PDM-1001

PDM-1002

PDM-1003

PDM-1004

PDM-1005

PDM-1006

PDM-1007

PDM-1008

PDM-1009

PDM-1010

PDM-1011

PDM-1012

PDM-1013

PDM-1014

PDM-1017

PDM-1019

PDM-1020

PDM-1021

PDM-1022

PDM-1023

PDM-1024

PDM-1025

PDM-1026

## PDTR Messages

[PDTR-1001](#)

[PDTR-1002](#)

## PLAT Messages

[PLAT-1000](#)

[PLAT-1001](#)

[PLAT-1002](#)

[PLAT-1003](#)

[PLAT-1004](#)

[PLAT-1072](#)

## PMGR Messages

[PMGR-1001](#)

[PMGR-1002](#)

[PMGR-1003](#)

[PMGR-1004](#)

[PMGR-1005](#)

[PMGR-1006](#)

[PMGR-1007](#)

[PMGR-1008](#)

[PMGR-1009](#)

[PMGR-1010](#)

[PMGR-1011](#)

## PORT Messages

[PORT-1003](#)

[PORT-1004](#)

[PORT-1005](#)

[PORT-1006](#)

[PORT-1007](#)

[PORT-1008](#)

[PORT-1009](#)

[PORT-1010](#)

## PS Messages

PS-1000

PS-1001

PS-1002

PS-1003

PS-1004

PS-1005

PS-1006

PS-1007

PS-1008

PS-1009

PS-1010

## PSWP Messages

PSWP-1001

PSWP-1002

PSWP-1003

PSWP-1004

PSWP-1005

PSWP-1006

PSWP-1007

## RAS Messages

RAS-1001

RAS-1002

RAS-1004

RAS-1005

RAS-1006

RAS-1007

RAS-2001

RAS-2002

RAS-2003

RAS-3001

RAS-3002

## 2 RCS Messages

[RAS-3003](#)

[RAS-3004](#)

### RCS Messages

[RCS-1001](#)

[RCS-1002](#)

[RCS-1003](#)

[RCS-1004](#)

[RCS-1005](#)

[RCS-1006](#)

[RCS-1007](#)

[RCS-1008](#)

[RCS-1009](#)

[RCS-1010](#)

[RCS-1011](#)

[RCS-1012](#)

[RCS-1013](#)

### RKD Messages

[RKD-1001](#)

[RKD-1002](#)

[RKD-1003](#)

[RKD-1004](#)

[RKD-1005](#)

### RMON Messages

[RMON-1001](#)

[RMON-1002](#)

### RPCD Messages

[RPCD-1001](#)

[RPCD-1002](#)

[RPCD-1003](#)

[RPCD-1004](#)

RPCD-1005

RPCD-1006

RPCD-1007

## RTE Messages

RTE-1001

## RTWR Messages

RTWR-1001

RTWR-1002

RTWR-1003

## SCN Messages

SCN-1001

SCN-1002

## SEC Messages

SEC-1001

SEC-1002

SEC-1003

SEC-1005

SEC-1006

SEC-1007

SEC-1008

SEC-1009

SEC-1010

SEC-1016

SEC-1022

SEC-1024

SEC-1025

SEC-1026

SEC-1028

SEC-1029

SEC-1030

## 2 SEC Messages

SEC-1031  
SEC-1032  
SEC-1033  
SEC-1034  
SEC-1035  
SEC-1036  
SEC-1037  
SEC-1038  
SEC-1039  
SEC-1040  
SEC-1041  
SEC-1042  
SEC-1043  
SEC-1044  
SEC-1045  
SEC-1046  
SEC-1049  
SEC-1050  
SEC-1051  
SEC-1052  
SEC-1053  
SEC-1054  
SEC-1055  
SEC-1056  
SEC-1057  
SEC-1059  
SEC-1062  
SEC-1063  
SEC-1064  
SEC-1065  
SEC-1069  
SEC-1071  
SEC-1072  
SEC-1073  
SEC-1074



SEC-1075  
SEC-1076  
SEC-1077  
SEC-1078  
SEC-1079  
SEC-1080  
SEC-1081  
SEC-1082  
SEC-1083  
SEC-1084  
SEC-1085  
SEC-1086  
SEC-1087  
SEC-1088  
SEC-1089  
SEC-1090  
SEC-1091  
SEC-1092  
SEC-1093  
SEC-1094  
SEC-1095  
SEC-1096  
SEC-1097  
SEC-1098  
SEC-1099  
SEC-1100  
SEC-1101  
SEC-1102  
SEC-1104  
SEC-1105  
SEC-1106  
SEC-1107  
SEC-1108  
SEC-1110  
SEC-1111

## 2 SEC Messages

SEC-1112  
SEC-1113  
SEC-1114  
SEC-1115  
SEC-1116  
SEC-1117  
SEC-1118  
SEC-1119  
SEC-1121  
SEC-1122  
SEC-1123  
SEC-1124  
SEC-1126  
SEC-1130  
SEC-1135  
SEC-1136  
SEC-1137  
SEC-1138  
SEC-1139  
SEC-1142  
SEC-1145  
SEC-1146  
SEC-1153  
SEC-1154  
SEC-1155  
SEC-1156  
SEC-1157  
SEC-1158  
SEC-1159  
SEC-1160  
SEC-1163  
SEC-1164  
SEC-1165  
SEC-1166  
SEC-1167

SEC-1168  
SEC-1170  
SEC-1171  
SEC-1172  
SEC-1173  
SEC-1174  
SEC-1175  
SEC-1176  
SEC-1180  
SEC-1181  
SEC-1182  
SEC-1183  
SEC-1184  
SEC-1185  
SEC-1186  
SEC-1187  
SEC-1188  
SEC-1189  
SEC-1190  
SEC-1191  
SEC-1192  
SEC-1193  
SEC-1194  
SEC-1195  
SEC-1196  
SEC-1197  
SEC-1198  
SEC-1199  
SEC-1200  
SEC-1201  
SEC-1202  
SEC-1203  
SEC-1250  
SEC-1251  
SEC-1253

## 2 SEC Messages

SEC-1300  
SEC-1301  
SEC-1302  
SEC-1303  
SEC-1304  
SEC-1305  
SEC-1306  
SEC-1307  
SEC-1308  
SEC-1309  
SEC-1310  
SEC-1311  
SEC-1312  
SEC-1313  
SEC-1314  
SEC-1315  
SEC-1316  
SEC-1317  
SEC-1318  
SEC-1319  
SEC-1320  
SEC-1321  
SEC-1322  
SEC-1323  
SEC-1324  
SEC-1325  
SEC-1326  
SEC-1327  
SEC-1328  
SEC-1329  
SEC-1330  
SEC-1331  
SEC-1332  
SEC-1333  
SEC-1334

SEC-1335  
SEC-1336  
SEC-1337  
SEC-1338  
SEC-1339  
SEC-3035  
SEC-3036  
SEC-3037  
SEC-3038  
SEC-3039  
SEC-3050  
SEC-3051  
SEC-3061  
SEC-3062  
SEC-3063  
SEC-3064  
SEC-3065  
SEC-3066  
SEC-3067  
SEC-4001

## SFLO Messages

SFLO-1001  
SFLO-1002  
SFLO-1003  
SFLO-1004  
SFLO-1005  
SFLO-1006  
SFLO-1007  
SFLO-1008

## SNMP Messages

SNMP-1001  
SNMP-1002

## 2 SPC Messages

SNMP-1003

SNMP-1004

SNMP-1005

SNMP-1006

SNMP-1009

### SPC Messages

SPC-1001

SPC-1002

SPC-1003

SPC-2001

SPC-2002

SPC-2003

SPC-2004

SPC-2005

SPC-2006

SPC-2007

SPC-2008

SPC-2009

SPC-2010

SPC-2011

SPC-2012

SPC-2013

SPC-2014

SPC-2040

SPC-2041

SPC-2042

SPC-2043

SPC-2044

SPC-3001

SPC-3002

SPC-3003

SPC-3004

SPC-3005

SPC-3006

SPC-3007  
SPC-3008  
SPC-3009  
SPC-3010  
SPC-3011  
SPC-3012  
SPC-3013  
SPC-3014  
SPC-3015

## SPM Messages

SPM-1001  
SPM-1002  
SPM-1003  
SPM-1004  
SPM-1005  
SPM-1006  
SPM-1007  
SPM-1008  
SPM-1009  
SPM-1010  
SPM-1011  
SPM-1012  
SPM-1013  
SPM-1014  
SPM-1015  
SPM-1016  
SPM-3001  
SPM-3002  
SPM-3003  
SPM-3004  
SPM-3005  
SPM-3006  
SPM-3007  
SPM-3008

## 2 SS Messages

SPM-3009  
SPM-3010  
SPM-3011  
SPM-3012  
SPM-3013  
SPM-3014  
SPM-3015  
SPM-3016  
SPM-3017  
SPM-3018  
SPM-3019  
SPM-3020  
SPM-3021  
SPM-3022  
SPM-3023  
SPM-3024  
SPM-3025  
SPM-3026  
SPM-3027  
SPM-3028  
SPM-3029

### SS Messages

SS-1000  
SS-1001  
SS-1002  
SS-1003  
SS-1004  
SS-1005  
SS-1006  
SS-1007  
SS-1008  
SS-1009  
SS-1010  
SS-1011



SS-1012

## SSMD Messages

SSMD-1001  
SSMD-1002  
SSMD-1003  
SSMD-1004  
SSMD-1005  
SSMD-1006  
SSMD-1007  
SSMD-1008  
SSMD-1200  
SSMD-1201  
SSMD-1202  
SSMD-1203  
SSMD-1204  
SSMD-1205  
SSMD-1206  
SSMD-1207  
SSMD-1208  
SSMD-1209  
SSMD-1210  
SSMD-1211  
SSMD-1212  
SSMD-1213  
SSMD-1214  
SSMD-1215  
SSMD-1216  
SSMD-1217  
SSMD-1300  
SSMD-1301  
SSMD-1302  
SSMD-1303  
SSMD-1304  
SSMD-1305

## 2 SULB Messages

SSMD-1306  
SSMD-1307  
SSMD-1308  
SSMD-1309  
SSMD-1310  
SSMD-1311  
SSMD-1312  
SSMD-1313  
SSMD-1314  
SSMD-1315  
SSMD-1316  
SSMD-1317  
SSMD-1318

### SULB Messages

SULB-1001  
SULB-1002  
SULB-1003  
SULB-1004  
SULB-1005  
SULB-1006  
SULB-1007  
SULB-1008  
SULB-1009  
SULB-1010  
SULB-1011  
SULB-1017  
SULB-1018  
SULB-1020  
SULB-1021  
SULB-1022  
SULB-1023  
SULB-1024  
SULB-1025  
SULB-1026

SULB-1030  
SULB-1031  
SULB-1032  
SULB-1033  
SULB-1034  
SULB-1035  
SULB-1036  
SULB-1037  
SULB-1038  
SULB-1039  
SULB-1040  
SULB-1041  
SULB-1042  
SULB-1043  
SULB-1044

## SWCH Messages

SWCH-1001  
SWCH-1002  
SWCH-1003  
SWCH-1004  
SWCH-1005  
SWCH-1006  
SWCH-1007  
SWCH-1008  
SWCH-1009  
SWCH-1010  
SWCH-1011  
SWCH-1012  
SWCH-1013  
SWCH-1014  
SWCH-1015  
SWCH-1016  
SWCH-1017  
SWCH-1018

## 2 SYSC Messages

SWCH-1019

SWCH-1020

SWCH-1021

SWCH-1022

SWCH-1023

SWCH-1024

SWCH-1025

SWCH-1026

### SYSC Messages

SYSC-1001

SYSC-1002

SYSC-1004

SYSC-1005

### SYSM Messages

SYSM-1001

SYSM-1002

SYSM-1003

SYSM-1004

SYSM-1005

SYSM-1006

SYSM-1007

### TAPE Messages

TAPE-1001

### TRCE Messages

TRCE-1001

TRCE-1002

TRCE-1003

TRCE-1004

TRCE-1005

TRCE-1006

TRCE-1007

TRCE-1008

TRCE-1009

TRCE-1010

TRCE-1011

TRCE-1012

TRCE-1013

## TRCK Messages

TRCK-1001

TRCK-1002

TRCK-1003

TRCK-1004

TRCK-1005

TRCK-1006

## TS Messages

TS-1001

TS-1002

TS-1006

TS-1007

TS-1008

## UCST Messages

UCST-1003

UCST-1007

UCST-1020

UCST-1021

UCST-1022

UCST-1023

UCST-1024

UCST-1026

UCST-1027

## 2 UPTH Messages

### UPTH Messages

[UPTH-1001](#)

[UPTH-1002](#)

### VDR Messages

[VDR-2001](#)

### VS Messages

[VS-1001](#)

[VS-1002](#)

[VS-1003](#)

[VS-1004](#)

[VS-1005](#)

[VS-1006](#)

[VS-1007](#)

[VS-1008](#)

### WEBD Messages

[WEBD-1001](#)

[WEBD-1002](#)

[WEBD-1004](#)

[WEBD-1005](#)

[WEBD-1006](#)

[WEBD-1007](#)

[WEBD-1008](#)

### XTUN Messages

[XTUN-1000](#)

[XTUN-1001](#)

[XTUN-1002](#)

[XTUN-1003](#)

[XTUN-1004](#)

[XTUN-1005](#)

[XTUN-1006](#)  
[XTUN-1007](#)  
[XTUN-1996](#)  
[XTUN-1997](#)  
[XTUN-1998](#)  
[XTUN-1999](#)  
[XTUN-2000](#)  
[XTUN-2001](#)  
[XTUN-2002](#)  
[XTUN-2003](#)  
[XTUN-2004](#)  
[XTUN-2005](#)  
[XTUN-2006](#)  
[XTUN-2007](#)  
[XTUN-2008](#)  
[XTUN-2009](#)  
[XTUN-2010](#)  
[XTUN-2011](#)  
[XTUN-2020](#)  
[XTUN-2021](#)  
[XTUN-2022](#)  
[XTUN-2023](#)  
[XTUN-2024](#)  
[XTUN-2025](#)

## ZEUS Messages

[ZEUS-1001](#)  
[ZEUS-1002](#)  
[ZEUS-1003](#)  
[ZEUS-1004](#)  
[ZEUS-1005](#)  
[ZEUS-1015](#)  
[ZEUS-1016](#)  
[ZEUS-1028](#)

## ZONE Messages

ZONE-1002  
ZONE-1003  
ZONE-1004  
ZONE-1007  
ZONE-1010  
ZONE-1013  
ZONE-1015  
ZONE-1017  
ZONE-1019  
ZONE-1022  
ZONE-1023  
ZONE-1024  
ZONE-1026  
ZONE-1027  
ZONE-1028  
ZONE-1029  
ZONE-1034  
ZONE-1036  
ZONE-1037  
ZONE-1038  
ZONE-1039  
ZONE-1040  
ZONE-1041  
ZONE-1042  
ZONE-1043  
ZONE-1044  
ZONE-1045  
ZONE-1046  
ZONE-1048  
ZONE-1049  
ZONE-1054  
ZONE-1057  
ZONE-1058



ZONE-1059

ZONE-1060

ZONE-1061

ZONE-1062

## 2 ZONE Messages

# Audit Messages

---

## AG Messages

[AG-1033](#)

[AG-1034](#)

[AG-1035](#)

[AG-1036](#)

[AG-1037](#)

## AN Messages

[AN-1003](#)

[AN-1004](#)

[AN-1005](#)

[AN-1006](#)

[AN-1010](#)

[AN-1011](#)

[AN-1012](#)

[AN-1013](#)

## AUTH Messages

[AUTH-1045](#)

[AUTH-1046](#)

[AUTH-1047](#)

[AUTH-3001](#)

[AUTH-3002](#)

[AUTH-3003](#)

[AUTH-3004](#)

[AUTH-3005](#)

[AUTH-3006](#)

[AUTH-3007](#)

[AUTH-3008](#)

## 3 BLS Messages

### BLS Messages

[BLS-1002](#)

[BLS-1003](#)

### CCFG Messages

[CCFG-1002](#)

[CCFG-1003](#)

[CCFG-1013](#)

### CNM Messages

[CNM-3001](#)

[CNM-3002](#)

[CNM-3003](#)

[CNM-3004](#)

[CNM-3005](#)

[CNM-3006](#)

[CNM-3007](#)

[CNM-3008](#)

[CNM-3009](#)

[CNM-3010](#)

[CNM-3011](#)

[CNM-3012](#)

### CONF Messages

[CONF-1000](#)

[CONF-1020](#)

[CONF-1022](#)

[CONF-1042](#)

[CONF-1043](#)

[CONF-1044](#)

### CVLM Messages

[CVLM-3001](#)

CVLM-3002  
CVLM-3003  
CVLM-3004  
CVLM-3005  
CVLM-3006  
CVLM-3007  
CVLM-3008  
CVLM-3009  
CVLM-3010  
CVLM-3011  
CVLM-3012  
CVLM-3013  
CVLM-3014  
CVLM-3015  
CVLM-3016  
CVLM-3017  
CVLM-3018  
CVLM-3019  
CVLM-3020  
CVLM-3021  
CVLM-3022  
CVLM-3023  
CVLM-3024  
CVLM-3025  
CVLM-3026  
CVLM-3027  
CVLM-3028

## ESS Messages

ESS-1008  
ESS-1009  
ESS-1010

## 3 FICU Messages

### FICU Messages

[FICU-1011](#)

[FICU-1012](#)

[FICU-1019](#)

[FICU-1020](#)

[FICU-1021](#)

### FW Messages

[FW-1202](#)

[FW-1274](#)

[FW-1402](#)

[FW-1404](#)

[FW-1405](#)

[FW-1406](#)

[FW-3001](#)

### HAM Messages

[HAM-1015](#)

### HTTP Messages

[HTTP-1002](#)

[HTTP-1003](#)

### IPAD Messages

[IPAD-1002](#)

### LOG Messages

[LOG-1005](#)

[LOG-1006](#)

[LOG-1007](#)

[LOG-1008](#)

[LOG-1011](#)

## MS Messages

[MS-1027](#)

[MS-1028](#)

[MS-1029](#)

[MS-1030](#)

## PMGR Messages

[PMGR-1001](#)

[PMGR-1003](#)

## PORT Messages

[PORT-1006](#)

[PORT-1007](#)

[PORT-1008](#)

[PORT-1009](#)

## RAS Messages

[RAS-2001](#)

[RAS-2002](#)

[RAS-2003](#)

[RAS-3005](#)

## SEC Messages

[SEC-1113](#)

[SEC-1114](#)

[SEC-1337](#)

[SEC-3001](#)

[SEC-3002](#)

[SEC-3003](#)

[SEC-3004](#)

[SEC-3005](#)

[SEC-3006](#)

[SEC-3007](#)

### 3 SEC Messages

SEC-3008  
SEC-3009  
SEC-3010  
SEC-3011  
SEC-3012  
SEC-3013  
SEC-3014  
SEC-3015  
SEC-3016  
SEC-3017  
SEC-3018  
SEC-3019  
SEC-3020  
SEC-3021  
SEC-3022  
SEC-3023  
SEC-3024  
SEC-3025  
SEC-3026  
SEC-3027  
SEC-3028  
SEC-3029  
SEC-3030  
SEC-3031  
SEC-3032  
SEC-3033  
SEC-3034  
SEC-3035  
SEC-3036  
SEC-3037  
SEC-3038  
SEC-3039  
SEC-3044  
SEC-3045  
SEC-3046



SEC-3047  
SEC-3048  
SEC-3049  
SEC-3050  
SEC-3051  
SEC-3061  
SEC-3062  
SEC-3063  
SEC-3064  
SEC-3065  
SEC-3066  
SEC-3067  
SEC-4001

## SNMP Messages

SNMP-1004  
SNMP-1005  
SNMP-1006  
SNMP-1009

## SPM Messages

SPM-3001  
SPM-3002  
SPM-3003  
SPM-3004  
SPM-3005  
SPM-3006  
SPM-3007  
SPM-3008  
SPM-3009  
SPM-3010  
SPM-3011  
SPM-3012  
SPM-3013

## 3 SULB Messages

SPM-3014  
SPM-3015  
SPM-3016  
SPM-3017  
SPM-3018  
SPM-3019  
SPM-3020  
SPM-3021  
SPM-3022  
SPM-3023  
SPM-3024  
SPM-3025  
SPM-3026  
SPM-3027  
SPM-3028  
SPM-3029

### SULB Messages

SULB-1001  
SULB-1002  
SULB-1003  
SULB-1004  
SULB-1009  
SULB-1010  
SULB-1017  
SULB-1018  
SULB-1020  
SULB-1021  
SULB-1023  
SULB-1024  
SULB-1026  
SULB-1030  
SULB-1031  
SULB-1032  
SULB-1033

SULB-1034

SULB-1035

SULB-1037

SULB-1038

SULB-1039

SULB-1040

SULB-1041

SULB-1042

### SWCH Messages

SWCH-1012

SWCH-1013

SWCH-1014

### UCST Messages

UCST-1021

UCST-1022

UCST-1023

UCST-1024

UCST-1026

UCST-1027

### ZONE Messages

ZONE-3001

ZONE-3002

ZONE-3003

ZONE-3004

ZONE-3005

ZONE-3006

ZONE-3007

ZONE-3008

ZONE-3009

ZONE-3010

ZONE-3011

### 3 ZONE Messages

ZONE-3012

ZONE-3013

ZONE-3014

ZONE-3015

ZONE-3016

ZONE-3017

ZONE-3018

ZONE-3019

ZONE-3020

ZONE-3021

ZONE-3022

ZONE-3023

ZONE-3024

ZONE-3025

ZONE-3026

# FFDC Messages

---

## ANV Messages

[ANV-1002](#)

## AUTH Messages

[AUTH-1014](#)

[AUTH-1044](#)

## BKSW Messages

[BKSW-1003](#)

## BL Messages

[BL-1002](#)

[BL-1003](#)

[BL-1004](#)

[BL-1008](#)

[BL-1009](#)

[BL-1011](#)

[BL-1016](#)

[BL-1020](#)

## BLS Messages

[BLS-1000](#)

[BLS-1001](#)

## BM Messages

[BM-1003](#)

[BM-1053](#)

## 4 C2 Messages

### C2 Messages

[C2-1002](#)

[C2-1012](#)

### C3 Messages

[C3-1002](#)

[C3-1012](#)

### CDR Messages

[CDR-1002](#)

### CHS Messages

[CHS-1002](#)

### EM Messages

[EM-1001](#)

[EM-1002](#)

[EM-1003](#)

[EM-1004](#)

[EM-1005](#)

[EM-1006](#)

[EM-1008](#)

[EM-1009](#)

[EM-1010](#)

[EM-1011](#)

[EM-1012](#)

[EM-1018](#)

[EM-1020](#)

[EM-1028](#)

[EM-1068](#)

[EM-1071](#)

[EM-1072](#)

## FABR Messages

[FABR-1011](#)

[FABR-1013](#)

[FABR-1019](#)

[FABR-1020](#)

[FABR-1021](#)

[FABR-1022](#)

[FABR-1031](#)

[FABR-1054](#)

## FABS Messages

[FABS-1001](#)

## FCMC Messages

[FCMC-1001](#)

## FCPH Messages

[FCPH-1001](#)

## FLOD Messages

[FLOD-1004](#)

## HAM Messages

[HAM-1001](#)

[HAM-1006](#)

[HAM-1007](#)

[HAM-1008](#)

[HAM-1009](#)

[HAM-1011](#)

## HAMK Messages

[HAMK-1001](#)

## HIL Messages

[HIL-1107](#)  
[HIL-1108](#)  
[HIL-1502](#)  
[HIL-1503](#)  
[HIL-1506](#)  
[HIL-1507](#)  
[HIL-1508](#)  
[HIL-1509](#)  
[HIL-1602](#)  
[HIL-1603](#)  
[HIL-1611](#)

## HLO Messages

[HLO-1001](#)  
[HLO-1002](#)

## HMON Messages

[HMON-1001](#)

## KSWD Messages

[KSWD-1001](#)  
[KSWD-1002](#)

## LFM Messages

[LFM-1004](#)

## LOG Messages

[LOG-1001](#)  
[LOG-1002](#)

## LSDB Messages

[LSDB-1003](#)



## MPTH Messages

[MPTH-1001](#)

[MPTH-1002](#)

## NBFS Messages

[NBFS-1002](#)

## PDM Messages

[PDM-1017](#)

## PLAT Messages

[PLAT-1000](#)

[PLAT-1003](#)

[PLAT-1004](#)

[PLAT-1072](#)

## PS Messages

[PS-1000](#)

## RAS Messages

[RAS-1004](#)

[RAS-1005](#)

## RCS Messages

[RCS-1012](#)

[RCS-1013](#)

## SCN Messages

[SCN-1001](#)

[SCN-1002](#)

## 4 SNMP Messages

### SNMP Messages

[SNMP-1004](#)

### SYSC Messages

[SYSC-1001](#)

[SYSC-1002](#)

### SYSM Messages

[SYSM-1001](#)

[SYSM-1005](#)

[SYSM-1006](#)

### TRCE Messages

[TRCE-1008](#)

### UCST Messages

[UCST-1007](#)

### WEBD Messages

[WEBD-1008](#)

### ZEUS Messages

[ZEUS-1002](#)

# Fabric OS System Messages

---

## AG Messages

### AG-1001

<b>Message</b>	N_Port ID virtualization (NPIV) is not supported by fabric port connected to port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the N_Port ID virtualization (NPIV) capability is not supported by the fabric port to which the Access Gateway is connected.
<b>Recommended Action</b>	<ul style="list-style-type: none"><li>• Execute the <b>portCfgNpivPort</b> command to enable NPIV capability on the port connected to the Access Gateway.</li><li>• Some blades and ports in a switch may not support NPIV. NPIV functionality cannot be enabled on such ports and they will not respond to NPIV requests. Refer to the <i>Access Gateway Administrator's Guide</i> for specific AG-compatibility requirements.</li><li>• On non-Brocade switches, refer to the manufacturer's documentation to determine whether the switch supports NPIV and how to enable NPIV on these types of switches.</li></ul>

### AG-1002

<b>Message</b>	Unable to find alternate N_Port during failover for N_Port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that no other N_Port is configured or the fabric was unstable during failover.
<b>Recommended Action</b>	Check whether an alternate N_Port is configured using the <b>portCfgShow</b> command. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AG-1003

<b>Message</b>	Unable to failover N_Port <port number>. Failover across different fabric is not supported.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the failover does not get blocked between two fabrics, although it is not a supported configuration.
<b>Recommended Action</b>	Configure two or more N_Ports to connect to the same fabric; then execute the <b>ag --failoverenable</b> command to enable failover on these N_Ports.

## AG-1004

<b>Message</b>	Invalid response to fabric login (FLOGI) request from the fabric for N_Port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the fabric sent an invalid response to the FLOGI Extended Link Service (ELS) for the specified N_Port.
<b>Recommended Action</b>	Check the configuration of the fabric switch. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AG-1005

<b>Message</b>	FDISC response was dropped because F_Port <port number> is offline.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the F_Port connected to the host is offline, which caused the Fabric Discovery (FDISC) response to drop.
<b>Recommended Action</b>	Check the configuration of the host connected to the specified F_Port.

## AG-1006

<b>Message</b>	Access Gateway mode has been <message>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Access Gateway mode has been enabled or disabled.
<b>Recommended Action</b>	Execute the <b>ag --modeshow</b> command to verify the current status of the Access Gateway mode.

## AG-1007

<b>Message</b>	FLOGI response not received for the N_Port <port number> connected to the fabric.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the N_Port connected to the fabric switch is not online. The specified N_Port has been disabled.
<b>Recommended Action</b>	Check the connectivity between the Access Gateway N_Port and the fabric switch port.

## AG-1008

<b>Message</b>	Invalid Port Login (PLOGI) response from the fabric on the N_Port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the fabric switch management server did not accept the N_Port Login (PLOGI) request sent by the Access Gateway.
<b>Recommended Action</b>	Check the configuration of the fabric switch connected to the Access Gateway. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AG-1009

<b>Message</b>	Sending FLOGI failed on N_Port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that there was a failure sending a Fabric Login (FLOGI) request from the Access Gateway to the fabric switch.
<b>Recommended Action</b>	Check the configuration of the fabric switch connected to the Access Gateway. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AG-1010

<b>Message</b>	Sending PLOGI failed on N_Port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that there was a failure sending an N_Port Login (PLOGI) request from the Access Gateway to the fabric switch.
<b>Recommended Action</b>	Check the configuration of the fabric switch connected to the Access Gateway. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AG-1011

<b>Message</b>	Sending FDISC failed on N_Port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that there was a failure sending a discover F_Port service parameter request from the Access Gateway to the fabric switch.
<b>Recommended Action</b>	Check the configuration of the fabric switch connected to the Access Gateway. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AG-1012

<b>Message</b>	Sending logout (LOGO) request failed on N_Port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that there was a failure sending an N_Port logout request from the Access Gateway to the fabric switch.
<b>Recommended Action</b>	Check the configuration of the fabric switch connected to the Access Gateway. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AG-1013

<b>Message</b>	F_Ports mapped to N_Port <port number> failed over to other N_Port(s).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified N_Port is failing over to other N_Ports connected to the same fabric.
<b>Recommended Action</b>	Execute the <b>ag --mapshow</b> command to display updated F_Port-to-N_Port mapping.

## AG-1014

<b>Message</b>	Failing back F_Ports mapped to N_Port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified N_Port is failing back F_Ports mapped to it.
<b>Recommended Action</b>	Execute the <b>ag --mapshow</b> command to display updated F_Port-to-N_Port mapping.

## AG-1015

<b>Message</b>	Unable to find online N_Ports to connect to the fabric.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that no other N_Port is configured or all N_Ports are currently offline.
<b>Recommended Action</b>	Check whether any other N_Port is configured using the <b>portCfgShow</b> command. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AG-1016

<b>Message</b>	Failing over F_Ports mapped to N_Port <port number> to other N_Port(s).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified N_Port has failed to come online. All F_Ports mapped to this N_Port are being failed over to other active N_Ports.
<b>Recommended Action</b>	Execute the <b>ag --mapshow</b> command to display updated F_Port-to-N_Port mapping.

## AG-1017

<b>Message</b>	No N_Port(s) are currently Online.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that no N_Ports are currently configured in the system or all configured N_Ports have failed to come online.
<b>Recommended Action</b>	Execute the <b>switchShow</b> command to display the status of all ports in the system. Execute the <b>portCfgShow</b> command to display the list of ports currently configured as N_Ports.



## AG-1018

<b>Message</b>	Host port should not be connected to port <port number> which is configured as N_Port.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that an initiator or target port is erroneously connected to a port configured for N_Port operation.
<b>Recommended Action</b>	Execute the <b>switchShow</b> command to display the status of all ports in the system. Execute the <b>portCfgShow</b> command to display the list of ports currently configured as N_Ports. Make sure the host is connected to an F_port.

## AG-1019

<b>Message</b>	Unable to failover N_Port <port number>. No other N_Port in port group:<pgid> is online.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that failover across port groups is not supported.
<b>Recommended Action</b>	Check whether an alternate N_Port is configured in the specified port group using the <b>ag --pgshow</b> command.

## AG-1020

<b>Message</b>	F_Ports to N_Ports route/mapping has been changed.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that F_Port-to-N_Port mapping has been changed because the switch has come online or some new N_Ports or F_Ports have come online.
<b>Recommended Action</b>	Execute the <b>ag --mapshow</b> command to display the updated F_Port-to-N_Port mapping.

**AG-1021**

<b>Message</b>	Unable to do Preferred-Failover of F_Port <port number>. Failover across different fabric is not supported.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that failover across N_Ports connected to different fabrics is not supported.
<b>Recommended Action</b>	Change the preferred N_Port settings of the specified F_Port using the <b>ag --prefset</b> command. Choose the preferred N_Port so that it is in the same fabric as the primary N_Port of this F_Port. Execute the <b>ag --show</b> command to check the fabric connectivity of the N_Ports.

**AG-1022**

<b>Message</b>	F_Port <f_port> is failed over to its preferred N_Port <n_port>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified F_Port is failing over to its preferred N_Port.
<b>Recommended Action</b>	Execute the <b>ag --mapshow</b> command to display the updated F_Port-to-N_Port mapping.

**AG-1023**

<b>Message</b>	F_Port <f_port> mapped to offline N_Port <n_port> is failed over to its preferred N_Port <preferred port>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified N_Port has failed to come online. The F_Port mapped to this N_Port had its preferred set and is online.
<b>Recommended Action</b>	Execute the <b>ag --mapshow</b> command to display updated F_Port-to-N_Port mapping.

## AG-1024

<b>Message</b>	F_Port <f_port> is failed back to its preferred N_Port <n_port>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified N_Port is failing back F_Ports, which are failed over to some other N_Port.
<b>Recommended Action</b>	Execute the <b>ag --mapshow</b> command to display the updated F_Port-to-N_Port mapping.

## AG-1025

<b>Message</b>	Port group of Slave N_Port <port number> is different than its Master N_Port <n_port>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the port groups of the Master and Slave N_Ports are different, while the trunk area assigned to the attached F_Ports on the edge switch is the same.
<b>Recommended Action</b>	Execute the <b>porttrunkarea --show</b> command on the attached switch to verify that the trunk area is assigned to all ports in the system, and execute the <b>porttrunkarea --enable</b> command to reconfigure the trunk area.

## AG-1026

<b>Message</b>	Unable to handle the login request on port <port number> due to insufficient resources.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that there are insufficient resources to accept the login request.
<b>Recommended Action</b>	Execute the <b>configure</b> command on the Access Gateway switch and increase the number of allowed logins on the specified port.  If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AG-1027

<b>Message</b>	Unable to handle this login request on port <port number> because NPIV capability is not enabled on this port.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that N_Port ID virtualization (NPIV) is not enabled on the specified port.
<b>Recommended Action</b>	Execute the <b>portCfgNpivPort</b> command on the Access Gateway switch to enable the NPIV capability on the port.

## AG-1028

<b>Message</b>	Device with Port WWN <port_name> tried to perform fabric login through port <f_port>, without having access permission.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the device does not have login access for the specified port as per Advanced Device Security (ADS) policy set by the user.
<b>Recommended Action</b>	Add the device to the ADS allow list for the specified port using the <b>ag --adsadd</b> command.

## AG-1029

<b>Message</b>	Port Group (ID: <pgid>) has ports going to different fabrics.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a misconfiguration.
<b>Recommended Action</b>	Connect all ports in the port group to the same fabric.

## AG-1030

<b>Message</b>	N_Port (ID: <port number>) has been determined to be unreliable.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the port goes online and offline often and therefore the port is marked as unreliable.
<b>Recommended Action</b>	No action is required. The port will automatically be marked as reliable after a certain interval of time, if the port toggling remains within the threshold limit.

## AG-1031

<b>Message</b>	Loop Detected for device with Port WWN <port_name> connected to port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a routing loop is detected for the device connected to the specified port.
<b>Recommended Action</b>	Check the device configuration.

## AG-1032

<b>Message</b>	N_Port (ID: <port number>) has recovered from an unreliable state.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the port state has been stable for the last five minutes.
<b>Recommended Action</b>	No action is required.

## AG-1033

<b>Message</b>	F_Port to N_Port mapping has been updated for N_Port (<n_port>).
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the F_Ports mapped to an N_Port have changed and the configuration file has been updated.
<b>Recommended Action</b>	No action is required.

## AG-1034

<b>Message</b>	F_Port cannot accept any more logins (<f_port>).
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the F_Port has already logged in the maximum number of devices.
<b>Recommended Action</b>	No action is required.

## AG-1035

<b>Message</b>	Device cannot login as ALPA value is not available (<alpa>).
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a device has already used the specified arbitrated loop physical address (ALPA) value.
<b>Recommended Action</b>	No action is required.

## AG-1036

<b>Message</b>	Port <port number> is connected to a non-Brocade fabric with Persistent ALPA enabled. Check the admin guide for supported configuration.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that one of the ports is connected to a non-Brocade fabric.
<b>Recommended Action</b>	Refer to the <i>Access Gateway Administrator's Guide</i> for the supported configuration.

## AG-1037

<b>Message</b>	Trunked N_Port (<n_port>) going offline. If switchshow CLI for the connected fabric switch port displays Persistently disabled: Area has been acquired, then check cabling: all trunked ports should be in same ASIC Port Group.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an incorrect cabling.
<b>Recommended Action</b>	If the <b>switchShow</b> command on the connected fabric switch port displays "Persistently disabled: Area has been acquired", then check cabling on the Access Gateway. All trunked ports in a single trunk must belong to the same application-specific integrated circuit (ASIC) port group.

## AG-1038

<b>Message</b>	Brocade 8000 ports are going to different fabrics, check N_Port (<n_port>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a misconfiguration.
<b>Recommended Action</b>	Connect all ports in the port group to the same fabric.

**AG-1039**

<b>Message</b>	F_Port <Port that was reset> was reset because a WWN mapped device using it, through N_Port <Port who's state change caused the reset>, went offline.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified F_Port was reset because an N_Port went offline and the changes need to be propagated to all involved devices.
<b>Recommended Action</b>	No action is required. This port reset was not an error.

**AG-1040**

<b>Message</b>	PID of the devices connected to Port <port number> may have changed, as the port was toggled. Check EE monitor configuration as it might not be functional.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that N_Port ID virtualization (NPIV) assigns a new port ID (PID) each time the same port is disabled and then re-enabled. As the PID has changed, the end-to-end (EE) monitors installed with the previous PID stops functioning.
<b>Recommended Action</b>	Install new EE monitors with the new PID of the port to be monitored by using the <b>perfAddEEMonitor</b> command.

**AG-1041**

<b>Message</b>	Static F_Ports mapped to N_Port <port number> are disabled as Trunking is enabled on the N_Port.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a trunk is enabled on the specified N_Port, and therefore the F_Port static mapping is disabled.
<b>Recommended Action</b>	Delete static mapping on the Access Gateway using the <b>ag --staticdel</b> command or disable the trunk on the N_Port using the <b>switchCfgTrunkPort</b> command.



## AG-1042

<b>Message</b>	Sending ELS_PORT_OPEN failed on N_Port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates there was a failure sending an ELS_PORT_OPEN request from the Access Gateway to the fabric switch.
<b>Recommended Action</b>	Check the configuration of the fabric switch connected to the Access Gateway. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AG-1043

<b>Message</b>	Authentication cannot be negotiated with the connected switch/HBA and therefore disabling the Port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that authentication has failed on the specified port. A possible reason could be that the edge switch connected to Access Gateway is using firmware earlier than Fabric OS v7.1.0.
<b>Recommended Action</b>	Check the authentication configuration of the edge switch using the <b>authutil --show</b> command.

## AG-1044

<b>Message</b>	Port <Port Number> has been disabled because switch requires authentication when device authentication policy is set to ON.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a device that does not support authentication has tried to log in to the switch when the device authentication policy is in ON status on the switch.
<b>Recommended Action</b>	Enable the authentication on the device or set the device authentication status to PASSIVE/OFF on the switch if it is not mandatory. Use the <b>authUtil</b> command to change the device authentication policy.

## AN Messages

### AN-1001

<b>Message</b>	Failed to allocate memory: (<function name>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified function has failed to allocate memory.
<b>Recommended Action</b>	Check memory usage on the switch using the <b>memShow</b> command. Restart or power cycle the switch.

### AN-1002

<b>Message</b>	Failed to initialize; rc = <error>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the initialization of the "trafd" daemon has failed.
<b>Recommended Action</b>	Download a new firmware version using the <b>firmwareDownload</b> command.

### AN-1003

<b>Message</b>	Latency bottleneck on port <slot number>/<port number within slot number>. <percentage of seconds affected by latency bottlenecking> pct. of <observation period over which the percentage of affected seconds is reported> secs. affected. Avg. delay <observed average time between frames during affected seconds> us. Avg. slowdown <observed throughput drop factor during affected seconds>.
<b>Message Type</b>	LOG   AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	WARNING
<b>Probable Cause</b>	For an F_Port, indicates that the attached device is slow in responding to frames going out of the specified port. This latency may be inherent in the device or due to heavy workload on the device.  For a long-distance E_Port, may indicate too few credits for the distance. For a non-long-distance E_Port, indicates latency produced by a device downstream of the E_Port and is an indication of back-pressure produced by that latency.

**Recommended Action** If the port is an F\_Port, examine the connected device for the source of the latency. If the port is a long-distance E\_Port, make sure that there are enough buffer credits to service the link distance.

## AN-1004

**Message** Congestion bottleneck on port <slot number>/<port number within slot number>. <percentage of seconds affected by congestion bottlenecking> pct. of <observation period over which the percentage of affected seconds is reported> secs. affected.

**Message Type** LOG | AUDIT

**Class** FABRIC

**Severity** WARNING

**Probable Cause** Indicates that the volume of outgoing traffic at the specified port is too high for the capacity of the link.

**Recommended Action** Add more capacity on the path, using trunk links if possible.

## AN-1005

**Message** Slot <slot number>, port <port number within slot number> has <bottleneck type> bottleneck cleared.

**Message Type** LOG | AUDIT

**Class** FABRIC

**Severity** INFO

**Probable Cause** Indicates that the bottleneck condition on the specified port has cleared.

**Recommended Action** No action is required.

## AN-1006

**Message** Bottleneck detection configuration is successfully changed.

**Message Type** AUDIT

**Class** FABRIC

**Severity** INFO

**Probable Cause** Indicates that the bottleneck detection configuration has been changed.

**Recommended Action** No action is required.

## AN-1010

<b>Message</b>	Severe latency bottleneck detected at slot <slot number> port <port number within slot number>.
<b>Message Type</b>	LOG   AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates credit loss at the specified port, a downstream port, or a very high latency device at the edge of the fabric.
<b>Recommended Action</b>	Contact your switch service provider for assistance.

## AN-1011

<b>Message</b>	Could not distinguish between primary and dependent severe latency bottleneck on slot <slot number> port <port number within slot number> because port mirroring is enabled on this port.
<b>Message Type</b>	LOG   AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that resources that are needed to determine whether there is complete credit loss on a virtual channel (VC) at the specified port are used by port mirroring.
<b>Recommended Action</b>	Contact your switch service provider for assistance.

## AN-1012

<b>Message</b>	Credits did not return from other end. Complete loss of credits on a VC on slot <slot number> port <port number within slot number>.
<b>Message Type</b>	LOG   AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a credit loss.
<b>Recommended Action</b>	If this message is not followed by the AN-1013 message, contact your switch service provider for assistance.

## AN-1013

<b>Message</b>	Performed link reset to recover the port credits on slot <slot number> port <port number within slot number>.
<b>Message Type</b>	LOG   AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a credit loss.
<b>Recommended Action</b>	The port is recovered. No action is required.

## ANV Messages

### ANV-1001

<b>Message</b>	Port <port number> port fault. Change the SFP or check the cable.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a deteriorated small form-factor pluggable (SFP) transceiver, an incompatible SFP transceiver pair, or a faulty cable between the peer ports.
<b>Recommended Action</b>	Verify that compatible SFP transceivers are used on the peer ports, the SFP transceivers have not deteriorated, and the Fibre Channel cable is not faulty. Replace the SFP transceivers or the cable, if necessary.

### ANV-1002

<b>Message</b>	Port <port number> chip faulted due to an internal error.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal error. All the ports on the chip will be disrupted.
<b>Recommended Action</b>	To recover a bladed system, execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands on the blade. To recover a non-bladed system, execute the <b>fastBoot</b> command on the switch.

### ANV-1003

<b>Message</b>	S<slot number>,C<chip index>: HW ASIC Chip error. Type = 0x<chip error type>, Error = <chip error string>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates an internal error in the application-specific integrated circuit (ASIC) hardware that may degrade the data traffic.
<b>Recommended Action</b>	Restart the system at the next maintenance window. If the problem persists, replace the blade.

## ANV-1004

<b>Message</b>	S<slot number>,C<chip index>: Invalid DMA ch pointer, chan:<Channel number>, good_addr:0x<Good address> bad_addr:0x<Bad address>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal error in the application-specific integrated circuit (ASIC) hardware that may degrade the data traffic.
<b>Recommended Action</b>	Restart the system at the next maintenance window. If the problem persists, replace the blade.

## ANV-1005

<b>Message</b>	S<slot number>,C<chip index>,A<anvil id>: Memory allocation failed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates memory allocation failure in the software.
<b>Recommended Action</b>	Restart the system at the next maintenance window. If the problem persists, replace the switch or contact your switch service provider.

## ANV-1006

<b>Message</b>	S<slot number>,C<chip index>: HW ASIC Chip fault. Type = 0x<chip error type>, Error = <chip error string>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates an internal error in the application-specific integrated circuit (ASIC) hardware that renders the chip as not operational.
<b>Recommended Action</b>	Restart the system at the next maintenance window. If the problem persists, replace the blade.

**ANV-1007**

<b>Message</b>	S<slot number>,C<chip index>: ANVIL PASS 1 low buff pool fault: <chip regval field> 0x<chip error type>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that Anvil Pass 1 is running out of free buffers, which may cause chip fault.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

**ANV-1008**

<b>Message</b>	S<slot number>,C<chip index>: MAC-VID classifier table is full. No space for new entry.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Media Access Control (MAC) VLAN ID (VID) classifier table is full and no more entries can be added.
<b>Recommended Action</b>	Delete some of the existing unused rules using the <b>portcfg arp</b> command and then add new entries.

**ANV-1015**

<b>Message</b>	Port reinitialized due to Link Reset failure on internal port S<slot number>,P<port number>(<blade port number>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified port is re-initialized due to link reset failure.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.



## ANV-1016

<b>Message</b>	Port is faulted due to port reinitialization failure on internal port S<slot number>,P<port number>(<blade port number>) with reason <port fault reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified port is faulted due to port re-initialization failure.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## ANV-1028

<b>Message</b>	Detected excessive Link resets on the port in a second. Slot <slot number>, Port <port number>(<blade port number>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the port received excessive link resets from peer port within 1 second and that exceeded threshold.
<b>Recommended Action</b>	When this error is observed persistently, change the small form-factor pluggable (SFP) transceiver or the cable on the peer port to which this port is connected.

## AUTH Messages

### AUTH-1001

<b>Message</b>	<Operation type> has been successfully completed.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the secret database operation has been updated using the <b>secAuthSecret</b> command. The values for <i>Operation type</i> can be "set" or "remove".
<b>Recommended Action</b>	No action is required.

### AUTH-1002

<b>Message</b>	<Operation type> has failed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified action has failed to update the secret database using the <b>secAuthSecret</b> command. The values for <i>Operation type</i> can be "set" or "remove".
<b>Recommended Action</b>	Execute the <b>secAuthSecret</b> command again. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

### AUTH-1003

<b>Message</b>	<data type> type has been successfully set to <setting value>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that an authentication configuration value was set to a specified value. The <i>data type</i> is authentication type, DH group type, hash type, or policy type.
<b>Recommended Action</b>	No action is required.

## AUTH-1004

<b>Message</b>	Failed to set <data type> type to <setting value>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the <b>authUtil</b> command has failed to set the authentication configuration value. The <i>data type</i> can be authentication type, DH group type, hash type, or policy type.
<b>Recommended Action</b>	Execute the <b>authUtil</b> command again. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AUTH-1005

<b>Message</b>	Authentication file does not exist: <error code>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an authentication file corruption.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AUTH-1006

<b>Message</b>	Failed to open authentication configuration file.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an internal problem with the Secure Fabric OS.
<b>Recommended Action</b>	Reinitialize authentication using the <b>portDisable</b> and <b>portEnable</b> commands or the <b>switchDisable</b> and <b>switchEnable</b> commands. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AUTH-1007

<b>Message</b>	The proposed authentication protocol(s) are not supported: port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the proposed authentication protocol types are not supported by the specified local port.
<b>Recommended Action</b>	Execute the <b>authUtil</b> command to make sure the local switch supports the Fibre Channel Authentication Protocol (FCAP) or Diffie Hellman - Channel Authentication Protocol (DH-CHAP) protocols.

## AUTH-1008

<b>Message</b>	No security license, operation failed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the switch does not have a security license.
<b>Recommended Action</b>	Verify that the security license is installed using the <b>licenseShow</b> command. If necessary, reinstall the license using the <b>licenseAdd</b> command.

## AUTH-1010

<b>Message</b>	Failed to initialize security policy: switch <switch number>, error <error code>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal problem with the Secure Fabric OS.
<b>Recommended Action</b>	Reboot or power cycle the switch. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AUTH-1011

<b>Message</b>	Failed to register for failover operation: switch <switch number> error <error code>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an internal problem with the Secure Fabric OS.
<b>Recommended Action</b>	Reinitialize authentication using the <b>portDisable</b> and <b>portEnable</b> commands or the <b>switchDisable</b> and <b>switchEnable</b> commands.  If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AUTH-1012

<b>Message</b>	Authentication <code> is rejected: port <port number> explain <explain code> reason <reason code>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified authentication is rejected because the remote entity does not support authentication.
<b>Recommended Action</b>	Verify the hash type, protocol, group, and authentication policy using the <b>authutil --show</b> command.

## AUTH-1013

<b>Message</b>	Cannot perform authentication request message: port <port number>, message code <message code>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the system is running low on resources when receiving an authentication request. Usually this problem is transient. The authentication may fail.
<b>Recommended Action</b>	Reinitialize authentication using the <b>portDisable</b> and <b>portEnable</b> commands or the <b>switchDisable</b> and <b>switchEnable</b> commands.  If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AUTH-1014

<b>Message</b>	Invalid port value to <operation>: port <port number>.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal problem with the Secure Fabric OS.
<b>Recommended Action</b>	<p>Reinitialize authentication using the <b>portDisable</b> and <b>portEnable</b> commands or the <b>switchDisable</b> and <b>switchEnable</b> commands.</p> <p>If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.</p>

## AUTH-1016

<b>Message</b>	Invalid value to start HBA authentication port: <port number>, pid <pid>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal failure.
<b>Recommended Action</b>	Copy the message and collect the switch information using the <b>supportShow</b> command, and contact your switch service provider.

## AUTH-1017

<b>Message</b>	Invalid value to start authentication request: port <port number>, operation code <operation code>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal problem with the Secure Fabric OS.
<b>Recommended Action</b>	<p>Reinitialize authentication using the <b>portDisable</b> and <b>portEnable</b> commands or the <b>switchDisable</b> and <b>switchEnable</b> commands.</p> <p>If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.</p>

## AUTH-1018

<b>Message</b>	Invalid value to check protocol type: port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal problem with the Secure Fabric OS.
<b>Recommended Action</b>	Reinitialize authentication using the <b>portDisable</b> and <b>portEnable</b> commands or the <b>switchDisable</b> and <b>switchEnable</b> commands.  If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AUTH-1020

<b>Message</b>	Failed to create timer for authentication: port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that an authentication message timer was not created. Usually this problem is transient. The authentication may fail.
<b>Recommended Action</b>	Reinitialize authentication using the <b>portDisable</b> and <b>portEnable</b> commands or the <b>switchDisable</b> and <b>switchEnable</b> commands.  If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AUTH-1022

<b>Message</b>	Failed to extract <data type> from <message> payload: port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the authentication process failed to extract a particular value from the receiving payload. Usually this problem is transient. The authentication may fail.
<b>Recommended Action</b>	Reinitialize authentication using the <b>portDisable</b> and <b>portEnable</b> commands or the <b>switchDisable</b> and <b>switchEnable</b> commands.  If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AUTH-1023

<b>Message</b>	Failed to <operation type> during <authentication phase>: port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	<p>Indicates an authentication operation failed for a certain authentication phase. The <i>Operation type</i> varies depending on authentication type:</p> <ul style="list-style-type: none"> <li>• Some operations for Switch Link Authentication Protocol (SLAP): certificate retrieve, certificate verification, signature verification, or nonce signing.</li> <li>• Some operations for Fibre Channel Authentication Protocol (FCAP): certificate retrieve, certificate verification, signature verification, or nonce signing.</li> <li>• Some operations for Diffie Hellman - Challenge Handshake Authentication Protocol (DH-CHAP): response calculation, challenge generation, or secret retrieve.</li> </ul> <p>The <i>authentication phase</i> specifies which phase of a particular authentication protocol failed.</p> <p>A nonce is a single-use, usually random value used in authentication protocols to prevent replay attacks.</p>
<b>Recommended Action</b>	<p>The error may indicate that an invalid entity tried to connect to the switch. Check the connection port for a possible unauthorized access attack.</p> <p>It may indicate that the public key infrastructure (PKI) object for SLAP or FCAP or the secret value for DH-CHAP on the local entity is not set up properly. Reinstall all PKI objects or reset the secret value for DH-CHAP properly.</p> <p>If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.</p>

## AUTH-1025

<b>Message</b>	Failed to get <data type> during <authentication phase>: port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the authentication process failed to get expected information during the specified authentication phase. Usually this problem is transient. The authentication may fail.
<b>Recommended Action</b>	<p>Reinitialize authentication using the <b>portDisable</b> and <b>portEnable</b> commands or the <b>switchDisable</b> and <b>switchEnable</b> commands.</p> <p>If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.</p>



## AUTH-1026

<b>Message</b>	Failed to <Device information> during negotiation phase: port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the authentication failed to get device or Host Bus Adapter (HBA) information due to an internal failure. Usually this problem is transient. If the authentication failed, retry the login.
<b>Recommended Action</b>	Reinitialize authentication using the <b>portDisable</b> and <b>portEnable</b> commands or the <b>switchDisable</b> and <b>switchEnable</b> commands.  If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AUTH-1027

<b>Message</b>	Failed to select <authentication value> during <authentication phase>: value <value> port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the authentication process failed to select an authentication value (DH Group, hash value, or protocol type) from a receiving payload for a particular authentication phase. This indicates that the local switch does not support the specified authentication value.
<b>Recommended Action</b>	Check the authentication configuration and reset the supported value if needed using the <b>authUtil</b> command.  Reinitialize authentication using the <b>portDisable</b> and <b>portEnable</b> commands or the <b>switchDisable</b> and <b>switchEnable</b> commands.  If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AUTH-1028

<b>Message</b>	Failed to allocate <data type> for <operation phase>: port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the authentication process failed because the system is low on memory. Usually this problem is transient. The authentication may fail.  The <i>Data type</i> is the payload or structure that failed to get memory. The <i>Operation phase</i> specifies which operation of a particular authentication phase failed.

## 5 AUTH-1029

**Recommended Action** Reinitialize authentication using the **portDisable** and **portEnable** commands or the **switchDisable** and **switchEnable** commands.

If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

### AUTH-1029

**Message** Failed to get <data type> for <message phase> message: port <port number>, retval <error code>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the authentication process failed to get a particular authentication value at a certain phase. Usually this problem is transient. The authentication may fail.

The *Data type* is the payload or structure that failed to get memory.

**Recommended Action** Reinitialize authentication using the **portDisable** and **portEnable** commands or the **switchDisable** and **switchEnable** commands.

If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

### AUTH-1030

**Message** Invalid message code for <message phase> message: port <port number>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the receiving payload does not have a valid message code for a particular authentication phase. Usually this problem is transient. The authentication may fail.

**Recommended Action** Reinitialize authentication using the **portDisable** and **portEnable** commands or the **switchDisable** and **switchEnable** commands.

If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

### AUTH-1031

**Message** Failed to retrieve secret value: port <port number>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the secret value was not set properly for the authenticated entity.

**Recommended Action** Reset the secret value using the **secAuthSecret** command.

Reinitialize authentication using the **portDisable** and **portEnable** commands or the **switchDisable** and **switchEnable** commands.

If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

## AUTH-1032

**Message** Failed to generate <data type> for <message payload> payload: length <data length>, error code <error code>, port <port number>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the authentication process failed to generate specific data (challenge, nonce, or response data) for an authentication payload. This usually relates to internal failure.

A nonce is a single-use, usually random value used in authentication protocols to prevent replay attacks. Usually this problem is transient. The authentication may fail.

**Recommended Action** Reinitialize authentication using the **portDisable** and **portEnable** commands or the **switchDisable** and **switchEnable** commands.

If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

## AUTH-1033

**Message** Disable port <port number> due to unauthorized switch <switch WWN value>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that an entity was not configured in the Switch Connection Control (SCC) policy and tried to connect to the port.

**Recommended Action** Add World Wide Name (WWN) of the entity to the SCC policy and reinitialize authentication by using the **portDisable** and **portEnable** commands or the **switchDisable** and **switchEnable** commands.

## AUTH-1034

**Message** Failed to validate name <entity name> in <authentication message>: port <port number>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the specified entity name in the payload is not in the correct format.

## 5 AUTH-1035

**Recommended Action** Reinitialize authentication using the **portDisable** and **portEnable** commands or the **switchDisable** and **switchEnable** commands.

If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

### AUTH-1035

**Message** Invalid <data type> length in <message phase> message: length <data length>, port <port number>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that a particular data field in the authentication message has an invalid length field. This error usually relates to internal failure. Usually this problem is transient. The authentication may fail.

**Recommended Action** Reinitialize authentication using the **portDisable** and **portEnable** commands or the **switchDisable** and **switchEnable** commands.

If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

### AUTH-1036

**Message** Invalid state <state value> for <authentication phase>: port <port number>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the switch received an unexpected authentication message. Usually this problem is transient. The authentication may fail.

**Recommended Action** Reinitialize authentication using the **portDisable** and **portEnable** commands or the **switchDisable** and **switchEnable** commands.

If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

## AUTH-1037

<b>Message</b>	Failed to <operation type> response for <authentication message>: init_len <data length>, resp_len <data length>, port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a Diffie Hellman - Challenge Handshake Authentication Protocol (DH-CHAP) authentication operation failed on the specified port due to mismatched response values between two entities.  The error may indicate that an invalid entity tried to connect to the switch. Check the connection port for a possible security attack.
<b>Recommended Action</b>	Reinitialize authentication using the <b>portDisable</b> and <b>portEnable</b> commands or the <b>switchDisable</b> and <b>switchEnable</b> commands.  If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AUTH-1038

<b>Message</b>	Failed to retrieve certificate during <authentication phase>: port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the public key infrastructure (PKI) certificate is not installed properly.
<b>Recommended Action</b>	Reinstall the PKI certificate using the <b>secCertUtil</b> command.  Reinitialize authentication using the <b>portDisable</b> and <b>portEnable</b> commands or the <b>switchDisable</b> and <b>switchEnable</b> commands.  If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## AUTH-1039

<b>Message</b>	Neighboring switch has conflicting authentication policy: Port <Port Number> disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the neighboring switch has a conflicting authentication policy enabled. The E_Port has been disabled because the neighboring switch has rejected the authentication negotiation, and the local switch has a strict switch authentication policy.

## 5 AUTH-1040

**Recommended Action** Correct the switch policy configuration on either of the switches using the **authUtil** command, and then enable the port using the **portEnable** command.

### AUTH-1040

**Message** Reject authentication on port <Port Number>, because switch authentication policy is set to OFF.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the local switch has rejected the authentication because the switch policy is turned off. If the neighboring switch has a strict (ON) switch policy, the port will be disabled due to conflicting configuration settings. Otherwise, the E\_Port will form without authentication.

**Recommended Action** If the port is disabled, correct the switch policy configuration on either of the switches using the **authUtil** command, and then enable the port on the neighboring switch using the **portEnable** command. If the E\_Port has formed, no action is required.

### AUTH-1041

**Message** Port <port number> has been disabled, because an authentication-reject was received with code '<Reason String>' and explanation '<Explanation String>'.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the specified port has been disabled because it received an authentication-reject response from the connected switch or device. The error may indicate that an invalid entity tried to connect to the switch.

**Recommended Action** Check the connection port for a possible security attack.  
Check the shared secrets using the **secAuthSecret** command and reinitialize authentication using the **portDisable** and **portEnable** commands.  
If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

### AUTH-1042

**Message** Port <port number> has been disabled, because authentication failed with code '<Reason String>' and explanation '<Explanation String>'.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the specified port has been disabled because the connecting switch or device failed to authenticate. The error may indicate that an invalid entity attempted to connect to the switch.

**Recommended Action** Check the connection port for a possible security attack.  
 Check the shared secrets using the **secAuthSecret** command and reinitialize authentication using the **portDisable** and **portEnable** commands.  
 If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

## AUTH-1043

**Message** Failed to enforce device authentication mode:<Device Auth Policy>(error: <Reason Code>).

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the Kernel mode setting for F\_Port authentication failed. Device authentication will be defaulted to OFF, and the switch will not participate in Diffie Hellman - Challenge Handshake Authentication Protocol (DH-CHAP) authentication with other devices.

**Recommended Action** Set the device authentication policy manually using the **authUtil** command.

## AUTH-1044

**Message** Authentication <Reason for disabling the port>. Disabling the port <port number>.

**Message Type** LOG | FFDC

**Severity** ERROR

**Probable Cause** Indicates that authentication has timed out after multiple retries. The specified port has been disabled as a result. This problem may be transient due to the system CPU load. In addition, a defective small form-factor pluggable (SFP) transceiver or faulty cable may have caused the failure.

**Recommended Action** Check the SFP transceiver and the cable; then enable the port using the **portEnable** command.

## AUTH-1045

**Message** Certificate not present in this switch in <authentication phase> port <port number>.

**Message Type** AUDIT | LOG

**Class** SECURITY

**Severity** ERROR

**Probable Cause** Indicates that the public key infrastructure (PKI) certificate is not installed in this switch.

## 5 AUTH-1046

**Recommended Action** Check the certificate availability using the **secCertUtil show -fcapall** command.  
Install the certificate and reinitialize authentication using the **portDisable** and **portEnable** commands or the **switchDisable** and **switchEnable** commands.  
If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

### AUTH-1046

**Message** <Operation type> has been successfully completed.

**Message Type** AUDIT | LOG

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates that the certificate database operation has been updated using the **secAuthCertificate** command. The values for *Operation type* can be "set" or "remove".

**Recommended Action** No action is required.

### AUTH-1047

**Message** <Operation type> has failed.

**Message Type** AUDIT | LOG

**Class** SECURITY

**Severity** ERROR

**Probable Cause** Indicates that the specified action has failed to update the certificate database using the **secAuthCertificate** command. The values for *Operation type* can be "set" or "remove".

**Recommended Action** Execute the **secAuthCertificate** command again.  
If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.



## AUTH-3001

<b>Message</b>	Event: <Event Name>, Status: success, Info: <Data type> type has been changed from [<Old value>] to [<New value>].
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that an authentication configuration value was set to a specified value. The <i>Data type</i> can be authentication type, DH group type, hash type, or policy type.
<b>Recommended Action</b>	No action is required.

## AUTH-3002

<b>Message</b>	Event: <Event Name>, Status: success, Info: <Event Related Info>.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the secret database operation has been updated using the <b>secAuthSecret</b> command.
<b>Recommended Action</b>	No action is required.

## AUTH-3003

<b>Message</b>	Event: <Event Name>, Status: success, Info: <Operation type> the PKI objects.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the public key infrastructure (PKI) objects were created using the <b>secCertUtil</b> command or that the PKI objects were removed using the <b>secCertUtil delete -fcapall</b> command. Operation type can be either "Created" or "Removed".
<b>Recommended Action</b>	No action is required.

## AUTH-3004

<b>Message</b>	Event: <Event Name>, Status: failed, Info: Neighboring switch has a conflicting authentication policy; Port <Port Number> disabled.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified E_Port was disabled because the neighboring switch rejected the authentication negotiation, and the local switch has a strict switch authentication policy.
<b>Recommended Action</b>	Correct the switch policy configuration on either of the switches using the <b>authUtil</b> command, and then enable the port using the <b>portEnable</b> command.

## AUTH-3005

<b>Message</b>	Event: <Event Name>, Status: failed, Info: Rejecting authentication request on port <Port Number> because switch policy is turned OFF.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the local switch has rejected the authentication request, because the switch policy is turned off. If the neighboring switch has a strict (ON) switch policy, the port will be disabled due to conflicting configuration settings. Otherwise, the E_Port will form without authentication.
<b>Recommended Action</b>	If the specified port is disabled, correct the switch policy configuration on either of the switches using the <b>authUtil</b> command, and then enable the port on the neighboring switch using the <b>portEnable</b> command. If the E_Port formed, no action is required.

## AUTH-3006

<b>Message</b>	Event: <Event Name>, Status: failed, Info: Authentication failed on port <port number> due to mismatch of DH-CHAP shared secrets.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a Diffie Hellman - Challenge Handshake Authentication Protocol (DH-CHAP) authentication operation failed on the specified port due to mismatched response values between two entities.  The error may indicate that an invalid entity tried to connect to the switch.

**Recommended Action** Check the connection port for a possible security attack.  
 Check the shared secrets using the **secAuthSecret** command and reinitialize authentication using the **portDisable** and **portEnable** commands.  
 If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

## AUTH-3007

**Message** Event: <Event Name>, Status: failed, Info: Port <port number> disabled due to receiving an authentication reject with code '<Reason String>' and Explanation '<Explanation String>'.

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates that the specified port was disabled because it received an authentication-reject response from the connected switch or device.

The error may indicate that an invalid entity tried to connect to the switch.

**Recommended Action** Check the connection port for a possible security attack.  
 Check the shared secrets using the **secAuthSecret** command and reinitialize authentication using the **portDisable** and **portEnable** commands.  
 If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

## AUTH-3008

**Message** Event: <Event Name>, Status: failed, Info: Port <port number> has been disabled due to authentication failure with code '<Reason String>' and explanation '<Explanation String>'.

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates that the specified port has been disabled because the connecting switch or device failed to authenticate.

The error may indicate that an invalid entity tried to connect to the switch.

**Recommended Action** Check the connection port for a possible security attack.  
 Check the shared secrets using the **secAuthSecret** command and reinitialize authentication using the **portDisable** and **portEnable** commands.  
 If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

## BKSW Messages

### BKSW-1003

<b>Message</b>	kSWD: <Warning message>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	<p>Indicates a warning state within the system.</p> <p>A critical application error was reported in the watchdog subsystem. This message is used to convey information regarding the state of the system. The switch will reboot (on single-CP switches) or fail over (on dual-CP switches).</p> <p>The <i>Warning message</i> variable will be one of the following:</p> <ul style="list-style-type: none"><li>• Detected unexpected termination of: <i>daemon name</i> - One of the critical daemons ended unexpectedly.</li><li>• <i>daemon name</i> failed to refresh SWD*** Sending SIGABRT to PID <i>process id number</i> - One of the critical daemons is found to be nonresponsive; sending signal abort (SIGABRT).</li></ul>
<b>Recommended Action</b>	Execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## BL Messages

### BL-1000

<b>Message</b>	Initializing ports...
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the switch has started initializing the ports.
<b>Recommended Action</b>	No action is required.

### BL-1001

<b>Message</b>	Port initialization completed.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the switch has completed initializing the ports.
<b>Recommended Action</b>	No action is required.

### BL-1002

<b>Message</b>	Init Failed: slot <slot number> DISABLED because internal ports were not ONLINE, <list of internal port number not ONLINE>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the blade initiation failed because one or more of the internal ports was not online. The blade is faulted.
<b>Recommended Action</b>	<p>Make sure that the blade is seated correctly.</p> <p>If the blade is seated correctly, execute the <b>diagPost</b> command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems.</p> <p>Additional blade fault messages precede and follow this error, providing more information. Refer to other error messages for recommended action.</p> <p>If the message persists, replace the blade.</p>

**BL-1003**

<b>Message</b>	Faulting blade in slot <slot number>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates a faulty blade in the specified slot.
<b>Recommended Action</b>	<p>Make sure that the blade is seated correctly.</p> <p>If the blade is seated correctly, execute the <b>diagPost</b> command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems.</p> <p>If the message persists, replace the blade.</p>

**BL-1004**

<b>Message</b>	Suppressing blade fault in slot <slot number>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the specified blade experienced a failure but was not faulted due to a user setting.
<b>Recommended Action</b>	<p>Execute the <b>diagPost</b> command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems.</p> <p>If the message persists, replace the blade.</p>

**BL-1006**

<b>Message</b>	Blade <slot number> NOT faulted. Peer blade <slot number> experienced abrupt failure.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the errors (mostly synchronization errors) on the specified blade are harmless. Probably, the standby control processor (CP) blade connected to the active CP blade has experienced transitory problems.
<b>Recommended Action</b>	<p>Execute the <b>haShow</b> command to verify that the standby CP is healthy. If the problem persists, remove and reinstall the faulty blade.</p> <p>If the standby CP was removed or faulted by user intervention, no action is required.</p>

## BL-1007

<b>Message</b>	blade #<blade number>: blade state is inconsistent with EM. bl_cflags 0x<blade control flags>, slot_on <slot_on flag>, slot_off <slot_off flag>, faulty <faulty flag>, status <blade status>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a failover occurred while a blade was initializing on the previously active control processor (CP).
<b>Recommended Action</b>	No action is required. The blade is reinitialized. Because reinitializing a blade is a disruptive operation and can stop I/O traffic, you may need to stop and restart the traffic during this process.

## BL-1008

<b>Message</b>	Slot <slot number> control-plane failure. Expected value: 0x<value 1>, Actual: 0x<value 2>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the blade has experienced a hardware failure or was removed without following the recommended removal procedure.
<b>Recommended Action</b>	<p>Make sure that the blade is seated correctly.</p> <p>If the blade is seated correctly, execute the <b>diagPost</b> command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems.</p> <p>If the message persists, replace the blade.</p>

## BL-1009

<b>Message</b>	Blade in slot <slot number> timed out initializing the chips.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the blade has failed to initialize the application-specific integrated circuit (ASIC) chips.

## 5 BL-1010

<b>Recommended Action</b>	<p>Make sure that the blade is seated correctly.</p> <p>If the blade is seated correctly, execute the <b>diagPost</b> command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems.</p> <p>If the message persists, replace the blade.</p>
---------------------------	------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

## BL-1010

<b>Message</b>	Blade in slot <slot number> inconsistent with the hardware settings.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a failover occurred while some hardware changes (such as changing the domain ID) were being made on the previously active control processor (CP).
<b>Recommended Action</b>	No action is required. This blade has been reinitialized. Because reinitializing a blade is a disruptive operation and can stop I/O traffic, you may need to stop and restart the traffic during this process.

## BL-1011

<b>Message</b>	Busy with emb-port int. for chip <chip number> in minis <minis number> on blade <slot number>, chip int. is disabled. interrupt status=0x<interrupt status>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that too many interrupts in the embedded port caused the specified chip to be disabled. The probable cause is too many abnormal frames; the chip is disabled to prevent the control processor (CP) from becoming too busy.
<b>Recommended Action</b>	<p>Make sure to capture the console output during this process.</p> <p>Check for a faulty cable, small form-factor pluggable (SFP) transceiver, or device attached to the specified port.</p> <p>On a bladed switch, execute the <b>diagPost</b> command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems.</p> <p>On a non-bladed switch, reboot or power cycle the switch.</p> <p>If the message persists, replace the blade or the (non-bladed) switch.</p>



## BL-1012

<b>Message</b>	bport <port number> port int. is disabled. status=0x<interrupt status> Port <port number> will be re-enabled in 1 minute.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the port generated an excessive number of interrupts that may prove unrecoverable to the switch operation. The port is disabled to prevent the control processor (CP) from becoming too busy. The bport is the blade port; this number may not correspond to a user port number.
<b>Recommended Action</b>	<p>Make sure to capture the console output during this process.</p> <p>Check for a faulty cable, small form-factor pluggable (SFP) transceiver, or device attached to the specified port.</p> <p>On a bladed switch, run the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands to power cycle the blade.</p> <p>On a non-bladed switch, reboot or power cycle the switch.</p> <p>If the message persists, replace the blade or the (non-bladed) switch.</p>

## BL-1013

<b>Message</b>	bport <port number> port is faulted. status=0x<interrupt status> Port <port number> will be re-enabled in 1 minute.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the port generated an excessive number of interrupts that may prove fatal to the switch operation. The port is disabled to prevent the control processor (CP) from becoming too busy. The <i>bport</i> number displayed in the message is the blade port; this number may not correspond to a user port number.
<b>Recommended Action</b>	<p>Make sure to capture the console output during this process.</p> <p>Check for a faulty cable, small form-factor pluggable (SFP) transceiver, or device attached to the specified port.</p> <p>On a bladed switch, run the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands to power cycle the blade.</p> <p>On a non-bladed switch, reboot or power cycle the switch.</p> <p>If the message persists, replace the blade.</p>

## BL-1014

<b>Message</b>	<code>bport &lt;port number&gt; port int. is disabled. status=0x&lt;interrupt status&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the port generated an excessive number of interrupts that may prove fatal to the switch operation. The port is disabled to prevent the control processor (CP) from becoming too busy. The <i>bport</i> number displayed in the message is the blade port; this number may not correspond to a user port number.
<b>Recommended Action</b>	<p>Make sure to capture the console output during this process.</p> <p>On a bladed switch, execute the <b>diagPost</b> command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems.</p> <p>On a non-bladed switch, execute the <b>reboot</b> command to restart the switch.</p> <p>If there is a hardware error, the <b>slotPowerOff</b> or <b>slotPowerOn</b> fails on the bladed switch, or errors are encountered again, replace the blade or the (non-bladed) switch.</p>

## BL-1015

<b>Message</b>	<code>bport &lt;port number&gt; port is faulted. status=0x&lt;interrupt status&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the port generated an excessive number of interrupts that may prove fatal to the switch operation. The port is disabled to prevent the control processor (CP) from becoming too busy. The <i>bport</i> number displayed in the message is the blade port; this number may not correspond to a user port number.
<b>Recommended Action</b>	<p>Make sure to capture the console output during this process.</p> <p>On a bladed switch, execute the <b>diagPost</b> command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems.</p> <p>On a non-bladed switch, execute the <b>reboot</b> command to restart the switch.</p> <p>If there is a hardware error, the <b>slotPowerOff</b> or <b>slotPowerOn</b> fails on the bladed switch, or errors are encountered again, replace the blade or the (non-bladed) switch.</p>

## BL-1016

<b>Message</b>	Blade port <port number> in slot <slot number> failed to enable.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the specified blade port could not be enabled.
<b>Recommended Action</b>	<p>Make sure that the blade is seated correctly.</p> <p>If the blade is seated correctly, execute the <b>diagPost</b> command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems.</p> <p>If the message persists, replace the blade.</p>

## BL-1017

<b>Message</b>	Slot <slot number> Initializing...
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the slot has started initializing the ports.
<b>Recommended Action</b>	No action is required.

## BL-1018

<b>Message</b>	Slot <slot number> Initialization completed.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the slot has completed initializing the ports.
<b>Recommended Action</b>	No action is required.

## BL-1019

<b>Message</b>	Slot <Slot number>, retry <Retry Number>, internal port retry initialization, <List of internal ports retrying initialization>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the slot had internal ports that are not online. Initiated a retry on ports that failed to go online.
<b>Recommended Action</b>	No action is required.

## BL-1020

<b>Message</b>	Switch timed out initializing the chips.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the switch has failed to initialize the application-specific integrated circuit (ASIC) chips.
<b>Recommended Action</b>	Reboot or power cycle the switch. If the message persists, replace the switch.

## BL-1021

<b>Message</b>	Retry <Retry Number>, internal port retry initialization, <List of internal ports retrying initialization>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the switch had internal ports that are not online. Initiated a retry on ports that failed to go online.
<b>Recommended Action</b>	No action is required.

## BL-1022

<b>Message</b>	Init Failed: Switch DISABLED because internal ports were not ONLINE, <list of internal port number not ONLINE>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the switch initiation failed because one or more of the internal ports was not online. The switch is faulted.
<b>Recommended Action</b>	Reboot or power cycle the switch. Additional fault messages precede and follow this error providing more information. Refer to other error messages for recommended action. If the message persists, replace the switch.

## BL-1023

<b>Message</b>	Blade in slot <slot number> was reset before blade init completed. As a result the blade is faulted.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the blade was reset before the initialization completed.
<b>Recommended Action</b>	Reboot or power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the message persists, replace the blade.

## BL-1024

<b>Message</b>	All ports on the blade in slot <slot number> will be reset as part of the firmware upgrade.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a recent firmware upgrade caused the blade firmware to be upgraded and resulted in the cold upgrade. As part of the upgrade, all datapath elements were reset.
<b>Recommended Action</b>	No action is required.

**BL-1025**

<b>Message</b>	All GigE/FCIP/Virtualization/FC Fastwrite ports on the blade in slot <slot number> will be reset as part of the firmware upgrade.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a recent firmware upgrade caused the blade's firmware to be upgraded and resulted in the cold upgrade. As part of the upgrade, all the Gigabit Ethernet, Fibre Channel over IP (FCIP), virtualization data elements, and FC Fastwrite ports were reset.
<b>Recommended Action</b>	No action is required.

**BL-1026**

<b>Message</b>	Internal port offline during warm recovery, state <port state> (0x<port ID>).
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that an internal port went offline during warm recovery of the switch. The switch will reboot and start cold recovery.
<b>Recommended Action</b>	Execute the <b>supportSave</b> command and then reboot switch. If the problem persists, replace the switch.

**BL-1027**

<b>Message</b>	Blade in slot <slot number> faulted, boot failed; status 0x<boot status> 0x<1250 0 boot status> 0x<1250 1 boot status>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the blade failed to boot properly.
<b>Recommended Action</b>	Reboot or power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the message persists, replace the blade.

## BL-1028

<b>Message</b>	Switch faulted; internal processor was reset before switch init completed.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the switch internal processor was reset before the initialization completed.
<b>Recommended Action</b>	Reboot or power cycle the switch using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the message persists, replace the switch.

## BL-1029

<b>Message</b>	All ports on the switch will be reset as part of the firmware upgrade.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a recent firmware upgrade caused the switch internal processor firmware to be upgraded and resulted in a cold upgrade. As part of the upgrade, all the datapath elements were reset.
<b>Recommended Action</b>	No action is required.

## BL-1030

<b>Message</b>	All GigE/FCIP/Virtualization/FC Fastwrite ports on the switch will be reset as part of the firmware upgrade.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a recent firmware upgrade caused the switch internal processor firmware to be upgraded and resulted in the cold upgrade. As part of the upgrade, all Gigabit Ethernet, Fibre Channel over IP (FCIP), virtualization data elements, and FC Fastwrite ports were reset.
<b>Recommended Action</b>	No action is required.

**BL-1031**

<b>Message</b>	Link timeout in internal port (slot <slot number>, port <port number>) resulted in blade fault. Use <code>slotpoweroff/slotpoweron</code> to recover the blade.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that link timeout occurred in one of the back-end internal ports.
<b>Recommended Action</b>	Power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands.

**BL-1032**

<b>Message</b>	(slot <slot number>,bitmap 0x<object control flags(bitmap)>) ports never came up ONLINE (reason <reason for port disable>, state <status of the blade>). Disabling slot.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that back-end (non-user) ports have not come online within the time limit.
<b>Recommended Action</b>	Execute the <b>diagPost</b> command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems.  If the message persists, replace the blade.

**BL-1033**

<b>Message</b>	(slot <slot number>,bitmap 0x<object control flags(bitmap)>) No disable acknowledgment from ports (state <status of the blade>). Disabling slot.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the system has timed out waiting for the disable messages from the user ports after disabling the ports.
<b>Recommended Action</b>	Execute the <b>diagPost</b> command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems.  If the message persists, replace the blade.



## BL-1034

<b>Message</b>	Slot <slot number> FC Initialization completed.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the slot has completed initializing the Fibre Channel (FC) ports.
<b>Recommended Action</b>	No action is required.

## BL-1035

<b>Message</b>	Slot <slot number> iSCSI port <iscsi port number> Initialization completed.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the slot has completed initializing the specified iSCSI port.
<b>Recommended Action</b>	No action is required.

## BL-1036

<b>Message</b>	Faulting 8G blade in slot = <slot number> due to incompatible stag mode. All EX/VEX ports must be disabled in order to enable the 8G blade in the chassis.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the 8 Gbps blade with legacy mode (EX_port having stag) will be disabled.
<b>Recommended Action</b>	Disable all EX_Ports and VEX_Ports and execute the <b>slotPowerOff</b> or <b>slotPowerOn</b> commands on the 8 Gbps blade. All EX_Ports and VEX_Ports can be re-enabled.

**BL-1037**

<b>Message</b>	Faulting chip in slot = <slot number>, miniS = <miniS number>,port = <port number> due to BE/BI port fault.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that all ports on the chip have been disabled due to a fault on the chip.
<b>Recommended Action</b>	<p>Make sure that the blade is seated correctly.</p> <p>If the blade is seated correctly, execute the <b>diagPost</b> command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems.</p> <p>Additional blade fault messages precede and follow this error, providing more information. Refer to other error messages for recommended action.</p> <p>If the message persists, replace the blade.</p>

**BL-1038**

<b>Message</b>	Inconsistent FPGA image version detected, please reboot the switch for recovery.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the field-programmable gate array (FPGA) image version is incompatible with the software version.
<b>Recommended Action</b>	Reboot the switch. If the message persists, replace the switch.

**BL-1039**

<b>Message</b>	Inconsistent FPGA image version detected, faulting the blade in slot <slot number>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the field-programmable gate array (FPGA) image version is incompatible with the software version.
<b>Recommended Action</b>	<p>Power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands.</p> <p>If the message persists, replace the blade.</p>

## BL-1041

<b>Message</b>	Dynamic area mode is enabled on default switch, Faulting the blade w/ ID <Blade ID of blade that has the mini SFP+ that does not support it> in slot <slot number> as it does not support this mode.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the blade does not support dynamic area mode on the default switch.
<b>Recommended Action</b>	Turn off the dynamic area mode using the <b>configure</b> command.

## BL-1045

<b>Message</b>	mini SFP+ (SN: <mini SFP+ serial number>) is only supported in certain high port count blades, not blade in slot <slot number of blade that has the mini SFP+ w/ ID <Blade ID of blade that has the mini SFP+ that does not support it>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that mini-SFP+ is supported only by a certain type of blade (FC8-64), but it can be inserted in other blades.
<b>Recommended Action</b>	Replace the mini-SFP+ with an SFP or SFP+.

## BL-1046

<b>Message</b>	<Slot number of blade that has the SFP> error on SFP in Slot <Port number into which the SFP is inserted>/Port <The type of error "checksum" or "data access" for general problems accessing the i2c accessible data> (<A detailed error code>). Try reseating or replacing it.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the checksum in an area on the small form-factor pluggable (SFP) transceiver does not match with the computed value, or there is problem accessing the data.
<b>Recommended Action</b>	Reseat the SFP transceiver. If problem persists, replace the SFP transceiver.

## BL-1047

<b>Message</b>	Buffer optimized mode is turned <buffer optimized mode> for slot <slot number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the buffer optimized mode is changed for the specified slot.
<b>Recommended Action</b>	No action is required.

## BL-1048

<b>Message</b>	FCoE Blade in slot <Slot> failed because the Interop mode is enabled on the switch.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the interop mode is turned on in the default switch while powering on the FCoE blade.
<b>Recommended Action</b>	Disable the interop mode using the <b>interopmode</b> command; then execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands on the FCoE blade.

## BL-1049

<b>Message</b>	Serdestunemode: <serdestuning mode>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the SerDes tuning mode is changed for the slot.
<b>Recommended Action</b>	No action is required.

## BL-1050

<b>Message</b>	Incompatible Blade Processor FPGA version with FOS7.0 firmware in slot=<slot number> on FX8-24. Contact support for upgrade instructions.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the blade processor field-programmable gate array (FPGA) version with Fabric OS v7.0.0 is incompatible on the FX8-24 blade.
<b>Recommended Action</b>	Contact your switch service provider for upgrade instructions.

## BL-1051

<b>Message</b>	Incompatible Blade Processor FPGA version with FOS7.0 firmware on 7800. Contact support for upgrade instructions.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the blade processor field-programmable gate array (FPGA) version with Fabric OS v7.0.0 is incompatible on the Brocade 7800 switch.
<b>Recommended Action</b>	Contact your switch service provider for upgrade instructions.

## BL-1052

<b>Message</b>	Link Reset threshold exceeded in the internal port (slot <slot number>, port <port number>). No core blade has been faulted because it has only one active core blade.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the internal port in the core blade exceeded the link reset threshold level. Faulting the peer edge blade because there is only one active core blade.
<b>Recommended Action</b>	Replace the core blade.

## BLS Messages

### BLS-1000

<b>Message</b>	<command name> of GE <port number> failed. Please retry the command. Data: inst=<ASIC instance> st=<ASIC initializing state> rsn=<reason code> fn=<message function> oid=<ASIC ID>.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the hardware is not responding to a command request, possibly because it is busy.
<b>Recommended Action</b>	Retry the command.

### BLS-1001

<b>Message</b>	FIPS <FIPS Test Name> failed; algo=<algorithm code> type=<algorithm type> slot=<Slot Number>.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that a Federal Information Protection Standard (FIPS) failure has occurred and requires faulting the blade or switch.
<b>Recommended Action</b>	Retry the command.

### BLS-1002

<b>Message</b>	An IPsec/IKE policy was added.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that an Internet Protocol Security (IPsec) or Internet Key Exchange (IKE) policy was added and the configuration file was updated.
<b>Recommended Action</b>	No action is required.

**BLS-1003**

<b>Message</b>	An IPsec/IKE policy was deleted.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that an Internet Protocol Security (IPsec) or Internet Key Exchange (IKE) policy was deleted and the configuration file was updated.
<b>Recommended Action</b>	No action is required.

**BLS-1004**

<b>Message</b>	Tape Read Pipelining is being disabled slot (<slot number>) port (<user port index>) tunnel (<The configured tunnel ID (0-7)>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Fabric OS version on the remote end of the tunnel does not support Tape Read Pipelining.
<b>Recommended Action</b>	No action is required.

**BLS-1005**

<b>Message</b>	S<slot number>,P<user port index>(<blade index>) [OID 0x<port OID>]: <string name of ge>: port faulted due to SFP validation failure. Please check if the SFP is valid for the configuration.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a deteriorated small form-factor pluggable (SFP) transceiver, an incompatible SFP transceiver pair, or a faulty cable between the peer ports.
<b>Recommended Action</b>	Verify that compatible SFP transceivers are used on the peer ports, the SFP transceivers have not deteriorated, and the Fibre Channel cable is not faulty. Replace the SFP transceivers or the cable if necessary.

## BM Messages

### BM-1001

<b>Message</b>	BM protocol version <Protocol version> in slot <Slot number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the firmware running on the control processor (CP) cannot communicate with the application processor (AP) blade in the indicated slot and determine the AP blade's firmware version. The reason can be one of the following: <ul style="list-style-type: none"> <li>• The CP blade is running a later version of firmware than the AP blade.</li> <li>• The CP blade is running an earlier version of firmware than the AP blade.</li> </ul>
<b>Recommended Action</b>	The problem can be corrected by changing the firmware version on either the CP or on the AP blade. You can modify the firmware version on the CP blade by using the <b>firmwareDownload</b> command. Refer to the release notes to determine whether a non-disruptive firmware download is supported between the revisions. Because the AP and CP blades cannot communicate, it is not possible to load new firmware on the AP blade. If necessary, send the AP blade back to the factory for a firmware update.

### BM-1002

<b>Message</b>	Connection established between CP and blade in slot <Slot number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the control processor (CP) has established a connection to the blade processor (BP) and can communicate.
<b>Recommended Action</b>	No action is required.

### BM-1003

<b>Message</b>	Failed to establish connection between CP and blade in slot <Slot number>. Faulting blade.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the control processor (CP) could not establish a connection to the blade processor (BP) to communicate.



**Recommended Action** Execute the **slotPowerOff** and **slotPowerOn** commands or reseal the affected blade.

## BM-1004

**Message** Blade firmware <Blade firmware> on slot <Slot> is not consistent with system firmware <System firmware>. Auto-leveling blade firmware to match system firmware.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the policy of the specified blade is to auto-level the blade firmware to the system firmware. This may be due to one of the following reasons:

- Blade firmware was detected to be different from the control processor (CP) firmware due to a firmware upgrade.
- The blade was recently inserted and had a different version of the firmware loaded.

**Recommended Action** No action is required. The blade will automatically download the updated firmware.

## BM-1005

**Message** Firmwaredownload timed-out for blade in slot <Slot>. Faulting blade.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the **firmwareDownload** command failed for the blade in the specified slot.

**Recommended Action** Execute the **slotPowerOff** and **slotPowerOn** commands or reseal the affected blade.

## BM-1006

**Message** Blade is not configured. Persistently disabling all ports for blade in slot <Slot number>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the policy of the specified blade is set to persistently disable all ports the first time the blade is detected. The message indicates either of the following:

- The blade was detected in this slot for the first time.
- The blade was configured under a different mode.

## 5 BM-1007

**Recommended Action** Configure the blade so that it will persistently enable the ports.

### BM-1007

**Message** If set, clear EX/VEX/FC Fastwrite configuration for all ports for blade in slot <Slot number>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates the specified blade was detected for the first time after an FR4-18i was previously configured in the same slot. The new blade requires the specified port configurations to be cleared.

**Recommended Action** No action is required. The blade ports are cleared automatically.

### BM-1008

**Message** Download of blade firmware failed for blade in slot <slot>. Reissue firmwaredownload to recover.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the automatic firmware upgrade on the blade failed because the blade firmware version was detected to be different from the control processor (CP) firmware version.

**Recommended Action** Execute the **firmwareDownload** command to recover the blade.

### BM-1009

**Message** Firmwaredownload timed-out for application processor. Faulting switch.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the firmware download on the application processor (AP) blade failed.

**Recommended Action** Execute the **slotPowerOff** and **slotPowerOn** commands or reseal the affected blade.

## BM-1010

<b>Message</b>	Resetting port configuration and linkcost for all ports for blade in slot <Slot number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified blade was detected for the first time after an FC10-6 was previously configured in the same slot. The new blade requires resetting the port configuration and linkcost.
<b>Recommended Action</b>	No action is required. The blade ports are cleared automatically.

## BM-1053

<b>Message</b>	Failed to establish connection between CP and Application Processor. Faulting switch.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the control processor (CP) could not establish a connection with the application processor (AP) to communicate.
<b>Recommended Action</b>	Execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or reseal the affected blade.

## BM-1054

<b>Message</b>	AP firmware <Blade firmware> is not consistent with system firmware <System firmware>. Auto-leveling AP firmware to match system firmware.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the policy of the specified blade is set to auto-level the blade firmware to the system firmware. This may be due to one of the following reasons: <ul style="list-style-type: none"> <li>• Blade firmware was detected to be different from the control processor (CP) firmware due to a firmware upgrade.</li> <li>• The blade was recently inserted and had a different version of the firmware loaded.</li> </ul>
<b>Recommended Action</b>	No action is required. The blade will automatically download the updated firmware.

## BM-1055

<b>Message</b>	Firmwaredownload timed-out for AP. Faulting switch.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that firmware download on the application processor (AP) blade has failed.
<b>Recommended Action</b>	Execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or reseal the affected blade.

## BM-1056

<b>Message</b>	AP is not configured. Persistently disabling all ports on the switch.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the policy of the specified switch is to persistently disable all ports the first time the AP is detected. This may be caused by one of the following reasons: <ul style="list-style-type: none"><li>• The AP was detected for the first time on this switch.</li><li>• The switch was configured under a different mode.</li></ul>
<b>Recommended Action</b>	Configure the switch to persistently enable all ports.

## BM-1058

<b>Message</b>	Download of AP firmware failed for the switch. Reissue firmwaredownload to recover.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the automatic firmware upgrade on the application processor (AP) failed because the firmware version running on the AP was detected to be different from the system firmware.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to recover the AP.

## C2 Messages

### C2-1001

<b>Message</b>	Port <port number> port faulted due to SFP validation failure. Check if the SFP is valid for the configuration.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a deteriorated small form-factor pluggable (SFP) transceiver, an incompatible SFP transceiver pair, or a faulty cable between the peer ports.
<b>Recommended Action</b>	Verify that compatible SFP transceivers are used on the peer ports, the SFP transceivers have not deteriorated, and the Fibre Channel cable is not faulty. Replace the SFP transceivers or the cable if necessary.

### C2-1002

<b>Message</b>	Port <port number> chip faulted due to an internal error.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal error. All the ports on the blade or switch will be disrupted.
<b>Recommended Action</b>	To recover a bladed system, execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands on the blade. To recover a non-bladed system, execute the <b>fastBoot</b> command on the switch.

### C2-1004

<b>Message</b>	S<slot number>,C<chip index>: Invalid DMA ch pointer, chan:<Channel number>, good_addr:0x<Good address> bad_addr:0x<Bad address>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal error in the application-specific integrated circuit (ASIC) hardware that may degrade the data traffic.
<b>Recommended Action</b>	Restart the system at the next maintenance window. If the problem persists, replace the blade.

**C2-1006**

<b>Message</b>	S<slot number>,C<chip index>: Internal link errors reported, no hardware faults identified, continuing monitoring: fault1:0x<fault1_cnt>, fault2:0x<fault2_cnt> thresh1:0x<threshold_used>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that some internal link errors have been detected. These errors can be normal in an active running system.  The system automatically starts a more detailed monitoring of the errors reported in the internal hardware. There is no action required by the user at this time. If any actual hardware failures are detected, the C2-1010 message will be generated identifying the failing field-replaceable unit (FRU).
<b>Recommended Action</b>	No action is required.

**C2-1007**

<b>Message</b>	S<slot number>,P<port number>(<blade port number>): best effort QoS will be turned off at next port state change as it is not supported under this configuration
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that quality of service (QoS) will be turned off automatically at the next port state change because best effort QoS is no longer supported on 4 Gbps or 8 Gbps platform long distance ports.
<b>Recommended Action</b>	No action is required.

**C2-1008**

<b>Message</b>	S<slot number>,P<port number>(<blade port number>): QoS overwrites portcfglongdistance vc_translation_link_init. ARB will be used on the link.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that quality of service (QoS) has overwritten the fill word IDLE used on the long distance links. Arbitrated loop (ARB) will be used on the link.
<b>Recommended Action</b>	No action is required.

## C2-1009

<b>Message</b>	S<slot number>,P<port number>( <blade port number>): portcfglongdistance vc_translation_link_init = 1 overwrites fill word IDLE. ARB will be used on the link.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the <b>portcfglongdistance vc_translation_link_init 1</b> command has overwritten the fill word IDLE. Arbitrated loop (ARB) will be used on the link.
<b>Recommended Action</b>	No action is required.

## C2-1010

<b>Message</b>	S<slot number>,C<chip index>: Internal monitoring has identified suspect hardware, blade may need to be reset or replaced: faul:0x<fault1_cnt>, fau2:0x<fault2_cnt> th2:0x<threshold_used>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that above-normal errors were observed in hardware that may or may not impact the data traffic.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## C2-1012

<b>Message</b>	S<slot number>,P<port number>( <blade port number>): Link Timeout on internal port ftx=<frame transmitted> tov=<real timeout value> (><expected timeout value>) vc_no=<vc number> crd(s)lost=<Credit(s) lost> complete_loss:<complete credit loss>.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that one or more credits have been lost on a back-end port, and there is no traffic on that port for two seconds.
<b>Recommended Action</b>	Turn on the back-end credit recovery to reset the link and recover the lost credits. If credit recovery has already been turned on, the link will be reset to recover the credits and no action is required.

**C2-1013**

<b>Message</b>	S<slot number>,P<port number>(<blade port number>): Duplicate rte_tbl_select detected.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the selected table is corrupted.
<b>Recommended Action</b>	This message must have a matching message for the other duplicate table. Reset both the specified ports. If it is a trunk, reset the entire trunk.

**C2-1014**

<b>Message</b>	Link Reset on Port S<slot number>,P<port number>(<blade port number>) vc_no=<vc number> crd(s)lost=<Credit(s) lost> <Source of link reset > trigger.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that one or more credits are lost and the link is reset.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

**C2-1015**

<b>Message</b>	Port re-initialized due to Link Reset failure on internal Port S<slot number>,P<port number>(<blade port number>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified port is re-initialized due to link reset failure.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.



## C2-1016

<b>Message</b>	Port is faulted due to port re-initialization failure on internal Port S<slot number>,P<port number>( <blade port number>) with reason <port fault reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified port failed due to port re-initialization failure.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## C2-1017

<b>Message</b>	Blade in Slot <slot number> failed due to unavailability of ports in the internal trunk.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified blade failed because of the unavailability of the ports in the internal trunk.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## C2-1018

<b>Message</b>	Link reset threshold value exceeded in the link S<slot number>,P<port number>( <blade port number>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified blade is faulted because the link reset threshold value has exceeded.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## C2-1019

<b>Message</b>	S<slot number>,C<chip index>: HW ASIC Chip TXQ FID parity error threshold reached type = 0x<chip error type>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an internal error is observed in the application-specific integrated circuit (ASIC) hardware that may degrade the data traffic.
<b>Recommended Action</b>	Restart the system at the next maintenance window.

## C2-1025

<b>Message</b>	S<slot number>,P<port number>(<blade port number>): Extra credit on F_port:ftx=<ftx> curr_cred=<current credits> actual_cred=<actual credits>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the device is returning the wrong number of receiver-ready (R_RDY) frames.
<b>Recommended Action</b>	When this error is observed persistently, replace the device.

## C2-1026

<b>Message</b>	S<slot number>,P<port number>(<blade port number>): Faulting F_port due to extra credit detected:ftx=<ftx> curr_cred=<current credits> actual_cred=<actual credits>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the device is returning the wrong number of receiver-ready (R_RDY) frames.
<b>Recommended Action</b>	When this error is observed persistently, replace the device.

## C2-1027

<b>Message</b>	Detected credit loss on Peer internal Port of Slot <slot number>, Port <port number>(<blade port number>) vc_no=<vc number> crd(s)lost=<Credit(s) lost> complete_loss:<complete credit loss>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that credit loss was detected on the peer port.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## C2-1028

<b>Message</b>	Detected excessive Link resets on the port in a second. Slot <slot number>, Port <port number>(<blade port number>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the port received excessive link resets from peer port within 1 second and that exceeded threshold.
<b>Recommended Action</b>	When this error is observed persistently, change the small form-factor pluggable (SFP) transceiver or the cable on the peer port to which this port is connected.

## C3 Messages

### C3-1001

<b>Message</b>	Port <port number> failed due to SFP validation failure. Check if the SFP is valid for the configuration.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a deteriorated small form-factor pluggable (SFP) transceiver, an incompatible SFP transceiver pair, or a faulty cable between the peer ports.
<b>Recommended Action</b>	Verify that compatible SFP transceivers are used on the peer ports, the SFP transceivers have not deteriorated, and the Fibre Channel cable is not faulty. Replace the SFP transceivers or the cable if necessary.

### C3-1002

<b>Message</b>	Port <port number> chip failed due to an internal error.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal error. All the ports on the blade or switch will be disrupted.
<b>Recommended Action</b>	To recover a bladed system, execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands on the blade. To recover a non-bladed system, execute the <b>fastBoot</b> command on the switch.

### C3-1004

<b>Message</b>	S<slot number>,C<chip index>: Invalid DMA ch pointer, chan:<Channel number>, good_addr:0x<Good address> bad_addr:0x<Bad address>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal error in the application-specific integrated circuit (ASIC) hardware that may degrade the data traffic.
<b>Recommended Action</b>	Reboot the system at the next maintenance window. If the problem persists, replace the blade.

## C3-1006

<b>Message</b>	S<slot number>,C<chip index>: Various non-critical hardware errors were observed: fault1:0x<fault1_cnt>, fault2:0x<fault2_cnt> thresh1:0x<threshold_used>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that some errors were found in hardware that may or may not impact the data traffic.
<b>Recommended Action</b>	No action is required. Usually these errors are transient.

## C3-1007

<b>Message</b>	S<slot number>,P<port number>(<blade port number>): best effort QoS will be turned off at next port state change as it is not supported under this configuration.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that quality of service (QoS) will be turned off automatically at the next port state change because best effort QoS is no longer supported on 4 Gbps or 8 Gbps platform long distance ports.
<b>Recommended Action</b>	No action is required.

## C3-1008

<b>Message</b>	S<slot number>,P<port number>(<blade port number>): QoS overwrites portcfglongdistance vc_translation_link_init. ARB will be used on the link.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that quality of service (QoS) has overwritten the fill word IDLE used on the long distance links. Arbitrated loop (ARB) will be used on the link.
<b>Recommended Action</b>	No action is required.

**C3-1009**

<b>Message</b>	S<slot number>,P<port number>( <blade port number>): portcfglongdistance vc_translation_link_init = 1 overwrites fill word IDLE. ARB will be used on the link.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the <b>portcfglongdistance vc_translation_link_init 1</b> command has overwritten the fill word IDLE. Arbitrated loop (ARB) will be used on the link.
<b>Recommended Action</b>	No action is required.

**C3-1010**

<b>Message</b>	S<slot number>,C<chip index>: Above normal hardware errors were observed: fault1:0x<fault1_cnt>, fault2:0x<fault2_cnt> thresh2:0x<threshold_used>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that above-normal errors were observed in hardware that may or may not impact the data traffic.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

**C3-1011**

<b>Message</b>	Detected a complete loss of credit on internal back-end VC: Slot <slot number>, Port <port number>( <blade port number>) vc_no=<vc number> crd(s)lost=<Credit(s) lost>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that all credits have been lost on the specified virtual channel (VC) and port.
<b>Recommended Action</b>	Turn on the back-end credit recovery to reset the link and recover the lost credits. If credit recovery has already been turned on, the link will be reset to recover the credits and no action is required.

## C3-1012

<b>Message</b>	S<slot number>,P<port number>(<blade port number>): Link Timeout on internal port ftx=<frame transmitted> tov=<real timeout value> (><expected timeout value>) vc_no=<vc number> crd(s)lost=<Credit(s) lost> complete_loss:<Compless credit loss>.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that one or more credits have been lost on a back-end port, and there is no traffic on that port for two seconds.
<b>Recommended Action</b>	Turn on the back-end credit recovery to reset the link and recover the lost credits. If credit recovery has already been turned on, the link will be reset to recover the credits and no action is required.

## C3-1013

<b>Message</b>	Multi RDY/Frame Loss detected on Slot <slot number>, Port <port number>(<blade port number>) m_rdy(0x<Multiple Credit(s) Lost>)/m_frame(0x<Multiple Frame(s) Lost>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that wait cycles to recover the lost frame or credit are exceeded on the specified port.
<b>Recommended Action</b>	Turn on the back-end credit recovery to reset the link and recover the lost credits. If credit recovery has already been turned on, the link will be reset to recover the credits and no action is required.

## C3-1014

<b>Message</b>	Link Reset on Port S<slot number>,P<port number>(<blade port number>) vc_no=<vc number> crd(s)lost=<Credit(s) lost> <Source of link reset > trigger.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that one or more credits were lost and the link is reset.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## C3-1015

<b>Message</b>	Port re-initialized due to Link Reset failure on internal Port S<slot number>,P<port number>(<blade port number>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified port is re-initialized due to link reset failure.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## C3-1016

<b>Message</b>	Port is faulted due to port re-initialization failure on internal Port S<slot number>,P<port number>(<blade port number>) with reason <port fault reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified port failed due to port re-initialization failure.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## C3-1017

<b>Message</b>	Blade in Slot-<slot number> failed due to unavailability of ports in the internal trunk.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified blade failed because of the unavailability of the ports in the internal trunk.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.



## C3-1018

<b>Message</b>	Link reset threshold value exceeded in the link S<slot number>,P<port number>(<blade port number>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified blade is faulted because the link reset threshold value has exceeded.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## C3-1019

<b>Message</b>	S<slot number>,C<chip index>: HW ASIC Chip TXQ FID parity error threshold reached type = 0x<chip error type>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an internal error is observed in the application-specific integrated circuit (ASIC) hardware that may degrade the data traffic.
<b>Recommended Action</b>	Restart the system at the next maintenance window.

## C3-1020

<b>Message</b>	S<slot number>,P<port number>(<blade port number>): Some non-critical CRC with good EOF errors were observed: current:0x<last_crc_good_eof_cnt>, last:0x<total_crc_good_eof_cnt> thresh1:0x<threshold_used>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that some non-critical errors were detected in the hardware.
<b>Recommended Action</b>	No action is required.

**C3-1021**

<b>Message</b>	S<slot number>,P<port number>(<blade port number>): Port is offline due to Encryption Compression Block error.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an internal error is observed in the application-specific integrated circuit (ASIC) hardware that may degrade the data traffic.
<b>Recommended Action</b>	When this error occurs, the software will automatically recover from the error and no action is required. However, if the problem persists, replace the blade.

**C3-1023**

<b>Message</b>	Single RDY/Frame Loss detected and recovered on Slot <slot number>,Port <port number>(<blade port number>) rdy(0x<Credit Lost>)/frame(0x<Frame Lost>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that above-normal errors are observed in hardware that may or may not impact the data traffic.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

**C3-1025**

<b>Message</b>	S<slot number>,P<port number>(<blade port number>): Extra credit on F_port:ftx=<ftx> curr_cred=<current credits> actual_cred=<actual credits>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the device is returning the wrong number of receiver-ready (R_RDY) frames.
<b>Recommended Action</b>	When this error is observed persistently, replace the device.

## C3-1026

<b>Message</b>	S<slot number>,P<port number>( <blade port number>): Faulting F_port due to extra credit detected:ftx=<ftx> curr_cred=<current credits> actual_cred=<actual credits>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the device is returning the wrong number of receiver-ready (R_RDY) frames.
<b>Recommended Action</b>	When this error is observed persistently, replace the device.

## C3-1027

<b>Message</b>	Detected credit loss on Peer internal Port of Slot <slot number>, Port <port number>( <blade port number>) vc_no=<vc number> crd(s)lost=<Credit(s) lost> complete_loss:<complete credit loss>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that credit loss was detected on the peer port.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## C3-1028

<b>Message</b>	Detected excessive Link resets on the port in a second. Slot <slot number>, Port <port number>( <blade port number>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the port received excessive link resets from peer port within 1 second and that exceeded the threshold.
<b>Recommended Action</b>	When this error is observed persistently, change the small form-factor pluggable (SFP) transceiver or the cable on the peer port to which this port is connected.

## CAL Messages

### CAL-1001

<b>Message</b>	Switch offline requested by remote domain <domain number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified remote domain requested the local domain to be disabled.
<b>Recommended Action</b>	Check the error message log on the remote domain using the <b>errShow</b> command to find the reason.

## CCFG Messages

### CCFG-1001

<b>Message</b>	Failed to initialize <module>, rc = <error>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the initialization of a module within the Converged Enhanced Ethernet (CEE) configuration management daemon has failed.
<b>Recommended Action</b>	Download a new firmware version using the <b>firmwareDownload</b> command.

### CCFG-1002

<b>Message</b>	Started loading CEE system configuration.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Converged Enhanced Ethernet (CEE) system configuration has started loading.
<b>Recommended Action</b>	No action is required.

### CCFG-1003

<b>Message</b>	System is ready to accept CEE user commands.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Converged Enhanced Ethernet (CEE) shell is ready to accept configuration commands.
<b>Recommended Action</b>	No action is required.

## CCFG-1004

<b>Message</b>	Configuration replay failed due to missing system startup configuration file.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the startup configuration file has been moved or deleted and therefore replaying the system configuration has failed.
<b>Recommended Action</b>	Execute the <b>copy file startup-config</b> command to restore the startup configuration file from any backup retrieved on the server.

## CCFG-1005

<b>Message</b>	Startup configuration file is updated.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the startup configuration file has been updated.
<b>Recommended Action</b>	No action is required.

## CCFG-1006

<b>Message</b>	Current system running configuration file is updated.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the current running configuration file has been updated.
<b>Recommended Action</b>	No action is required.

## CCFG-1007

<b>Message</b>	Startup configuration is deleted.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the startup configuration file has been moved or deleted.

**Recommended Action** No action is required.

## CCFG-1008

**Message** CMSH init failed: <msg>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the CEE Management Shell (CMSH) initialization has failed.

**Recommended Action** No action is required.

## CCFG-1009

**Message** Successfully copied to <destination>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that a configuration file has been copied to the specified destination.

**Recommended Action** No action is required.

## CCFG-1010

**Message** Current system running configuration file is updated partially.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the current running configuration file has been updated partially.

**Recommended Action** No action is required.

### CCFG-1011

**Message** Linecard configuration mismatch on slot <slot>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the inserted line card is different from the pre-configured line card on the specified slot.

**Recommended Action** Execute the **no linecard** command to remove the line card configuration.

### CCFG-1012

**Message** Blade in slot <slot> failed to reach ONLINE state within <timeout> seconds after receiving system ready.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the blade in the specified slot has failed to come online within the specified timeout interval after receiving the system ready event.

**Recommended Action** Execute the **slotPowerOff** and **slotPowerOn** commands on the specified slot to bring the blade online.

### CCFG-1013

**Message** <mode\_command>.

**Message Type** AUDIT

**Class** CFG

**Severity** INFO

**Probable Cause** Indicates that the switch state has changed.

**Recommended Action** No action is required.



## CDR Messages

### CDR-1001

<b>Message</b>	Port <port number> port fault. Change the SFP or check cable.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a deteriorated small form-factor pluggable (SFP) transceiver, an incompatible SFP transceiver pair, a faulty cable between the peer ports, or the port speed configuration does not match the capability of the SFP transceiver.
<b>Recommended Action</b>	Verify that compatible SFP transceivers are used on the peer ports, the SFP transceivers have not deteriorated, and the Fibre Channel cable is not faulty. Replace the SFP transceivers or the cable if necessary.

### CDR-1002

<b>Message</b>	Port <port number> chip faulted due to internal error.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal error. All the ports on the blade or switch will be disrupted.
<b>Recommended Action</b>	To recover a bladed system, execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands on the blade. To recover a non-bladed system, execute the <b>fastBoot</b> command on the switch.

### CDR-1003

<b>Message</b>	S<slot number>,C<chip index>: HW ASIC Chip error type = 0x<chip error type>. If the problem persists, blade may need to be reset or replaced.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an internal error in the application-specific integrated circuit (ASIC) hardware that may degrade the data traffic.
<b>Recommended Action</b>	Restart the system at the next maintenance window. If the problem persists, replace the blade.

**CDR-1004**

<b>Message</b>	S<slot number>,C<chip index>: Invalid DMA ch pointer, chan:<Channel number>, good_addr:0x<Good address> bad_addr:0x<Bad address>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal error in the application-specific integrated circuit (ASIC) hardware that may degrade the data traffic.
<b>Recommended Action</b>	Restart the system at the next maintenance window. If the problem persists, replace the blade.

**CDR-1005**

<b>Message</b>	S<slot number>,P<port number>(<blade port number>): best effort QoS will be turned off at next port state change as it is not supported under this configuration.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that quality of service (QoS) will be turned off automatically at the next port state change because best effort QoS is no longer supported on 4 Gbps or 8 Gbps platform long distance ports.
<b>Recommended Action</b>	No action is required.

**CDR-1006**

<b>Message</b>	S<slot number>,P<port number>(<blade port number>): QoS overwrites portcfglongdistance vc_translation_link_init. ARB will be used on the link.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that quality of service (QoS) has overwritten the fill word IDLE used on the long distance links. Arbitrated loop (ARB) will be used on the link.
<b>Recommended Action</b>	No action is required.

## CDR-1007

<b>Message</b>	S<slot number>,C<chip index>: Internal link errors have been reported, no hardware faults identified, continuing to monitor for errors: flt1:0x<fault1_cnt>, flt2:0x<fault2_cnt> thresh1:0x<threshold_used>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that some errors were found in hardware that may or may not impact the data traffic.
<b>Recommended Action</b>	No action is required.

## CDR-1008

<b>Message</b>	S<slot number>,C<chip index>: HW ASIC Chip warning Level 1 type = 0x<chip error type>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an internal error in the application-specific integrated circuit (ASIC) hardware that may or may not degrade the data traffic.
<b>Recommended Action</b>	Restart the system at the next maintenance window.

## CDR-1009

<b>Message</b>	S<slot number>,C<chip index>: HW ASIC Chip warning Level 2 type = 0x<chip error type>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an internal error in the application-specific integrated circuit (ASIC) hardware that may or may not degrade the data traffic.
<b>Recommended Action</b>	Restart the system at the next maintenance window.

**CDR-1010**

<b>Message</b>	S<slot number>,C<chip index>: Internal monitoring of faults has identified suspect hardware, blade may need to be reset or replaced: fault1:0x<fault1_cnt>, fault2:0x<fault2_cnt> thresh2:0x<threshold_used>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that above-normal errors observed in hardware that may or may not impact the data traffic.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

**CDR-1011**

<b>Message</b>	S<slot number>,P<port number>(<blade port number>): Link Timeout on internal port ftx=<frame transmitted> tov=<real timeout value> (><expected timeout value>) vc_no=<vc number> crd(s)lost=<Credit(s) lost> complete_loss:<complete credit loss>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that one or more credits have been lost on a back-end port, and there is no traffic on that port for two seconds.
<b>Recommended Action</b>	Turn on the back-end credit recovery to reset the link and recover the lost credits. If credit recovery has already been turned on, the link will be reset to recover the credits and no action is required.

**CDR-1012**

<b>Message</b>	S<slot number>,P<port number>(<blade port number>): Port Fault: Hard <Hard fault>(<Fault reason>) fault1=<Fault1 count> fault2=<Fault2 count> (0x<LIP and LLI fault count> 0x<RX_FIFO and HSS fault count> 0x<BWAIT fault count>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified port has failed. Port initialization will be retried.
<b>Recommended Action</b>	Replace the SFP transceiver and the cable and then re-enable the port.

## CDR-1014

<b>Message</b>	Link Reset on Internal Port S<slot number>,P<port number>(<blade port number>) vc_no=<vc number> crd(s)lost=<Credit(s) lost>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that one or more credits were lost and the link is reset.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## CDR-1015

<b>Message</b>	Port re-initialized due to Link Reset failure on internal Port S<slot number>,P<port number>(<blade port number>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that specified port got re-initialized due to link reset failure.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## CDR-1016

<b>Message</b>	Port is faulted due to port re-initialization failure on internal Port S<slot number>,P<port number>(<blade port number>) with reason <port fault reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified port is faulted due to port re-initialization failure.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## CDR-1017

<b>Message</b>	Blade in Slot <slot number> faulted due to unavailable ports in internal Trunk.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified blade is faulted due to unavailable ports in internal trunk.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## CDR-1018

<b>Message</b>	Blade in Slot <slot number> faulted due to Link reset threshold value exceeded.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified blade is faulted because the link reset threshold is exceeded.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## CDR-1019

<b>Message</b>	S<slot number>,C<chip index>: HW ASIC Chip TXQ FID parity error threshold reached type = 0x<chip error type>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an internal error is observed in the application-specific integrated circuit (ASIC) hardware that may degrade the data traffic.
<b>Recommended Action</b>	Restart the system at the next maintenance window.

## CDR-1022

<b>Message</b>	S<slot number>,P<port number>(<blade port number>): Link Timeout on External port, ftx=<frame transmitted> tov=<real timeout value> (><expected timeout value>) vc_no=<vc number> crd(s)lost=<Credit(s) lost>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that above-normal errors are observed in hardware that may or may not impact the data traffic.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## CDR-1028

<b>Message</b>	Detected excessive Link resets on the port in a second. Slot <slot number>, Port <port number>(<blade port number>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the port received excessive link resets from peer port within 1 second and that exceeded threshold.
<b>Recommended Action</b>	When this error is observed persistently, change the small form-factor pluggable (SFP) transceiver or the cable on the peer port to which this port is connected.

## CHS Messages

### CHS-1002

<b>Message</b>	<code>ki_gd_register_action failed with rc = &lt;return val&gt;.</code>
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal error.
<b>Recommended Action</b>	To recover a bladed system, execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands on the blade. To recover a non-bladed system, execute the <b>fastBoot</b> command on the switch.

### CHS-1003

<b>Message</b>	<code>Slot ENABLED but Not Ready during recovery, disabling slot = &lt;slot number&gt; rval = &lt;return value&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the slot state has been detected as inconsistent during failover or recovery.
<b>Recommended Action</b>	For a bladed switch, execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands to power cycle the blade. For a non-bladed switch, restart or power cycle the switch.

### CHS-1004

<b>Message</b>	<code>Blade attach failed during recovery, disabling slot = &lt;slot number&gt;, rval = &lt;return value&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified blade has failed during failover or recovery.
<b>Recommended Action</b>	For a bladed switch, execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands to power cycle the blade. For a non-bladed switch, restart or power cycle the switch.



## CHS-1005

<b>Message</b>	Diag attach failed during recovery, disabling slot = <slot number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the diagnostic blade attach operation has failed during failover or recovery.
<b>Recommended Action</b>	For a bladed switch, execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands to power cycle the blade. For a non-bladed switch, restart or power cycle the switch.

## CNM Messages

### CNM-1001

<b>Message</b>	Failed to allocate memory: (<function name>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified function has failed to allocate memory.
<b>Recommended Action</b>	Check memory usage on the switch using the <b>memShow</b> command. Restart or power cycle the switch.

### CNM-1002

<b>Message</b>	Failed to initialize <module> rc = <error>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the initialization of a module within the Cluster Node Manager (CNM) has failed.
<b>Recommended Action</b>	Download a new firmware version using the <b>firmwareDownload</b> command.

### CNM-1003

<b>Message</b>	Crypto device cfg between local switch (<local domain id>) and peer (<peer domain id>) out of sync. New encryption session not allowed.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the encryption engine nodes in the cluster encryption group have different configurations.
<b>Recommended Action</b>	Synchronize the configuration in the cluster group using the <b>cryptocfg</b> command.

## CNM-1004

<b>Message</b>	iSCSI service is <status> on the switch.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the crypto service is enabled or disabled on the switch.
<b>Recommended Action</b>	No action is required.

## CNM-1005

<b>Message</b>	Posting event CNM_EVT_GRP_LEADER_ELECTED Name [<nodeName>], WWN [<WWN>].
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the cluster Encryption Group (EG) leader is elected.
<b>Recommended Action</b>	No action is required.

## CNM-1006

<b>Message</b>	Posting event CNM_EVT_NODE_JOIN nodeName [<nodeName>], WWN [<WWN>], ipaddress [<IP address>].
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the member node has joined.
<b>Recommended Action</b>	No action is required.

## CNM-1007

<b>Message</b>	Posting event CNM_EVT_GRP_LEADER_FAILED Name [<nodeName>]
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Encryption Group (EG) leader has failed.

## 5 CNM-1008

**Recommended Action** No action is required.

### CNM-1008

**Message** Posting event CNM\_EVT\_NODE\_EJECT nodeName [<nodeName>], WWN [<WWN>].

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified node is ejected from the Encryption Group (EG).

**Recommended Action** No action is required.

### CNM-1009

**Message** Posting event CNM\_EVT\_STANDALONE\_MODE.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the node is in standalone mode.

**Recommended Action** No action is required.

### CNM-1010

**Message** Posting event CNM\_EVT\_CLUSTER\_UDATA\_UPDATE cid [<client id>], ulen [<udata len>].

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates the client data update.

**Recommended Action** No action is required.

## CNM-1011

<b>Message</b>	Posting event CNM_EVT_NODE_JOIN_TIMEOUT nodeName [<nodeName>], WWN [<wwn>], ipaddress [<ipAddr>].
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the node join timeout.
<b>Recommended Action</b>	Take the peer node offline, and rejoin the node to Encryption Group (EG).

## CNM-1012

<b>Message</b>	Posting event CNM_EVT_EG_DELETED.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Encryption Group (EG) is deleted.
<b>Recommended Action</b>	No action is required.

## CNM-1013

<b>Message</b>	Posting event GL Node Split condition, isolating peer GL node <nodeName>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Encryption Group (EG) is split.
<b>Recommended Action</b>	No action is required.

## CNM-1014

<b>Message</b>	Posting event Node Admission Control passed, admitting node [<nodeName>].
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the node admission control was successful.

## 5 CNM-1015

**Recommended Action** No action is required.

### CNM-1015

**Message** Posting event Potential Cluster Split condition.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates a Potential Cluster Split condition.

**Recommended Action** No action is required.

### CNM-1016

**Message** Posting event Detected a EG degrade condition.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates an Encryption Group (EG) degrade condition.

**Recommended Action** No action is required.

### CNM-1017

**Message** Got JOIN REQUEST from un-recognized GL node [`<rxglname>`], configured GL node is [`<glname>`].

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates a join request was received from an invalid group leader (GL) node.

**Recommended Action** No action is required.

## CNM-1018

<b>Message</b>	Got CNM_FSM_EVT_JOIN_REQ when already a member, My assigned name [<nodename>], dropping request.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the node is already a member of the Encryption Group (EG).
<b>Recommended Action</b>	No action is required.

## CNM-1019

<b>Message</b>	Join Rejected by GL node, fix certificate and later add member node from GL node, or reboot the member node.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an invalid member node certificate.
<b>Recommended Action</b>	Install a valid certificate and add member node to the group leader (GL) node, or reboot the member node.

## CNM-1020

<b>Message</b>	Node Admission Control failed due to mismatch in certificates, rejecting node [<nodename>].
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that node admission control has failed.
<b>Recommended Action</b>	No action is required.

## CNM-1021

<b>Message</b>	Failed to sign the node authentication message, admission control might fail.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that node admission control has failed.
<b>Recommended Action</b>	No action is required.

## CNM-1022

<b>Message</b>	Operation not allowed on GL Node.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an operation is not allowed on a group leader (GL) node.
<b>Recommended Action</b>	No action is required.

## CNM-1023

<b>Message</b>	Group Leader node eject is not allowed.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an eject operation is not allowed in group leader (GL) node.
<b>Recommended Action</b>	No action is required.

## CNM-1024

<b>Message</b>	Operation not required on GL node.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an operation is not required on a group leader (GL) node.



**Recommended Action** No action is required.

## CNM-1025

**Message** Operation not allowed, as member is active with the Cluster. Eject member node and retry.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates an operation is not allowed on a member node.

**Recommended Action** Eject member node and retry the operation.

## CNM-1026

**Message** Recvd HBT Msg with version mismatch, Recvd Hdr version 0x<received hardware version> Exp Hdr version 0x<expected hardware version> Node <WWN>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that a version mismatch has occurred.

**Recommended Action** Upgrade the firmware or delete the node from the Encryption Group (EG).

## CNM-1027

**Message** Received HBT from non-Group Member Node [<WWN>].

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates an operation is not allowed on a non-group member node.

**Recommended Action** No action is required.

## CNM-1028

<b>Message</b>	Certfile <certificate file name> already exists. No need to sync up.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the certificate file for the node already exists.
<b>Recommended Action</b>	No action is required.

## CNM-1029

<b>Message</b>	Certfile <certificate file name> content does not match the cert sent by GL.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the contents of the node's certificate file is different from the certificate file sent by the group leader (GL) node.
<b>Recommended Action</b>	No action is required.

## CNM-1030

<b>Message</b>	Certfile <certificate file name> read less number of bytes <nbytes>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the read operation of the certificate file returned a fewer number of bytes than expected.
<b>Recommended Action</b>	No action is required.

## CNM-1031

<b>Message</b>	Certfile <certificate file name> open failed with errno <error num>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an attempt to open the certificate file has failed.

**Recommended Action** No action is required.

## CNM-1032

**Message** Certfile <certificate file name> size <file size> does not match cert file size <length> sent by GL.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that there is a size mismatch between a node's certificate file and the certificate file received from the group leader (GL).

**Recommended Action** No action is required.

## CNM-1033

**Message** Some of the defined nodes in the Encryption Group are not ONLINE. Encryption Group is in degraded state.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the cluster is in a degraded state.

**Recommended Action** No action is required.

## CNM-1034

**Message** All the defined nodes in the Encryption Group are ONLINE. Cluster is in converged state.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the cluster is in a converged state.

**Recommended Action** No action is required.

## CNM-1035

<b>Message</b>	Cluster is in degraded state. Posting degrade event.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an event is being posted to specify the cluster is in a degraded state.
<b>Recommended Action</b>	No action is required.

## CNM-1036

<b>Message</b>	All the active nodes of the cluster are in ONLINE state. Posting converged event.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an event is being posted to specify the cluster is in a converged state.
<b>Recommended Action</b>	No action is required.

## CNM-1037

<b>Message</b>	Split-Brain Arbitration lost, minority GL Node, remote:local [<remote_count>:<local_gl_ncount>].
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that split-brain arbitration is lost.
<b>Recommended Action</b>	No action is required.

## CNM-1038

<b>Message</b>	Split-Brain Arbitration won, majority GL Node, remote:local [<remote_count>:<local_gl_ncount>].
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that split-brain arbitration is won.
<b>Recommended Action</b>	No action is required.

## CNM-1039

<b>Message</b>	Split-Brain Arbitration lost, Minority WWN/GL Node, remote_WWN:local_WWN <wbuf>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that split-brain arbitration is lost.
<b>Recommended Action</b>	No action is required.

## CNM-1040

<b>Message</b>	Split-Brain Arbitration won, Majority WWN/GL Node, remote_WWN:local_WWN <WWN>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that split-brain arbitration is won.
<b>Recommended Action</b>	No action is required.

## CNM-1041

<b>Message</b>	Updating persistent Cluster DB, please avoid powering off the switch.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the system is updating the persistent database.

## 5 CNM-1042

**Recommended Action** No action is required.

### CNM-1042

**Message** Completed updating persistent Cluster DB.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates the persistent database update is complete.

**Recommended Action** No action is required.

### CNM-1043

**Message** Received HBT from undefined node IPAddress [<ip>], WWN [<wwn>]. Possible configuration error.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the remote node's WWN may be changed.

**Recommended Action** No action is required.

### CNM-1044

**Message** Cluster Create Failed as the Certificate files not found, Please do the initnode.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the initnode is not invoked.

**Recommended Action** Execute the **cryptocfg --initnode** command.

## CNM-1045

<b>Message</b>	Member node [<wwn>] is having dual IP stack. Registering member node with dual IP in an EG with only IPv6 is not allowed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the member node with dual IP stack was registered with the IPv6 Encryption Group (EG).
<b>Recommended Action</b>	No action is required.

## CNM-1046

<b>Message</b>	Posting event CNM_EVT_NODE_LEAVE nodeName [<nodeName>], WWN [<wwn>].
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the node has decided to leave the Encryption Group (EG).
<b>Recommended Action</b>	No action is required.

## CNM-1047

<b>Message</b>	Network Interface to Remote Node [<ip>] is [<string>].
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the status of the network interface is up or down.
<b>Recommended Action</b>	No action is required.

## CNM-1048

<b>Message</b>	Posting <string>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the event that is posted.

## 5 CNM-1049

**Recommended Action** No action is required.

### CNM-1049

**Message** Failed to define node, Node Name [<string>].

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates the failure to define the node object.

**Recommended Action** No action is required.

### CNM-1050

**Message** Node Admission Control failed due to mismatch in Access Gateway Daemon (AGD) mode settings, rejecting node [<nodename>].

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates mode mismatch between the switches, such as the Access Gateway mode mismatch.

**Recommended Action** No action is required.

### CNM-1051

**Message** Join Rejected by GL Node due to Access Gateway Daemon mode mismatch, ensure mode settings are same across all nodes in EG.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates mode mismatch between the switches, such as the Access Gateway mode mismatch.

**Recommended Action** No action is required.



## CNM-1052

<b>Message</b>	Member node registered with another Encryption Group. To proceed eject the member node [<nodename>] from other EG.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the member node is registered with another Encryption Group (EG).
<b>Recommended Action</b>	No action is required.

## CNM-1053

<b>Message</b>	Node is already a registered member of another EG. First eject the current node [<nodename>] from the existing EG and then try.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the node is already a registered member of another Encryption Group (EG).
<b>Recommended Action</b>	Eject the specified node from EG and retry the operation.

## CNM-1054

<b>Message</b>	Encryption Group database state [<state>] with node IP [<node>], WWN [<wwn>].
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the status of the cluster database.
<b>Recommended Action</b>	No action is required.

## CNM-1055

<b>Message</b>	Got CNM_FSM_EVT_JOIN_REQ when already a member from same GL node, rejoining EG with GL [<glname>].
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the node is rejoining the Encryption Group (EG).
<b>Recommended Action</b>	No action is required.

## CNM-1056

<b>Message</b>	Posting event CNM_EVT_EE_INITIALIZING Slot [<slot>], WWN [<wwn>], IP [<ip>], flags [<flags>].
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the encryption engine is added into the Encryption Group (EG).
<b>Recommended Action</b>	No action is required.

## CNM-1057

<b>Message</b>	Posting event CNM_EVT_ONLINE Slot [<slot>], WWN [<wwn>], IP [<ip>], flags [<flags>].
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the encryption engine is online in the Encryption Group (EG).
<b>Recommended Action</b>	No action is required.

## CNM-1058

<b>Message</b>	Posting event CNM_EVT_OFFLINE Slot [<slot>], WWN [<wwn>], IP [<ip>], flags [<flags>].
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the encryption engine is removed from the Encryption Group (EG).
<b>Recommended Action</b>	No action is required.

## CNM-1059

<b>Message</b>	Local Node CP certificate pair mismatch detected, re-initialize the node.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the certificate pair is mismatched.
<b>Recommended Action</b>	No action is required.

## CNM-1060

<b>Message</b>	Local Node CP certificate pair match detected.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the certificate pair is matched.
<b>Recommended Action</b>	No action is required.

## CNM-1061

<b>Message</b>	IP of the switch changed from [<old_ip_address>] to [<new_ip_address>].
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the switch IP address has changed.

## 5 CNM-1062

**Recommended Action** No action is required.

### CNM-1062

**Message** Copied certificate to [<ofname>] due to change in IP.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the certificate was copied to the file with new IP name.

**Recommended Action** No action is required.

### CNM-3001

**Message** Event: cryptocfg Status: success, Info: encryption group \"<encryption\_group\_name>\" created.

**Message Type** AUDIT | LOG

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates that the specified encryption group was created.

**Recommended Action** No action is required.

### CNM-3002

**Message** Event: cryptocfg Status: success, Info: encryption group deleted.

**Message Type** AUDIT | LOG

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates an encryption group was deleted.

**Recommended Action** No action is required.

## CNM-3003

<b>Message</b>	Event: cryptocfg Status: success, Info: Membernode \"<member_node_WWN>\" added to encryption group.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified member node was added to an encryption group.
<b>Recommended Action</b>	No action is required.

## CNM-3004

<b>Message</b>	Event: cryptocfg Status: success, Info: Membernode \"<member_node_WWN>\" ejected from encryption group.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified member node was ejected from an encryption group.
<b>Recommended Action</b>	No action is required.

## CNM-3005

<b>Message</b>	Event: cryptocfg Status: success, Info: Membernode \"<member_node_WWN>\" left encryption group.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified member node left an encryption group.
<b>Recommended Action</b>	No action is required.

## CNM-3006

<b>Message</b>	Event: cryptocfg Status: success, Info: Heartbeat miss count set to <heartbeat_misses>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the heartbeat miss value was set.
<b>Recommended Action</b>	No action is required.

## CNM-3007

<b>Message</b>	Event: cryptocfg Status: success, Info: Heartbeat timeout set to <heartbeat_timeout>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the heartbeat timeout value was set.
<b>Recommended Action</b>	No action is required.

## CNM-3008

<b>Message</b>	Event: cryptocfg Status: success, Info: Routing mode of EE in slot <slot> set to <routingmode>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the encryption engine routing mode was set.
<b>Recommended Action</b>	No action is required.

## CNM-3009

<b>Message</b>	Event: cryptocfg Status: success, Info: <nodeType> <nodeWWN> registered.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified member node was registered.
<b>Recommended Action</b>	No action is required.

## CNM-3010

<b>Message</b>	Event: cryptocfg Status: success, Info: Membernode <membernodeWWN> unregistered.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified member node was unregistered.
<b>Recommended Action</b>	No action is required.

## CNM-3011

<b>Message</b>	Event: cryptocfg Status: success, Info: Encryption group synchronized.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an encryption group was synchronized.
<b>Recommended Action</b>	No action is required.

## CNM-3012

<b>Message</b>	Deleteing an EG with LUNs setup for encryption can lead to LUNs being disabled if Encryption Group name is not preserved (<egName>).
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Encryption Group (EG) was deleted. Recreate EG with the same name if LUNs are set up for encryption.
<b>Recommended Action</b>	Preserve the EG name when EG is recreated if LUNs are set up for encryption.



## CONF Messages

### CONF-1000

<b>Message</b>	<code>configDownload completed successfully &lt;Info about the parameters and AD.&gt;</code>
<b>Message Type</b>	LOG   AUDIT
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>configDownload</b> operation was initiated and completed successfully. The <i>Info about the parameters and AD</i> variable is the description of the classes of configuration parameters that were downloaded. If Admin Domain (AD) is enabled, the AD number is specified in the description.
<b>Recommended Action</b>	No action is required.

### CONF-1001

<b>Message</b>	<code>configUpload completed successfully &lt;Info about the parameters and AD.&gt;</code>
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>configUpload</b> operation was initiated and completed successfully. The <i>Info about the parameters and AD</i> variable is the description of the classes of configuration parameters that were uploaded. If Admin Domain (AD) is enabled, the AD number is specified in the description.
<b>Recommended Action</b>	No action is required.

### CONF-1020

<b>Message</b>	<code>configDownload not permitted &lt;AD Number if AD is configured on the system.&gt;</code>
<b>Message Type</b>	AUDIT
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a <b>configDownload</b> operation is not permitted. There are many possible causes.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to view the error log. Correct the error and execute the <b>configDownload</b> command again.

## CONF-1021

<b>Message</b>	configUpload not permitted <AD Number if AD is configured on the system>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a <b>configUpload</b> operation is not permitted. There are many possible causes.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to view the error log. Correct the error and execute the <b>configUpload</b> command again.

## CONF-1022

<b>Message</b>	Downloading configuration without disabling the switch was unsuccessful.
<b>Message Type</b>	AUDIT
<b>Class</b>	CFG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an attempt to download the configuration without disabling the switch was unsuccessful because there are one or more parameters that require the switch to be disabled.
<b>Recommended Action</b>	Disable the switch using the <b>switchDisable</b> command and download the configuration.

## CONF-1023

<b>Message</b>	configDownload failed <Message>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a <b>configDownload</b> operation has failed.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to view the error log. Correct the error and execute the <b>configDownload</b> command again.

## CONF-1024

<b>Message</b>	<code>configUpload failed &lt;Message&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a <b>configUpload</b> operation has failed.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to view the error log. Correct the error and execute the <b>configUpload</b> command again.

## CONF-1030

<b>Message</b>	<code>Configuration database full, data not committed (key: &lt;Key of failed configuration data&gt;).</code>
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the previous configuration commands have resulted in a database full condition. Configuration changes associated with the specified key was not applied.
<b>Recommended Action</b>	Use <b>configure</b> command and various other commands to erase configuration parameters that are no longer required. As a last resort, execute the <b>configDefault</b> command and reconfigure the system.

## CONF-1031

<b>Message</b>	<code>configDefault completed successfully &lt;Message&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>configDefault</b> command was initiated and completed successfully.
<b>Recommended Action</b>	No action is required.

## CONF-1032

**Message** `configRemove completed successfully <Message>.`

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the **configRemove** command was initiated and completed successfully.

**Recommended Action** No action is required.

## CONF-1040

**Message** `configDefault Failed. <Message>.`

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that an error occurred while executing the **configDefault** command.

**Recommended Action** Execute the **errShow** command to view the error log. Correct the error and execute the **configDefault** command again.

## CONF-1041

**Message** `configRemove Failed. <Message>.`

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that an error occurred while executing the **configRemove** command.

**Recommended Action** Execute the **errShow** command to view the error log. Correct the error and execute the **configRemove** command again.

## CONF-1042

<b>Message</b>	Fabric Configuration Parameter <Parameter> changed to <Value>
<b>Message Type</b>	LOG   AUDIT
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the fabric configuration parameter value has been changed.
<b>Recommended Action</b>	No action is required.

## CONF-1043

<b>Message</b>	Fabric Configuration Parameter <Parameter> changed to <Value>
<b>Message Type</b>	LOG   AUDIT
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the fabric configuration parameter value has been changed.
<b>Recommended Action</b>	No action is required.

## CONF-1044

<b>Message</b>	Fabric Configuration Parameter <Parameter> changed from <Old_Location> to <New_Location>
<b>Message Type</b>	LOG   AUDIT
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the fabric configuration parameter value has been changed by a user.
<b>Recommended Action</b>	No action is required.

## CTAP Messages

### CTAP-1001

<b>Message</b>	Key acquisition for <Pool or Container> <Begins or Complete>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a change in the tape pool database has triggered the key acquisition process for each pool.
<b>Recommended Action</b>	Do not start tape backup or restore operations involving tape pools until the process is complete.

## CVLC Messages

### CVLC-1001

**Message** <Re-key type (First time encryption/Key expired/Manual)> re-key <Re-key action (started/completed/failed/cancelled)>, LUN SN: <LUN serial number>. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the first-time encryption, key expired, or manual re-key operation is performed. The operation has been started, completed, failed, or cancelled.

**Recommended Action** No action is required.

### CVLC-1002

**Message** Tape session <Re-key action (started/cancelled/failed)>. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that a tape session was started, failed, or cancelled.

**Recommended Action** No action is required.

### CVLC-1003

**Message** Forceful LUN policy change to clear text while re-key session is still active. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the encryption LUN policy was forcefully changed while a re-key session was still active.

**Recommended Action** No action is required.

## CVLC-1004

<b>Message</b>	Forceful encryption LUN removal while re-key session is still active. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the encryption LUN was forcefully removed while a re-key session was still active.
<b>Recommended Action</b>	No action is required.

## CVLC-1005

<b>Message</b>	There are no LUNs found from the target. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that there are no LUNs found from the target-initiator pair.
<b>Recommended Action</b>	No action is required.

## CVLC-1006

<b>Message</b>	Duplicate LUN serial number <LUN SN> found. Container: <Target container name>, Initiator: <Initiator physical WWN>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that there is more than one LUN serial number discovered from the same target. Therefore, encryption on this target is disabled.
<b>Recommended Action</b>	No action is required.



## CVLC-1007

<b>Message</b>	Removal of encryption LUN is not allowed when decrypt of existing data is enabled. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that there has been an attempt to remove the encryption LUN while decryption of existing data is still enabled.
<b>Recommended Action</b>	To preserve the user data, execute the <b>cryptocfg --modify -LUN -cleartext</b> command to convert to cleartext LUN. Use the <b>cryptocfg --modify -LUN -cleartext</b> command to disable decryption of existing data. Then try to delete the LUN again.

## CVLC-1008

<b>Message</b>	LUN discovery failure: <Discovery state>, Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that LUN discovery failed.
<b>Recommended Action</b>	No action is required.

## CVLC-1009

<b>Message</b>	Wrong device type: should be <Expected device type (Disk/Tape)>, found <Discovered device type (Disk/Tape)>. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that LUN discovery failed.
<b>Recommended Action</b>	No action is required.

## CVLC-1010

<b>Message</b>	Tape license is required for tape container: <Target container name>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the tape container is configured with non-Brocade mode but there is no valid license.
<b>Recommended Action</b>	Obtain a license for non-Brocade mode.

## CVLC-1011

<b>Message</b>	Third party license is required for encryption LUN in third party mode. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the encryption LUN is configured with non-Brocade mode but there is no valid license.
<b>Recommended Action</b>	Obtain a license for non-Brocade mode.

## CVLC-1012

<b>Message</b>	Disk metadata is in wrong format (<Metadata format found (Brocade/Third party)>). Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the metadata found on the disk LUN is in the wrong format.
<b>Recommended Action</b>	Use the <b>cryptoCfg</b> command to change the metadata mode of the LUN.

## CVLC-1013

<b>Message</b>	Unable to retrieve key record from the key archive. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the encryption engine is unable to retrieve the key record base on the key ID found in the metadata.
<b>Recommended Action</b>	No action is required.

## CVLC-1014

<b>Message</b>	Missing Key ID from user input. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the data state in the LUN configuration is in the encrypted state without a key ID and there is no metadata found on the LUN.
<b>Recommended Action</b>	Use the <b>cryptoCfg</b> command to add the key ID, if available.

## CVLC-1015

<b>Message</b>	LUN is set to read only mode. Reason: <Reason for LUN is set to read only mode>. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the LUN is set to read-only mode because there is a conflict in the configuration.
<b>Recommended Action</b>	No action is required.

## CVLC-1016

**Message** LUN is out of read only mode. Reason: <Reason for LUN is out of read only mode>. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the LUN is set to read/write mode.

**Recommended Action** No action is required.

## CVLC-1017

**Message** Event: <Description of the event>. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates a warning or an error event.

**Recommended Action** No action is required.

## CVLC-1018

**Message** Event: <Description of the event>. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates an informational event.

**Recommended Action** No action is required.

## CVLC-1019

<b>Message</b>	Metadata exists while data state is clear text. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the data state in the LUN configuration is cleartext, but metadata exists on the LUN.
<b>Recommended Action</b>	Use the <b>cryptoCfg</b> command to confirm the configuration.

## CVLC-1020

<b>Message</b>	Metadata exists while LUN is clear text. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that metadata exists on the LUN that is in cleartext state.
<b>Recommended Action</b>	Use the <b>cryptoCfg</b> command to confirm the configuration.

## CVLC-1021

<b>Message</b>	User provided key ID <Key ID provided by the user> is ignored while metadata <Key ID from metadata> exists. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the key ID provided is ignored because metadata exists on the LUN.
<b>Recommended Action</b>	No action is required.

**CVLC-1022**

<b>Message</b>	User provided key ID <Key ID provided by the user> is ignored while data state is clear text. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the key ID provided is ignored because the data state is cleartext.
<b>Recommended Action</b>	No action is required.

**CVLC-1023**

<b>Message</b>	Rebalance recommended on EE: <EE name>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that due to container configuration changes, weights are not balanced on OB1s.
<b>Recommended Action</b>	Run the <b>cryptocfg --rebalance</b> command to increase system performance.

**CVLC-1024**

<b>Message</b>	Device Decommission operation <Decommission state (succeeded/failed)>. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the device decommission process has either succeeded or failed.
<b>Recommended Action</b>	No action is required.

## CVLC-1025

<b>Message</b>	Secondary Metadata exists for encrypted LUN not configured with <b>-newLUN</b> option. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the secondary metadata exists on the LUN that is not configured with the <b>-newLUN</b> option.
<b>Recommended Action</b>	Use the <b>cryptoCfg</b> command to remove and add the LUN with the <b>-newLUN</b> option.

## CVLC-1026

<b>Message</b>	Some secondary metadata missing for encrypted LUN configured with <b>-newLUN</b> option. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the secondary metadata does not exist on all logical block addresses (LBAs) for a LUN that is configured with the <b>-newLUN</b> option.
<b>Recommended Action</b>	No action is required.

## CVLC-1027

<b>Message</b>	Encrypted LUN configured with <b>-newLUN</b> option does not contain any metadata. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the metadata was corrupted.
<b>Recommended Action</b>	No action is required.

## CVLC-1028

<b>Message</b>	Not starting auto rekey on LUN with uncompressible blocks 1-16. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a warning event.
<b>Recommended Action</b>	Perform a manual re-key on this LUN.

## CVLC-1029

<b>Message</b>	Mirror LUN is disabled as primary LUN is being rekeyed without splitting the mirror. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that performing first-time encryption or manual re-key of primary LUN without splitting the mirror.
<b>Recommended Action</b>	Break the mirror and re-establish the mirror after re-key on primary LUN is complete.

## CVLC-1030

<b>Message</b>	Primary LUN may be out of sync with mirror LUN. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the manual re-key was completed on primary LUN.
<b>Recommended Action</b>	Perform the following steps. <ol style="list-style-type: none"><li>1. Make the target ports of the mirror LUN offline to hosts.</li><li>2. Re-establish the mirror.</li><li>3. After the mirror is in sync, split the mirror.</li><li>4. Bring back the target ports of the mirror LUN online.</li></ol>



## CVLC-1031

<b>Message</b>	Primary LUN is restored from mirror LUN. LUN in read-only mode. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a re-keyed primary LUN may have been restored from a mirror LUN without synchronizing.
<b>Recommended Action</b>	Perform the following steps. <ol style="list-style-type: none"><li>1. Create a new primary LUN.</li><li>2. Add the new primary LUN to its container with the <b>-newLUN</b> option.</li><li>3. Using host-based migration application, copy data from the old to the new primary LUN.</li></ol>

## CVLC-1032

<b>Message</b>	Secondary metadata for LUN has been restored. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the host I/Os to secondary metadata region.
<b>Recommended Action</b>	No action is required.

## CVLC-1033

<b>Message</b>	Rebalance completed for EE: <EE name>. Device login in progress.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a rebalance operation was performed.
<b>Recommended Action</b>	No action is required.

## CVLC-1034

<b>Message</b>	Rekey failed on Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID> because <Failure reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the first-time encryption, key expired, or manual re-key operation failed.
<b>Recommended Action</b>	No action is required.

## CVLC-1035

<b>Message</b>	A decommissioned LUN has been added back as encrypted LUN. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a decommissioned LUN has been added as an encrypted LUN.
<b>Recommended Action</b>	Perform the following steps. <ol style="list-style-type: none"><li>1. Remove the LUN from the container.</li><li>2. Add the LUN back as a cleartext LUN.</li><li>3. Modify the LUN policy to encrypt.</li></ol>

## CVLC-1039

<b>Message</b>	Refresh DEK operation <Refresh DEK status (SUCCEEDED/FAILED)>. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the status of the refresh DEK operation.
<b>Recommended Action</b>	No action is required.

## CVLC-1041

<b>Message</b>	<Host IO to secondary meta-data block rejected>. Container: <Target container name>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the host write operation on secondary metadata block region failed.
<b>Recommended Action</b>	Disable the initiator port.

## CVLM Messages

### CVLM-1001

<b>Message</b>	Failed to allocate memory: (<function name>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified function has failed to allocate memory.
<b>Recommended Action</b>	Check the memory usage on the switch using the <b>memShow</b> command. Restart or power cycle the switch.

### CVLM-1002

<b>Message</b>	Failed to initialize <module> rc = <error>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the initialization of a module within the Crypto Virtual LUN Manager (CVLM) daemon has failed.
<b>Recommended Action</b>	Download a new firmware version using the <b>firmwareDownload</b> command.

### CVLM-1003

<b>Message</b>	Crypto device configuration has been committed by switch (<Switch WWN>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified switch has committed a crypto device configuration.
<b>Recommended Action</b>	No action is required.

## CVLM-1004

**Message** Crypto device configuration between local switch (<local switch WWN>) and peer (<peer switch WWN>) is out of sync. New encryption session is not allowed.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that encryption engine nodes in the cluster encryption group have different configurations.

**Recommended Action** Synchronize the configuration in the cluster group using the **cryptocfg --commit** command.

## CVLM-1005

**Message** Crypto service is <status> on the switch.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the crypto service is enabled or disabled on the switch.

**Recommended Action** No action is required.

## CVLM-1006

**Message** Crypto device <device WWN> in target container <container name> is not in AD0.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the crypto device in the crypto target container is not in root zone database (AD0).

**Recommended Action** Use the **ad** command to move the crypto device into AD0.

## CVLM-1007

**Message** Redirect zone update failure. Status is <status>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the redirect zone update has failed.

## 5 CVLM-1008

**Recommended Action** Run the **cryptocfg --commit** command again.

### CVLM-1008

**Message** The member (<EE node WWN> <EE slot num>) of HAC (<HAC name>) is not in the fabric.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the member of the HA cluster (HAC) is not in the fabric.

**Recommended Action** Check the inter-switch link (ISL) port connected to the fabric.

### CVLM-1009

**Message** The member (<EE node WWN> <EE slot num>) of HAC (<HAC name>) is in the fabric.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the member of the HA cluster (HAC) is found in the fabric.

**Recommended Action** No action is required.

### CVLM-1010

**Message** The IP address of EE (<EE node WWN> <EE slot num>) IO link is not configured.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the IP address of the encryption engine IO link is not configured.

**Recommended Action** Configure the encryption engine IO link IP address using the **ipAddrSet** command.

## CVLM-1011

<b>Message</b>	The HAC failover occurs at EE (<EE node WWN> <EE slot num>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the HA cluster (HAC) failover occurs at the encryption engine.
<b>Recommended Action</b>	No action is required.

## CVLM-1012

<b>Message</b>	The HAC failback occurs at EE (<EE node WWN> <EE slot num>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the HA cluster (HAC) failback occurs at the encryption engine.
<b>Recommended Action</b>	No action is required.

## CVLM-1013

<b>Message</b>	Redirect zone create failed because no Host/Target (<HostPortWWN>/<TargetPortWWN>) L2 zone exists.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that creation of the redirect zone has failed.
<b>Recommended Action</b>	Create the Layer 2 zone for host and target and run the <b>cryptocfg --commit</b> command again.

## CVLM-1014

<b>Message</b>	RD zone getting deleted for which there is no Host/Target (<HostPortWWN>/<TargetPortWWN>) L2 zone exists in effective configuration.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates deletion of Frame Redirect (RD) zone and there is no corresponding Layer 2 zone present, but IT pair is in crypto configuration.
<b>Recommended Action</b>	Disable the target access to the host, recreate the Layer 2 zone for host and target, and run the <b>cryptocfg --commit</b> command again to recreate the RD zone.

## CVLM-1015

<b>Message</b>	Unable to read basewwn from blade in slot <Slot>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a failure to read the base WWN programmed on SEEPROM from this blade. Probably, SEEPROM is not programmed properly.
<b>Recommended Action</b>	WWN allocation is not possible from this blade, but the blade can be used for crypto operations. SEEPROM needs to be reprogrammed on this blade.

## CVLM-1016

<b>Message</b>	Invalid base WWN (<BaseWWN>) and/or page index (<Page>) received from the blade in slot <Slot>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that invalid base WWN and index are read from SEEPROM on this blade. Probably, SEEPROM is not programmed properly.
<b>Recommended Action</b>	WWN allocation is not possible from this blade, but the blade can be used for crypto operations. SEEPROM needs to be reprogrammed on this blade.



## CVLM-3001

<b>Message</b>	Event: cryptocfg Status: success, Info: Failback mode set to <failbackmode>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the failback mode was set.
<b>Recommended Action</b>	No action is required.

## CVLM-3002

<b>Message</b>	Event: cryptocfg Status: success, Info: HA cluster \"<HAClusterName>\" created.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified HA cluster was created.
<b>Recommended Action</b>	No action is required.

## CVLM-3003

<b>Message</b>	Event: cryptocfg Status: success, Info: HA cluster \"<HAClusterName>\" deleted.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified HA cluster was deleted.
<b>Recommended Action</b>	No action is required.

**CVLM-3004**

<b>Message</b>	Event: cryptocfg Status: success, Info: Cluster member added to HA cluster \ \"<HAClusterName>\".
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that an HA cluster member was added.
<b>Recommended Action</b>	No action is required.

**CVLM-3005**

<b>Message</b>	Event: cryptocfg Status: success, Info: Cluster member removed from HA cluster \ \"<HAClusterName>\".
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that an HA cluster member was removed.
<b>Recommended Action</b>	No action is required.

**CVLM-3006**

<b>Message</b>	Event: cryptocfg Status: success, Info: Current node WWN/slot <CurrentWWN> / <CurrentSlot> replaced with new node WWN/slot: <NewWWN> / <NewSlot>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that an HA cluster member was replaced.
<b>Recommended Action</b>	No action is required.

**CVLM-3007**

<b>Message</b>	Event: cryptocfg Status: success, Info: <diskOrTape> container \"<containerName>\" created.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified crypto-target container was created.
<b>Recommended Action</b>	No action is required.

**CVLM-3008**

<b>Message</b>	Event: cryptocfg Status: success, Info: Container \"<containerName>\" deleted.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified crypto-target container was deleted.
<b>Recommended Action</b>	No action is required.

**CVLM-3009**

<b>Message</b>	Event: cryptocfg Status: success, Info: Manual failback from EE <currentnodeWWN>/<currentSlot> to EE <newnodeWWN>/<newnodeSlot>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a manual failback was performed to an encryption engine.
<b>Recommended Action</b>	No action is required.

**CVLM-3010**

<b>Message</b>	Event: cryptocfg Status: success, Info: Move crypto target container \ <code>&lt;cryptoTargetContainer&gt;</code> to EE <code>&lt;newEEWWN&gt;/&lt;newEESlot&gt;</code> .
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified crypto-target container was moved to another encryption engine.
<b>Recommended Action</b>	No action is required.

**CVLM-3011**

<b>Message</b>	Event: cryptocfg Status: success, Info: Initiator PWWN \ <code>&lt;initiatorPWWN&gt;</code> Initiator NWWN \ <code>&lt;initiatorNWWN&gt;</code> added to crypto target container \ <code>&lt;cryptoTargetContainer&gt;</code> .
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that an initiator was added to a crypto-target container.
<b>Recommended Action</b>	No action is required.

**CVLM-3012**

<b>Message</b>	Event: cryptocfg Status: success, Info: Initiator \ <code>&lt;initiator&gt;</code> removed from crypto target container \ <code>&lt;cryptoTargetContainer&gt;</code> .
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified initiator was removed from the crypto-target container.
<b>Recommended Action</b>	No action is required.

**CVLM-3013**

<b>Message</b>	Event: cryptocfg Status: success, Info: LUN <LUNSpec>, attached through Initiator \"<Initiator>\", added to crypto target container \"<cryptoTargetContainer>\".
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a LUN was added to a crypto-target container.
<b>Recommended Action</b>	No action is required.

**CVLM-3014**

<b>Message</b>	Event: cryptocfg Status: success, Info: LUN <LUN Number>, attached through Initiator \"<Initiator>\" in crypto target container \"<cryptoTargetContainer>\", modified.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified LUN in the crypto-target container was modified.
<b>Recommended Action</b>	No action is required.

**CVLM-3015**

<b>Message</b>	Event: cryptocfg Status: success, Info: LUN <LUN Number>, attached through initiator \"<Initiator>\", removed from crypto target container \"<cryptoTargetContainer>\".
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified LUN was removed from the crypto-target container.
<b>Recommended Action</b>	No action is required.

**CVLM-3016**

<b>Message</b>	Event: cryptocfg Status: success, Info: LUN <LUN Number>, attached through Initiator \"<Initiator>\" in crypto target container \"<cryptoTargetContainer>\", enabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified LUN in a crypto-target container was enabled.
<b>Recommended Action</b>	No action is required.

**CVLM-3017**

<b>Message</b>	Event: cryptocfg Status: success, Info: Tape pool \"<tapepoolLabelOrNum>\" created.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified tape pool was created.
<b>Recommended Action</b>	No action is required.

**CVLM-3018**

<b>Message</b>	Event: cryptocfg Status: success, Info: Tape pool \"<tapepoolLabelOrNum>\" deleted.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified tape pool was deleted.
<b>Recommended Action</b>	No action is required.

**CVLM-3019**

<b>Message</b>	Event: cryptocfg Status: success, Info: Tapepool \ <code>&lt;tapepoolLabelOrNum&gt;</code> modified.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified tape pool was modified.
<b>Recommended Action</b>	No action is required.

**CVLM-3020**

<b>Message</b>	Event: cryptocfg Status: success, Info: Manual rekey of LUN <code>&lt;LUNSpec&gt;</code> attached through Initiator \ <code>&lt;Initiator&gt;</code> in crypto tgt container \ <code>&lt;cryptoTargetContainer&gt;</code> .
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a manual re-key of a LUN was performed.
<b>Recommended Action</b>	No action is required.

**CVLM-3021**

<b>Message</b>	Event: cryptocfg Status: success, Info: Manual rekey all performed.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a complete manual re-key was performed.
<b>Recommended Action</b>	No action is required.

## CVLM-3022

**Message** Event: cryptocfg Status: success, Info: Resume rekey of LUN <LUNSpec> attached through Initiator \"<Initiator>\" in crypto tgt container \"<cryptoTargetContainer>\".

**Message Type** AUDIT | LOG

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates that a resume re-key was performed.

**Recommended Action** No action is required.

## CVLM-3023

**Message** Event: cryptocfg Status: success, Info: Transaction committed.

**Message Type** AUDIT | LOG

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates that a transaction commit operation was performed.

**Recommended Action** No action is required.

## CVLM-3024

**Message** Event: cryptocfg Status: success, Info: Transaction <transactionID> aborted.

**Message Type** AUDIT | LOG

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates that a transaction abort operation was performed.

**Recommended Action** No action is required.



**CVLM-3025**

<b>Message</b>	Event: cryptocfg Status: started, Info: Decommission of device (container <cryptoTargetContainer> initiator <Initiator>, LUN <LUN>).
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the decommission operation has started.
<b>Recommended Action</b>	No action is required.

**CVLM-3026**

<b>Message</b>	Event: cryptocfg Status: Failed, Info : Decommission of device (container <cryptoTargetContainer>, Initiator <Initiator>, LUN <LUN>).
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the decommission operation has failed for the device.
<b>Recommended Action</b>	Run the <b>cryptocfg --decommission</b> command.

**CVLM-3027**

<b>Message</b>	Event: cryptocfg Status: success, Info: Decommission of device (container <cryptoTargetContainer>, initiator <Initiator>, LUN <LUN>).
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the decommission operation has been completed for the device.
<b>Recommended Action</b>	No action is required.

## CVLM-3028

<b>Message</b>	Event: cryptocfg Status: success, Info: SRDF mode set to <srdfmode>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Symmetrix Remote Data Facility (SRDF) mode was set.
<b>Recommended Action</b>	No action is required.

## DOT1 Messages

### DOT1-1001

<b>Message</b>	802.1X is enabled globally.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that 802.1X is enabled globally.
<b>Recommended Action</b>	No action is required.

### DOT1-1002

<b>Message</b>	802.1X is disabled globally.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that 802.1X is disabled globally.
<b>Recommended Action</b>	No action is required.

### DOT1-1003

<b>Message</b>	802.1X is enabled for port <port_name>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that 802.1X is enabled on the specified port.
<b>Recommended Action</b>	No action is required.

## DOT1-1004

<b>Message</b>	Port <port_name> is forcefully unauthorized.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified port has been unauthorized forcefully using the <b>dot1x port-control force-unauthorized</b> command.
<b>Recommended Action</b>	No action is required.

## DOT1-1005

<b>Message</b>	802.1X authentication is successful on port <port_name>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that 802.1X authentication has succeeded on the specified port.
<b>Recommended Action</b>	No action is required.

## DOT1-1006

<b>Message</b>	802.1X authentication has failed on port <port_name>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that 802.1X authentication has failed on the specified port due to incorrect credentials or the remote authentication dial-in user service (RADIUS) server is not functioning properly.
<b>Recommended Action</b>	Check the credentials configured with the supplicant and the RADIUS server.

## DOT1-1007

<b>Message</b>	No RADIUS server available for authentication.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that there is no remote authentication dial-in user service (RADIUS) server available for authentication.
<b>Recommended Action</b>	Execute the <b>aaaConfig --show</b> command to verify that the configured RADIUS servers are reachable and functioning.

## DOT1-1008

<b>Message</b>	Port <port_name> is forcefully authorized.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified port has been authorized forcefully using the <b>dot1x port-control forced-authorized</b> command.
<b>Recommended Action</b>	No action is required.

## DOT1-1009

<b>Message</b>	802.1X is disabled for port <port_name>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that 802.1X is disabled on the specified port.
<b>Recommended Action</b>	No action is required.

## 5 DOT1-1010

### DOT1-1010

<b>Message</b>	Port <port_name> is set in auto mode.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified port is set to auto mode.
<b>Recommended Action</b>	No action is required.

## ECC Messages

### ECC-1000

<b>Message</b>	ECC Error <Multiple or single occurrence of errors of a given type detected> occurrence of <Automatic calibration error detected><Multiple bit error detected><Single bit error detected><Memory select error detected>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the processor memory controller has detected one of the several types of double data rate (DDR) memory errors. Single bit errors are corrected, but other errors indicate either software errors or problems with the target system DRAM. Single bit errors can be expected to occur infrequently and can be caused by uncontrollable external events like cosmic rays, but frequent single bit errors can be indications of a degrading DRAM device.
<b>Recommended Action</b>	Frequent single bit errors and all other error types should be reported to technical support for further action.

### ECC-1001

<b>Message</b>	ECC Error <Multiple or single occurrence of multiple bit ECC error detected><Multiple or single occurrence of single bit ECC error detected><Multiple of single occurrence of access outside the defined physical memory space detected> detected.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the processor memory controller has detected one of the several types of double data rate (DDR) memory errors. Single bit errors are corrected, but other errors indicate either software errors or problems with the target system DRAM. Single bit errors can be expected to occur infrequently and can be caused by uncontrollable external events like cosmic rays, but frequent single bit errors can be indications of a degrading DRAM device.
<b>Recommended Action</b>	Frequent single bit errors and all other error types should be reported to technical support for further action.

## EM Messages

### EM-1001

<b>Message</b>	<FRU ID> is overheating: Shutting down.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the specified field-replaceable unit (FRU) is shutting down due to overheating. This event is typically due to a faulty fan and can also be caused by the switch environment.
<b>Recommended Action</b>	<p>Verify that the location temperature is within the operational range of the switch. Refer to the <i>Hardware Reference Manual</i> for the environmental temperature range of your switch.</p> <p>Execute the <b>fanShow</b> command to verify that all fans are running at normal speeds. If any fans are missing or not performing at high enough speed, they should be replaced.</p>

### EM-1002

<b>Message</b>	System fan(s) status <fan FRU>.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a non-bladed system has overheated and may shutdown. All fan speeds are dumped to the console.
<b>Recommended Action</b>	<p>Verify that the location temperature is within the operational range of the switch. Refer to the <i>Hardware Reference Manual</i> for the environmental temperature range of your switch.</p> <p>Execute the <b>fanShow</b> command to verify that all fans are running at normal speeds. If any fans are missing or are not performing at a high enough speed, they should be replaced.</p>

### EM-1003

<b>Message</b>	<FRU ID> has unknown hardware identifier: FRU faulted.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that a field-replaceable unit (FRU) header could not be read or is not valid. The FRU is faulted.
<b>Recommended Action</b>	<p>Execute the <b>diagPost</b> command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade by using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems.</p> <p>For the Brocade 300 and 6510, replace the switch.</p>



## EM-1004

<b>Message</b>	<FRU ID> failed to power on.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the specified field-replaceable unit (FRU) failed to power on and is not being used. The <i>FRU ID</i> value is composed of a FRU type string and an optional number to identify the unit, slot, or port. The Brocade 300 switch has 4 fans and 1 power supply, but these parts cannot be replaced: the entire switch is a FRU.
<b>Recommended Action</b>	Reseat the FRU. If the problem persists, replace the FRU.

## EM-1005

<b>Message</b>	<FRU Id> has faulted. Sensor(s) above maximum limits.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that a blade in the specified slot or the switch (for non-bladed switches) is shutdown for environmental reasons; its temperature or voltage is out of range.
<b>Recommended Action</b>	Check the environment and make sure the room temperature is within the operational range of the switch. Execute the <b>fanShow</b> command to verify fans are operating properly. Make sure there are no blockages of the airflow around the chassis. If the temperature problem is isolated to the blade itself, replace the blade. Voltage problems on a blade are likely a hardware problem on the blade itself; replace the blade.

## EM-1006

<b>Message</b>	<FRU Id> has faulted. Sensor(s) below minimum limits.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the voltage on a switch is below minimum limits. The switch or specified blade is being shutdown for environmental reasons; the voltage is too low.
<b>Recommended Action</b>	If this problem occurs on a blade, it usually indicates a hardware problem on the blade; replace the blade. If this problem occurs on a switch, it usually indicates a hardware problem on the main board; replace the switch.

**EM-1008**

<b>Message</b>	Unit in <Slot number or Switch> with ID <FRU Id> is faulted, it is incompatible with the <type of incompatibility> configuration, check FOS firmware version as a possible cause.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that a blade inserted in the specified slot or the switch (for non-bladed switches) is not compatible with the platform configuration (includes the firmware version) or the switch configuration. The blade is faulted.
<b>Recommended Action</b>	If the blade is incompatible, upgrade the firmware or replace the blade and make sure the replacement blade is compatible with your control processor (CP) type and firmware. If the incompatibility is with the logical switch configuration, change the configuration by using the <b>lscfg</b> command to be consistent with the blade type, or remove the blade.

**EM-1009**

<b>Message</b>	<FRU Id> powered down unexpectedly.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the environmental monitor (EM) received an unexpected power-down notification from the specified field-replaceable unit (FRU). This may indicate a hardware malfunction in the FRU.
<b>Recommended Action</b>	Reseat the FRU. If the problem persists, replace the FRU.

**EM-1010**

<b>Message</b>	Received unexpected power down for <FRU Id> But <FRU Id> still has power.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the environmental monitor (EM) received an unexpected power-down notification from the specified field-replaceable unit (FRU). However, the specified FRU still appears to be powered up after four seconds.
<b>Recommended Action</b>	Reseat the blade. If the problem persists, replace the blade.

## EM-1011

<b>Message</b>	Received unexpected power down for <FRU Id>, but cannot determine if it has power.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the environmental monitor (EM) received an unexpected power-down notification from the specified field-replaceable unit (FRU). However, after four seconds, it cannot be determined if it has powered down or not.
<b>Recommended Action</b>	Reseat the blade. If the problem persists, replace the blade.

## EM-1012

<b>Message</b>	<FRU Id> failed <state> state transition, unit faulted.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that a switch blade or non-bladed switch failed to transition from one state to another. It is faulted. The specific failed target state is displayed in the message. There are serious internal Fabric OS configuration or hardware problems on the switch.
<b>Recommended Action</b>	Reseat the specified field-replaceable unit (FRU). If the problem persists, restart or power cycle the switch.  Execute the <b>diagPost</b> command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade by using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems.  If the problem still persists, replace the FRU.

## EM-1013

<b>Message</b>	Failed to update FRU information for <FRU Id>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the environmental monitor (EM) was unable to update the time alive or original equipment manufacturer (OEM) data in the memory of a field-replaceable unit (FRU).
<b>Recommended Action</b>	If you executed the <b>fruInfoSet</b> command, execute the command again; otherwise, the update is automatically attempted again. If it continues to fail, reseat the FRU.  If the problem persists, replace the FRU.

## EM-1014

<b>Message</b>	Unable to read sensor on <FRU Id> (<Return code>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the environmental monitor (EM) was unable to access the sensors on the specified field-replaceable unit (FRU).
<b>Recommended Action</b>	Reseat the FRU. If the problem persists, replace the FRU.

## EM-1015

<b>Message</b>	Warm recovery failed (<Return code>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a problem was discovered when performing consistency checks during a warm boot.
<b>Recommended Action</b>	Monitor the switch. If the problem persists, restart or power cycle the switch.

## EM-1016

<b>Message</b>	Cold recovery failed (<Return code>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a problem was discovered when performing consistency checks during a cold boot.
<b>Recommended Action</b>	Monitor the switch. If the problem persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## EM-1017

<b>Message</b>	Uncommitted WWN change detected. Cold reboot required.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a user did not commit a changed World Wide Name (WWN) value before performing a system restart, power cycle, or firmware download operation.
<b>Recommended Action</b>	Change and commit the new WWN value.

## EM-1018

<b>Message</b>	CP blade in slot <slot number> failed to retrieve current chassis type (<return code>/<error code>/0x<unit number>).
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that there was a failure to read the chassis type from the system.
<b>Recommended Action</b>	Verify that the control processor (CP) blade is operational and is properly seated in its slot.

## EM-1019

<b>Message</b>	Current chassis configuration option (<Chassis config option currently in effect>) is not compatible with standby firmware version (Pre 4.4), cannot allow HA Sync.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the current chassis configuration option is not supported by the firmware on the standby control processor (CP). This is true even if the standby CP comes up and is operational. High availability (HA) synchronization of the CPs will not be allowed.
<b>Recommended Action</b>	Change the chassis configuration option to 1 using the <b>chassisConfig</b> command, or upgrade the firmware on the standby CP to the version running on the active CP.

## EM-1020

<b>Message</b>	Unit in <Slot number> with ID <FRU Id> is faulted, it's an FCoE blade and the Ethernet switch service is not enabled. Please run <fosconfig --enable ethsw>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a blade inserted in the specified slot requires the Ethernet switch service, which is not enabled. The blade is faulted.
<b>Recommended Action</b>	Execute the <b>fosconfig --enable ethsw</b> command to enable the Ethernet switch service. Note that this is a disruptive command, which requires the system to be restarted. Otherwise, remove the blade.

## EM-1028

<b>Message</b>	HIL Error: <function> failed to access history log for FRU: <FRU Id> (rc=<return code>).
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a problem accessing the data on the World Wide Name (WWN) card field-replaceable unit (FRU) or the WWN card storage area on the main logic board.  The problems were encountered when the software attempted to write to the history log storage to record an event for the specified FRU. The return code is for internal use only. This can indicate a significant hardware problem.  The <i>FRU ID</i> value is composed of a FRU type string and an optional number to identify the unit, slot, or port.
<b>Recommended Action</b>	If the problem persists, restart or power cycle the switch. If the problem still persists, replace the WWN card, or the switch (for non-bladed switches).

## EM-1029

<b>Message</b>	<FRU Id>, a problem occurred accessing a device on the I2C bus (<error code>). Operational status (<state of the FRU when the error occurred>) not changed, access is being retried.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Inter-Integrated Circuit (I2C) bus had problems and a timeout occurred.

<b>Recommended Action</b>	This is often a transient error. Watch for the EM-1048 message, which indicates that the problem has been resolved. If the problem persists, check for loose or dirty connections. Remove all dust and debris before reseating the field-replaceable unit (FRU). If it continues to fail, replace the FRU.
---------------------------	------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

## EM-1031

<b>Message</b>	<FRU Id> ejector not closed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the environmental monitor (EM) has found a switch blade that is inserted, but at least one ejector switch is not latched. The blade in the specified slot is treated as not inserted.
<b>Recommended Action</b>	Close the ejector switch (raise the slider in most blades or completely screw in the upper thumbscrew) if the field-replaceable unit (FRU) is intended for use. Refer to the appropriate <i>Hardware Reference Manual</i> for instructions on inserting the switch blades.

## EM-1033

<b>Message</b>	CP in <FRU Id> set to faulty because CP ERROR asserted.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the standby control processor (CP) has been detected as faulty. The high availability (HA) feature will not be available. This message occurs every time the other CP restarts, even as part of a clean warm failover. In most situations, this message is followed by the EM-1047 message, and no action is required for the standby CP; however, find the reason for failover.
<b>Recommended Action</b>	If the standby CP was restarted, wait for the error to clear (execute the <b>slotShow</b> command to determine if it has cleared). Watch for the EM-1047 message to verify that this error has cleared.  If the standby CP continues to be faulty or if it was not intentionally restarted, check the error logs on the other CP (using the <b>errDump</b> command) to determine the cause of the error state.  Reseat the field-replaceable unit (FRU). If the problem persists, replace the FRU.

## EM-1034

<b>Message</b>	<FRU Id> set to faulty, rc=<return code>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified field-replaceable unit (FRU) has been marked as faulty for the specified reason.

## 5 EM-1035

<b>Recommended Action</b>	Reseat the FRU. Execute the <b>diagPost</b> command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade by using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems. If the problem persists, replace the FRU.
---------------------------	------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

## EM-1035

<b>Message</b>	2 circuit paired Power Supplies are faulty, please check the <Switch side> AC main switch/circuit to see if it has power.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that both power supplies associated with one of the two main circuits are present but faulty, the circuit's switch may have been turned off, or the AC power source has been interrupted for that circuit. The <i>Switch side</i> value designates the circuit switch facing the cable side of the chassis, and is one of the following values: <ul style="list-style-type: none"><li>• left - Controls the odd-numbered power supply units.</li><li>• right - Controls the even-numbered power supply units.</li></ul>
<b>Recommended Action</b>	Verify that the identified AC circuit switch is turned on, the power cord is properly attached and undamaged, and the power source is operating properly.

## EM-1036

<b>Message</b>	<FRU Id> is not accessible.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified field-replaceable unit (FRU) is not present on the switch. If the FRU is a World Wide Name (WWN) card, the default WWN and IP addresses are used for the switch.
<b>Recommended Action</b>	Reseat the FRU. If the problem persists, restart or power cycle the switch. Execute the <b>diagPost</b> command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade by using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems. If the problem still persists, replace the FRU.



## EM-1037

<b>Message</b>	<code>&lt;FRU Id&gt; is no longer faulted.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified power supply is no longer marked faulty; probably because its AC power supply has been turned on.
<b>Recommended Action</b>	No action is required.

## EM-1042

<b>Message</b>	<code>Important FRU header data for &lt;FRU Id&gt; is not valid.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified field-replaceable unit (FRU) has an incorrect number of sensors in its FRU header-derived information. This could mean that the FRU header was corrupted or read incorrectly, or corrupted in the object database, which contains information about all FRUs.
<b>Recommended Action</b>	Reseat the FRU. If the problem persists, replace the FRU.

## EM-1043

<b>Message</b>	<code>Can't power &lt;FRU Id&gt; &lt;state (on or off)&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified field-replaceable unit (FRU) cannot be powered on or off.
<b>Recommended Action</b>	The specified FRU is not responding to the commands and should be replaced.

**EM-1044**

<b>Message</b>	Can't power on <FRU Id>, its logical switch is shut down.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified field-replaceable unit (FRU) cannot be powered on because the associated logical switch is shutdown.
<b>Recommended Action</b>	Execute the <b>switchStart</b> command on the associated logical switch.

**EM-1045**

<b>Message</b>	<FRU Id> is being powered <new state>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an automatic power adjustment is being made because of the (predicted) failure of a power supply or the insertion or removal of a port blade. The <i>new state</i> value can be one of the following values: <ul style="list-style-type: none"> <li>• On - A port blade is being powered on because the power is available (a power supply was inserted or a port blade was removed or powered down).</li> <li>• Off - A port blade has been powered down because of the (predicted) failure of the power supply.</li> <li>• Down - A newly inserted port blade was not powered on because there was not enough power available.</li> </ul>
<b>Recommended Action</b>	The Brocade 24000 requires only a single power supply for a fully populated chassis; however, you must always operate the system with at least two power supplies for redundancy.

**EM-1046**

<b>Message</b>	Error status received for blade ID <id value> for the blade in slot <slot number>, <blade incompatibility type: platform, backplane, or switch configuration>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified blade is incompatible.

<b>Recommended Action</b>	<p>If the blade ID listed is incorrect, the field-replaceable unit (FRU) header for the blade is corrupted and the blade must be replaced.</p> <p>If the error is due to the platform, the blade ID listed is not supported for that platform (CP) type. Remove the blade from the chassis.</p> <p>If the error is due to the backplane, the CP type (CP256) is not supported on that chassis (backplane revision D2). Remove the blade from the chassis.</p> <p>If the error is due to the switch configuration, the logical switch configuration of the blade is incorrect. Execute the <b>lscfg</b> command to correct the switch or port configuration for the ports on the blade.</p>
---------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

## EM-1047

<b>Message</b>	CP in slot <slot number> not faulty, CP ERROR deasserted.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the control processor (CP) is no longer faulted. This message usually follows the EM-1033 message. The new standby CP is in the process of restarting and has turned off the CP_ERR signal.
<b>Recommended Action</b>	No action is required.

## EM-1048

<b>Message</b>	<FRU Id> I2C access recovered: state <current state>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Inter-Integrated Circuit (I2C) bus problems have been resolved and I2C access to the field-replaceable unit (FRU) has become available again.
<b>Recommended Action</b>	No action is required. The EM-1048 message is displayed when the EM-1029 error is resolved.

## EM-1049

<b>Message</b>	FRU <FRU Id> insertion detected.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a field-replaceable unit (FRU) of the type and location specified by the <i>FRU ID</i> value was detected as having been inserted into the chassis.

## 5 EM-1050

**Recommended Action** No action is required.

### EM-1050

**Message** FRU <FRU Id> removal detected.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that a field-replaceable unit (FRU) of the type and location specified by the *FRU ID* value was removed from the chassis.

**Recommended Action** Verify that the FRU was intended to be removed. If not, replace the FRU as soon as possible.

### EM-1051

**Message** <FRU Id>: Inconsistency detected, FRU reinitialized.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that an inconsistent state was found in the field-replaceable unit (FRU). This occurs if the state of the FRU was changing during a failover. The FRU is reinitialized and the traffic may have been disrupted.

**Recommended Action** No action is required.

### EM-1057

**Message** Blade:<Slot Id> is getting reset:<Fault reason>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the blade is being automatically reset because of known resettable transient errors such as an application-specific integrated circuit (ASIC) parity error.

**Recommended Action** No action is required if the switch does not reach the reset threshold for the switch or blade. If the reset threshold is reached on the switch or blade, the switch or blade will be faulted and should be replaced.

**EM-1058**

<b>Message</b>	Switch gets reset:<Fault reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is being automatically reset because of a known resettable transient problem such as an application-specific integrated circuit (ASIC) parity error.
<b>Recommended Action</b>	No action is required if the switch does not reach the reset threshold for the switch or blade. If the reset threshold is reached on the switch or blade, the switch or blade will be faulted and should be replaced.

**EM-1059**

<b>Message</b>	<Slot number or Switch> with ID <Blade Id> may not be supported on this platform, check FOS firmware version as a possible cause.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a blade inserted in the specified slot or the switch (for non-bladed switches) is incompatible with the switch configuration software. The blade will not be completely usable.  The blade may only be supported by a later (or earlier) version of the firmware.
<b>Recommended Action</b>	Change the control processor (CP) firmware or replace the blade. Make sure the replacement is compatible with your switch type and firmware.

**EM-1060**

<b>Message</b>	Stopping synchronization of the system due to blade incompatibility with software version on standby CP.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a blade in the system is not supported by the firmware on the standby control processor (CP).
<b>Recommended Action</b>	Remove all blades of this type or upgrade the standby CP. After an appropriate action is taken, restart the standby CP or execute the <b>haSyncStart</b> command to enable the high availability (HA) state synchronization. Until this is done, the system will remain out of synchronization.

**EM-1061**

<b>Message</b>	Synchronization halted. Remove all blades of type <Blade Type Id> or upgrade your standby CP, then reboot or run haSyncStart.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the blade in the system is not supported by the firmware on the standby control processor (CP).
<b>Recommended Action</b>	Remove all blades of the specified type or upgrade the standby CP. After an appropriate action is taken, restart the standby CP or execute the <b>haSyncStart</b> command to enable the high availability (HA) state synchronization. Until this is done, the system will remain out of synchronization.

**EM-1062**

<b>Message</b>	Blade in slot <Slot Id> faulted as it exceeds the maximum support limit of <Limit> blades with Blade ID <Blade Type Id> in the chassis.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that too many blades of a particular type are in the system.
<b>Recommended Action</b>	Remove the faulted blade.

**EM-1063**

<b>Message</b>	Blade in slot <Slot Id> faulted because it exceeds the maximum support limit of <Limit> blades with Blade IDs <Applicable blade Type IDs> in the chassis.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that too many blades of a set of particular types are in the system.
<b>Recommended Action</b>	Remove the faulted blade.

## EM-1064

<b>Message</b>	Blade:<Slot Id> is being powered off (based on user configuration) upon receiving a HW ASIC ERROR, reason:<Fault reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the blade is being powered off because a hardware (HW) application-specific integrated circuit (ASIC) error was detected, and you have selected to power off the problem blade when such a condition occurred.
<b>Recommended Action</b>	Contact your switch service provider for assistance.

## EM-1065

<b>Message</b>	SAS Virtualization Services are not available due to incompatibility between the FOS and SAS versions<Slot number or blank for single board systems>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the version of the control processor firmware (CFOS) or the blade processor firmware (BFOS) is not compatible with the Storage Application Services (SAS) or other application firmware versions.
<b>Recommended Action</b>	Upgrade the Fabric OS firmware or the SAS firmware by using the <b>firmwareDownload</b> command. Refer to the release notes for a compatible version of firmware.

## EM-1066

<b>Message</b>	SAS Virtualization Services are now available <Slot number or blank for single board systems>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the previously incompatible Fabric OS or Storage Application Services (SAS) firmware has been upgraded and is now compatible.
<b>Recommended Action</b>	No action is required.

## EM-1067

<b>Message</b>	Stopping synchronization of the system due to <version> incompatibility with standby CP.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the software version on the standby control processor (CP) is incompatible with this software feature enabled on this Fabric OS firmware version.
<b>Recommended Action</b>	Upgrade the software on the standby CP or disable the software feature on this CP. To disable the Ethernet switch service, execute the <b>fosconfig --disable ethsw</b> command. To view the buffer optimization mode for the slots, execute the <b>bufopmod --showall</b> command, and then execute the <b>bufopmode --reset slot</b> command to disable the feature for those slots before downgrading. To disable FC8-16 Serdes tuning mode, execute the <b>serdestunemode --reset</b> command.

## EM-1068

<b>Message</b>	High Availability Service Management subsystem failed to respond. A required component is not operating.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the high availability (HA) subsystem has not returned a response within four minutes of the request from the environmental monitor (EM). It usually indicates that some component has not started properly or has terminated. The specific component that has failed may be indicated in other messages or debug data. There are serious internal Fabric OS configuration or hardware problems on the switch.
<b>Recommended Action</b>	Restart or power cycle the switch. If the problem persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## EM-1069

<b>Message</b>	Slot <FRU slot number> is being powered off.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the blade in the specified slot is being intentionally powered off.
<b>Recommended Action</b>	No action is required.



## EM-1070

<b>Message</b>	Slot <FRU slot number> is being powered on.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the blade in the specified slot is being intentionally powered on.
<b>Recommended Action</b>	No action is required.

## EM-1071

<b>Message</b>	Unit in <Slot number> with ID <FRU Id> is faulted, it is incompatible with the following blade id(s): <blade incompatibility list>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that a blade inserted in the specified slot is incompatible with another blade in the system.
<b>Recommended Action</b>	Determine which blade is essential to your configuration and remove blades that are incompatible with it.

## EM-1072

<b>Message</b>	Chassis cannot become ready since no Core Blades are available.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that all core blades are either missing, faulted, or powered off. There must be at least one core blade in enabled state for the chassis to be considered ready.
<b>Recommended Action</b>	Insert and close the ejector switch on missing core blades. Reseat or replace core blades that are faulted or powered off.

## EM-2003

**Message** <Slot Id or Switch for pizza boxes> has failed the POST tests. FRU is being faulted.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that a field-replaceable unit (FRU) has failed the Power-On Self-Test (POST). Refer to the */tmp/post[1/2].slot#.log* file for more information on the faults. To view this log file, you must be logged in at the root level. The ID will be Switch for non-bladed systems.

**Recommended Action** On bladed systems, reseal the specified FRU.  
On non-bladed switches, restart or power cycle the switch.  
If the problem persists, perform the following actions:

- Execute the **diagPost** command to make sure that Power-On Self-Test (POST) is enabled; then power cycle the blade by using the **slotPowerOff** and **slotPowerOn** commands or have the blade's ejector switch cycled to run POST and verify that the blade does not have any hardware problems.
- On bladed systems, replace the specified FRU; otherwise, replace the switch.

## ESS Messages

### ESS-1001

<b>Message</b>	A few switches in the fabric do not support the Coordinated HotCode protocol.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates one or more switches in the fabric do not support the Coordinated HotCode protocol. Continuing with the firmware download may cause data traffic disruption.
<b>Recommended Action</b>	Discontinue the firmware download, identify the down-level switch or switches that do not support the Coordinated HotCode protocol, and upgrade the down-level switches. Then, restart the firmware download on this switch. Note that upgrading a down-level Brocade switch in a mixed interop fabric may still cause data traffic disruption.

### ESS-1002

<b>Message</b>	The pause message is rejected by the domain <domain id>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that during the Coordinated HotCode protocol, a switch in the fabric has rejected the pause message which prevented the protocol from completing. Any data traffic disruption observed during the firmware download may have been due to the rejected pause message.
<b>Recommended Action</b>	No action is required.

### ESS-1003

<b>Message</b>	The pause retry count is exhausted for the domain <domain id>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that during the Coordinated HotCode protocol, a switch in the fabric did not accept the pause message which prevented the protocol from completing. Any data traffic disruption observed during the firmware download may have been due to this issue.
<b>Recommended Action</b>	No action is required.

## ESS-1004

<b>Message</b>	The resume message is rejected by the domain <domain id>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that during the Coordinated HotCode protocol, a switch in the fabric has rejected the resume message which prevented the protocol from completing. Any data traffic disruption observed during the firmware download may have been due to the rejected resume message.
<b>Recommended Action</b>	No action is required.

## ESS-1005

<b>Message</b>	The resume retry count is exhausted for the domain <domain id>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that during the Coordinated HotCode protocol, a switch in the fabric did not accept the resume message which prevented the protocol from completing. Any data traffic disruption observed during the firmware download may have been due to this issue.
<b>Recommended Action</b>	No action is required.

## ESS-1008

<b>Message</b>	Fabric Name - <fabric_name> configured (received from domain <domain id>).
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the fabric name is configured or renamed.
<b>Recommended Action</b>	No action is required.

## ESS-1009

<b>Message</b>	Fabric Name Mismatch - local(<fabric_name>) remote(<r_fabric_name> - received from domain <domain id>).
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FABRIC
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified fabric name is not unique for this fabric.
<b>Recommended Action</b>	Select an appropriate fabric name and set it again from any switch.

## ESS-1010

<b>Message</b>	Duplicate Fabric Name - <fabric_name> matching with FID <Fabric ID>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FABRIC
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the configured fabric name is already used for another partition.
<b>Recommended Action</b>	Select a different fabric name and reconfigure.

## ESW Messages

### ESW-1001

<b>Message</b>	Switch is not in ready state - Switch enable failed, switch status= 0x<switch status>, c_flags = 0x<switch control flags>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the switch enable operation has failed.
<b>Recommended Action</b>	If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

### ESW-1002

<b>Message</b>	Security violation: Unauthorized device <wwn name of device> tries to FLOGI to port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified device is not present in the authorized profile list.
<b>Recommended Action</b>	Verify that the device is authorized to log in to the switch. If the device is authorized, execute the <b>secPolicyDump</b> command to verify whether the World Wide Name (WWN) of the specified device is listed. If it is not listed, execute the <b>secPolicyAdd</b> command to add this device to an existing policy.

### ESW-1003

<b>Message</b>	Slot ENABLED but Not Ready during recovery, disabling slot = <slot number>(<return value>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the slot state has been detected as inconsistent during failover or recovery.
<b>Recommended Action</b>	For a bladed switch, execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands to power cycle the blade. For a non-bladed switch, restart or power cycle the switch.

## ESW-1004

<b>Message</b>	Blade attach failed during recovery, disabling slot = <slot number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified blade has failed during failover or recovery.
<b>Recommended Action</b>	For a bladed switch, execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands to power cycle the blade. For a non-bladed switch, restart or power cycle the switch.

## ESW-1005

<b>Message</b>	Diag attach failed during recovery, disabling slot = <slot number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the diagnostic blade attach operation has failed during failover or recovery.
<b>Recommended Action</b>	For a bladed switch, execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands to power cycle the blade. For a non-bladed switch, restart or power cycle the switch.

## ESW-1006

<b>Message</b>	HA state out of sync: Standby CP (ver = <standby SWC version>) does not support NPIV functionality. (active ver = <active SWC version>, NPIV devices = <'1' if NPIV devices exist; Otherwise '0'>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the standby control processor (CP) does not support N_Port ID Virtualization (NPIV) functionality, but the switch has some NPIV devices logged in to the fabric.
<b>Recommended Action</b>	Load a firmware version on the standby CP that supports NPIV functionality using the <b>firmwareDownload</b> command.

## ESW-1007

<b>Message</b>	Switch port <port number> disabled due to \"<disable reason>\".
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch port is disabled due to the reason displayed in the message.
<b>Recommended Action</b>	Based on the disable reason displayed, take appropriate action to restore the port. If the disable reason is "Insufficient frame buffers", reduce the distance or speed settings for the port to reduce the buffer requirement of the link. Alternatively, one or more ports in the port group must be disabled to make more buffers available for the link. Refer to the <i>Fabric OS Administrator's Guide</i> for more information.

## ESW-1008

<b>Message</b>	<area string> are port swapped on ports that do not support port swap. Slot <slot number> will be faulted.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the blade is enabled with the port configuration that already has the area swapped.
<b>Recommended Action</b>	Replace the blade with ports that support port swap. Then swap ports back to the port's default area. Refer to the <i>Fabric OS Administrator's Guide</i> for more information.



## EVMD Messages

### EVMD-1001

<b>Message</b>	Event could not be sent to remote proxy = <Remote proxy switch id>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the event could not be sent to remote proxy. This could happen if the remote proxy switch cannot be reached through in-band.
<b>Recommended Action</b>	Make sure that the specified remote domain is present in the fabric.

## FABR Messages

### FABR-1001

<b>Message</b>	<code>port &lt;port number&gt;, &lt;segmentation reason&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified switch port is isolated because of a segmentation resulting from mismatched configuration parameters.
<b>Recommended Action</b>	Based on the segmentation reason displayed with the message, look for a possible mismatch of relevant configuration parameters in the switches at both ends of the link.  Run the <b>configure</b> command to modify the appropriate switch parameters on both the local and remote switch.

### FABR-1002

<b>Message</b>	<code>fabGaid: no free multicast alias IDs.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the fabric does not have any available multicast alias IDs to assign to the alias server.
<b>Recommended Action</b>	Verify alias IDs using the <b>fabricShow</b> command on the principal switch.

### FABR-1003

<b>Message</b>	<code>port &lt;port number&gt;: ILS &lt;command&gt; bad size &lt;payload size&gt;, wanted &lt;expected payload size&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an internal link service (ILS) information unit of invalid size has been received. The neighbor switch has sent a payload with an invalid size.

<b>Recommended Action</b>	<p>Investigate the neighbor switch for problems. Run the <b>errShow</b> command on the neighbor switch to view the error log for additional messages.</p> <p>Check for a faulty cable or deteriorated small form-factor pluggable (SFP). Replace the cable or the SFP if necessary.</p> <p>Run the <b>portLogDumpPort</b> command on both the receiving and transmitting ports.</p> <p>Run the <b>fabStatsShow</b> command on both the receiving and transmitting switches.</p> <p>If the message persists, run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.</p>
---------------------------	------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

## FABR-1004

<b>Message</b>	port: <port number>, req iu: 0x<address of IU request sent>, state: 0x<command sent>, resp iu: 0x<address of response IU received>, state 0x<response IU state>, <additional description>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the information unit response was invalid for the specified command sent. The fabric received an unknown response. This message is rare and usually indicates a problem with the Fabric OS kernel.
<b>Recommended Action</b>	<p>If this message is due to a one-time event because of the incoming data, the system will discard the frame. If it is due to problems with the kernel, the system will recover by performing a failover.</p> <p>If the message persists, run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.</p>

## FABR-1005

<b>Message</b>	<command sent>: port <port number>: status 0x<reason for failure> (<description of failure reason>) xid = 0x<exchange ID of command>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the application failed to send an async command for the specified port. The message provides additional details regarding the reason for the failure and the exchange ID of the command. This can happen if a port is about to go down.
<b>Recommended Action</b>	<p>No action is required. This message is often transitory.</p> <p>If the message persists, run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.</p>

## FABR-1006

<b>Message</b>	Node free error, caller: <error description>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Fabric OS is trying to free or deallocate memory space that has already been deallocated. This message is rare and usually indicates a problem with the Fabric OS.
<b>Recommended Action</b>	In case of severe memory corruption, the system may recover by performing an automatic failover. If the message persists, run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

## FABR-1007

<b>Message</b>	IU free error, caller: <function attempting to de-allocate IU>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a failure occurred when deallocating an information unit. This message is rare and usually indicates a problem with the Fabric OS.
<b>Recommended Action</b>	In case of severe memory corruption, the system may recover by performing an automatic failover. If the message persists, run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

## FABR-1008

<b>Message</b>	<error description>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that errors occurred during the request domain ID state; the information unit cannot be allocated or sent. If this message occurs with FABR-1005, the problem is usually transitory. Otherwise, this message is rare and usually indicates a problem with the Fabric OS. The error descriptions are as follows: <ul style="list-style-type: none"> <li>• FAB RDI: cannot allocate IU</li> <li>• FAB RDI: cannot send IU</li> </ul>
<b>Recommended Action</b>	No action is required if the message appears with the FABR-1005 message. If the message persists, run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

## FABR-1009

<b>Message</b>	<error description>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that errors were reported during the exchange fabric parameter state; cannot allocate domain list due to a faulty exchange fabric parameter (EFP) type. This message is rare and usually indicates a problem with the Fabric OS.
<b>Recommended Action</b>	The fabric daemon will discard the EFP. The system will recover through the EFP retrieval process. If the message persists, run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

## FABR-1010

<b>Message</b>	<error description>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that errors occurred while cleaning up the request domain ID (RDI). The error description provides further details. This message is rare and usually indicates a problem with the Fabric OS.
<b>Recommended Action</b>	If the message persists, run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

## FABR-1011

<b>Message</b>	<error description>.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Fabric OS is unable to inform the Fabric OS State Synchronization Management module (FSSME) that the fabric is stable or unstable. This message is rare and usually indicates a problem with the Fabric OS.
<b>Recommended Action</b>	If the message persists, run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

## FABR-1012

<b>Message</b>	<function stream>: no such type, <invalid type>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the fabric is not in the appropriate state for the specified process. This message is rare and usually indicates a problem with the Fabric OS.
<b>Recommended Action</b>	The fabric daemon will take proper action to recover from the error. If the message persists, run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

## FABR-1013

<b>Message</b>	No Memory: pid=<fabric process id> file=<source file name> line=<line number within the source file>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that there is not enough memory in the switch for the fabric module to allocate. This message is rare and usually indicates a problem with the Fabric OS.
<b>Recommended Action</b>	The system will recover by failing over to the standby CP. If the message persists, run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

## FABR-1014

<b>Message</b>	Port <port number> Disabled: Insistent Domain ID <Domain ID> could not be obtained. Principal Assigned Domain ID = <Domain ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified port received a request domain ID (RDI) accept message containing a principal-switch-assigned domain ID that is different from the insistent domain ID (IDID). Fibre connectivity (FICON) mode requires an insistent domain ID. If an RDI response has a different domain ID, then the port is disabled.
<b>Recommended Action</b>	Run the <b>configShow</b> command to view the fabric.ididmode. A 0 means the IDID mode is disabled; a 1 means it is enabled. Set the switch to insistent domain ID mode. This mode is set under the <b>configure</b> command or in Web Tools on the <b>Switch Admin &gt; Configure</b> window.

## FABR-1015

<b>Message</b>	FICON Insistent DID max retry exceeded: All E_Ports will be disabled. Switch is isolated.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the application exceeded request domain ID (RDI) requests for the insistent domain ID. All E_Ports are disabled; isolating the specified switch from the fabric.
<b>Recommended Action</b>	Verify that the insistent domain ID is unique in the fabric and then re-enable the E_Ports. Run the <b>fabricShow</b> command to view the domain IDs across the fabric and the <b>configure</b> command to change the insistent domain ID mode. Refer to the <i>Fabric OS Command Reference</i> for more information on these commands.

## FABR-1016

<b>Message</b>	ficonMode is enabled.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that FICON mode is enabled on the switch through a user interface command.
<b>Recommended Action</b>	No action is required.

## FABR-1017

<b>Message</b>	ficonMode is disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that FICON mode is disabled on the switch through a user interface command.
<b>Recommended Action</b>	No action is required.

## FABR-1018

<b>Message</b>	PSS principal failed (<reason for not becoming the principal switch>: <WWN of new principal switch>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a failure occurred when trying to set the principal switch using the <b>fabricPrincipal</b> command. The message notifies you that the switch failed to become the principal switch because of one of the following reasons: <ul style="list-style-type: none"> <li>• The switch joined an existing fabric and bypassed the FO state.</li> <li>• The fabric already contains a principal switch that has a lower World Wide Name (WWN).</li> </ul>
<b>Recommended Action</b>	Make sure that no other switch is configured as the principal switch. Force a fabric rebuild by using the <b>switchDisable</b> and <b>switchEnable</b> commands.  Refer to the <i>Fabric OS Command Reference</i> for more information about the <b>fabricPrincipal</b> command.

## FABR-1019

<b>Message</b>	Critical fabric size (<current domains>) exceeds supported configuration (<supported domains>).
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that this switch is a value-line switch and has exceeded the limited fabric size: that is, a specified limit to the number of domains. This limit is defined by your specific value-line license key. The fabric size has exceeded this specified limit, and the grace period counter has started. If the grace period is complete and the size of the fabric is still outside the specified limit, Web Tools is disabled.
<b>Recommended Action</b>	Bring the fabric size within the licensed limits. Either a full fabric license must be added or the size of the fabric must be changed to within the licensed limit. Contact your switch provider to obtain a full fabric license.

## FABR-1020

<b>Message</b>	Web Tools will be disabled in <days> days <hours> hours and <minutes> minutes.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that this switch has a value-line license and has a limited number of domains. If more than the specified number of domains are in the fabric, a counter is started to disable Web Tools. This message displays the number of days left in the grace period. After this time, Web Tools is disabled.



**Recommended Action** Bring the fabric size within the licensed limits. Either a full fabric license must be added or the size of the fabric must be changed to within the licensed limit. Contact your switch provider to obtain a full fabric license.

## FABR-1021

**Message** Web Tools is disabled.

**Message Type** FFDC | LOG

**Severity** CRITICAL

**Probable Cause** Indicates that this switch has a value-line license and has a limited number of domains. If more than the specified number of domains are in the fabric, a counter is started to disable Web Tools. This grace period has expired and Web Tools has been disabled.

**Recommended Action** Bring the fabric size within the licensed limits. Either a full fabric license must be added or the size of the fabric must be changed to within the licensed limit. Contact your switch provider to obtain a full fabric license.

## FABR-1022

**Message** Fabric size (<actual domains>) exceeds supported configuration (<supported domains>). Fabric limit timer (<type>) started from <grace period in seconds>.

**Message Type** FFDC | LOG

**Severity** CRITICAL

**Probable Cause** Indicates that the fabric size has exceeded the value-line limit, and the grace period counter has started. If the grace period is complete and the size of the fabric is still outside the specified limit, Web Tools is disabled.

**Recommended Action** Bring the fabric size within the licensed limits. Either a full fabric license must be added or the size of the fabric must be changed to within the licensed limit. Contact your switch provider to obtain a full fabric license.

## FABR-1023

**Message** Fabric size is within supported configuration (<supporteddomains>). Fabric limit timer (<type>) stopped at <grace period in seconds>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the fabric size is within specified limits. Either a full fabric license was added or the size of the fabric was changed to within the licensed limit.

**Recommended Action** No action is required.

**FABR-1024**

<b>Message</b>	Initializing fabric size limit timer <grace period>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the fabric size has exceeded the limit set by your value-line switches. Value-line switches have a limited fabric size (for example, a specified limit on the number of domains). This value is defined by your specific value-line license key. The fabric size has exceeded this specified limit. The grace period timer has been initialized. If the grace period is complete and the size of the fabric is still outside the specified limit, Web Tools is disabled.
<b>Recommended Action</b>	Bring the fabric size within the licensed limits. Either a full fabric license must be added or the size of the fabric must be changed to within the licensed limit. Contact your switch provider to obtain a full fabric license.

**FABR-1029**

<b>Message</b>	Port <port number> negotiated <flow control mode description> (mode = <received flow control mode>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a different flow control mode, as described in the message, is negotiated with the port at the other end of the link. The flow control is a mechanism of throttling the transmitter port to avoid buffer overrun at the receiving port. There are three types of flow control modes: <ul style="list-style-type: none"> <li>• VC_RDY mode: Virtual-channel flow control mode. This is a proprietary protocol.</li> <li>• R_RDY mode: Receiver-ready flow control mode. This is the Fibre Channel standard protocol, that uses R_RDY primitive for flow control.</li> <li>• DUAL_CR mode: Dual-credit flow control mode. In both of the previous modes, the buffer credits are fixed, based on the port configuration information. In this mode, the buffer credits are negotiated as part of exchange link parameter (ELP) exchange. This mode also uses the R_RDY primitive for flow control.</li> </ul>
<b>Recommended Action</b>	No action is required.

**FABR-1030**

<b>Message</b>	fabric: Domain <new domain ID> (was <old domain ID>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the domain ID has changed.

**Recommended Action** No action is required.

## FABR-1031

**Message** Maximum number of retries sending ILS from port <port number> exceeded.

**Message Type** LOG | FFDC

**Severity** WARNING

**Probable Cause** Indicates the fabric exhausted the maximum number of retries sending internal link service (ILS) to the iswitch daemon on the specified E\_Port.

**Recommended Action** Run the **top** command to see if iswitchd is extremely busy or if another process is using excessive CPU resources.

## FABR-1032

**Message** Remote switch with domain ID <Domain ID> and switchname <Switchname> running an unsupported FOS version v2.x has joined the fabric.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that a switch with an unsupported Fabric OS version 2.x has joined the fabric.

**Recommended Action** Remove the switch with the unsupported Fabric OS version 2.x from the fabric

## FABR-1034

**Message** Area <Area that has already been acquired> have been acquired by port <Port that has already acquired the area>. Persistently disabling port <Port that is being disabled>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates you must enable Trunk Area on a port for another port to use the same area.

**Recommended Action** Move the cable to a port area that is not in use, or disable Trunk Area. You must manually enable the port or the port remains disabled forever.  
Refer to the *Fabric OS Administrator's Guide* for more information.

**FABR-1035**

<b>Message</b>	Slave area <Area that does not match Master port's area> does not match Master port <Master port >. Persistently disabling port <Port that is being disabled>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the Slave port's Trunk Area differs from that of the Master port.
<b>Recommended Action</b>	Move the cable to a port to match with the same Master Trunk Area, or disable Trunk Area. You must manually enable the port or the port remains disabled forever. Refer to the <i>Fabric OS Administrator's Guide</i> for more information.

**FABR-1036**

<b>Message</b>	F_Port trunks are only allowed on Trunk Area enabled port. Persistently disabling port <Port that is being disabled>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified port is being disabled because when the port on a switch is Trunk Area-enabled, it does not allow other devices like Access Gateway (AG) or HBA that are not Trunk Area-enabled.
<b>Recommended Action</b>	Move the cable to a port that does not have Trunk Area enabled.

**FABR-1037**

<b>Message</b>	Port configuration incompatible with Trunk Area enabled port. Persistently disabling port <Port that is being disabled>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified port is being disabled because when the port attempts to go online, the switch finds the Trunk Area enabled is incompatible with port configurations such as long distance, port mirror, fast write, or EX_Port.
<b>Recommended Action</b>	Check the port configurations to disable long distance, port mirror, fast write, or EX_Port.

## FABR-1038

<b>Message</b>	Trunking license not present with F port trunking enabled. Persistently disabling port <Port that is being disabled>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified port is being disabled because F_Port trunking is enabled without a trunking license being present.
<b>Recommended Action</b>	Install a trunking license or disable F_Port trunking on the port.

## FABR-1039

<b>Message</b>	Invalid domain ID zero received from principal switch(domain id=<Principal domain id>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an invalid domain ID zero has been received.
<b>Recommended Action</b>	Check the principal switch for the invalid domain ID zero.

## FABR-1040

<b>Message</b>	Speed is not 2G, 4G, or 8G with F_Port trunking enabled. Persistently disabling port <Port that is being disabled>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the speed is not compatible for F_Port trunks.
<b>Recommended Action</b>	Change the speed for the port or disable F_Port trunking on the port.

**FABR-1041**

<b>Message</b>	Port <Port that is being disabled> is disabled due to trunk protocol error.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a link reset was received before the completion of the trunking protocol on the port.
<b>Recommended Action</b>	Enable the port by running the <b>portEnable</b> command. The port may recover by re-initialization of the link. If the message persists, run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

**FABR-1043**

<b>Message</b>	Detected Fabric ID conflict with remote (not neighbor) switch <Switchname> (domain <Domain ID>), FID <Fabric ID>. No local E_Ports disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the remote switch has a Fabric ID (FID) conflict with the local switch. But no ports are disabled because the remote switch is not an adjacent to the local switch.
<b>Recommended Action</b>	Make sure that all the switches in the fabric have the same FID or upgrade the switch firmware to a VF-capable firmware.

**FABR-1044**

<b>Message</b>	Detected Fabric ID conflict with neighbor switch <Switchname> (domain <Domain ID>), FID <Fabric ID>. E_Ports (<Number of E_Ports disabled>) connected to the switch are disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the neighbor switch has a Fabric ID (FID) conflict with the local switch. All E_Ports directly connected to the conflicting switch are disabled.
<b>Recommended Action</b>	Make sure that all the switches in the fabric have the same FID or upgrade the switch firmware to a VF-capable firmware.

## FABR-1045

<b>Message</b>	Detected Base Switch conflict with remote (not neighbor) switch <Switchname> (domain <Domain ID>), BS <Base Switch Mode>. No local E_Ports disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the remote switch has a Base Switch attribute conflict with the local switch. But no ports are disabled because the remote switch is not an adjacent to the local switch.
<b>Recommended Action</b>	Make sure that all the switches in the fabric have the same Base Switch attribute or disable VF mode for the conflicting switch using the <b>fosConfig</b> command.

## FABR-1046

<b>Message</b>	Detected Base Switch conflict with neighbor switch <Switchname> (domain <Domain ID>), BS <Base Switch Mode>. E_Ports (<Number of E_Ports disabled>) connected to the switch are disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the remote switch has a Base Switch attribute conflict with the local switch. All the E_Ports directly connected to the conflicting switch are disabled.
<b>Recommended Action</b>	Make sure that all the switches in the fabric have the same Base Switch attribute or upgrade the switch firmware to a VF-capable firmware.

## FABR-1047

<b>Message</b>	Area unavailable to assign to the port. Persistently disabling port <Port that is being disabled>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that there are no areas available to assign to the port during port creation.
<b>Recommended Action</b>	Move some ports out of the default switch to make areas available.

## FABR-1048

<b>Message</b>	Detected Fabric ID (FID <InheritedFID> inherited) conflict with switch <Switchname> (domain <Domain ID>, FID <Fabric ID>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a switch in the fabric has a Fabric ID (FID) conflict with the inherited FID of the local switch.
<b>Recommended Action</b>	Make sure that all the switches in the fabric have the same FID or upgrade the switch firmware to a VF-capable firmware.

## FABR-1049

<b>Message</b>	Detected Fabric ID (FID <InheritedFID> inherited) conflict with neighbor switch <Switchname> (domain <Domain ID>, FID <Fabric ID>). E_Ports (<Number of E_Ports disabled>) connected to the switch are disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the neighbor switch has a Fabric ID (FID) conflict with the inherited FID of the local switch. All E_Ports directly connected to the conflicting switch are disabled.
<b>Recommended Action</b>	Make sure that all the switches in the fabric have the same FID or upgrade the switch firmware to a VF-capable firmware.

## FABR-1050

<b>Message</b>	<License> license not present. F_Port trunking cannot be enabled on port(<Port>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the trunking or Server Application Optimization (SAO) license is not installed.
<b>Recommended Action</b>	Install the license required.



## FABR-1051

<b>Message</b>	D-Port <Testname> test failed for slot <Slot> and port <Port>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the D_Port test failed for the given slot and port due to one of the following reasons: <ul style="list-style-type: none"> <li>• The small form-factor pluggable (SFP) fault detected by electrical loopback test failure.</li> <li>• The cable fault detected by optical loopback test failure.</li> <li>• An application-specific integrated circuit (ASIC) issue detected by link traffic test failure.</li> </ul>
<b>Recommended Action</b>	Replace the faulty SFPs, cables, or blade.

## FABR-1052

<b>Message</b>	The configured port speed (16G/10G on non FC16 blade or 1G on FC16 blade) is invalid. Persistently disabling port <Port that is being disabled>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the configured speed (16 Gbps or 10 Gbps on the non-FC16 blade or 1 Gbps on the FC16 blade) for the specified port is invalid.
<b>Recommended Action</b>	Execute the <b>portCfgSpeed</b> command to change the port speed.

## FABR-1053

<b>Message</b>	The switch is disabled due to an inconsistency found in the interop config parameters.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the configuration keys have interopmode parameters such as switch.interopMode and switch.mcdtFabricmode set.
<b>Recommended Action</b>	Execute the <b>interopmode</b> command to reset the parameters.

## FABR-1054

<b>Message</b>	Rebooting the standby as it received an update before port [ <code>&lt;Port Number&gt;</code> ] is expanded.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the standby control processor (CP) did not have the port because the port expand operation is still in progress and the standby CP has received a port update. The standby CP reboots automatically to ensure sync and attain the normal state. This is a rare occurrence.
<b>Recommended Action</b>	No action is required.

## FABR-1055

<b>Message</b>	F_Port trunking cannot be enabled on the slot <code>&lt;Slot Number&gt;</code> port <code>&lt;Port Number&gt;</code> due to inconsistent port configuration.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified F_Port is unable to join its assigned trunk area group because of mismatch in the port configuration with the other trunk area members.
<b>Recommended Action</b>	Check the configuration of the port with all other ports intended to be part of the same trunk group. Use the <b>porttrunkarea --show</b> to identify the trunk members of the specified F_Port and the <b>portcfgshow</b> command to identify the conflicting configuration between the trunk members.

## FABS Messages

### FABS-1001

<b>Message</b>	<Function name> <Description of memory need>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the system is low on memory and cannot allocate more memory for new operations. This is usually an internal Fabric OS problem or file corruption. The <i>Description of memory need</i> variable specifies the memory size that was being requested. The value can be any whole number.
<b>Recommended Action</b>	Reboot or power cycle the switch.

### FABS-1002

<b>Message</b>	<Function name> <Description of problem>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an internal problem has been detected by the software. This is usually an internal Fabric OS problem or file corruption.
<b>Recommended Action</b>	Reboot or power cycle the switch. If the message persists, run the <b>firmwareDownload</b> command to update the firmware.

### FABS-1004

<b>Message</b>	<Function name and description of problem> process <Process ID number> (<Current command name>) <Pending signal number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an operation has been interrupted by a signal. This is usually an internal Fabric OS problem or file corruption.
<b>Recommended Action</b>	Reboot or power cycle the switch.

## FABS-1005

<b>Message</b>	<Function name and description of problem> (<ID type>= <ID number>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an unsupported operation has been requested. This is usually an internal Fabric OS problem or file corruption. The following is a possible value for <i>function name and description of problem</i> variable:  fabsys_write: Unsupported write operation: process xxx  In this value, xxx is the process ID (PID), which could be any whole number.
<b>Recommended Action</b>	Reboot or power cycle the active CP (for modular systems) or the switch (for single-board systems).  If the message persists, run the <b>firmwareDownload</b> command to update the firmware.

## FABS-1006

<b>Message</b>	<Function name and description of problem>: object <object type id> unit <slot>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that there is no device in the slot with the specified object type ID in the system module record. This could indicate a serious Fabric OS data problem on the switch. The possible values for <i>function name and description of problem</i> variable are: <ul style="list-style-type: none"> <li>• setSoftState: bad object</li> <li>• setSoftState: invalid type or unit</li> <li>• media_sync: Media oid mapping failed</li> <li>• fabsys_media_i2c_op: Media oid mapping failed</li> <li>• fabsys_media_i2c_op: obj is not media type</li> <li>• media_class_hdlr: failed sending media state to blade driver</li> </ul>
<b>Recommended Action</b>	If the message is isolated, monitor the error messages on the switch. If the error is repetitive or if the fabric failed, failover or reboot the switch.  If the message persists, run the <b>firmwareDownload</b> command to update the firmware.

## FABS-1007

<b>Message</b>	<Function name>: Media state is invalid - status=<Status value>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Fabric OS has detected an invalid value in an object status field. This is usually an internal Fabric OS problem or file corruption.
<b>Recommended Action</b>	Reboot or power cycle the switch. If the message persists, run the <b>firmwareDownload</b> command to update the firmware.

## FABS-1008

<b>Message</b>	<Function name>: Media oid mapping failed.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Fabric OS was unable to locate a necessary object handle. This is usually an internal Fabric OS problem or file corruption.
<b>Recommended Action</b>	Reboot or power cycle the switch.

## FABS-1009

<b>Message</b>	<Function name>: type is not media.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Fabric OS was unable to locate an appropriate object handle. This is usually an internal Fabric OS problem or file corruption.
<b>Recommended Action</b>	Reboot or power cycle the switch.

**FABS-1010**

<b>Message</b>	<Function name>: Wrong media_event <Event number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Fabric OS detected an unknown event type. This is usually an internal Fabric OS problem or file corruption.
<b>Recommended Action</b>	Reboot or power cycle the switch. If the message persists, run the <b>firmwareDownload</b> command to update the firmware.

**FABS-1011**

<b>Message</b>	<Method name>[<Method tag number>]:Invalid input state 0x<Input state code>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that an unrecognized state code was used in an internal Fabric OS message for a field-replaceable unit (FRU).
<b>Recommended Action</b>	Reboot or power cycle the CP or system. If the message persists, run the <b>firmwareDownload</b> command to update the firmware.

**FABS-1013**

<b>Message</b>	<Method name>[<Method tag number>]:Unknown blade type 0x<Blade type>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an unrecognized type of blade has been discovered in the system. This may be caused by an incorrect field-replaceable unit (FRU) header, inability to read the FRU header, or the blade may not be supported by this platform or Fabric OS version.
<b>Recommended Action</b>	Verify that the blade is valid for use in this system and this version of Fabric OS. Reseat the blade. If this is a valid blade and reseating does not solve the problem, replace the blade.

## FABS-1014

<b>Message</b>	<Method name>[<Method tag number>]:Unknown FRU type 0x<FRU Object type>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an unrecognized type of field-replaceable unit (FRU) has been discovered in the system. This may be caused by an incorrect FRU header, inability to read the FRU header, or the FRU may not be supported by this platform or Fabric OS version.
<b>Recommended Action</b>	Verify that the FRU is valid for use in this system and this version of Fabric OS. Reseat the FRU. If this is a valid FRU and reseating does not solve the problem, replace the FRU

## FABS-1015

<b>Message</b>	<Method name>[<Method tag number>]:Request to enable FRU type 0x<FRU Object type>, unit <Unit number> failed. err code <Error code>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the specified FRU could not be enabled. This is usually an internal Fabric OS problem.
<b>Recommended Action</b>	Remove and reinsert the FRU. Reboot or power cycle the CP or system. If the message persists, run the <b>firmwareDownload</b> command to update the firmware.

## FBC Messages

### FBC-1001

**Message** Firmware version on AP blade is incompatible with that on the CP.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates the control processor (CP) blade determined that the firmware version running on the application processor (AP) blade is not compatible with that running on CP. The AP and CP blades cannot communicate.

**Recommended Action** The problem can be corrected by changing the firmware version on either the CP or on the AP blade. You can modify the firmware version on the CP blade by using the **firmwareDownload** command. Refer to the release notes to determine whether a non-disruptive firmware download is supported between the revisions. Because the AP and CP blades cannot communicate, it is not possible to load new firmware on the AP blade. If necessary, send the AP blade back to the factory for a firmware update.



## FCMC Messages

### FCMC-1001

<b>Message</b>	System is low on memory and has failed to allocate new memory.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the switch is low on memory and failed to allocate new memory for an information unit (IU).
<b>Recommended Action</b>	A non-bladed switch will automatically reboot. For a bladed switch, the active CP blade will automatically fail over and the standby CP will become the active CP.

## FCOE Messages

### FCOE-1001

<b>Message</b>	<code>calloc failed for &lt;object&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a memory failure.
<b>Recommended Action</b>	Check the memory usage on the switch using the <b>memShow</b> command.

### FCOE-1002

<b>Message</b>	<code>Max loggingroup limit reached at &lt;limit&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that too many login groups have been added.
<b>Recommended Action</b>	Check the maximum login group value displayed in the message.

### FCOE-1003

<b>Message</b>	<code>&lt;device&gt;: member in another loggingroup &lt;lg&gt; being removed.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the device World Wide Name (WWN) you are trying to add is present in some other login group, and therefore it will be removed from that login group and added to the new login group.
<b>Recommended Action</b>	Check the login group changes using the <b>fcoelogincfg --show</b> command.

## FCOE-1004

**Message** <device>: removing member from <lg> failed.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that removing a device from the login group has failed.

**Recommended Action** Execute the **supportSave** command and restart the system. If the problem persists, contact your switch service provider.

## FCOE-1005

**Message** <device>: membership check failed in loggingroup: <lg>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the membership check for the device has failed.

**Recommended Action** Check the device for failed membership using the **fcoelogincfg --show** command.

## FCOE-1006

**Message** file operation failed on <filename> for <operation> operation: errno:<error>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates a file operation failure.

**Recommended Action** Check the error code for the file operation failure and contact your switch service provider for assistance.

## FCOE-1007

**Message** IfIndex Limit Reached <num\_fcoe\_entity>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the interface index (IfIndex) limit has reached the maximum.

## 5 FCOE-1009

**Recommended Action** Check the lflindex limit displayed in the message.

### FCOE-1009

**Message** Addition of N\_Port mapping failed. Max N\_Port mapping limit reached: <max n\_port>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the N\_Port mapping has reached its maximum limit.

**Recommended Action** Remove unwanted N\_Port mappings using the **fcoelogingroup --remove** command and try adding N\_Port mapping using the **fcoelogingroup --add** command.

### FCOE-1010

**Message** FSS Registration or FCoE Trace initialization failed.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the Fabric OS state synchronization (FSS) registration or initialization of the FCoE trace has failed.

**Recommended Action** Execute the **supportSave** command and restart the system. If the problem persists, contact your switch service provider.

### FCOE-1012

**Message** Request to delete port from VLAN <vid> failed.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that a request to delete ports from the specified VLAN has failed.

**Recommended Action** Execute the **supportSave** command and restart the system. If the problem persists, contact your switch service provider.

## FCOE-1014

<b>Message</b>	Request to add ports to VLAN <vid> failed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a request to add ports to the specified VLAN has failed.
<b>Recommended Action</b>	Execute the <b>supportSave</b> command and restart the system. If the problem persists, contact your switch service provider.

## FCOE-1015

<b>Message</b>	Request to add MACs to Layer 2 for ifindex 0x<ifindex> failed, rc:<reason code>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a request to add MAC entries to Layer 2 for the specified slot or port has failed.
<b>Recommended Action</b>	Check the reason code for the failure and contact your switch service provider for assistance.

## FCOE-1016

<b>Message</b>	Request to delete VLAN <vid> failed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a request to delete the specified VLAN has failed because the VLAN may be in use.
<b>Recommended Action</b>	Disable the active FCoE login session using the <b>no fcoe</b> command and try deleting the VLAN again.

## FCOE-1017

<b>Message</b>	Request to add FCMAP failed for VLAN <vid>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a request to add FCMAP has failed. When the VLAN is in use, its FCMAP cannot be modified.

## 5 FCOE-1019

**Recommended Action** Disable the active FCoE session on VLAN using the **no fcoe** command and try adding the FCMAP again.

### FCOE-1019

**Message** FLOGI ignored as FCMAP is not configured on FCoE VLAN.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that FCMAP has not been configured on FCoE VLAN.

**Recommended Action** Configure FCMAP on the FCoE VLAN using the **fcoe --fcmmapset** command.

### FCOE-1021

**Message** Port is already logged in.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the N\_Port device has already logged in or is in the process; duplicate FLOGI received.

**Recommended Action** No action is required.

### FCOE-1022

**Message** Max FCoE device login limit reached.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the switch has reached its maximum allowed FCoE device limit.

**Recommended Action** Do not add any more FCoE devices to the switch.

## FCOE-1023

<b>Message</b>	<portindex>, Too many logins on FCoE controller, max allowed = <MAX_DEVS_PER_CTLR>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the controller has reached its maximum allowed FCoE login limit.
<b>Recommended Action</b>	Log out some of the logged-in devices using the <b>fcoe --resetlogin</b> command and then log in a new device. You can view the list of logged-in devices using the <b>fcoe --loginshow</b> command.

## FCOE-1024

<b>Message</b>	FDISC received from E_node without prior FLOGI.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a FDISC frame is received from the end node that has not logged in. The end node must send a fabric login (FLOGI) before it can send an FDISC.
<b>Recommended Action</b>	It is due to a CNA or target driver issue. Contact CNA or target driver support team for assistance.

## FCOE-1025

<b>Message</b>	FCoE logout received on FIP VN port.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates pre-FIP logout for a device that has logged in using the FCoE Initialization Protocol (FIP).
<b>Recommended Action</b>	It is due to a CNA or target driver issue. Contact CNA or target driver support team for assistance.

## FCOE-1026

<b>Message</b>	FDISC/FLOGI mismatch. FDISC addressed to different FCF than base FLOGI.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the base port has sent a fabric login (FLOGI) but the subsequent FDISC frames that were received on the switch do not match the original FLOGI.
<b>Recommended Action</b>	It is due to a CNA or target driver issue. Contact CNA or target driver support team for assistance.

## FCOE-1027

<b>Message</b>	<message> : <mac1>:<mac2>:<mac3>:<mac4>:<mac5>:<mac6>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Fibre Channel Forwarders (FCF) controller is not found for the DA. The end node may be sending the FLOGI with a wrong DA MAC address.
<b>Recommended Action</b>	Some parameters are not exchanged correctly between the switch and the end device. Reconfigure the port.

## FCOE-1028

<b>Message</b>	<message> : <wwn1>:<wwn2>:<wwn3>:<wwn4>:<wwn5>:<wwn6>:<wwn7>:<wwn8>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the FCoE device with the specified World Wide Name (WWN) is not a member of the login group.
<b>Recommended Action</b>	Change the FCoE login group policy on the switch using the <b>fcoelogingroup</b> command so that the device can log in.



**FCOE-1029**

<b>Message</b>	Version mismatch between FIP FDISC and root VN port.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a version mismatch between the fabric login (FLOGI) and FDISC.
<b>Recommended Action</b>	It is due to a CNA or target driver issue. Contact CNA or target driver support team for assistance.

**FCOE-1030**

<b>Message</b>	Version mismatch between FIP LOGO and root VN port.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a version mismatch between the FCoE initialization protocol (FIP) logout and the base fabric login (FLOGI).
<b>Recommended Action</b>	It is due to a CNA or target driver issue. Contact CNA or target driver support team for assistance.

**FCOE-1031**

<b>Message</b>	FCoE port deleted port <port> slot <slot>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that an FCoE port has been deleted.
<b>Recommended Action</b>	No action is required.

**FCOE-1032**

<b>Message</b>	We are in WARM RECOVERING state...
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that high availability (HA) failover or switch reboot may be in progress.

## 5 FCOE-1033

**Recommended Action** Wait until the chassis has fully recovered before you perform any operations.

### FCOE-1033

**Message** FIP v1 FLOGI received - VF port in use.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that a device is trying to log in to a port that already has a device logged in.

**Recommended Action** No action is required.

### FCOE-1034

**Message** Discarded frame received on priority <pkt\_ctrlp->pri\_in> for which PFC/FCoE is disabled.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that a frame is received on the specified priority, for which priority-based flow control (PFC) or FCoE is disabled.

**Recommended Action** Change the CEE map assigned to the FCoE map to accommodate the PFC for the specified FCoE priority or change the FCoE priority using the **fabric-map default** command under the FCoE configuration mode.

### FCOE-1037

**Message** Login group dropped for switch WWN: <switch WWN>, due to name conflict while merging.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that same login group name exists for two different switches that have different organizationally unique identifiers (OUIs), but the last three bytes are same.

**Recommended Action** Create the login group for the switch World Wide Name (WWN) with another name that will not lead to a name conflict.

## FCOE-1038

<b>Message</b>	logingroup#<logingroup number> (<logingroup name>) created.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified login group is added to the switch login group table.
<b>Recommended Action</b>	No action is required.

## FCOE-1039

<b>Message</b>	Logingroup <logingroup name> deleted.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified login group is deleted from the switch login group table.
<b>Recommended Action</b>	No action is required.

## FCOE-1040

<b>Message</b>	Logingroup name changed from <old logingroup name> to <new logingroup name>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the login group has been renamed.
<b>Recommended Action</b>	No action is required.

## FCOE-1041

<b>Message</b>	Transaction aborted.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the ongoing FCoE login configuration transaction is aborted.

## 5 FCOE-1042

**Recommended Action** No action is required.

### FCOE-1042

**Message** FCoE login configuration transaction saved fabric-wide.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the FCoE login configuration transaction is saved fabric-wide.

**Recommended Action** No action is required.

### FCOE-1043

**Message** FCoE login configuration management disabled.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the FCoE login configuration management is disabled.

**Recommended Action** No action is required.

### FCOE-1044

**Message** FCoE login configuration management enabled.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the FCoE login configuration management is enabled.

**Recommended Action** No action is required.

## FCOE-1045

<b>Message</b>	FCoE port <port number> is configured as VE port.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified FCoE port is configured as a virtual expansion (VE) port.
<b>Recommended Action</b>	No action is required.

## FCOE-1046

<b>Message</b>	fcoed.conf file is truncated. Please reconfigure FCoE ports.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the magic number in the fcoed.conf file does not match. Therefore, the fcoed.conf file is truncated and updated with a new magic number.
<b>Recommended Action</b>	Reconfigure the FCoE ports as all the port configurations will be lost.

## FCOE-1047

<b>Message</b>	fcoed.conf file is not present, therefore creating.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the fcoed.conf file is not available and therefore creating a new file.
<b>Recommended Action</b>	No action is required.

## FCOE-1048

<b>Message</b>	FCoE port <port number> is configured as VF port.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified FCoE port is configured as a virtual fabric (VF) port.

## 5 FCOE-1048

**Recommended  
Action**      No action is required.

## FCPD Messages

### FCPD-1001

<b>Message</b>	Probing failed on <error string>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	<p>Indicates that a Fibre Channel Protocol (FCP) switch probed devices on a loop port, and probing failed on the L_Port, arbitrated loop physical address (AL_PA), or the F_Port. For ALPA, the valid range is 0x00 through 0xFF. The <i>error</i> variable can be either of the following:</p> <ul style="list-style-type: none"> <li>• L_Port <i>port_number</i> ALPA <i>alpa_number</i></li> <li>• F_Port <i>port_number</i></li> </ul> <p>This could happen due to some firmware issue with the device controller on the specified port.</p>
<b>Recommended Action</b>	Contact the device vendor for any firmware-related issues. Also, consider upgrading the device firmware.

### FCPD-1002

<b>Message</b>	port <port number>, bad R_CTL for fcp probing: 0x<R_CTL value>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the response frame received on the specified port for an inquiry request contains an invalid value in the routing control field. This could happen due to some firmware issue with the device controller on the specified port.
<b>Recommended Action</b>	Contact the device vendor for any firmware-related issues. Also, consider upgrading the device firmware.

### FCPD-1003

<b>Message</b>	Probing failed on <error string> which is possibly a private device which is not supported in this port type.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that device probing has failed because private devices will not respond to the switch port login (PLOGI) during probing.

## 5 FCPD-1003

**Recommended Action** The Brocade 4100, 4900, 5000, 7500, and AP 7600 do not support private loop devices. Refer to the switch vendor for a list of other port types that support private devices for inclusion into the fabric.



## FCPH Messages

### FCPH-1001

<b>Message</b>	<code>&lt;function&gt;: &lt;failed function call&gt; failed, out of memory condition.</code>
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the switch is low on memory and failed to allocate new memory for a Fibre Channel driver instance. The <i>function</i> value can only be <code>fc_create</code> . This function creates a Fibre Channel driver instance. The <i>failed function call</i> can only be <code>kmalloc_wrapper</code> , which has failed. This function call is for kernel memory allocation.
<b>Recommended Action</b>	A non-bladed switch will automatically reboot. For a bladed switch, the active CP blade will automatically fail over and the standby CP will become the active CP.

### FCPH-1002

<b>Message</b>	<code>Port &lt;Port Number&gt; has been disabled since switch requires authentication when device authentication policy is set to ON.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a device that does not support authentication has tried to log in to the switch when the device authentication policy is in ON status on the switch.
<b>Recommended Action</b>	Enable the authentication on the device or set the device authentication status to PASSIVE/OFF on the switch if it is not mandatory. Use the <b>authUtil</b> command to change the device authentication policy.

### FCPH-1003

<b>Message</b>	<code>New port &lt;Port Number&gt; has same Port WWN as old port &lt;Port Number&gt; as part of duplicate Port WWN detection policy.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified new port has the same Port World Wide Name (PWWN) as the old port.
<b>Recommended Action</b>	No action is required.

## FCPH-1004

<b>Message</b>	NPIV port <Port Number> has same Port WWN as old port <Port Number> with pid 0x<Port PID> as part of duplicate Port WWN detection policy.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified N_Port ID virtualization (NPIV) port has the same Port World Wide Name (PWWN) as the old port.
<b>Recommended Action</b>	No action is required.

## FCPH-1005

<b>Message</b>	FDISC exch=0x<ExchangeId> sid=0x<SourceID> did=0x<DestinationID> on port <Port> rejected; temporary mem alloc error. Please bounce port of affected device.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that in busy login conditions, the buffer used for quick memory allocations (known as <i>atomic malloc</i> ) can be quickly depleted and not replenished before the next allocation occurs.
<b>Recommended Action</b>	Reset the specified port using the <b>portDisable</b> and <b>portEnable</b> commands.

## FCR Messages

### FCR-1001

<b>Message</b>	FC router proxy device in edge created at port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a proxy device at a port in the edge fabric has been imported at the specified port.
<b>Recommended Action</b>	No action is required.

### FCR-1002

<b>Message</b>	FC router proxy device in edge deleted at port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a proxy device at a port in the edge fabric has been deleted at the specified port.
<b>Recommended Action</b>	No action is required.

### FCR-1003

<b>Message</b>	FC router physical DEVICES newly exported at port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that one or more physical devices have been newly exported through the specified port.
<b>Recommended Action</b>	No action is required.

## FCR-1004

<b>Message</b>	FC router physical devices offline at port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that one or more physical devices connected to the specified port have gone offline.
<b>Recommended Action</b>	Verify that the devices were intended to be taken offline. If not, verify that the devices are functioning properly. Verify that all small form-factor pluggables (SFPs) are seated correctly. Check for faulty cables, deteriorated SFPs, or dirty connections. Replace the cables and the SFPs if necessary.

## FCR-1005

<b>Message</b>	FC router LSAN zone device removed at port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a device is removed from the logical storage area network (LSAN) zone in the edge fabric.
<b>Recommended Action</b>	No action is required.

## FCR-1006

<b>Message</b>	FC router LSAN zone device added at port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a device is added to a logical storage area network (LSAN) zone in the edge fabric.
<b>Recommended Action</b>	No action is required.

## FCR-1007

<b>Message</b>	FC router LSAN zone deleted at port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a logical storage area network (LSAN) zone attached to the specified port was deleted in the edge fabric.
<b>Recommended Action</b>	No action is required.

## FCR-1008

<b>Message</b>	FC router LSAN zone created at port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a logical storage area network (LSAN) zone was created at the specified port in the edge fabric.
<b>Recommended Action</b>	No action is required.

## FCR-1009

<b>Message</b>	FC router LSAN zone enabled at port <port number>: <enabled name>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a logical storage area network (LSAN) zone was enabled in the edge fabric attached to the specified port. The enabled LSAN zone configuration is listed.
<b>Recommended Action</b>	No action is required.

## FCR-1010

<b>Message</b>	FC router LSAN zone disabled at port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a logical storage area network (LSAN) zone is disabled in the edge fabric attached to the specified port.
<b>Recommended Action</b>	No action is required.

## FCR-1011

<b>Message</b>	Remote LSAN zone updated in domain <domain ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a logical storage area network (LSAN) zone update was received from another domain.
<b>Recommended Action</b>	No action is required.

## FCR-1012

<b>Message</b>	FC Router fabric build completed on port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Fibre Channel router has completed a fabric build at the specified port.
<b>Recommended Action</b>	No action is required.

## FCR-1013

<b>Message</b>	Phantom FSPF database exchange completed on port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified EX_Port has completed the fabric shortest path first (FSFP) database exchange.
<b>Recommended Action</b>	No action is required.

## FCR-1015

<b>Message</b>	New EX_Port or VEX_Port added on port <port number> in domain <domain ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that an EX_Port was created on the specified port in the specified domain.
<b>Recommended Action</b>	No action is required.

## FCR-1016

<b>Message</b>	FCR fabric no longer reachable at port id <port number> (0x<port number (hex)>) fabric ID <fabric ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a fabric is no longer accessible through the backbone fabric. This may be caused by a link or switch failure.
<b>Recommended Action</b>	No action is required.

## FCR-1018

<b>Message</b>	FC router proxy device entries exhausted on port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the number of proxy devices is greater than allowed by the port resource.
<b>Recommended Action</b>	Remove excess logical storage area network (LSAN) zones or devices until the number of proxy devices exported is within the range allowed by the port resource. Use the <b>fcrResourceShow</b> command to view resources including LSAN zone resources, LSAN device resources, and proxy device port resources. Use the <b>fcrProxyDevshow</b> command to view how many proxy devices are created in the fabric with the port resource problem. LSAN zones are removed using standard zoning commands such as <b>zoneShow</b> , <b>zoneRemove</b> , <b>zoneDelete</b> , <b>cfgDelete</b> , and <b>cfgDisable</b> in the edge fabric. Proxy devices can be removed by zoning operations or by bringing physical devices offline (for example, disabling the port that a device is attached to, and then disconnecting the cable or disabling the device).

## FCR-1019

<b>Message</b>	EX_Port or VEX_Port entries exhausted at port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the number of EX_Port or VEX_Port entries being created is greater than allowed by the port resource.
<b>Recommended Action</b>	Disable EX_Ports or VEX_Ports until the number of ports is within the range allowed by the port resource. The EX_Port or VEX_Port limit is displayed using the <b>fcrRouteShow</b> command. Use the <b>portDisable</b> command to disable EX_Ports.

## FCR-1020

<b>Message</b>	Local LSAN zone entries for FC router exhausted; max limit: <LSAN zone limit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of LSAN zones created within a MetaSAN exceeds the local LSAN zone database limitations.
<b>Recommended Action</b>	Remove excess LSAN zones so that the number of LSAN zones created is within the range of the local database limitations. To do that, perform the following steps: <ol style="list-style-type: none"> <li>1. Use the <b>portDdisable</b> command to disable all the EX_Ports that received this error message.</li> <li>2. Use the <b>portDdisable</b> command to disable all the other EX_Ports on that FCR connected to the same edge fabrics to which the EX_Ports disabled in step 1 are connected.</li> </ol>



3. Use zoning commands on the edge fabrics, to reduce the LSAN zone entries on the edge fabrics.
4. Use the **portEnable** command on each EX\_Port, one at a time, and verify that this error is not reported again.

## FCR-1021

<b>Message</b>	Local LSAN device entries exhausted.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of devices created through logical storage area network (LSAN) zones within the MetaSAN exceeds the local LSAN zone database limitations.
<b>Recommended Action</b>	Remove excess device entries within LSAN zones so that the number of devices is within the range of the local zone database limitations.

## FCR-1022

<b>Message</b>	Local proxy device slot entries exhausted.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that resources to persistently store the proxy device slot to the remote world wide name (WWN) have been consumed.
<b>Recommended Action</b>	Remove the proxy device slots by using the <b>fcrProxyConfig</b> command or limit proxy devices by removing logical storage area network (LSAN) zone entries.

## FCR-1023

<b>Message</b>	Local phantom port WWN entries exhausted.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of port World Wide Names (WWNs) detected to be in use exceeds the local port WWN resources.
<b>Recommended Action</b>	Limit the number of port WWNs required by limiting the remote edge fabric connectivity (which limits the number of translate domains). You can also limit the number of proxy devices for a translate domain (which limits the number of translate domain ports required) by limiting the devices specified in logical storage area network (LSAN) zones.

**FCR-1024**

<b>Message</b>	Local LSAN zone <zone name> device entries for edge LSAN exhausted.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of devices in a logical storage area network (LSAN) defined in the edge fabric is greater than allowed by the local LSAN zone database limitations.
<b>Recommended Action</b>	Remove excess device entries from this LSAN zone until the number of devices is within the range of the local LSAN zone database limitations.

**FCR-1025**

<b>Message</b>	Local phantom node WWN entries exhausted.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of node World Wide Names (WWNs) detected to be in use exceeds the local node WWN resources.
<b>Recommended Action</b>	Reduce the number of node WWNs required by limiting the remote edge fabric connectivity (which limits the number of translate domains).

**FCR-1026**

<b>Message</b>	In slot <slot number>, Node WWN roll over.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the node World Wide Name (WWN) pool has rolled over in the specified slot, and WWN entries not detected to be in use are reused as needed.
<b>Recommended Action</b>	It is unlikely that WWN conflicts will occur as a result of pool rollover unless the switch is deployed in a very large MetaSAN environment with a large number of logical storage area network (LSAN) devices and fabrics, or there are highly dynamic changes to EX_Port connectivity. WWN conflicts might cause unpredictable behavior in management applications. To avoid WWN conflicts, all EX_Ports attached to fabrics with highly dynamic changes to EX_Port connectivity should be disabled and then re-enabled.

## FCR-1027

<b>Message</b>	In slot <slot number>, Port WWN roll over.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the port World Wide Name (WWN) pool has rolled over in the specified slot, and WWN entries not detected to be in use are reused as needed.
<b>Recommended Action</b>	It is unlikely that WWN conflicts will occur as a result of pool rollover unless the switch is deployed in a very large MetaSAN environment with a large number of logical storage area network (LSAN) devices and fabrics, or there are highly dynamic changes to EX_Port connectivity. WWN conflicts might cause unpredictable behavior in management applications. To avoid WWN conflicts, all EX_Ports attached to fabrics with highly dynamic changes to EX_Port or VEX_Port connectivity should be disabled and then re-enabled.

## FCR-1028

<b>Message</b>	In slot <slot number>, node WWN pool 95 percent allocated.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the node World Wide Name (WWN) pool is close to rollover in the specified slot, and that the WWN entries not detected to be in use will be reused as needed.
<b>Recommended Action</b>	It is unlikely that WWN conflicts will occur as a result of pool rollover unless the switch is deployed in a very large MetaSAN environment with a large number of logical storage area network (LSAN) devices and fabrics, or there are highly dynamic changes to EX_Port or VEX_Port connectivity. WWN conflicts might cause unpredictable behavior in management applications. To avoid WWN conflicts, all EX_Ports attached to fabrics with highly dynamic changes to EX_Port connectivity should be disabled and then re-enabled.

## FCR-1029

<b>Message</b>	In slot <slot number>, Port WWN pool 95 percent allocated.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the port World Wide Name (WWN) pool has rolled over in the specified slot, and WWN entries not detected to be in use are reused as needed.
<b>Recommended Action</b>	It is unlikely that WWN conflicts will occur as a result of pool rollover unless the switch is deployed in a very large MetaSAN environment with a large number of logical storage area network (LSAN) devices and fabrics, or there are highly dynamic changes to EX_Port connectivity. WWN conflicts might cause unpredictable behavior in management applications. To avoid WWN conflicts, all EX_Ports attached to fabrics with highly dynamic changes to EX_Port connectivity should be disabled and then re-enabled.

## FCR-1030

<b>Message</b>	Physical device <device WWN> came online at fabric <fabric ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the physical device World Wide Name (WWN) came online in the specified fabric.
<b>Recommended Action</b>	No action is required.

## FCR-1031

<b>Message</b>	Physical device <device WWN> went offline in fabric <fabric ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the physical device World Wide Name (WWN) went offline in the specified fabric.
<b>Recommended Action</b>	No action is required.

## FCR-1032

<b>Message</b>	Edge fabric enabled security on port <port number> in fabric <fabric ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that Secure mode was turned on in the edge fabric.
<b>Recommended Action</b>	No action is required.

## FCR-1033

<b>Message</b>	Edge fabric disabled security on port <port number> in fabric <fabric ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that Secure mode was turned off in the edge fabric.

**Recommended Action** No action is required.

## FCR-1034

**Message** LSAN zone added in backbone fabric.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that a new logical storage area network (LSAN) zone was added to the backbone fabric.

**Recommended Action** No action is required.

## FCR-1035

**Message** LSAN zone device added in the backbone fabric.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that a new device to a logical storage area network (LSAN) zone was added to the backbone fabric.

**Recommended Action** No action is required.

## FCR-1036

**Message** LSAN zone <zone name> enabled in the backbone fabric.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified logical storage area network (LSAN) zone was enabled in the backbone fabric. The enabled LSAN zone configuration is listed.

**Recommended Action** No action is required.

## FCR-1037

<b>Message</b>	LSAN zone disabled in the backbone fabric.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a logical storage area network (LSAN) zone is disabled in the backbone fabric.
<b>Recommended Action</b>	No action is required.

## FCR-1038

<b>Message</b>	Total zone entries exceeded local fabric limits by <overflow> entries, in zone: <zone name>, zone limit: <LSAN zone limit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of cfg, zone, or alias entries created in a local fabric is greater than the local switch's zone database limitations.
<b>Recommended Action</b>	Remove excess cfg, zone, or alias entries so that the number of logical storage area network (LSAN) zones created is within the range of the local database limitations.

## FCR-1039

<b>Message</b>	Local LSAN zone <zone name> device entries for backbone LSAN exhausted.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of devices in the specified logical storage area network (LSAN) defined in the backbone fabric is greater than allowed by the local LSAN zone database limitations.
<b>Recommended Action</b>	Remove excess device entries from this LSAN zone until the number of devices is within the range of the local LSAN zone database limitations.

## FCR-1040

<b>Message</b>	Proxy device deleted in the backbone fabric.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a proxy device created in the backbone fabric was deleted.
<b>Recommended Action</b>	No action is required.

## FCR-1041

<b>Message</b>	LSAN zone device removed in the backbone fabric.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a logical storage area network (LSAN) zone device within the backbone fabric was removed.
<b>Recommended Action</b>	No action is required.

## FCR-1042

<b>Message</b>	LSAN zone removed in the backbone fabric.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a logical storage area network (LSAN) zone within the backbone fabric was removed.
<b>Recommended Action</b>	No action is required.

## FCR-1043

<b>Message</b>	Proxy device created in the backbone fabric.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a proxy device was created in the backbone fabric.

## 5 FCR-1048

**Recommended Action** No action is required.

### FCR-1048

**Message** On EX port (<port number>) setting port <credit type> credits failed.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the indicated credit type was not set. Setting port credits failed.

**Recommended Action** Execute the **portEnable** command.  
If the problem persists, reboot the switch.  
If the message persists, collect switch information using the **supportSave** command, and contact your switch service provider.

### FCR-1049

**Message** EX\_Port (<port number>) received an ELP command that is not supported.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates an incoming exchange link parameter (ELP) command that is not supported.

**Recommended Action** Use the **portEnable** and **portDisable** to enable or disable the port.  
If the problem persists, contact your switch service provider.

### FCR-1053

**Message** Port <port number> was disabled, <disable reason>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the specified port was disabled because of a mismatched configuration parameter.

**Recommended Action** Use the specified disable reason to identify a possible configuration parameter mismatch between the EX\_Port and the switch at the other end of the link.



## FCR-1054

<b>Message</b>	Port <port number> received ILS <command> of incorrect size (<actual payload size>); valid ILS size is <expected payload size>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an internal link service (ILS) IU of invalid size was received from the switch on the other end of the link.
<b>Recommended Action</b>	<p>Check the error message log on the other switch using the <b>errShow</b> command for additional messages.</p> <p>Check for a faulty cable or deteriorated small form-factor pluggable (SFP). Replace the cable or the SFP if necessary.</p> <p>Run the <b>portLogDumpPort</b> command on both the receiving and transmitting ports.</p> <p>Run the <b>fabStatsShow</b> command on the transmitting switch.</p> <p>If the message persists, collect switch information using the <b>supportSave</b> command, and contact your switch service provider.</p>

## FCR-1055

<b>Message</b>	Switch with domain ID <domain ID> does not support backbone to edge imports.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a switch that does not support backbone-to-edge routing was detected in the backbone. Edge-to-edge routing will work, but backbone-to-edge routing may fail.
<b>Recommended Action</b>	No action is required if backbone-to-edge routing is not required. Otherwise, replace the switch with one that supports backbone-to-edge routing.

## FCR-1056

<b>Message</b>	Switch <switch WWN> with front domain ID <domain ID> does not support backbone to edge imports.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a switch that does not support backbone-to-edge routing is running in the MetaSAN.
<b>Recommended Action</b>	No action is required if backbone-to-edge routing is not needed. Otherwise, replace the switch with one that supports backbone-to-edge routing.

## FCR-1057

<b>Message</b>	EX_Port(<port number>) incompatible long distance parameters on link.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the port, which is configured in long distance mode, has incompatible long distance parameters.
<b>Recommended Action</b>	Check the port configuration on both sides of the link using the <b>portCfgShow</b> command. Investigate the other switch for more details. Run the <b>errShow</b> command on the other switch to view the error log for additional messages.

## FCR-1058

<b>Message</b>	Port <port number> isolated due to mismatched configuration parameter; <segmentation reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified port was isolated after segmentation caused by mismatched configuration parameters or by a domain ID assigned by the principal switch that did not match the insistent domain ID of this port.
<b>Recommended Action</b>	Check the switches on both ends of the link for a possible mismatch in switch or port configuration parameters such as Operating Mode, E_D_TOV, R_A_TOV, Domain ID Offset, and so on. Run the <b>portCfgExport</b> command to modify the appropriate parameters on the local switch. Run the appropriate configuration command to modify the switch or port parameters on the remote switch.

## FCR-1059

<b>Message</b>	EX_Port <port number> was disabled due to an authentication failure.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the authentication, which uses the Diffie Hellman - Challenge Handshake Authentication Protocol (DH-CHAP), failed on the EX_Port.
<b>Recommended Action</b>	Verify that the shared secrets on both sides of the link match. Disable and enable the ports by using the <b>portDisable</b> and the <b>portEnable</b> commands to restart authentication.

## FCR-1060

<b>Message</b>	EX_Port(<port number>) has an incompatible configuration setting.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that virtual channel (VC) Link Init is enabled on the local switch and the remote switch is negotiating in R_RDY mode. The fabric might not form properly.
<b>Recommended Action</b>	<p>Check the configuration on the local switch using the <b>portCfgShow</b> command to verify that the VC Link Init is disabled, if the remote switch is configured in R_RDY mode or only capable of R_RDY mode.</p> <ul style="list-style-type: none"> <li>• VC_RDY mode: Virtual channel flow control mode. This is a proprietary protocol.</li> <li>• R_RDY mode: Receiver-ready flow control mode. This is the Fibre Channel standard protocol, that uses R_RDY primitive for flow control.</li> </ul>

## FCR-1061

<b>Message</b>	Backbone fabric created on port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a backbone fabric was built on the specified port.
<b>Recommended Action</b>	No action is required.

## FCR-1062

<b>Message</b>	Port <port number> disabled, system only supports <maximum ports> EX/VEX_ports.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the maximum number of supported EX_Ports or VEX_Ports was exceeded. To enable the specified port, disable any other operational port and then re-enable the port.
<b>Recommended Action</b>	No action is required.

**FCR-1063**

<b>Message</b>	Fabric <fabric ID> for switch with domain ID: <domain ID> mismatch with local fabric ID <local fabric ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the fabric ID of the switch does not match the local switch.
<b>Recommended Action</b>	Run the <b>switchShow</b> command to display the fabric ID. Change the fabric ID to match on both ends by modifying either the local or remote host using the <b>fcrConfigure</b> command.

**FCR-1064**

<b>Message</b>	Fabric ID of backbone FC-Routers mismatch or overlap.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that either a backbone fabric split and both are connected to a common edge fabric, or the fabric ID of two backbone fabrics connected to an edge fabric are the same.
<b>Recommended Action</b>	If the backbone fabric split, merge the fabrics. If two (or more) backbone fabrics have the same IDs, make the fabric IDs unique using the <b>fcrConfigure</b> command.

**FCR-1065**

<b>Message</b>	Fabric on port <port number> was assigned two different fabric IDs.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that another port on the switch is connected to the same edge fabric with a different fabric ID assignment.
<b>Recommended Action</b>	Change the port fabric ID to the same value as the other ports connected to the edge fabric using the <b>portCfgExport</b> or <b>portCfgVexport</b> commands.

## FCR-1066

<b>Message</b>	Fabric on port <port number> has the same fabric ID as another fabric.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that either the fabric split, or there is another fabric (possibly the backbone) that has the same fabric ID as the fabric connected to the specified port.
<b>Recommended Action</b>	If the fabric split, merge the fabrics and manually re-enable the port. If there is another fabric with the same ID, change the fabric ID for the port using the <b>portCfgExport</b> or <b>portcfgVExport</b> commands.

## FCR-1067

<b>Message</b>	Zone configurations, total LSAN zones and aliases, exceeded on port <port number> by <overflow> entries; max entries: <LSAN zone limit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the total number of zone configurations created in connected fabric exceeds the maximum number supported by the Fibre Channel.  The limit includes both active and configured information that is part of the zoning database in the edge fabric. Non-LSAN zones are not counted in the limit.
<b>Recommended Action</b>	Limit the logical storage area network (LSAN) zoning-related zone configuration in the edge fabric connected to this port.

## FCR-1068

<b>Message</b>	The FC Routing service is disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the FC Routing service is disabled. This is caused by issuing the <b>fosConfig --disable fcr</b> , <b>configDefault</b> , or the <b>configDownload</b> command with the <b>fcrState</b> set to 2 (disabled). Note that the FC Routing service is disabled by the factory.
<b>Recommended Action</b>	No action is required.

**FCR-1069**

<b>Message</b>	The FC Routing service is enabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the FC Routing service is enabled. This is caused by the <b>fosConfig --enable fcr</b> or the <b>configDownload</b> command with the <b>fcrState</b> set to 1 (enabled). Note that the FC Routing service is disabled by the factory.
<b>Recommended Action</b>	No action is required.

**FCR-1070**

<b>Message</b>	The FC Routing configuration is set to default.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the FC Routing configuration is set to the default by the user. This removes all prior FC Routing configurations.
<b>Recommended Action</b>	No action is required.

**FCR-1071**

<b>Message</b>	Port <port number> is changed from non FCR port to FCR port.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the port became an EX_Port or VEX_Port.
<b>Recommended Action</b>	No action is required.

## FCR-1072

<b>Message</b>	Port <port number> is changed from FCR port to non FCR port.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the port is no longer an EX_Port or VEX_Port.
<b>Recommended Action</b>	No action is required.

## FCR-1073

<b>Message</b>	Switch with domain ID <domain ID> in fabric <fabric ID> has lower limit of LSAN Zones supported.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that an older version switch in the backbone or edge that supports a different limit of logical storage area network (LSAN) zones was detected.
<b>Recommended Action</b>	Use the <b>fcrResourceShow</b> command on all Fibre Channel Routers in the Meta-SAN to find lowest supported LSAN zone limits. Ensure the total number of LSAN zones in the Meta-SAN are within the lowest supported limit of LSAN zones.

## FCR-1074

<b>Message</b>	HA sync lost as remote CP supports only <LSAN Count> LSAN Zones.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the remote control processor (CP) has older firmware, which supports a lower number of logical storage area network (LSAN) zones. This is causing the loss of high availability (HA) sync.
<b>Recommended Action</b>	Keep the number of LSAN zones to the lower limit of the two CPs or upgrade the remote CP.

**FCR-1075**

<b>Message</b>	Zone Name configuration is larger than <Zone Name Limit> characters in the edge fabric connected to port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the zone name configuration size created in the connected fabric exceeds the maximum supported by the FC Router. This size is equal to the total number of characters used by all the zone names in the edge fabric zoning database.  The limit includes both LSAN and non-LSAN zone names defined in the zoning name database of the edge fabric.
<b>Recommended Action</b>	Limit the zone configuration size in the edge fabric connected to this port by either reducing the number of zones or changing the zone names to smaller names.

**FCR-1076**

<b>Message</b>	Port <port number> disabled, system only supports <maximum fds> front domains.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the maximum number of supported front domains was exceeded. To enable the specified port, disable any other operational front domain and then re-enable the port.
<b>Recommended Action</b>	Make sure to remain within the maximum number of supported front domains.

**FCR-1077**

<b>Message</b>	Port <port number> rejected fabric binding request/check from the M-Model switch; <Fabric ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an M-Model edge switch attempted to either activate or check the fabric binding. This port will be disabled if this event occurred during a check of fabric binding and not during failure to activate fabric binding. The error is caused when the binding list details configured on the M-Model switch do not match with the currently configured front port domain ID and WWN of the EX_Port on which this operation was attempted.
<b>Recommended Action</b>	Ensure that the M-Model switch has the same currently configured details such as the front port domain ID and WWN of the EX_Port on which this operation was attempted.



## FCR-1078

<b>Message</b>	LSAN name <LSAN name> is too long. It is dropped.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the length of the logical storage area network (LSAN) name exceeds the limit of 64 characters.
<b>Recommended Action</b>	Change the name and reactivate the zone database.

## FCR-1079

<b>Message</b>	Domain <Domain> has conflict matrix database with local domain.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the specified domain has a different matrix database from the local domain.
<b>Recommended Action</b>	Change the matrix database.

## FCR-1080

<b>Message</b>	The pause response timer for domain <Domain> expired.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that during the Coordinated HotCode protocol, a switch in the fabric has not responded to the pause message which prevented the protocol from completing. Any data traffic disruption observed during the firmware download may have been the result of the rejected pause message.
<b>Recommended Action</b>	No action is required.

## FCR-1081

<b>Message</b>	The pause message is rejected by the domain <Domain>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that during the Coordinated HotCode protocol, a switch in the fabric has rejected the pause message which prevented the protocol from completing. Any data traffic disruption observed during the firmware download may have been the result of the rejected pause message.
<b>Recommended Action</b>	No action is required.

## FCR-1082

<b>Message</b>	The pause retry count is exhausted for the domain <Domain>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that during the Coordinated HotCode protocol, a switch in the fabric did not accept the pause message which prevented the protocol from completing. Any data traffic disruption observed during the firmware download may have been the result of this issue.
<b>Recommended Action</b>	No action is required.

## FCR-1083

<b>Message</b>	The resume message is rejected by the domain <Domain>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that during the Coordinated HotCode protocol, a switch in the fabric has rejected the pause message which prevented the protocol from completing. Any data traffic disruption observed during the firmware download may have been the result of the rejected resume message.
<b>Recommended Action</b>	No action is required.

## FCR-1084

<b>Message</b>	The resume retry count is exhausted for the domain <Domain>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that during the Coordinated HotCode protocol, a switch in the fabric did not accept the resume message which prevented the protocol from completing. Any data traffic disruption observed during the firmware download may have been the result of this issue.
<b>Recommended Action</b>	No action is required.

## FCR-1085

<b>Message</b>	HA sync lost as remote CP does not support FCR based matrix.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the remote control processor (CP) has older firmware, which does not support the FCR-based matrix while the local CP has the feature enabled. This is causing the loss of the high availability (HA) synchronization.
<b>Recommended Action</b>	Disable the FCR-based matrix or upgrade the remote CP.

## FCR-1086

<b>Message</b>	HA sync lost as remote CP does not support 8 Gbps-capable FC based EX_Ports.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the remote control processor (CP) has older firmware, which does not support 8 Gbps-capable FC based EX_Port. This is causing the loss of the high availability (HA) synchronization.
<b>Recommended Action</b>	Disable 8 Gbps-capable FC based EX_Ports or upgrade the remote CP.

## FCR-1087

<b>Message</b>	ExPort <ExPort > connects to fabric <fabric > with capability to use XISL domain <Domain >.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the EX_Port connects to the logical fabric containing a domain that has the capability to use extended ISL (XISL).
<b>Recommended Action</b>	Disable "Allow to use XISL" mode of the domain by using the <b>configure</b> command.

## FCR-1088

<b>Message</b>	LSAN <Enforce/Speed> tag <Tag Name> added.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the user has added a LSAN tag.
<b>Recommended Action</b>	No action is required.

## FCR-1089

<b>Message</b>	LSAN <Enforce/Speed> tag <Tag Name> removed.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the user has removed a LSAN tag.
<b>Recommended Action</b>	No action is required.

## FCR-1091

<b>Message</b>	Backbone Fabric ID changed to <Tag>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the backbone fabric ID has been changed.
<b>Recommended Action</b>	No action is required.

## FCR-1092

<b>Message</b>	FCR ELS trap entries exhausted.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the FCR ELS trap entries are exhausted.
<b>Recommended Action</b>	Execute the <b>supportSave</b> command and contact your switch service provider.

## FCR-1093

<b>Message</b>	Slave EX-Port <Slave> interopmode conflicts with trunk master <Master>. Disabling the port.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the slave EX_Port is disabled due to interop conflict with trunk master
<b>Recommended Action</b>	Configure the slave EX_Port with the trunk master interop mode.

## FCR-1094

<b>Message</b>	No Integrated Routing license present. EX-Port <ExPort> will not perform device sharing with other Brocade Native mode fabric(s).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an EX_Port has been configured in Brocade Native mode. Device sharing will not occur with other Brocade Native mode fabrics because the Integrated Routing license is not installed.
<b>Recommended Action</b>	Install Integrated Routing license if device sharing is needed with other Brocade Native mode fabrics.

## FCR-1095

<b>Message</b>	The EX-Port <ExPort> is configured in 'McData/Open' Mode which is no longer supported, hence will be disabled next time port is offline and online.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an EX_Port has been configured in 'McData/Open' mode. Initially after HA failover, the EX_Port will come up in McDATA mode. Further toggling will disable the port.
<b>Recommended Action</b>	Remove the 'McData/Open' interop modes in all EX_Ports

## FCR-1096

<b>Message</b>	Failed to allocate <data type> for <operation phase>: port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the authentication process failed because the system is low on memory. <i>Data type</i> is the payload or structure that failed to get memory. <i>Operation phase</i> specifies which operation of a particular authentication phase failed.
<b>Recommended Action</b>	Usually this problem is transient. The authentication may fail. Reinitialize authentication using the <b>portDisable</b> and <b>portEnable</b> commands or the <b>switchDisable</b> and <b>switchEnable</b> commands. If the message persists, run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

## FCR-1097

<b>Message</b>	Failed to get <data type> for <message phase> message: port <port number>, retval <error code>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the authentication process failed to get a particular authentication value at certain phase. <i>Data type</i> is the payload or structure that failed to get memory.
<b>Recommended Action</b>	Usually this problem is transient. The authentication may fail. Reinitialize authentication using the <b>portDisable</b> and <b>portEnable</b> commands or the <b>switchDisable</b> and <b>switchEnable</b> commands.  If the message persists, run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

## FCR-1098

<b>Message</b>	Invalid message code for <message phase> message: port <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the receiving payload does not have valid message code for a particular authentication phase.
<b>Recommended Action</b>	Usually this problem is transient. The authentication may fail. Reinitialize authentication using the <b>portDisable</b> and <b>portEnable</b> commands or the <b>switchDisable</b> and <b>switchEnable</b> commands.  If the message persists, run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

## FICN Messages

### FICN-1003

<b>Message</b>	FICON Tape Emulation License Key is not installed.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates FICON Tape Emulation requires a License Key.
<b>Recommended Action</b>	Use the appropriate License Key.

### FICN-1004

<b>Message</b>	FICON XRC Emulation License Key is not installed.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates FICON eXtended Remote Copy (XRC) Emulation requires a License Key.
<b>Recommended Action</b>	Use the appropriate License Key.

### FICN-1005

<b>Message</b>	FICON GEPort <GE port number> TID <Tunnel number> Feature Change verified Xrc <1 or 0 - XRC Emulation Enabled or Disabled> TapeWrt <1 or 0 - Tape Write Emulation Enabled or Disabled> TapeRd <1 or 0 - FICON Tape Read Emulation Enabled or Disabled> TinTir <1 or 0 - FICON TIN/TIR Emulation Enabled or Disabled> DvcAck <1 or 0 - FICON Device Level Ack Emulation Enabled or Disabled> RdBlkId <1 or 0 - FICON Write Emulation Read Block ID Emulation Enabled or Disabled>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the configuration was changed manually.
<b>Recommended Action</b>	No action is required.



**FICN-1006**

<b>Message</b>	FICON GEPort <GE port number> TID <Tunnel number> Feature Change failed Xrc <1 or 0 - XRC Emulation Enabled or Disabled> TapeWrt <1 or 0 - Tape Write Emulation Enabled or Disabled> TapeRd <1 or 0 - FICON Tape Read Emulation Enabled or Disabled> TinTir <1 or 0 - FICON TIN/TIR Emulation Enabled or Disabled> DvcAck <1 or 0 - FICON Device Level Ack Emulation Enabled or Disabled> RdBlkId <1 or 0 - FICON Write Emulation Read Block ID Emulation Enabled or Disabled>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the feature change has failed because the FCIP tunnel ID associated with the FICON tunnel is still active.
<b>Recommended Action</b>	Disable the applicable FCIP tunnel to make the feature change effective.

**FICN-1007**

<b>Message</b>	DevDiskEgr:FICON Selective Reset:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> State=0x<Current Emulation State> stat_array=0x<the Last 4 Status values that were received from the device>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a Selective Reset from the channel was received as either a normal part of path recovery or the starting sequence in an error case.
<b>Recommended Action</b>	If there was a job failure associated with this event, contact your vendor's customer support.

**FICN-1008**

<b>Message</b>	DevDiskEgr:FICON Purge Path received Path=0x<VEPortNumber HostDomain HostPort DeviceDomcontactain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a FICON Purge Path was received from the channel as a part of path recovery.
<b>Recommended Action</b>	If there was a job failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1009**

<b>Message</b>	DevIng:CmdReject Sense Data rcvd:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> LastCmds=0x<the Last 4 commands issued to the device> Sense Data:Bytes0-0xB=0x<bytes 0-3 of sense data from the device><bytes 4-7 of sense data from the device><bytes 8-0x0b of sense data from the device>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a Unit Check status was received from a device and a sense command was issued to read the sense data.
<b>Recommended Action</b>	If there was a job failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1010**

<b>Message</b>	DevDiskEgr:Device level exception flag found for Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>: Oxid=0x<The OXID that was reported in the Device Level Exception Frame>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a Device Level Exception frame was received from the FICON channel.
<b>Recommended Action</b>	If there was a job or I/O failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1011**

<b>Message</b>	DevDiskIng:XRC Incorrect RRS SeqNum Rcvd Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> Expected=0x<The RRS Sequence number that was expected from the device> Received=0x<The RRS Sequence number that was actually received from the device> Oxid=0x<The data frame's OXID>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the Control unit or device presented a Read Record Set Sequence number different from the SDM's expected sequence number.
<b>Recommended Action</b>	If there was an XRC volume or session suspended associated with this event, contact your vendor's customer support for assistance.

**FICN-1012**

<b>Message</b>	DevDiskIng:Device level exception found for Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>: Oxid=0x<The OXID that was reported in the Device Level Exception Frame>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a Device Level Exception frame received from the FICON direct attached storage device (DASD) Control Unit.
<b>Recommended Action</b>	If there was a job or I/O failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1013**

<b>Message</b>	DevDiskIng:Status=0x<Status that was received from the DASD device in an odd state> received in odd state=0x<The current emulation state> from Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> sent LBY.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that when the device sent the status in an incorrect state, the emulation processing rejected the status with an LBY frame.
<b>Recommended Action</b>	If there was a job or I/O failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1014**

<b>Message</b>	DevEgr:Device level exception flag found for Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>: Oxid=0x<The OXID used to deliver the non-AS Device Level Exception>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a frame was received that indicated a device level exception.
<b>Recommended Action</b>	If there was an I/O failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1015**

**Message** DevEgr:cuPath=0x<VEPortNumber HostDomain HostPort DeviceDomain>\*\*\*\*\*:Discarding Invalid LRCd SOF=0x<The invalid Frame's SOF value (SOFix or SOFnx)> count=<The total number of frames that have been received from the peer with incorrect FICON LRC values>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates a frame was received from the peer emulation processing with an invalid Longitudinal Redundancy Checking (LRC) values. This indicates data corruption between the emulation processing components.

**Recommended Action** Contact your vendor's customer support for assistance.

**FICN-1016**

**Message** DevIng:Received Logical Path Removed response:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR><CUADDR>\*\*.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates the FICON Control Unit sent a Logical Path Removed (LPR) frame to the FICON channel.

**Recommended Action** No action is required.

**FICN-1017**

**Message** DevIng:Received Logical Path Established response:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR><CUADDR>\*\*.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates the FICON Control Unit sent an Logical Path Established (LPE) frame to the FICON channel.

**Recommended Action** No action is required.

**FICN-1018**

<b>Message</b>	DevIng:FCUB Lookup failed for Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR>*****.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the FICON Control Unit sent a frame that cannot be associated with a FICON Control Unit number (CUADDR).
<b>Recommended Action</b>	Contact your vendor's customer support for assistance.

**FICN-1019**

<b>Message</b>	DevTapeEgr:AS Link Level Reject (LRJ) from Chan on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> LastCmd=0x<the Last 4 commands issued to the device> LastStatus=0x<the Last 4 status values received from the device>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the FICON channel indicated in the path issued a Link Level Reject (LRJ) frame for a sequence from the device.
<b>Recommended Action</b>	If there was a job failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1020**

<b>Message</b>	DevTapeEgr:FICON Cancel received Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> state=0x<the current emulation state for the device> tflags=0x<the current emulation tape control flags for the device> sflags=0x<the current emulation status control flags for the device>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the FICON channel issued a Cancel sequence for a device in emulation.
<b>Recommended Action</b>	If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1021**

**Message** DevTapeEgr:FICON Tape Cancel:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> Elapsed Time=<the current SIO time in seconds for the device>.<the current SIO time in milliseconds for the device> seconds.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates the FICON channel issued a Cancel sequence for a device in emulation.

**Recommended Action** If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1022**

**Message** DevTapeEgr:FICON Selective Reset:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> State=0x<the current state of the device that received the selective reset> statArray=0x<the last 4 status values received from the device> cmdArray=0x<the last 4 commands that were issued to the device> tflags=0x<the current emulation tape control flags for the device> sflags=0x<the current emulation status control flags for the device>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates the FICON channel issued a Selective Reset for a device that was active in emulation.

**Recommended Action** If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1023**

**Message** DevTapeEgr:FICON Selective Reset:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> Elapsed Time=<the current SIO time in seconds for the device>.<the current SIO time in milliseconds for the device> seconds.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates the FICON channel issued a Selective Reset sequence for a device.

**Recommended Action** If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

## FICN-1024

<b>Message</b>	DevTapeEgr:FICON Purge received Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the FICON channel issued a Purge Path command sequence for a device.
<b>Recommended Action</b>	If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.

## FICN-1025

<b>Message</b>	DevTapeIng:Auto Sense Data received on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> Bytes0-0xB=0x<bytes 0-3 of sense data from the device><bytes 4-7 of sense data from the device><bytes 8-0x0b of sense data from the device>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the FICON Tape Write Pipelining processed sense data from a FICON device.
<b>Recommended Action</b>	If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.

## FICN-1026

<b>Message</b>	DevTapeIng:UnusualStatus:WriteCancelSelr:Generating Final Ending Status Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the FICON Tape Write Pipelining is completing an emulated Selective Reset sequence.
<b>Recommended Action</b>	If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.

**FICN-1027**

<b>Message</b>	DevTapeIng:Device level exception found for Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>: Oxid=0x<The OXID of the frame that included the Device Level Exception>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an active emulation device delivered a Device Level Exception frame to the emulation processing.
<b>Recommended Action</b>	If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.

**FICN-1028**

<b>Message</b>	HostDiskIng:FICON Cancel received Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> state=0x<The current emulation state of the device>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an active emulation device received a cancel operation from the FICON channel.
<b>Recommended Action</b>	If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.

**FICN-1029**

<b>Message</b>	HostDiskIng:FICON Selective Reset:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> state=0x<The current emulation state of the device> LastCmds=0x<The last 4 commands received from the channel for this device> LastStatus=0x<The last 4 status values presented to the channel for this device>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an active disk emulation device received a Selective Reset from the FICON channel.
<b>Recommended Action</b>	If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.



**FICN-1030**

<b>Message</b>	HostDiskIng:FICON Purge received:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an active disk emulation device received a FICON Purge Path from the channel.
<b>Recommended Action</b>	If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.

**FICN-1031**

<b>Message</b>	HostDiskIng:FICON System Reset received on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR><CUADDR>**.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the FICON channel sent a System Reset to the disk control unit.
<b>Recommended Action</b>	No action is required. The MVS system was either set to initial program load (IPL) or performing error recovery.

**FICN-1032**

<b>Message</b>	HostDiskIng:XRC Read Channel Extender Capabilities detected on Path: 0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the eXtended Remote Copy (XRC) System Data mover was restarted to discover the capabilities of the channel extension equipment.
<b>Recommended Action</b>	No action is required. This is a part of the XRC initialization.

## FICN-1033

<b>Message</b>	HostEgr:Logical Path Established on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR><CUADDR>**.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the peer-side FICON Control Unit has accepted a logical path establishment command sequence with the FICON channel.
<b>Recommended Action</b>	No action is required. This is a part of the FICON path initialization.

## FICN-1034

<b>Message</b>	HostEgr:Discarding Invalid LRCd Frame on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort>***** count=<The total number of frames that have been received with an invalid LRC.>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the channel emulation processing received a frame with an invalid FICON LRC from the peer. This indicates that the channel side noted corruption from the Control Unit- or device-side processing.
<b>Recommended Action</b>	Contact your vendor's customer support for assistance.

## FICN-1035

<b>Message</b>	HostIng:FICON System Reset received on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort><LPAR><CUADDR>**.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a locally connected FICON channel issued a System Reset to the specified FICON Control Unit.
<b>Recommended Action</b>	No action is required. This is a part of the FICON path initialization.

**FICN-1036**

<b>Message</b>	HostIng:FICON RLP Request on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort><LPAR><CUADDR>**. .
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a locally connected FICON channel issued a Remove Logical Path sequence to the specified FICON Control Unit.
<b>Recommended Action</b>	No action is required. This is a part of the FICON path deactivation.

**FICN-1037**

<b>Message</b>	HostIng:FICON ELP Request on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort><LPAR><CUADDR>**. .
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a locally connected FICON channel issued an Establish Logical Path sequence to the specified FICON Control Unit.
<b>Recommended Action</b>	No action is required. This is a part of the FICON path activation.

**FICN-1038**

<b>Message</b>	fcFicIngHost:FDCB Lookup failed for Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort>*****. .
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a locally connected FICON channel sent a frame that could not be associated with a FICON device.
<b>Recommended Action</b>	Contact your vendor's customer support for assistance.

**FICN-1039**

<b>Message</b>	HostIng:FCUB Lookup failed for Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR>*****.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a locally connected FICON channel sent a frame that could not be associated with a FICON Control Unit.
<b>Recommended Action</b>	Contact your vendor's customer support for assistance.

**FICN-1040**

<b>Message</b>	HostTapeEgr:Tape:CmdReject Sense Data Rcvd:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> LastCmds=0x<Last 4 commands received from the channel for this device> SenseData:Bytes0-0xB=0x<Bytes 0-3 of sense data from the device><Bytes 4-7 of sense data from the device><Bytes 8-0x0b of sense data from the device>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an active disk emulation device received a FICON Purge Path from the channel.
<b>Recommended Action</b>	If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.

**FICN-1041**

<b>Message</b>	HostTapeEgr:AS Link Level Reject (LRJ) from CU Rx Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> LastCmd=0x<Last 4 commands issued to this device from the channel> LastStatus=0x<Last 4 status values sent to the channel from this device>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a Link Level Reject (LRJ) received from a device indicates that the Control Unit has lost the logical path to the Logical Partition (LPAR).
<b>Recommended Action</b>	If this was an unexpected event, contact your vendor's customer support for assistance.

**FICN-1042**

<b>Message</b>	HostTapeIng:FICON Cancel received Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> state=0x<the current emulation state for this device>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a job was canceled during a Tape Write Pipelining.
<b>Recommended Action</b>	If this was an unexpected event (cancel is normally an operator event), contact your vendor's customer support for assistance.

**FICN-1043**

<b>Message</b>	HostTapeIng::FICON Selective Reset:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> state=0x<the current emulation state for this device> LastCmds=0x<the last 4 commands received from the channel for this device> LastStatus=0x<the last 4 status values presented to the channel for this device>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that protocol errors in emulation in the Control Unit or network errors can cause a Selective Reset.
<b>Recommended Action</b>	If this was an unexpected event, contact your vendor's customer support for assistance.

**FICN-1044**

<b>Message</b>	HostTapeIng:FICON Selective Reset:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> Elapsed Time=<the number of seconds since the last IO started for this device>.<the number of milliseconds since the last IO started for this device> seconds.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that protocol errors in emulation in the Control Unit or network errors can cause a Selective Reset.
<b>Recommended Action</b>	If this was an unexpected event, contact your vendor's customer support for assistance.

**FICN-1045**

<b>Message</b>	HostTapeIng:FICON Purge received:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a Purge Path was received from the locally connected FICON channel. This is performed during the path recovery.
<b>Recommended Action</b>	If this was an unexpected event, contact your vendor's customer support for assistance.

**FICN-1046**

<b>Message</b>	HostTapeIng:LRJ received on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> lastCmds=0x<Last 4 commands received from the channel for this device> lastStatus=0x<Last 4 status values presented to the channel for this device> treating as system reset event.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a Link Level Reject (LRJ) from a FICON channel indicates that the channel no longer has a path established to the Control Unit.
<b>Recommended Action</b>	This is normally an unexpected event; contact your vendor's customer support for assistance.

**FICN-1047**

<b>Message</b>	fcFicSetEmulation:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> FDCB Not Idle state=0x<Current emulation state of the FICON device> prevState=0x<Previous emulation state of the FICON device> set to state=0x<The new state to which the device is transitioning>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates there is an internal emulation error. This message should not be encountered.
<b>Recommended Action</b>	This is an unexpected event; contact your vendor's customer support for assistance.

**FICN-1048**

<b>Message</b>	DevDiskEgr:FICON Cancel received Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> state=0x<Current emulation state of the FICON device> sflags=0x<The current emulation status flags>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the operator has canceled a read or write job.
<b>Recommended Action</b>	This is an unexpected event; contact your vendor's customer support for assistance.

**FICN-1049**

<b>Message</b>	ProcessIngTirData:Lost Logical Path for Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr><CUADDR>** Index=<Current processing index in the TIR data from the locally connected channel or control unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a TIR received from a FICON endpoint indicates that it no longer has an established path to its peer.
<b>Recommended Action</b>	This is an unexpected event; contact your vendor's customer support for assistance.

**FICN-1050**

<b>Message</b>	ProcessEgrTirData:Lost Logical Path for Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr><CUADDR>** Index=<Current processing index in the TIR data from the remotely connected channel or control unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a TIR received from a far-side FICON endpoint indicates that it no longer has an established path to its peer.
<b>Recommended Action</b>	This is an unexpected event; contact your vendor's customer support for assistance.

## FICN-1051

<b>Message</b>	XRC Session Established: SessID=<SDM Assigned Session ID>, Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a PSF command has been received to initiate an eXtended Remote Copy (XRC) session with the extended direct attached storage device (DASD) device.
<b>Recommended Action</b>	No action is required. This is a part of the XRC session establishment.

## FICN-1052

<b>Message</b>	XRC Session Terminated: SessID=<SDM Assigned Session ID>, Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a PSF command has been received to break an eXtended Remote Copy (XRC) session with the extended direct attached storage device (DASD) device.
<b>Recommended Action</b>	If this was an unexpected event, contact your vendor's customer support for assistance.

## FICN-1053

<b>Message</b>	XRC Withdraw From Session: SessID=<SDM Assigned Session ID>, Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a PSF command has been received to withdraw from the eXtended Remote Copy (XRC) session with the extended direct attached storage device (DASD) device.
<b>Recommended Action</b>	If this was an unexpected event, contact your vendor's customer support for assistance.



**FICN-1054**

<b>Message</b>	XRC Device Suspended: SessID=<SDM Assigned Session ID>, Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a PSF command has been received to suspend an eXtended Remote Copy (XRC) session with the extended direct attached storage device (DASD) device.
<b>Recommended Action</b>	If this was an unexpected event, contact your vendor's customer support for assistance.

**FICN-1055**

<b>Message</b>	XRC All Devices Suspended: SessID=<SDM Assigned Session ID>, Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a PSF command has been received to suspend all extended direct attached storage device (DASD) devices from the eXtended Remote Copy (XRC) session.
<b>Recommended Action</b>	If this was an unexpected event, contact your vendor's customer support for assistance.

**FICN-1056**

<b>Message</b>	FICON Emulation Error Error Code=<The internal emulation error code value>, Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> LastStates=0x<The 4 oldest emulation states for this device><The prior emulation state for this device><The current emulation state for this device>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal coding error within emulation processing.
<b>Recommended Action</b>	This is an unexpected event; contact your vendor's customer support for assistance.

## FICN-1057

<b>Message</b>	Error return from frame generation processing for a FICON device: Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal resource shortage caused an error so that an emulation frame could not be created and sent to a device.
<b>Recommended Action</b>	This is an unexpected event; contact your vendor's customer support for assistance.

## FICN-1058

<b>Message</b>	Error return from frame generation processing for a FICON control unit: Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort><LPAR><CUADDR>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal resource shortage caused an error so that an emulation frame could not be created and sent to a Control Unit.
<b>Recommended Action</b>	This is an unexpected event; contact your vendor's customer support for assistance.

## FICN-1059

<b>Message</b>	Error return from frame generation for a FICON Image: Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort><LPAR>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal resource shortage caused an error so that an emulation frame could not be created and sent to an Logical Partition (LPAR).
<b>Recommended Action</b>	This is an unexpected event; contact your vendor's customer support for assistance.

**FICN-1060**

<b>Message</b>	Error return from fcFwdPrcegressFrame: Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal resource shortage caused an error so that an emulation frame could not be created and sent to a device.
<b>Recommended Action</b>	This is an unexpected event; contact your vendor's customer support for assistance.

**FICN-1061**

<b>Message</b>	Error return from fcFwdRemoveEmulHashEntry: Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal issue has been encountered in the removal of an existing fast path hash table entry.
<b>Recommended Action</b>	This is an unexpected event; contact your vendor's customer support for assistance.

**FICN-1062**

<b>Message</b>	Ingress Abort:Oxid=0x<the OXID of the aborted exchange>;Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>;LastStates=0x<prior emulation state array><previous emulation state><current emulation state>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an abort operation has been received from the local FC interface for an active emulation exchange.
<b>Recommended Action</b>	This is an unexpected event; contact your vendor's customer support for assistance.

**FICN-1063**

<b>Message</b>	Egress Abort:Oxid=0x<the OXID of the aborted exchange>:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>:LastStates=0x<prior emulation state array><previous emulation state><current emulation state>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an abort operation has been received from a peer FC interface for an active emulation exchange.
<b>Recommended Action</b>	This is an unexpected event; contact your vendor's customer support for assistance.

**FICN-1064**

<b>Message</b>	Ingress Abort:Oxid=0x<the OXID of the aborted exchange>:Unknown Path on GEPort=<GEPortNumber> VEPort=<VEPortNumber> from SID=0x<Source Domain><Source Port> to DID=0x<Destination Domain><Destination Port>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an abort operation has been received from a local FC interface for an exchange.
<b>Recommended Action</b>	If there were associated I/O errors at the same time as this event, contact your vendor's customer support for assistance.

**FICN-1065**

<b>Message</b>	Egress Abort:Oxid=0x<the OXID of the aborted exchange>:Unknown Path on GEPort=<GEPortNumber> VEPort=<VEPortNumber> from SID=0x<Source Domain ><Source Port> to DID=0x<Destination Domain><Destination Port>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an abort operation has been received from a peer FC interface for an exchange.
<b>Recommended Action</b>	If there were associated I/O errors at the same time as this event, contact your vendor's customer support for assistance.

**FICN-1066**

<b>Message</b>	MemAllocFailed for GEPort=<VEPortNumber> VEport=<GE0 or GE1 number> could not create required structure.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an internal resource limit has been encountered so that additional control block memory could not be allocated.
<b>Recommended Action</b>	This is an unexpected event; either the maximum number of emulation devices are already in use or there is an internal memory leak. Contact your vendor's customer support for assistance.

**FICN-1067**

<b>Message</b>	Ingress Abort:Oxid=0x<the OXID of the aborted exchange>:Abort for CH=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR>****.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an abort operation has been received from a local FC interface for an emulation CH exchange.
<b>Recommended Action</b>	If there were associated I/O errors at the same time as this event, contact your vendor's customer support for assistance.

**FICN-1068**

<b>Message</b>	Ingress Abort:Oxid=0x<the OXID of the aborted exchange>:Abort for CU=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR><CUADDR>**.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an abort operation has been received from a local FC interface for an emulation Control Unit exchange.
<b>Recommended Action</b>	If there were associated I/O errors at the same time as this event, contact your vendor's customer support for assistance.

**FICN-1069**

<b>Message</b>	Emulation Configuration Error on TunnelId <Tunnel ID>:.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an error has been noted in the FICON configuration. Refer to the string for the nature of the configuration issue.
<b>Recommended Action</b>	If resolution of the configuration issue cannot be completed, contact your vendor's customer support for assistance.

**FICN-1070**

<b>Message</b>	DevTapeIngr:Exceptional Status rcvd on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> state=0x<current emulation state> status=0x<the exceptional status value>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the normal end of tape status (0x0D or 0x05) is received from the device or error status (including Unit Check 0x02) is received from an active emulation device.
<b>Recommended Action</b>	The end of tape is a normal event during pipelining and not the unit check. If there are associated I/O error messages with this event, contact your vendor's customer support for assistance.

**FICN-1071**

<b>Message</b>	HostTapeIngr:Tape Loaded on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the tape I/Os are processed from a locally connected Logical Partition (LPAR), which indicates that a tape is loaded on a device.
<b>Recommended Action</b>	No action is required.

**FICN-1072**

<b>Message</b>	DevTapeEgr:Tape Loaded on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the tape I/Os are processed from a locally connected Logical Partition (LPAR), which indicates that a tape is loaded on a device.
<b>Recommended Action</b>	No action is required.

**FICN-1073**

<b>Message</b>	HostTapeIngr:Unloaded:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>:states=0x<4 prior emulation states><previous emulation state><current emulation state>:cmds=0x<last 4 commands received from the channel for this device>:status=0x<last 4 status values sent to the channel for this device>:flags=0x<tape report bit flags (0x80-Tape Loaded,0x40-WriteEmul,0x20-RdBlkEmul,0x10-RdCpEmul)>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a Rewind and Unload I/O has been processed from a locally connected Logical Partition (LPAR), which indicates that a tape should be unloaded on a device.
<b>Recommended Action</b>	No action is required.

**FICN-1074**

<b>Message</b>	HostTapeIngr:WriteReport:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>:Emuls=0x<the number of idle state to non-idle state transitions while this tape was loaded>:Cmds=0x<the number of emulated host write commands processed while this tape was loaded>:Chains=0x<the number of emulated host chains processed while this tape was loaded>:MBytes=<the number of emulated write Kilobytes processed while this tape was loaded>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a Rewind and Unload I/O has been processed from a locally connected Logical Partition (LPAR) and Tape Write Pipelining was performed on the currently loaded tape.

## 5 FICN-1075

**Recommended Action** No action is required.

### FICN-1075

**Message** HostTapeIngr:ReadBlkReport:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>;Emuls=0x<the number of idle state to non-idle state transitions while this tape was loaded>;Cmds=0x<the number of emulated host read commands processed while this tape was loaded>;Chains=0x<the number of emulated host chains processed while this tape was loaded>;MBytes=<the number of emulated read Kilobytes processed while this tape was loaded>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates a Rewind and Unload I/O has been processed from a locally connected Logical Partition (LPAR) and Read Block pipelining was performed on the currently loaded tape.

**Recommended Action** No action is required.

### FICN-1076

**Message** HostTapeIngr:ReadCpReport:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>;Emuls=0x<the number of idle state to non-idle state transitions while this tape was loaded>;Cmds=0x<the number of emulated host read commands processed while this tape was loaded>;Chains=0x<the number of emulated host chains processed while this tape was loaded>;MBytes=<the number of emulated read Kilobytes processed while this tape was loaded>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates a Rewind and Unload I/O has been processed from a locally connected Logical Partition (LPAR) and Read Channel Program pipelining was performed on the currently loaded tape.

**Recommended Action** No action is required.



**FICN-1077**

**Message** DevTapeEgr:Unloaded:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>:states=0x<4 prior emulation states><previous emulation state><current emulation state>:cmds=0x<last 4 commands received from the channel for this device>:status=0x<last 4 status values received from the channel for this device>:flags=0x<tape report bit flags (0x80-Tape Loaded,0x40-WriteEmul,0x20-RdBlkEmul,0x10-RdCpEmul)>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates a Rewind and Unload I/O has been processed from a remotely connected Logical Partition (LPAR), which indicates that a tape should be unloaded on a device.

**Recommended Action** No action is required.

**FICN-1078**

**Message** DevTapeEgr:WriteReport:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>:Emuls=0x<the number of idle state to non-idle state transitions while this tape was loaded>:Cmds=0x<the number of emulated host write commands processed while this tape was loaded>:Chains=0x<the number of emulated host chains processed while this tape was loaded>:MBytes=<the number of emulated write Kilobytes processed while this tape was loaded>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates a Rewind and Unload I/O has been processed from a remotely connected Logical Partition (LPAR) and Write Tape Pipelining was performed on the currently loaded tape.

**Recommended Action** No action is required.

**FICN-1079**

**Message** DevTapeEgr:ReadBlkReport:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>;Emuls=0x<the number of idle state to non-idle state transitions while this tape was loaded>;Cmds=0x<the number of emulated host read commands processed while this tape was loaded>;Chains=0x<the number of emulated host chains processed while this tape was loaded>;MBytes=<the number of emulated read Kilobytes processed while this tape was loaded>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates a Rewind and Unload I/O has been processed from a remotely connected Logical Partition (LPAR) and Read Block pipelining was performed on the currently loaded tape.

**Recommended Action** No action is required.

**FICN-1080**

**Message** DevTapeEgr:ReadCpReport:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>;Emuls=0x<the number of idle state to non-idle state transitions while this tape was loaded>;Cmds=0x<the number of emulated host read commands processed while this tape was loaded>;Chains=0x<the number of emulated host chains processed while this tape was loaded>;MBytes=<the number of emulated read Kilobytes processed while this tape was loaded>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates a Rewind and Unload I/O has been processed from a remotely connected Logical Partition (LPAR) and Read Channel Program pipelining was performed on the currently loaded tape.

**Recommended Action** No action is required.

**FICN-1081**

**Message** DevTapeIng:LRJ received on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> lastCmds=0x<Last 4 commands received from the channel for this device> lastStatus=0x<Last 4 status values presented to the channel for this device> treating as system reset event.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates a Link Level Reject (LRJ) from a FICON channel indicates that the channel does not have a path established to the Control Unit.

**Recommended Action** This is normally an unexpected event; contact your vendor's customer support for assistance.

## FICN-1082

**Message** EmulEls:CSWR\_RSCN received on GEPort=<GEPortNumber> VEPort=<VEPortNumber> Domain=0x<Domain> Port=0x<Port Host/Device Side>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates an attached port which had a FICON emulated path established has logged out from the switch.

**Recommended Action** This may be an unexpected event; contact your vendor's customer support for assistance.

## FICN-1083

**Message** EmulEls:SW\_RSCN received on GEPort=<GEPortNumber> VEPort=<VEPortNumber> Domain=0x<Domain> Port=0x<Port Host/Device Side>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates an attached port with the established FICON emulated path has logged out from the switch.

**Recommended Action** This may be an unexpected event; contact your vendor's customer support for assistance.

## FICN-1084

**Message** fcFicInit: No DRAM2 memory available, FICON emulation is disabled.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates a faulty DRAM2 was detected and access to its address range is prohibited.

**Recommended Action** This is an unexpected event; contact your vendor's customer support for assistance.

## FICN-1085

<b>Message</b>	FICON FCIP Tunnel is Up on GE<Either ge0 or gel>, tunnel Id=<The configured tunnel ID (0-7)>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a FICON FCIP tunnel has been established successfully to the peer switch.
<b>Recommended Action</b>	No action is required.

## FICN-1086

<b>Message</b>	FICON FCIP Tunnel is Down on GE<Either ge0 or gel>, tunnel Id=<The configured tunnel ID (0-7)>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a FICON FCIP tunnel to the peer switch has been terminated.
<b>Recommended Action</b>	This is an unexpected event; contact your vendor's customer support for assistance.

## FICN-1087

<b>Message</b>	DevTeraEgr:AS Link Level Reject (LRJ) from Chan on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> LastCmd=0x<the Last 4 commands issued to the device> LastStatus=0x<the Last 4 status values received from the device>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the FICON channel indicated in the path issued an Link Level Reject (LRJ) frame for a sequence from the device.
<b>Recommended Action</b>	If there was a job failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1088**

<b>Message</b>	DevTeraEgr:FICON Cancel received Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> state=0x<the current emulation state for the device> tflags=0x<the current emulation tera control flags for the device> sflags=0x<the current emulation status control flags for the device>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the FICON channel issued a Cancel sequence for a device in emulation.
<b>Recommended Action</b>	If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1089**

<b>Message</b>	DevTeraEgr:FICON Tera Cancel:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> Elapsed Time=<the current SIO time in seconds for the device>.<the current SIO time in milliseconds for the device> seconds.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the FICON channel issued a Cancel sequence for a device in emulation.
<b>Recommended Action</b>	If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1090**

<b>Message</b>	DevTeraEgr:FICON Selective Reset:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> State=0x<the current state of the device that received the selective reset> statArray=0x<the last 4 status values received from the device> cmdArray=0x<the last 4 commands that were issued to the device> tflags=0x<the current emulation tera control flags for the device> sflags=0x<the current emulation status control flags for the device>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the FICON channel issued a Selective Reset for a device that was active in emulation.
<b>Recommended Action</b>	If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1091**

<b>Message</b>	DevTeraEgr:FICON Selective Reset:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> Elapsed Time=<the current SIO time in seconds for the device>.<the current SIO time in milliseconds for the device> seconds.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the FICON channel issued a Selective Reset sequence for a device.
<b>Recommended Action</b>	If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1092**

<b>Message</b>	DevTeraEgr:FICON Purge received Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the FICON channel issued a Purge Path command sequence for a device.
<b>Recommended Action</b>	If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.

**FICN-1093**

<b>Message</b>	DevTeraIng:Auto Sense Data received on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> Bytes0-0xB=0x<bytes 0-3 of sense data from the device><bytes 4-7 of sense data from the device><bytes 8-0x0b of sense data from the device>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the FICON tera write pipelining processed sense data from a FICON device.
<b>Recommended Action</b>	If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.

## FICN-1094

<b>Message</b>	DevTeraIng:UnusualStatus:WriteCancelSelr:Generating Final Ending Status Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the FICON tera write pipeline is completing an emulated Selective Reset sequence.
<b>Recommended Action</b>	If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.

## FICN-1095

<b>Message</b>	DevTeraIng:Device level exception found for Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>: Oxid=0x<The OXID of the frame that included the Device Level Exception>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an active emulation device delivered a Device Level Exception frame to the emulation processing.
<b>Recommended Action</b>	If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.

## FICN-1096

<b>Message</b>	HostTeraEgr:CmdReject Sense Data Rcvd:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> LastCmds=0x<Last 4 commands received from the channel for this device> SenseData:Bytes0-0xB=0x<Bytes 0-3 of sense data from the device><Bytes 4-7 of sense data from the device><Bytes 8-0x0b of sense data from the device>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an active Teradata emulation sequence received a Command Reject Sense from the device.
<b>Recommended Action</b>	If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.

**FICN-1097**

<b>Message</b>	HostTeraEgr:AS Link Level Reject (LRJ) from CU Rx Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> LastCmd=0x<Last 4 commands issued to this device from the channel> LastStatus=0x<Last 4 status values sent to the channel from this device>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a Link Level Reject (LRJ) received from a device indicates that the Control Unit has lost the logical path to the Logical Partition (LPAR).
<b>Recommended Action</b>	If this was an unexpected event; contact your vendor's customer support for assistance.

**FICN-1098**

<b>Message</b>	HostTeraIng:FICON Cancel received Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> state=0x<the current emulation state for this device>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a job was canceled during a Write Tape Pipelining.
<b>Recommended Action</b>	If this was an unexpected event (cancel is normally an operator event), contact your vendor's customer support for assistance.

**FICN-1099**

<b>Message</b>	HostTeraIng::FICON Selective Reset:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> state=0x<the current emulation state for this device> LastCmds=0x<the last 4 commands received from the channel for this device> LastStatus=0x<the last 4 status values presented to the channel for this device>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the channel recognized a timeout condition and issued a Selective Reset.
<b>Recommended Action</b>	If this was an unexpected event, contact your vendor's customer support for assistance.



**FICN-1100**

**Message** HostTeraIng:FICON Selective Reset:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> Elapsed Time=<the number of seconds since the last IO started for this device>.<the number of milliseconds since the last IO started for this device> seconds.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that protocol errors in emulation in the Control Unit or network errors can cause Selective Reset.

**Recommended Action** If this was an unexpected event, contact your vendor's customer support for assistance.

**FICN-1101**

**Message** HostTeraIng:FICON Purge received:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates a Purge Path was received from the locally connected FICON channel. This is performed during the path recovery.

**Recommended Action** If this was an unexpected event, contact your vendor's customer support for assistance.

**FICN-1102**

**Message** HostTeraIng:LRJ received on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> lastCmds=0x<Last 4 commands received from the channel for this device> lastStatus=0x<Last 4 status values presented to the channel for this device> treating as system reset event.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates a Link Level Reject (LRJ) from a FICON channel indicates that the channel believes that it no longer has a path established to the Control Unit.

**Recommended Action** This is normally an unexpected event; contact your vendor's customer support for assistance.

**FICN-1103**

<b>Message</b>	DevTeraIngr:Exceptional Status rcvd on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> state=0x<current emulation state> status=0x<the exceptional status value>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the status (0x0D or 0x05) indicating the device is going down was received from the device or error status (including Unit Check 0x02) is received from an active emulation device.
<b>Recommended Action</b>	The device going down is a normal event during pipelining and not the unit check. If there are associated I/O error messages with this event, contact your vendor's customer support for assistance.

**FICN-1104**

<b>Message</b>	DevTeraEgr:Device Ready on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the Teradata device has been initialized and is ready for emulation operations.
<b>Recommended Action</b>	No action is required.

**FICN-1105**

<b>Message</b>	DevTeraIng:LRJ received on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> lastCmds=0x<Last 4 commands received from the channel for this device> lastStatus=0x<Last 4 status values presented to the channel for this device> treating as system reset event.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a Link Level Reject (LRJ) from a FICON channel indicates that the channel does not have a path established to the Control Unit.
<b>Recommended Action</b>	This is normally an unexpected event; contact your vendor's customer support for assistance.

**FICN-1106**

**Message** DevPrintEgr:AS Link Level Reject (LRJ) from Chan on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> LastCmd=0x<the Last 4 commands issued to the device> LastStatus=0x<the Last 4 status values received from the device>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates the FICON channel indicated in the path issued a Link Level Reject (LRJ) frame for a sequence from the device.

**Recommended Action** If there was a job failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1107**

**Message** DevPrintEgr:FICON Cancel received Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> state=0x<the current emulation state for the device> tflags=0x<the current emulation tera control flags for the device> sflags=0x<the current emulation status control flags for the device>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates the FICON channel issued a Cancel sequence for a device in emulation.

**Recommended Action** If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1108**

**Message** DevPrintEgr:FICON Tera Cancel:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> Elapsed Time=<the current SIO time in seconds for the device>.<the current SIO time in milliseconds for the device> seconds.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates the FICON channel issued a Cancel sequence for a device in emulation.

**Recommended Action** If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1109**

**Message** DevPrintEgr:FICON Selective Reset:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> State=0x<the current state of the device that received the selective reset> statArray=0x<the last 4 status values received from the device> cmdArray=0x<the last 4 commands that were issued to the device> tflags=0x<the current emulation tera control flags for the device> sflags=0x<the current emulation status control flags for the device>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates the FICON channel issued a Selective Reset for a device that was active in emulation.

**Recommended Action** If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1110**

**Message** DevPrintEgr:FICON Selective Reset:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> Elapsed Time=<the current SIO time in seconds for the device>.<the current SIO time in milliseconds for the device> seconds.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates the FICON channel issued a Selective Reset sequence for a device.

**Recommended Action** If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

**FICN-1111**

**Message** DevPrintEgr:FICON Purge received Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates the FICON channel issued a Purge Path command sequence for a device.

**Recommended Action** If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.

**FICN-1112**

<b>Message</b>	DevPrintIng:Auto Sense Data received on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> Bytes0-0xB=0x<bytes 0-3 of sense data from the device><bytes 4-7 of sense data from the device><bytes 8-0x0b of sense data from the device>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the FICON Printer write pipelining processed sense data from a FICON device.
<b>Recommended Action</b>	If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.

**FICN-1113**

<b>Message</b>	DevPrintIng:LRJ received on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> lastCmds=0x<Last 4 commands received from the channel for this device> lastStatus=0x<Last 4 status values presented to the channel for this device> treating as system reset event.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a Link Level Reject (LRJ) from a FICON channel indicates that the channel does not have a path established to the Control Unit.
<b>Recommended Action</b>	This is normally an unexpected event; contact your vendor's customer support for assistance.

**FICN-1114**

<b>Message</b>	DevPrintIng:Device level exception found for Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>: Oxid=0x<The OXID of the frame that included the Device Level Exception>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an active emulation device delivered a Device Level Exception frame to the emulation processing.
<b>Recommended Action</b>	If there was an unexpected job failure or I/O Error associated with this event, contact your vendor's customer support for assistance.

**FICN-1115**

**Message** HostPrintEgr:CmdReject Sense Data Rcvd:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> LastCmds=0x<Last 4 commands received from the channel for this device> SenseData:Bytes0-0xB=0x<Bytes 0-3 of sense data from the device><Bytes 4-7 of sense data from the device><Bytes 8-0x0b of sense data from the device>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates an active Print emulation sequence received Command Reject Sense data from the device.

**Recommended Action** If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.

**FICN-1116**

**Message** HostPrintEgr:AS Link Level Reject (LRJ) from CU Rx Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> LastCmd=0x<Last 4 commands issued to this device from the channel> LastStatus=0x<Last 4 status values sent to the channel from this device>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that a Link Level Reject (LRJ) was received from a device indicating that the Control Unit has lost the logical path to the Logical Partition (LPAR).

**Recommended Action** If this was an unexpected event; contact your vendor's customer support for assistance.

**FICN-1117**

**Message** HostPrintIng:FICON Cancel received Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> state=0x<the current emulation state for this device>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates a job was canceled during Print write pipelining.

**Recommended Action** If this was an unexpected event (cancel is normally an operator event), contact your vendor's customer support for assistance.

**FICN-1118**

**Message** HostPrintIng::FICON Selective Reset:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> state=0x<the current emulation state for this device> LastCmds=0x<the last 4 commands received from the channel for this device> LastStatus=0x<the last 4 status values presented to the channel for this device>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the channel recognized a timeout condition and issued a Selective Reset.

**Recommended Action** If this was an unexpected event, contact your vendor's customer support for assistance.

**FICN-1119**

**Message** HostPrintIng:FICON Selective Reset:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> Elapsed Time=<the number of seconds since the last IO started for this device>.<the number of milliseconds since the last IO started for this device> seconds.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the channel recognized a timeout condition and issued a Selective Reset.

**Recommended Action** If this was an unexpected event, contact your vendor's customer support for assistance.

**FICN-1120**

**Message** HostPrintIng:FICON Purge received:Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates a Purge Path was received from the locally connected FICON channel. This is performed during FICON path recovery.

**Recommended Action** If this was an unexpected event, contact your vendor's customer support for assistance.

**FICN-1121**

<b>Message</b>	HostPrintIng:LRJ received on Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr> lastCmds=0x<Last 4 commands received from the channel for this device> lastStatus=0x<Last 4 status values presented to the channel for this device> treating as system reset event.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates than a Link Level Reject (LRJ) received from a FICON channel indicates that the channel no longer has a path established to the Control Unit.
<b>Recommended Action</b>	This is normally an unexpected event; contact your vendor's customer support for assistance.

**FICN-1122**

<b>Message</b>	DevPrintIng:UnusualStatus:WriteCancelSelr:Generating Final Ending Status Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the FICON Print write pipeline sequence has received unit check status.
<b>Recommended Action</b>	If there was an unexpected job failure or I/O error associated with this event, contact your vendor's customer support for assistance.

**FICN-2005**

<b>Message</b>	FICON VEPort <VE port number> Feature Change verified Xrc <1 or 0 - XRC Emulation Enabled or Disabled> TapeWrt <1 or 0 - Tape Write Emulation Enabled or Disabled> TapeRd <1 or 0 - FICON Tape Read Emulation Enabled or Disabled> TinTir <1 or 0 - FICON TIN/TIR Emulation Enabled or Disabled> DvcAck <1 or 0 - FICON Device Level Ack Emulation Enabled or Disabled> RdBlkId <1 or 0 - FICON Write Emulation Read Block ID Emulation Enabled or Disabled>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the configuration was changed manually.
<b>Recommended Action</b>	No action is required.



## FICN-2006

<b>Message</b>	FICON VEPort <VE port number> Feature Change failed Xrc <1 or 0 - XRC Emulation Enabled or Disabled> TapeWrt <1 or 0 - Tape Write Emulation Enabled or Disabled> TapeRd <1 or 0 - FICON Tape Read Emulation Enabled or Disabled> TinTir <1 or 0 - FICON TIN/TIR Emulation Enabled or Disabled> DvcAck <1 or 0 - FICON Device Level Ack Emulation Enabled or Disabled> RdBlkId <1 or 0 - FICON Write Emulation Read Block ID Emulation Enabled or Disabled>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the FCIP Tunnel ID associated with the FICON tunnel must be down or disabled for a feature change to become effective.
<b>Recommended Action</b>	Disable the applicable FCIP tunnel to make the feature change effective.

## FICN-2064

<b>Message</b>	Ingress Abort:Oxid=0x<the OXID of the aborted exchange>:Unknown Path on VEPort=<VEPortNumber> from SID=0x<Source Domain><Source Port> to DID=0x<Destination Domain><Destination Port>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an abort operation has been received from a local FC interface for an exchange.
<b>Recommended Action</b>	If there were associated I/O errors at the same time as this event, contact your vendor's customer support for assistance.

## FICN-2065

<b>Message</b>	Egress Abort:Oxid=0x<the OXID of the aborted exchange>:Unknown Path on VEPort=<VEPortNumber> from SID=0x<Source Domain ><Source Port> to DID=0x<Destination Domain><Destination Port>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an abort operation has been received from a peer FC interface for an exchange.
<b>Recommended Action</b>	If there were associated I/O errors at the same time as this event, contact your vendor's customer support for assistance.

## FICN-2066

<b>Message</b>	MemAllocFailed for VEport=<VEPortNumber> could not create required structure.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an internal resource limit has been encountered so that additional control block memory could not be allocated.
<b>Recommended Action</b>	This is an unexpected event; either the maximum number of emulation devices are already in use or there is an internal memory leak. Contact your vendor's customer support for assistance.

## FICN-2082

<b>Message</b>	EmulEls:CSWR_RSCN received on VEPort=<VEPortNumber> Domain=0x<Host/Device Side Domain> Port=0x<Host/Device Side Port>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an attached port which had a FICON emulated path established has logged out from the switch.
<b>Recommended Action</b>	This may be an unexpected event; contact your vendor's customer support for assistance.

## FICN-2083

<b>Message</b>	EmulEls:SW_RSCN received on VEPort=<VEPortNumber> Domain=0x<Host/Device Side Domain> Port=0x<Host/Device Side Port>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an attached port with the established FICON emulated path has logged out from the switch.
<b>Recommended Action</b>	This may be an unexpected event; contact your vendor's customer support for assistance.

**FICN-2085**

<b>Message</b>	FICON or FCP Emulation Enabled FCIP Tunnel is Up on VEPort=<VEPortNumber>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a FICON or Fibre Channel Protocol (FCP) emulation-enabled FCIP tunnel has been established successfully to the peer switch.
<b>Recommended Action</b>	No action is required.

**FICN-2086**

<b>Message</b>	FICON or FCP Emulation Enabled FCIP Tunnel is Down on VEport=<VEPortNumber>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a FICON or Fibre Channel Protocol (FCP) emulation-enabled FCIP tunnel to the peer switch has been terminated.
<b>Recommended Action</b>	This is an unexpected event; contact your vendor's customer support for assistance.

**FICN-2087**

<b>Message</b>	FICON connected 3900 printer discovered Path=0x<VEPortNumber HostDomain HostPort DeviceDomain><DevicePort LPAR CUADDR DeviceAddr>-invalid compression mode.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that FICON Printer emulation is enabled, but cannot be performed for this device because the compression mode on the tunnel is not set to None or Aggressive.
<b>Recommended Action</b>	If you desire FICON Printer emulation for this device, modify the tunnel compression mode to None (mode 0) or Aggressive (mode 3).

## FICU Messages

### FICU-1001

<b>Message</b>	<error message>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that one of the configuration management functions have failed. The <i>key</i> variable is a component of the Fabric OS configuration database and is for support use only. The <i>error</i> variable is an internal error number.
<b>Recommended Action</b>	Execute the <b>haFailover</b> command on the switch if it has redundant control processors (CPs) or reboot the switch. Execute the <b>switchStatusShow</b> command to check if the flash memory is full. If the flash memory is full, execute the <b>supportSave</b> command to clear the core files.

### FICU-1002

<b>Message</b>	<function name>: Failed to get RNID from Management Server Domain=<domain> rc=<error>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the fibre connectivity control unit port (FICON-CUP) daemon failed to get the switch request node ID (RNID) from the management server because of a Fabric OS problem. The <i>domain</i> variable displays the domain ID of the target switch for this RNID. The <i>error</i> variable is an internal error number.
<b>Recommended Action</b>	If this is a bladed switch, execute the <b>haFailover</b> command. If the problem persists, or if this is a non-bladed switch, download a new firmware version using the <b>firmwareDownload</b> command.

### FICU-1003

<b>Message</b>	<function name>: <message> FICON-CUP License Not Installed: (<error>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the fibre connectivity control unit port (FICON-CUP) license is not installed on the switch.
<b>Recommended Action</b>	Execute the <b>licenseShow</b> command to check the installed licenses on the switch. The switch cannot be managed using FICON-CUP commands until the FICON-CUP license is installed. Contact your switch supplier for a FICON-CUP license. Execute the <b>licenseAdd</b> command to add the license to your switch.

## FICU-1004

<b>Message</b>	<function name>: Failed to set FICON Management Server (FMS) mode: conflicting PID Format:<pid_format>, FMS Mode:<mode>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	<p>Indicates that a process ID (PID) format conflict was encountered. The core PID format is required for fibre connectivity control unit port (FICON-CUP).</p> <p>The <i>pid_format</i> variable displays the PID format currently running on the fabric, and is one of the following:</p> <ul style="list-style-type: none"> <li>• 0 - VC-encoded PID format</li> <li>• 1 - Core PID format</li> <li>• 2 - Extended-edge PID format</li> </ul> <p>The <i>mode</i> variable displays whether FICON Management Server (FMS) mode is enabled, and is one of the following: 0 means FMS mode is enabled and 1 means FMS mode is disabled.</p>
<b>Recommended Action</b>	To enable FMS mode, the core PID format must be used in the fabric. Change the PID format to core PID using the <b>configure</b> command and re-enable FMS Mode using the <b>ficonCupSet</b> command. Refer to the <i>Fabric OS Administrator's Guide</i> for information on core PID mode.

## FICU-1005

<b>Message</b>	Failed to initialize <module>, rc = <error>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that initialization of a module within the fibre connectivity control unit port (FICON-CUP) daemon failed.
<b>Recommended Action</b>	Download a new firmware version using the <b>firmwareDownload</b> command.

## FICU-1006

<b>Message</b>	Control Device Allegiance Reset: (Logical Path: 0x<PID>:0x<channel image ID>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the path with the specified process ID (PID) and channel image ID lost allegiance to a fibre connectivity control unit port (FICON-CUP) device.

## 5 FICU-1007

**Recommended Action** Check if the FICON channel corresponding to the PID in the message is functioning correctly.

### FICU-1007

**Message** <function name>: Failed to allocate memory while performing <message>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that memory resources are low. This may be a transient problem.

**Recommended Action** Check the memory usage on the switch using the **memShow** command.  
If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

### FICU-1008

**Message** FMS mode has been enabled. Port(s):<port number(s)> have been disabled due to port address conflict.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified ports were disabled when the FICON Management Server (FMS) mode was enabled. This is due to a port address conflict or the port address being reserved for the CUP management port.

**Recommended Action** No action is required.

### FICU-1009

**Message** FMS Mode enable failed due to insufficient frame filtering resources on some ports.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the frame filtering resources required to enable FICON Management Server mode (fmsMode) were not available on some of the ports.

**Recommended Action** Execute the **haFailover** command on the switch if it has redundant control processors (CPs) or reboot the switch.

## FICU-1010

<b>Message</b>	FMS mode enable failed due to port(s) with areas 0xFE or 0xFF is(are) connected to device(s) .
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the FICON Management Server (FMS) mode was not enabled because ports with areas 0xFE or 0xFF are connected to devices.
<b>Recommended Action</b>	Disable ports with areas 0xFE or 0xFF using the <b>portDisable</b> command.

## FICU-1011

<b>Message</b>	FMS mode has been enabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the FICON Management Server mode (fmsMode) has been enabled.
<b>Recommended Action</b>	No action is required.

## FICU-1012

<b>Message</b>	FMS mode has been disabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the FICON Management Server mode (fmsMode) has been disabled.
<b>Recommended Action</b>	No action is required.

## FICU-1013

<b>Message</b>	Host data file cannot be reset to proper size.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the file system is too full to create the host data file at the proper size.
<b>Recommended Action</b>	Execute the <b>switchStatusShow</b> command to check if the flash memory is full. If the flash memory is full, execute the <b>supportSave</b> command to clear the core files.

## FICU-1017

<b>Message</b>	FMSMODE enable failed because reserved area is bound to a device.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that one or both of the reserved areas 0xFE and 0xFF is bound to a device.
<b>Recommended Action</b>	Execute the <b>wwnaddress --show</b> command to display all devices currently bound to areas. Execute the <b>wwnaddress --unbind</b> command to release the reserved area from the device.

## FICU-1018

<b>Message</b>	FMSMODE enable noticed swapped ports.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that some ports are swapped at the time FICON Management Server mode (fmsMode) is enabled.
<b>Recommended Action</b>	Verify the expected FICON port address and port number relationship. For more information, refer to the "FICON and FICON CUP in Virtual Fabrics" section of the <i>FICON Administrator's Guide</i> .



## FICU-1019

<b>Message</b>	Switch has been set offline by LP(<LP ID>).
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the FICON Management Server (FMS) has disabled the switch.
<b>Recommended Action</b>	No action is required.

## FICU-1020

<b>Message</b>	Port Addr ( <port mask> ) have been Blocked by <source>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the FICON Management Server (FMS) has blocked ports.
<b>Recommended Action</b>	No action is required.

## FICU-1021

<b>Message</b>	Port Addr ( <port mask> ) have been Unblocked by <source>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the FICON Management Server (FMS) has unblocked ports.
<b>Recommended Action</b>	No action is required.

## FICU-1022

<b>Message</b>	Detected FC8-48 and/or FC8-64 that are not manageable when FMS mode is enabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the presence of unmanageable ports such as 48-port blade ports in the virtual fabric-disabled chassis.
<b>Recommended Action</b>	No action is required. For more information on the FICON CUP restrictions, refer to the <i>FICON Administrator's Guide</i> .

## FICU-1023

<b>Message</b>	Detected 48 port blade when FMS mode is enabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates presence of 48-port blade ports in the switch.
<b>Recommended Action</b>	No action is required. For more information on the FICON CUP restrictions, refer to the <i>FICON Administrator's Guide</i> .

## FICU-1024

<b>Message</b>	Detected 64 port blade when FMS mode is enabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates presence of 64-port blade ports in the switch.
<b>Recommended Action</b>	No action is required. For more information on the FICON CUP restrictions, refer to the <i>FICON Administrator's Guide</i> .

## FKLB Messages

### FKLB-1001

<b>Message</b>	exchange <xid> overlapped, pid=<pid>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the FC kernel driver has timed out the exchange while the application is still active. When the FC kernel driver reuses the exchange, the application will overlap. This happens on a timed-out exchange; it automatically recovers after the application times out the exchange.
<b>Recommended Action</b>	No action is required.

## FLOD Messages

### FLOD-1001

<b>Message</b>	Unknown LSR type: port <port number>, type <LSR header type>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the link state record (LSR) type is unknown. The following two LSR header types are the only known types: <ul style="list-style-type: none"> <li>• 1 - Unicast</li> <li>• 3 - Multicast</li> </ul>
<b>Recommended Action</b>	No action is required; the record is discarded.

### FLOD-1003

<b>Message</b>	Link count exceeded in received LSR, value = <link count number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the acceptable link count received was exceeded in the link state record (LSR).
<b>Recommended Action</b>	No action is required; the record is discarded.

### FLOD-1004

<b>Message</b>	Excessive LSU length = <LSU length>.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the link state update (LSU) size exceeds the value the system can support.
<b>Recommended Action</b>	Reduce the number of switches in the fabric or reduce the number of redundant inter-switch links (ISLs) between two switches.

## FLOD-1005

<b>Message</b>	Invalid received domain ID: <domain number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the received link state record (LSR) contained an invalid domain number.
<b>Recommended Action</b>	No action is required; the LSR is discarded.

## FLOD-1006

<b>Message</b>	Transmitting invalid domain ID: <domain number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the transmitted link state record (LSR) contained an invalid domain number.
<b>Recommended Action</b>	No action is required; the LSR is discarded.

## FSPF Messages

### FSPF-1001

<b>Message</b>	Input Port <port number> out of range.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified input port number is out of range because it does not exist on the switch.
<b>Recommended Action</b>	No action is required. This is a temporary kernel error that does not affect your system. If the problem persists, execute the <b>supportSave</b> command and contact your service provider.

### FSPF-1002

<b>Message</b>	Wrong neighbor ID (<domain ID>) in Hello message from port <port number>, expected ID = <domain ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the switch has received a wrong domain ID from its neighbor switch in the HELLO message from a specified port. This may happen when a domain ID for a switch has been changed.
<b>Recommended Action</b>	No action is required.

### FSPF-1003

<b>Message</b>	Remote Domain ID <domain number> out of range, input port = <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified remote domain ID is out of range.
<b>Recommended Action</b>	No action is required. The frame is discarded.

## FSPF-1005

<b>Message</b>	Wrong Section Id <section number>, should be <section number>, input port = <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that an incorrect section ID was reported from the specified input port. The section ID is part of the fabric shortest path first (FSPF) protocol and is used to identify a set of switches that share an identical topology database.
<b>Recommended Action</b>	This switch does not support a non-zero section ID. Any connected switch from another manufacturer with a section ID other than 0 is incompatible in a fabric of Brocade switches. Disconnect the incompatible switch.

## FSPF-1006

<b>Message</b>	FSPF Version <FSPF version> not supported, input port = <port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the fabric shortest path first (FSPF) version is not supported on the specified input port.
<b>Recommended Action</b>	Update the FSPF version by running the <b>firmwareDownload</b> command. All current versions of the Fabric OS support FSPF version 2.

## FSPF-1007

<b>Message</b>	ICL triangular topology is broken between the neighboring domains: <domain number> and <domain number>. Please fix it ASAP.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the inter-chassis link (ICL) triangular topology is broken and becomes linear. It may cause frame drop or performance slowdown.
<b>Recommended Action</b>	Connect the two domains using ICL or regular inter-switch link (ISL) to form a triangular topology.

## FSPF-1008

<b>Message</b>	ICL triangular topology is formed among the domains: <domain number> (self), <domain number>, and <domain number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the inter-chassis link (ICL) triangular topology is formed.
<b>Recommended Action</b>	No action is required.

## FSPF-1009

<b>Message</b>	16G ICL topology is not recommended on local domain <domain number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the current 16 Gbps inter-chassis link (ICL) topology is not recommended.
<b>Recommended Action</b>	Use the <b>switchShow</b> , <b>isIShow</b> , and <b>IsdbShow</b> commands to identify the neighbor domains that violate the ICL connectivity requirement.

## FSPF-1010

<b>Message</b>	ICL Topology is valid on local domain <domain number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the current inter-chassis link (ICL) topology is valid for routing from the local switch.
<b>Recommended Action</b>	No action is required.

## FSPF-1011

<b>Message</b>	16G ICL topology is unbalanced.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the current configuration of inter-chassis link (ICL) paths are unbalanced.



**Recommended Action** Investigate current ICL configuration to ensure that all recommendations for cabling are satisfied.

## FSPF-1012

**Message** All existing ICL topology imbalances have been corrected.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the existing inter-chassis link (ICL) configuration that was resulting in an unbalanced topology has been corrected.

**Recommended Action** No action is required.

## FSS Messages

### FSS-1001

<b>Message</b>	Component (<component name>) dropping HA data update (<update ID>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an application has dropped a high availability (HA) data update.
<b>Recommended Action</b>	For a dual control processor (CP) system, enable the HA state synchronization using the <b>haSyncStart</b> command. For non-bladed systems, restart the switch using the <b>reboot</b> command.  If the problem persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

### FSS-1002

<b>Message</b>	Component (<component name>) sending too many concurrent HA data update transactions (<dropped update transaction ID>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an application has sent too many concurrent high availability (HA) data updates.
<b>Recommended Action</b>	For a dual CP system, enable the HA state synchronization using the <b>haSyncStart</b> command. For non-bladed systems, restart the switch using the <b>reboot</b> command.  If the problem persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

### FSS-1003

<b>Message</b>	Component (<component name>) misused the update transaction (<transaction ID>) without marking the transaction beginning.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Fabric OS state synchronization (FSS) service has dropped the update because an application did not set the transaction flag correctly.
<b>Recommended Action</b>	For a dual CP system, enable the high availability (HA) state synchronization using the <b>haSyncStart</b> command. For non-bladed systems, restart the switch using the <b>reboot</b> command.  If the problem persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## FSS-1004

<b>Message</b>	Memory shortage.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the system ran out of memory.
<b>Recommended Action</b>	<p>Execute the <b>memShow</b> command to view memory usage in the switch.</p> <p>For a dual CP system, enable the high availability (HA) state synchronization using the <b>haSyncStart</b> command. For non-bladed systems, restart the switch using the <b>reboot</b> command.</p> <p>If the problem persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.</p>

## FSS-1005

<b>Message</b>	FSS read failure.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the read system call to the Fabric OS state synchronization (FSS) device has failed.
<b>Recommended Action</b>	If the problem persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## FSS-1006

<b>Message</b>	No FSS message available.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that data is not available on the Fabric OS state synchronization (FSS) device.
<b>Recommended Action</b>	If the problem persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

**FSS-1007**

<b>Message</b>	<component name>: Faulty Ethernet connection.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the Ethernet connection between the active control processor (CP) and the standby CP is not healthy. This error occurs when the standby CP does not respond to a request from the active CP within five seconds. This usually indicates a problem with the internal Ethernet connection and the disruption of the synchronization process.
<b>Recommended Action</b>	Execute the <b>supportShow</b> or <b>supportSave</b> command to validate the network configuration and then execute the <b>haSyncStart</b> command to restore the high availability (HA) synchronization. If the problem persists, contact your switch service provider.

**FSS-1008**

<b>Message</b>	FSS Error: <Error Message>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that a Fabric OS state synchronization (FSS) error has occurred.
<b>Recommended Action</b>	Execute the <b>supportSave</b> command and contact your switch service provider.

**FSS-1009**

<b>Message</b>	FSS Error: <Error Message>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a Fabric OS state synchronization (FSS) error has occurred for the specified component. The error code is displayed in the message.
<b>Recommended Action</b>	Execute the <b>supportSave</b> command and contact your switch service provider.

## FSS-1010

<b>Message</b>	FSS Warning: <Warning Message>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a Fabric OS state synchronization (FSS) error may have occurred.
<b>Recommended Action</b>	Execute the <b>supportSave</b> command and contact your switch service provider.

## FSS-1011

<b>Message</b>	FSS Info: <Info Message>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a Fabric OS state synchronization (FSS) related informational message.
<b>Recommended Action</b>	No action is required.

## FSSM Messages

### FSSM-1002

<b>Message</b>	HA State is in sync.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the high availability (HA) state of the active control processor (CP) is in synchronization with the HA state of the standby CP. If the standby CP is healthy, the failover will be nondisruptive.
<b>Recommended Action</b>	No action is required.

### FSSM-1003

<b>Message</b>	HA State out of sync.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the high availability (HA) state of the active control processor (CP) is out of synchronization with the HA state of the standby CP. If the active CP failover occurs when the HA state is out of synchronization, the failover is disruptive.
<b>Recommended Action</b>	<p>If this message was logged as a result of a user-initiated action (such as running the <b>reboot</b> command), no action is required.</p> <p>Otherwise, execute the <b>haSyncStart</b> command on the active CP to resynchronize the HA state.</p> <p>If the HA state does not synchronize, execute the <b>haDump</b> command to diagnose the problem.</p> <p>If the problem persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.</p>

### FSSM-1004

<b>Message</b>	Incompatible software version in HA synchronization.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	<p>Indicates that the active control processor (CP) and the standby CP in a dual CP system are running firmware that is incompatible with each other. If the active CP fails, the failover will be disruptive.</p> <p>In a switch system, this message is logged when a firmware upgrade or downgrade was invoked. The new firmware version is not compatible with the current running version. This causes a disruptive firmware upgrade or downgrade.</p>

**Recommended Action** For a dual CP system, execute the **firmwareDownload** command to load compatible firmware on the standby CP.

## FW Messages

### FW-1001

<b>Message</b>	<label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the internal temperature of the switch has changed.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation. To prevent recurring messages, disable the changed alarm for this threshold. If you receive a temperature-related message, check for an accompanying fan-related message and check fan performance. If all fans are functioning normally, check the climate control in your lab.

### FW-1002

<b>Message</b>	<Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the internal temperature of the switch has fallen below the low boundary.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation. Typically, low temperatures mean that the fans and airflow of a switch are functioning normally.  Verify that the location temperature is within the operational range of the switch. Refer to the hardware reference manual for the environmental temperature range of your switch.

### FW-1003

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the internal temperature of the switch has risen above the high boundary to a value that might damage the switch.
<b>Recommended Action</b>	This message generally appears when a fan fails. If so, a fan-failure message accompanies this message. Replace the fan.



## FW-1004

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the internal temperature of the switch has changed from a value outside of the acceptable range to a value within the acceptable range.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation. If you receive a temperature-related message, check for an accompanying fan-related message and check fan performance. If all fans are functioning normally, check the climate control in your lab.

## FW-1005

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the speed of the fan has changed. Fan problems typically contribute to temperature problems.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation. Consistently abnormal fan speeds generally indicate that the fan is malfunctioning.

## FW-1006

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the speed of the fan has fallen below the low boundary. Fan problems typically contribute to temperature problems.
<b>Recommended Action</b>	Consistently abnormal fan speeds generally indicate that the fan is failing. Replace the fan field-replaceable unit (FRU).

## FW-1007

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the speed of the fan has risen above the high boundary. Fan problems typically contribute to temperature problems.
<b>Recommended Action</b>	Consistently abnormal fan speeds generally indicate that the fan is failing. Replace the fan field-replaceable unit (FRU).

## FW-1008

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the speed of the fan has changed from a value outside of the acceptable range to a value within the acceptable range. Fan problems typically contribute to temperature problems.
<b>Recommended Action</b>	No action is required. Consistently abnormal fan speeds generally indicate that the fan is failing. If this message occurs repeatedly, replace the fan field-replaceable unit (FRU).

## FW-1009

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the state of the power supply has changed from faulty to functional or from functional to faulty.
<b>Recommended Action</b>	If the power supply is functioning correctly, no action is required. If the power supply is functioning below the acceptable boundary, verify that it is seated correctly in the chassis. Run the <b>psShow</b> command to view the status of the power supply. If the power supply continues to be a problem, replace the faulty power supply.

## FW-1010

<b>Message</b>	<Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the power supply is faulty. The power supply is not producing enough power.
<b>Recommended Action</b>	Verify that you have installed the power supply correctly and that it is correctly seated in the chassis. If the problem persists, replace the faulty power supply.

## FW-1011

<b>Message</b>	<Label>, is above high boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the power supply is functioning properly.
<b>Recommended Action</b>	Set the high boundary above the normal operation range.

## FW-1012

<b>Message</b>	<Label>, is between high and low boundaries (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the power supply counter changed from a value outside of the acceptable range to a value within the acceptable range.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1033**

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the temperature of the small form-factor pluggable (SFP) has changed. Frequent fluctuations in SFP temperature may indicate a deteriorating SFP.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1034**

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the temperature of the small form-factor pluggable (SFP) has fallen below the low boundary.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1035**

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the temperature of the small form-factor pluggable (SFP) has risen above the high boundary. Frequent fluctuations in temperature may indicate a deteriorating SFP.
<b>Recommended Action</b>	Replace the SFP.

## FW-1036

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the temperature of the small form-factor pluggable (SFP) has changed from a value outside of the acceptable range to a value within the acceptable range. Frequent fluctuations in temperature may indicate a deteriorating SFP.
<b>Recommended Action</b>	No action is required.

## FW-1037

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the receive power value of the small form-factor pluggable (SFP) has changed. The receive performance area measures the amount of incoming laser to help you determine whether the SFP is in good working condition. If the counter often exceeds the threshold, the SFP is deteriorating.
<b>Recommended Action</b>	Incoming laser fluctuations usually indicate a deteriorating SFP. If the message persists, replace the SFP.

## FW-1038

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the receive power value of the small form-factor pluggable (SFP) has fallen below the low boundary. The receive performance area measures the amount of incoming laser to help you determine whether the SFP is in good working condition. If the counter often exceeds the threshold, the SFP is deteriorating.
<b>Recommended Action</b>	Verify that your optical components are clean and function properly. Replace deteriorating cables or SFPs. Check for damage from heat or age.

**FW-1039**

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the receive power value of the small form-factor pluggable (SFP) has risen above the high boundary. The receive performance area measures the amount of incoming laser to help you determine whether the SFP is in good working condition. If the counter often exceeds the threshold, the SFP is deteriorating.
<b>Recommended Action</b>	Replace the SFP before it deteriorates.

**FW-1040**

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the receive power value of the small form-factor pluggable (SFP) has changed from a value outside of the acceptable range to a value within the acceptable range. The receive performance area measures the amount of incoming laser to help you determine whether the SFP is in good working condition. If the counter often exceeds the threshold, the SFP is deteriorating.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1041**

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the transmit power value of the small form-factor pluggable (SFP) has changed. The transmit performance area measures the amount of outgoing laser to help you determine whether the SFP is in good working condition. If the counter often exceeds the threshold, the SFP is deteriorating.
<b>Recommended Action</b>	Transmitting laser fluctuations usually indicates a deteriorating SFP. If the message persists, replace the SFP.

## FW-1042

<b>Message</b>	<Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the transmit power value of the small form-factor pluggable (SFP) has fallen below the low boundary. The transmit performance area measures the amount of outgoing laser to help you determine whether the SFP is in good working condition. If the counter often exceeds the threshold, the SFP is deteriorating.
<b>Recommended Action</b>	Verify that your optical components are clean and function properly. Replace deteriorating cables or SFPs. Check for damage from heat or age.

## FW-1043

<b>Message</b>	<Label>, is above high boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the transmit power value of the small form-factor pluggable (SFP) has risen above the high boundary. The transmit performance area measures the amount of outgoing laser to help you determine whether the SFP is in good working condition. If the counter often exceeds the threshold, the SFP is deteriorating.
<b>Recommended Action</b>	Replace the SFP.

## FW-1044

<b>Message</b>	<Label>, is between high and low boundaries (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the transmit power value of the small form-factor pluggable (SFP) has changed from a value outside of the acceptable range to a value within the acceptable range. The transmit performance area measures the amount of outgoing laser to help you determine whether the SFP is in good working condition. If the counter often exceeds the threshold, the SFP is deteriorating.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1045**

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the value of the small form-factor pluggable (SFP) voltage has changed. If the supplied voltage of the SFP transceiver is outside of the normal range, this may indicate a hardware failure.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation. If the message persists, replace the SFP.

**FW-1046**

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the value of the small form-factor pluggable (SFP) voltage has fallen below the low boundary.
<b>Recommended Action</b>	Verify that your optical components are clean and function properly. Replace deteriorating cables or SFPs. Check for damage from heat or age.

**FW-1047**

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the value of the small form-factor pluggable (SFP) voltage has risen above the high boundary.
<b>Recommended Action</b>	The supplied current of the SFP transceiver is outside of the normal range, indicating possible hardware failure. If the current rises above the high boundary, you must replace the SFP.



## FW-1048

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the value of the small form-factor pluggable (SFP) voltage has changed from a value outside of the acceptable range to a value within the acceptable range.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1049

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the value of the small form-factor pluggable (SFP) voltage has changed. Frequent voltage fluctuations indicate that the SFP is deteriorating.
<b>Recommended Action</b>	Replace the SFP.

## FW-1050

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the value of the small form-factor pluggable (SFP) voltage has fallen below the low boundary.
<b>Recommended Action</b>	Configure the low threshold to 1 so that the threshold triggers an alarm when the value falls to 0 (Out_of_Range). If continuous or repeated alarms occur, replace the SFP before it deteriorates.

## FW-1051

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the value of the small form-factor pluggable (SFP) voltage has risen above the high boundary. High voltages indicate possible hardware failures.
<b>Recommended Action</b>	Frequent voltage fluctuations indicate that the SFP is deteriorating. Replace the SFP.

## FW-1052

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the value of the small form-factor pluggable (SFP) voltage has changed from a value outside of the acceptable range to a value within the acceptable range.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1053

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the value of the small form-factor pluggable (SFP) Power on Hours has fallen below the low boundary.
<b>Recommended Action</b>	Configure the low threshold to 1 so that the threshold triggers an alarm when the value falls to 0 (Out_of_Range). If continuous or repeated alarms occur, replace the SFP before it deteriorates.

## FW-1054

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the value of the small form-factor pluggable (SFP) Power on Hours has risen above the high boundary. The high value indicates the maximum lifetime use of the SFP.
<b>Recommended Action</b>	Replace the SFP.

## FW-1113

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of times E_Ports have gone down has changed. E_Ports go down each time you remove a cable or small form-factor pluggable (SFP). SFP failures also cause E_Ports to go down. Down E_Port may be caused by transient errors.
<b>Recommended Action</b>	Check both ends of the physical connection and verify that the SFPs and cables are functioning properly.

## FW-1114

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of times E_Ports have gone down has fallen below the low boundary. E_Ports go down each time you remove a cable or small form-factor pluggable (SFP). SFP failures also cause E_Ports to go down. Down E_Port may be caused by transient errors.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation. A low number of E_Port failures means that the switch is functioning normally.

**FW-1115**

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of times E_Ports have gone down has risen above the high boundary. E_Ports go down each time you remove a cable or small form-factor pluggable (SFP). SFP failures also cause E_Ports to go down. Down E_Port may be caused by transient errors.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation. Check both ends of the physical connection and verify that the SFP functions properly.

**FW-1116**

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of times E_Ports have gone down has changed from a value outside of the acceptable range to a value within the acceptable range. E_Ports go down each time you remove a cable or small form-factor pluggable (SFP). SFP failures also cause E_Ports to go down. Down E_Port may be caused by transient errors.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1117**

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of fabric reconfigurations has changed. The following occurrences can cause a fabric reconfiguration: <ul style="list-style-type: none"> <li>• Two switches with the same domain ID have connected to one another.</li> <li>• Two fabrics have joined.</li> <li>• An E_Port has gone offline.</li> <li>• A principal link has segmented from the fabric.</li> </ul>

**Recommended Action** Verify that the cable is properly connected at both ends. Verify that the small form-factor pluggables (SFPs) have not become faulty. An inexplicable fabric reconfiguration might be a transient error and might not require troubleshooting.

## FW-1118

**Message** <Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of fabric reconfigurations has fallen below the low boundary. The following occurrences can cause a fabric reconfiguration:

- Two switches with the same domain ID have connected to one another.
- Two fabrics have joined.
- An E\_Port has gone offline.
- A principal link has segmented from the fabric.

A low number of fabric reconfigurations means that the fabric is functioning normally.

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1119

**Message** <Label>, is above high boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of fabric reconfigurations has risen above the high boundary. The following occurrences can cause a fabric reconfiguration:

- Two switches with the same domain ID have connected to one another.
- Two fabrics have joined.
- An E\_Port has gone offline.
- A principal link has segmented from the fabric.

**Recommended Action** Verify that all inter-switch link (ISL) cables are properly connected at both ends. Verify that the small form-factor pluggable (SFP) has not become faulty. An inexplicable fabric reconfiguration might be a transient error and might not require troubleshooting.

**FW-1120**

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of fabric reconfigurations has changed from a value outside of the acceptable range to a value within the acceptable range. The following occurrences can cause a fabric reconfiguration: <ul style="list-style-type: none"> <li>• Two switches with the same domain ID have connected to one another.</li> <li>• Two fabrics have joined.</li> <li>• An E_Port has gone offline.</li> <li>• A principal link has segmented from the fabric.</li> </ul>
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1121**

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of domain ID changes has changed. Domain ID changes occur when there is a conflict of domain IDs in a single fabric and the principal switch must assign another domain ID to the switch.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1122**

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of domain ID changes has fallen below the low boundary. Domain ID changes occur when there is a conflict of domain IDs in a single fabric and the principal switch has to assign another domain ID to the switch. A low number of domain ID changes means that the fabric is functioning normally.

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1123

**Message** <Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of domain ID changes has risen above the high boundary. Domain ID changes occur when there is a conflict of domain IDs in a single fabric and the principal switch has to assign another domain ID to the switch.

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1124

**Message** <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of domain ID changes has changed from a value outside of the acceptable range to a value within the acceptable range. Domain ID changes occur when there is a conflict of domain IDs in a single fabric and the principal switch has to assign another domain ID to the switch.

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1125

**Message** <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of segmentations has changed. Segmentation changes might occur due to the following reasons:

- Zone conflicts.
- Domain conflicts.
- Segmentation of the principal link between two switches.

- Incompatible link parameters. During E\_Port initialization, ports exchange link parameters. Rarely, incompatible parameters result in segmentation.

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1126

**Message** <Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of segmentations has fallen below the low boundary. Segmentation changes might occur due to the following reasons:

- Zone conflicts.
- Domain conflicts.
- Segmentation of the principal link between two switches.
- Incompatible link parameters. During E\_Port initialization, ports exchange link parameters. Rarely, incompatible parameters result in segmentation.

A low number of segmentation errors means that the fabric is functioning normally.

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1127

**Message** <Label>, is above high boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of segmentations has risen above the high boundary. Segmentation changes might occur due to the following reasons:

- Zone conflicts.
- Domain conflicts.
- Segmentation of the principal link between two switches.
- Incompatible link parameters. During E\_Port initialization, ports exchange link parameters. Rarely, incompatible parameters result in segmentation.

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.



## FW-1128

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of segmentations has changed from a value outside of the acceptable range to a value within the acceptable range. Segmentation changes might occur due to the following reasons: <ul style="list-style-type: none"> <li>• Zone conflicts.</li> <li>• Domain conflicts.</li> <li>• Segmentation of the principal link between two switches.</li> <li>• Incompatible link parameters. During E_Port initialization, ports exchange link parameters. Rarely, incompatible parameters result in segmentation.</li> </ul>
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1129

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of zone changes has changed. Zone changes occur when there is a change to the effective zone configuration.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1130

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of zone changes has fallen below the low boundary. Zone changes occur when there is a change to the effective zone configuration. A low number of zone configuration changes means that the fabric is functioning normally.

## 5 FW-1131

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

### FW-1131

**Message** <Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of zone changes has risen above the high boundary. Zone changes occur when there is a change to the effective zone configuration.

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

### FW-1132

**Message** <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of zone changes has changed from a value outside of the acceptable range to a value within the acceptable range. Zone changes occur when there is a change to the effective zone configuration.

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

### FW-1133

**Message** <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of fabric logins has changed. Fabric logins occur when a port or device initializes with the fabric. The event is called fabric login (FLOGI).

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1134

<b>Message</b>	<Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of fabric logins has fallen below the low boundary. Fabric logins occur when a port or device initializes with the fabric. The event is called fabric login (FLOGI). A low number of fabric logins means that the fabric is functioning normally.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1135

<b>Message</b>	<Label>, is above high boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of fabric logins has risen above the high boundary. Fabric logins occur when a port or device initializes with the fabric. The event is called fabric login (FLOGI).
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1136

<b>Message</b>	<Label>, is between high and low boundaries (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of fabric logins has changed from a value outside of the acceptable range to a value within the acceptable range. Fabric logins occur when a port or device initializes with the fabric. The event is called fabric login (FLOGI).
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1137

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of small form-factor pluggable (SFP) state changes has changed. SFP state changes occur when the SFP is inserted or removed.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1138

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of small form-factor pluggable (SFP) state changes has fallen below the low boundary. SFP state changes occur when the SFP is inserted or removed. A low number of SFP state changes means that the switch is functioning normally.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1139

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of small form-factor pluggable (SFP) state changes has risen above the high boundary. SFP state changes occur when the SFP is inserted or removed.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1140

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of small form-factor pluggable (SFP) state changes has changed from a value outside of the acceptable range to a value within the acceptable range. SFP state changes occur when the SFP is inserted or removed.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1160

<b>Message</b>	<Port Name> <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of link failures that the port experiences has changed. Link loss errors occur when a link experiences a loss of signal and fails. Both physical and hardware problems can cause link loss errors. Link loss errors frequently occur due to a loss of synchronization.
<b>Recommended Action</b>	Check both ends of your cable connection. Verify that the cable and small form-factor pluggables (SFPs) are not faulty.  Losses of synchronization commonly causes link failures. If you receive concurrent loss of synchronization errors, troubleshoot the loss of synchronization.

## FW-1161

<b>Message</b>	<Port Name> <Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of link failures that the port experiences has fallen below the low boundary. Link loss errors occur when a link experiences a loss of signal and fails. Both physical and hardware problems can cause link loss errors. Link loss errors frequently occur due to a loss of synchronization. Check for concurrent loss of synchronization errors and, if applicable, troubleshoot them. A low number of link loss errors means that the switch is functioning normally.
<b>Recommended Action</b>	Check for concurrent loss of synchronization errors and, if applicable, troubleshoot them. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1162**

<b>Message</b>	<Port Name> <Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of link failures that the port experiences has risen above the high boundary. Link loss errors occur when a link experiences a loss of signal and fails. Both physical and hardware problems can cause link loss errors. Link loss errors frequently occur due to a loss of synchronization.
<b>Recommended Action</b>	Check both ends of your cable connection. Verify that the cable and small form-factor pluggables (SFPs) are not faulty.  Losses of synchronization commonly cause link failures. If you receive concurrent loss of synchronization errors, troubleshoot the loss of synchronization.

**FW-1163**

<b>Message</b>	<Port Name> <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of link failures that the port experiences has changed from a value outside of the acceptable range to a value within the acceptable range. Link loss errors occur when a link experiences a loss of signal and fails. Both physical and hardware problems can cause link loss errors. Link loss errors frequently occur due to a loss of synchronization. Check for concurrent loss of synchronization errors and, if applicable, troubleshoot them.
<b>Recommended Action</b>	Check for concurrent loss of synchronization errors and, if applicable, troubleshoot them. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1164**

<b>Message</b>	<Port Name> <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of synchronization losses that the port experiences has changed. Loss of synchronization errors frequently occur due to a faulty small form-factor pluggable (SFP) or cable. Signal losses often create synchronization losses.

**Recommended Action** Check both ends of your cable connection. Verify that the cable and SFPs are not faulty.  
If you continue to experience synchronization loss errors, troubleshoot your host bus adapter (HBA) and contact your switch service provider.

## FW-1165

**Message** <Port Name> <Label>, is below low boundary(High=<High value>, Low=<Low value>).  
Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of synchronization losses that the port experiences has fallen below the low boundary. Loss of synchronization errors frequently occur due to a faulty small form-factor pluggable (SFP) or cable. Signal losses often create synchronization losses. A low number of synchronization losses means that the switch is functioning normally.

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1166

**Message** <Port Name> <Label>, is above high boundary(High=<High value>, Low=<Low value>).  
Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the number of synchronization losses that the port experiences has risen above the high boundary. Loss of synchronization errors frequently occur due to a faulty small form-factor pluggable (SFP) or cable. Signal losses often create synchronization losses.

**Recommended Action** Check both ends of your cable connection. Verify that the cable and SFPs are not faulty.  
If you continue to experience loss of synchronization errors, troubleshoot your host bus adapter (HBA) and contact your switch service provider.

**FW-1167**

<b>Message</b>	<Port Name> <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of synchronization losses that the port experiences has changed from a value outside of the acceptable range to a value within the acceptable range. Loss of synchronization errors frequently occur due to a faulty small form-factor pluggable (SFP) or cable. Signal losses often create synchronization losses.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1168**

<b>Message</b>	<Port Name> <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of signal losses that the port experiences has changed. Loss of signal generally indicates a physical problem.
<b>Recommended Action</b>	Check both ends of your cable connection. Verify that the cable and small form-factor pluggables (SFPs) are not faulty.

**FW-1169**

<b>Message</b>	<Port Name> <Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of signal losses that the port experiences has fallen below the low boundary. Loss of signal generally indicates a physical problem. A low number of signal loss errors means that the switch is functioning normally.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.



**FW-1170**

<b>Message</b>	<Port Name> <Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of signal losses that the port experiences has risen above the high boundary. Loss of signal generally indicates a physical problem.
<b>Recommended Action</b>	Check both ends of your cable connection. Verify that the cable is not faulty.

**FW-1171**

<b>Message</b>	<Port Name> <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of signal losses that the port experiences has changed from a value outside of the acceptable range to a value within the acceptable range. Frequent loss of signal generally indicates a physical problem.
<b>Recommended Action</b>	Check both ends of your cable connection. Verify that the cable and small form-factor pluggables (SFPs) are not faulty.

**FW-1172**

<b>Message</b>	<Port Name> <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of protocol errors that the port experiences has changed. Occasional protocol errors occur due to software glitches. Persistent protocol errors occur due to hardware problems.
<b>Recommended Action</b>	Check both ends of your cable connection. Verify that the cable and small form-factor pluggables (SFPs) are not faulty.

**FW-1173**

<b>Message</b>	<Port Name> <Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of protocol errors that the port experiences has fallen below the low boundary. Occasional protocol errors occur due to software glitches. Persistent protocol errors occur due to hardware problems. A low number of protocol errors means that the switch is functioning normally.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1174**

<b>Message</b>	<Port Name> <Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of protocol errors that the port experiences has risen above the high boundary. Occasional protocol errors occur due to software glitches. Persistent protocol errors occur due to hardware problems.
<b>Recommended Action</b>	Check both ends of your connection. Verify that your cable and small form-factor pluggables (SFPs) are not faulty.

**FW-1175**

<b>Message</b>	<Port Name> <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of protocol errors that the port experiences has changed from a value outside of the acceptable range to a value within the acceptable range. Occasional protocol errors occur due to software glitches. Persistent protocol errors occur due to hardware problems.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1176**

<b>Message</b>	<Port Name> <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of invalid words that the port experiences has changed. Invalid words usually indicate a hardware problem with a small form-factor pluggable (SFP) or cable.
<b>Recommended Action</b>	Verify that both ends of the connections, the SFP, and the cable are not faulty.

**FW-1177**

<b>Message</b>	<Port Name> <Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of invalid words that the port experiences has fallen below the low boundary. Invalid words usually indicate a hardware problem with a small form-factor pluggable (SFP) or cable. A low number of invalid words means that the switch is functioning normally.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1178**

<b>Message</b>	<Port Name> <Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of invalid words that the port experiences has risen above the high boundary. Invalid words usually indicate a hardware problem with a small form-factor pluggable (SFP) or cable.
<b>Recommended Action</b>	Verify that both ends of the connections, the SFP, and the cable are not faulty.

**FW-1179**

<b>Message</b>	<Port Name> <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of invalid words that the port experiences has changed from a value outside of the acceptable range to a value within the acceptable range. Invalid words usually indicate a hardware problem with a small form-factor pluggable (SFP) or cable.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1180**

<b>Message</b>	<Port Name> <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of invalid cyclic redundancy checks (CRCs) that the port experiences has changed. Frequent fluctuations in CRC errors generally indicate an aging fabric.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.  Check your small form-factor pluggables (SFPs), cables, and connections for faulty hardware. Verify that all optical hardware is clean.

**FW-1181**

<b>Message</b>	<Port Name> <Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of invalid cyclic redundancy checks (CRCs) that the port experiences has fallen below the low boundary. A low number of invalid CRCs means that the switch is functioning normally.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1182**

<b>Message</b>	<Port Name> <Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of invalid cyclic redundancy checks (CRCs) that the port experiences has risen above the high boundary. This error generally indicates a deteriorating fabric hardware.
<b>Recommended Action</b>	Check your small form-factor pluggables (SFPs), cables, and connections for faulty hardware. Verify that all optical hardware is clean.

**FW-1183**

<b>Message</b>	<Port Name> <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of invalid cyclic redundancy checks (CRCs) that the port experiences has changed from a value outside of the acceptable range to a value within the acceptable range. Frequent fluctuations in CRC errors generally indicate an aging fabric.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation. Check your small form-factor pluggables (SFPs), cables, and connections for faulty hardware. Verify that all optical hardware is clean.

**FW-1184**

<b>Message</b>	<Port Name> <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the percentage of incoming traffic that the port experiences has changed.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1185**

<b>Message</b>	<Port Name> <Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the percentage of incoming traffic that the port experiences has fallen below the low boundary.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1186**

<b>Message</b>	<Port Name> <Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the percentage of incoming traffic that the port experiences has risen above the high boundary.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1187**

<b>Message</b>	<Port Name> <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the percentage of incoming traffic that the port experiences has changed from a value outside of the acceptable range to a value within the acceptable range.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1188**

<b>Message</b>	<Port Name> <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the percentage of outgoing traffic that the port experiences has changed.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1189**

<b>Message</b>	<Port Name> <Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the percentage of outgoing traffic that the port experiences has fallen below the low boundary.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1190**

<b>Message</b>	<Port Name> <Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the packet loss and utilization areas for VE_Port has risen above the high boundary.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1191**

<b>Message</b>	<Port Name> <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the percentage of outgoing traffic that the port experiences has changed from a value outside of the acceptable range to a value within the acceptable range.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1192**

<b>Message</b>	<Port Name> <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of state changes that the port experiences has changed. The state of the port has changed for one of the following reasons: the port has gone offline, has come online, is testing, is faulty, has become an E_Port, has become an F_Port, has segmented, or has become a trunk port.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1193**

<b>Message</b>	<Port Name> <Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of state changes that the port experiences has fallen below the low boundary. The state of the port has changed for one of the following reasons: the port has gone offline, has come online, is testing, is faulty, has become an E_Port, has become an F_Port, has segmented, or has become a trunk port.  A low number of port state changes means that the switch is functioning normally.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.



**FW-1194**

<b>Message</b>	<Port Name> <Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of state changes that the port experiences has risen above the high boundary. The state of the port has changed for one of the following reasons: the port has gone offline, has come online, is testing, is faulty, has become an E_Port, has become an F_Port, has segmented, or has become a trunk port.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1195**

<b>Message</b>	<Port Name> <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of state changes that the port experiences has changed from a value outside of the acceptable range to a value within the acceptable range. The state of the port has changed for one of the following reasons: the port has gone offline, has come online, is testing, is faulty, has become an E_Port, has become an F_Port, has segmented, or has become a trunk port.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1196**

<b>Message</b>	<Port Name> <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of link resets that the port experiences has changed. Link resets occur due to link timeout errors that indicate no frame activity.
<b>Recommended Action</b>	Check both ends of your cable connection. Verify if the cable and small form-factor pluggables (SFPs) are faulty.

**FW-1197**

<b>Message</b>	<Port Name> <Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of link resets that the port experiences has fallen below the low boundary level. Link resets occur due to link timeout errors that indicate no frame activity. A low number of link resets means that the switch is functioning normally.
<b>Recommended Action</b>	Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1198**

<b>Message</b>	<Port Name> <Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of link resets that the port experiences has increased above the high boundary level. Link resets occur due to link timeout errors that indicate no frame activity. Both physical and hardware problems can cause link resets to increase.
<b>Recommended Action</b>	Check both ends of your cable connection. Verify if the cable and small form-factor pluggables (SFPs) are faulty.

**FW-1199**

<b>Message</b>	<Port Name> <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of link resets that the port experiences has changed from a value beyond the acceptable range to a value within the acceptable range. Link resets occur due to link timeout errors that indicate no frame activity. Both physical and hardware problems can cause link resets to increase.
<b>Recommended Action</b>	Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1200

<b>Message</b>	<Port Name> <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of C3 transmit timeout frames has changed.
<b>Recommended Action</b>	Check the target device; it could be slow.

## FW-1201

<b>Message</b>	<Port Name> <Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of C3 transmit timeout frames is below the low threshold. A low number of C3 transmit timeout means that the switch is functioning normally.
<b>Recommended Action</b>	Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1202

<b>Message</b>	<Port Name> <Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FW
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the number of C3 transmit timeout frames is above the high threshold.
<b>Recommended Action</b>	Check the target device; it could be slow.

## FW-1203

<b>Message</b>	<Port Name> <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of C3 transmit timeout frames is between the high and low thresholds.
<b>Recommended Action</b>	Check the target device; it could be slow.

## FW-1204

<b>Message</b>	<Port Name> <Label> value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the trunk utilization has changed.
<b>Recommended Action</b>	No action is required.

## FW-1205

<b>Message</b>	<Port Name> <Label> is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the trunk utilization has reduced below the low boundary threshold.
<b>Recommended Action</b>	No action is required.

## FW-1206

<b>Message</b>	<Port Name> <Label> is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the trunk utilization is above its threshold level.
<b>Recommended Action</b>	Increase the bandwidth by adding more links to the trunk.

## FW-1207

<b>Message</b>	<Port Name> <Label> is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the trunk utilization is between the low and high thresholds.
<b>Recommended Action</b>	No action is required.

## FW-1216

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of Arbitrated Loop Physical Address (ALPA) cyclic redundancy check (CRC) errors has changed. This indicates that errors have been detected in the FC frame. Invalid CRC messages occur when the number of CRC errors in Fibre Channel frames for specific source ID (S_ID) and destination ID (D_ID) pairs change. These messages might also be caused by dirty equipment, temperature fluctuations, and aging equipment. You should set your high boundaries to five- or six-digit figures, because only large numbers of messages indicate a problem in this area.
<b>Recommended Action</b>	Verify that your optical components are clean and function properly. Replace deteriorating cables or small form-factor pluggables (SFPs). Check for damage from heat or age.

**FW-1217**

**Message** <Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of Arbitrated Loop Physical Address (ALPA) cyclic redundancy check (CRC) errors has fallen below the low boundary. This indicates that errors have been detected in the FC frame. Invalid CRC messages occur when the number of CRC errors in Fibre Channel frames for specific source ID (S\_ID) and destination ID (D\_ID) pairs change. These messages might also be caused by dirty equipment, temperature fluctuations, and aging equipment. You should set your high boundaries to five- or six-digit figures, because only large numbers of messages indicate a problem in this area.

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation. A low level of invalid CRC errors means that the switch is functioning normally.

**FW-1218**

**Message** <Label>, is above high boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the number of cyclic redundancy check (CRC) errors has risen above the high boundary. This indicates that errors have been detected in the FC frame. Invalid CRC messages occur when the number of CRC errors in Fibre Channel frames for specific source ID (S\_ID) and destination ID (D\_ID) pairs change. These messages might also be caused by dirty equipment, temperature fluctuations, and aging equipment. You should set your high boundaries to five- or six-digit figures, because only large numbers of messages indicate a problem in this area.

**Recommended Action** You should configure a five- or six-figure high boundary for this area. Only five-figure (or higher) values for CRC errors indicate problems. Check for a faulty cable or deteriorated small form-factor pluggable (SFP). Replace the cable or the SFP if necessary. Clean the connectors. Check for damage from heat or deterioration from age.

## FW-1219

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of cyclic redundancy check (CRC) errors has changed from a value outside of the acceptable range to a value within the acceptable range. This indicates that errors have been detected in the FC frame. Invalid CRC messages occur when the number of CRC errors in Fibre Channel frames for specific source ID (S_ID) and destination ID (D_ID) pairs change. These messages might also be caused by dirty equipment, temperature fluctuations, and aging equipment. You should set your high boundaries to five- or six-digit figures, because only large numbers of messages indicate a problem in this area.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1240

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of end-to-end cyclic redundancy check (CRC) errors has changed. Invalid CRC messages occur when the number of CRC errors in Fibre Channel frames for specific source ID (S_ID) and destination ID (D_ID) pairs change. These messages might also be caused by dirty equipment, temperature fluctuations, and aging equipment.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1241

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of end-to-end cyclic redundancy check (CRC) errors has fallen below the low boundary. Invalid CRC messages occur when the number of CRC errors in Fibre Channel frames for specific source ID (S_ID) and destination ID (D_ID) pairs change. These messages might also be caused by dirty equipment, temperature fluctuations, and aging equipment.

## 5 FW-1242

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation. A low number of CRC errors means that the fabric is functioning normally. The CRC error area of the end-to-end performance monitor class helps you tune the fabric. To reduce CRC messages, experiment with alternative topologies and cabling schemes.

### FW-1242

**Message** <Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the number of end-to-end cyclic redundancy check (CRC) errors has risen above the high boundary. Invalid CRC messages occur when the number of CRC errors in Fibre Channel frames for specific source ID (S\_ID) and destination ID (D\_ID) pairs change. These messages might also be caused by dirty equipment, temperature fluctuations, and aging equipment.

**Recommended Action** The CRC error area of the end-to-end performance monitor class helps you tune the fabric. To reduce CRC errors, experiment with alternative topologies and cabling schemes. Clean equipment, check temperatures, and replace old hardware.

### FW-1243

**Message** <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of end-to-end cyclic redundancy check (CRC) errors has changed from a value outside of the acceptable range to a value within the acceptable range. Invalid CRC messages occur when the number of CRC errors in Fibre Channel frames for specific source ID (S\_ID) and destination ID (D\_ID) pairs change. These messages might also be caused by dirty equipment, temperature fluctuations, and aging equipment.

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.



## FW-1244

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of end-to-end word frames that the switch receives has changed. Receive performance messages appear due to the number of word frames that travel from the configured S_ID to the D_ID pair.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1245

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of end-to-end word frames that the switch receives has fallen below the low boundary. Receive performance messages appear due to the number of word frames that travel from the configured S_ID to the D_ID pair.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1246

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of end-to-end word frames that the switch receives has risen above the high boundary. Receive performance messages appear due to the number of word frames that travel from the configured S_ID to the D_ID pair.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1247

<b>Message</b>	<Label>, is between high and low boundaries (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of end-to-end word frames that the switch receives has changed from a value outside of the acceptable range to a value within the acceptable range. Receive performance messages appear due to the number of word frames that travel from the configured S_ID to the D_ID pair.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1248

<b>Message</b>	<Label>, value has changed (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of end-to-end word frames that the switch transmits has changed. Transmit performance messages appear due to the number of word frames that travel from the configured S_ID to the D_ID pair.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1249

<b>Message</b>	<Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of end-to-end word frames that the switch transmits has fallen below the low boundary. Transmit performance messages appear due to the number of word frames that travel from the configured S_ID to the D_ID pair.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1250

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of end-to-end word frames that the switch transmits has risen above the high boundary. Transmit performance messages appear due to the number of word frames that travel from the configured S_ID to the D_ID pair.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1251

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of end-to-end word frames that the switch transmits has changed from a value outside of the acceptable range to a value within the acceptable range. Transmit performance messages appear due to the number of word frames that travel from the configured S_ID to the D_ID pair.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1272

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of frame types or commands that the port receives has changed. The port has received Small Computer System Interface (SCSI) Read, SCSI Write, SCSI Read and Write, SCSI Traffic, or IP commands in a frame.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1273**

<b>Message</b>	<Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of frame types or commands that the port receives has fallen below the low boundary. The port has received a Small Computer System Interface (SCSI) Read, SCSI Write, SCSI Read and Write, SCSI Traffic, or IP commands in a frame.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1274**

<b>Message</b>	<Label>, is above high boundary (High=<Filter Counter>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FW
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of frame types or commands that the port receives has risen above the high boundary. The port has received a Small Computer System Interface (SCSI) Read, SCSI Write, SCSI Read and Write, SCSI Traffic, or IP commands in a frame.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1275**

<b>Message</b>	<Label>, is between high and low boundaries (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of frame types or commands that the port receives has changed from a value outside of the acceptable range to a value within the acceptable range. The port has received a Small Computer System Interface (SCSI) Read, SCSI Write, SCSI Read and Write, SCSI Traffic, or IP commands in a frame.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1296

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of Telnet violations has changed. Telnet violations indicate that a Telnet connection request has been received from an unauthorized IP address. The TELNET_POLICY contains a list of IP addresses that are authorized to establish Telnet connections to switches in the fabric.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the IP address that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1297

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of Telnet violations has fallen below the low boundary. Telnet violations indicate that a Telnet connection request has been received from an unauthorized IP address. The TELNET_POLICY contains a list of IP addresses that are authorized to establish Telnet connections to switches in the fabric.
<b>Recommended Action</b>	No action is required.

## FW-1298

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of Telnet violations has risen above the high boundary. Telnet violations indicate that a Telnet connection request has been received from an unauthorized IP address. The TELNET_POLICY contains a list of IP addresses that are authorized to establish Telnet connections to switches in the fabric.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the IP address that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1299

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of Telnet violations has changed from a value outside of the acceptable range to a value within the acceptable range. Telnet violations indicate that a Telnet connection request has been received from an unauthorized IP address. The TELNET_POLICY contains a list of IP addresses that are authorized to establish Telnet connections to switches in the fabric.
<b>Recommended Action</b>	No action is required.

## FW-1300

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of Hypertext Transfer Protocol (HTTP) violations has changed. HTTP violations indicate that a browser connection request has been received from an unauthorized IP address. The HTTP_POLICY contains a list of IP addresses that are authorized to establish browser connections to the switches in the fabric.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the IP address that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1301

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of Hypertext Transfer Protocol (HTTP) violations has fallen below the low boundary. HTTP violations indicate that a browser connection request has been received from an unauthorized IP address. The HTTP_POLICY contains a list of IP addresses that are authorized to establish browser connections to the switches in the fabric.
<b>Recommended Action</b>	No action is required.

## FW-1302

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of Hypertext Transfer Protocol (HTTP) violations has risen above the high boundary. HTTP violations indicate that a browser connection request has been received from an unauthorized IP address. The HTTP_POLICY contains a list of IP addresses that are authorized to establish browser connections to the switches in the fabric.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the IP address that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1303

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of Hypertext Transfer Protocol (HTTP) violations has changed from a value outside of the acceptable range to a value within the acceptable range. HTTP violations indicate that a browser connection request has been received from an unauthorized IP address. The HTTP_POLICY contains a list of IP addresses that are authorized to establish browser connections to the switches in the fabric.
<b>Recommended Action</b>	No action is required.

## FW-1304

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of application programming interface (API) violations has changed. API violations indicate that an API connection request has been received from an unauthorized IP address. The Simple Network Management Protocol policy (SNMP_POLICY) contains a list of IP addresses that are authorized to establish API connections to switches in the fabric.

## 5 FW-1305

**Recommended Action** Execute the **errShow** command to determine the IP address that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

### FW-1305

**Message** <Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of application programming interface (API) violations has fallen below the low boundary. API violations indicate that an API connection request has been received from an unauthorized IP address. The Simple Network Management Protocol policy (SNMP\_POLICY) contains a list of IP addresses that are authorized to establish API connections to switches in the fabric.

**Recommended Action** No action is required.

### FW-1306

**Message** <Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the number of application programming interface (API) violations has risen above the high boundary. API violations indicate that an API connection request has been received from an unauthorized IP address. The Simple Network Management Protocol policy (SNMP\_POLICY) contains a list of IP addresses that are authorized to establish API connections to switches in the fabric.

**Recommended Action** Execute the **errShow** command to determine the IP address that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.



## FW-1307

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of application programming interface (API) violations has changed from a value outside of the acceptable range to a value within the acceptable range. API violations indicate that an API connection request has been received from an unauthorized IP address. The Simple Network Management Protocol policy (SNMP_POLICY) contains a list of IP addresses that are authorized to establish API connections to switches in the fabric.
<b>Recommended Action</b>	No action is required.

## FW-1308

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of read SNMP (RSNMP) violations has changed. RSNMP violations indicate that an SNMP "get" operation request has been received from an unauthorized IP address.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the IP address that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1309

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of read SNMP (RSNMP) violations has fallen below the low boundary. RSNMP violations indicate that an SNMP "get" operation request has been received from an unauthorized IP address.
<b>Recommended Action</b>	No action is required.

**FW-1310**

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of read SNMP (RSNMP) violations has risen above the high boundary. RSNMP violations indicate that an SNMP "get" operation request has been received from an unauthorized IP address.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the IP address that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

**FW-1311**

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of read SNMP (RSNMP) violations has changed from a value outside of the acceptable range to a value within the acceptable range. RSNMP violations indicate that an SNMP "get" operation request has been received from an unauthorized IP address.
<b>Recommended Action</b>	No action is required.

**FW-1312**

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of write SNMP (WSNMP) violations has changed. WSNMP violations indicate that an SNMP "get/set" operation request has been received from an unauthorized IP address.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the IP address that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1313

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of write SNMP (WSNMP) violations has fallen below the low boundary. WSNMP violations indicate that an SNMP "get/set" operation request has been received from an unauthorized IP address.
<b>Recommended Action</b>	No action is required.

## FW-1314

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of write SNMP (WSNMP) violations has risen above the high boundary. WSNMP violations indicate that an SNMP "get/set" operation request has been received from an unauthorized IP address.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the IP address that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1315

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of write SNMP (WSNMP) violations has changed from a value outside of the acceptable range to a value within the acceptable range. WSNMP violations indicate that an SNMP "get/set" operation request has been received from an unauthorized IP address.
<b>Recommended Action</b>	No action is required.

## FW-1316

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of SCSI Enclosure Services (SES) violations has changed. SES violations indicate that a Small Computer System Interface (SCSI) Enclosure Services request has been received from an unauthorized World Wide Name (WWN). The SES_POLICY contains a list of WWNs of device ports that are allowed to access the SES Server functionality.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the IP address that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1317

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of SCSI Enclosure Services (SES) violations has fallen below the low boundary. SES violations indicate that a Small Computer System Interface (SCSI) Enclosure Services request has been received from an unauthorized World Wide Name (WWN). The SES_POLICY contains a list of WWNs of device ports that are allowed to access the SES Server functionality.
<b>Recommended Action</b>	No action is required.

## FW-1318

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of SCSI Enclosure Services (SES) violations has risen above the high boundary. SES violations indicate that a Small Computer System Interface (SCSI) Enclosure Services request has been received from an unauthorized World Wide Name (WWN). The SES_POLICY contains a list of WWNs of device ports that are allowed to access the SES Server functionality.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the WWN of the device that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1319

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of SCSI Enclosure Services (SES) violations has changed from a value outside of the acceptable range to a value within the acceptable range. SES violations indicate that a Small Computer System Interface (SCSI) Enclosure Services (SES) request has been received from an unauthorized World Wide Name (WWN). The SES_POLICY contains a list of WWNs of device ports that are allowed to access the SES Server functionality.
<b>Recommended Action</b>	No action is required.

## FW-1320

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of Management Server (MS) violations has changed. MS violations indicate that an MS access request has been received from an unauthorized World Wide Name (WWN). The MS_POLICY contains a list of WWNs of device ports that are allowed to access the Management Server functionality.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the WWN of the device that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1321

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of Management Server (MS) violations has fallen below the low boundary. MS violations indicate that an MS access request has been received from an unauthorized World Wide Name (WWN). The MS_POLICY contains a list of WWNs of device ports that are allowed to access the Management Server functionality.
<b>Recommended Action</b>	No action is required.

## FW-1322

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of Management Server (MS) violations has risen above the high boundary. MS violations indicate that an MS access request has been received from an unauthorized World Wide Name (WWN). The MS_POLICY contains a list of WWNs of device ports that are allowed to access the Management Server functionality.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the WWN of the device that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1323

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of Management Server (MS) violations has changed from a value outside of the acceptable range to a value within the acceptable range. MS violations indicate that an MS access request has been received from an unauthorized World Wide Name (WWN). The MS_POLICY contains a list of WWNs of device ports that are allowed to access the Management Server functionality.
<b>Recommended Action</b>	No action is required.

## FW-1324

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of serial violations has changed. Serial violations indicate that an unauthorized serial port request has been received. The SERIAL_POLICY contains a list of switch World Wide Names (WWNs) for which serial port access is enabled.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the WWN of the device that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1325

<b>Message</b>	<Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of serial violations has fallen below the low boundary. Serial violations indicate that an unauthorized serial port request has been received. The SERIAL_POLICY contains a list of switch World Wide Names (WWNs) for which serial port access is enabled.
<b>Recommended Action</b>	No action is required.

## FW-1326

<b>Message</b>	<Label>, is above high boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of serial violations has risen above the high boundary. Serial violations indicate that an unauthorized serial port request has been received. The SERIAL_POLICY contains a list of switch World Wide Names (WWNs) for which serial port access is enabled.
<b>Recommended Action</b>	Run the <b>errShow</b> command to determine the WWN of the device that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1327

<b>Message</b>	<Label>, is between high and low boundaries (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of serial violations has changed from a value outside of the acceptable range to a value within the acceptable range. Serial violations indicate that an unauthorized serial port request has been received. The SERIAL_POLICY contains a list of switch World Wide Names (WWNs) for which serial port access is enabled.
<b>Recommended Action</b>	No action is required.

## FW-1328

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of front panel violations has changed. Front panel violations indicate that an unauthorized front panel request has been received. The FRONT_PANEL_POLICY contains a list of switch World Wide Names (WWNs) for which front panel access is enabled.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the WWN of the device that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1329

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of front panel violations has fallen below the low boundary. Front panel violations indicate that an unauthorized front panel request has been received. The FRONT_PANEL_POLICY contains a list of switch World Wide Names (WWNs) for which front panel access is enabled.
<b>Recommended Action</b>	No action is required.

## FW-1330

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of front panel violations has risen above the high boundary. Front panel violations indicate that an unauthorized front panel request has been received. The FRONT_PANEL_POLICY contains a list of switch World Wide Names (WWNs) for which front panel access is enabled.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the WWN of the device that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.



## FW-1331

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of front panel violations has changed from a value outside of the acceptable range to a value within the acceptable range. Front panel violations indicate that an unauthorized front panel request has been received. The FRONTPANEL_POLICY contains a list of switch World Wide Names (WWNs) for which front panel access is enabled.
<b>Recommended Action</b>	No action is required.

## FW-1332

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of Switch Connection Control (SCC) policy violations has changed. SCC violations indicate that an unauthorized switch tried to join the fabric. The SCC_POLICY contains a list of switches by World Wide Name (WWN) that are allowed to be members of a fabric.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the WWN of the device that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1333

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of Switch Connection Control (SCC) policy violations has fallen below the low boundary. SCC violations indicate that an unauthorized switch tried to join the fabric. The SCC_POLICY contains a list of switches by World Wide Name (WWN) that are allowed to be members of a fabric.
<b>Recommended Action</b>	No action is required.

## FW-1334

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of Switch Connection Control (SCC) policy violations has risen above the high boundary. SCC violations indicate that an unauthorized switch tried to join the fabric. The SCC_POLICY contains a list of switches by World Wide Name (WWN) that are allowed to be members of a fabric.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the WWN of the device that sent the request. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1335

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of Switch Connection Control (SCC) policy violations has changed from a value outside of the acceptable range to a value within the acceptable range. SCC violations indicate that an unauthorized switch tried to join the fabric. The SCC_POLICY contains a list of switches by World Wide Name (WWN) that are allowed to be members of a fabric.
<b>Recommended Action</b>	No action is required.

## FW-1336

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of Device Connection Control (DCC) violations has changed. DCC violations indicate that an unauthorized device tried to join the fabric. The DCC_POLICY allows for the specification of rules for binding device ports (typically HBA ports) to specific switch ports. DCC policies ensure that whenever a device performs a fabric login (FLOGI) request, the World Wide Name (WWN) specified in the FLOGI is validated to be connected to the authorized port. Enforcement for private loop devices not performing FLOGI is done through the name server.

**Recommended Action** Execute the **errShow** command to determine the device WWN, switch WWN, and switch port. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1337

**Message** <Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of Device Connection Control (DCC) violations has fallen below the low boundary. DCC violations indicate that an unauthorized device tried to join the fabric. The DCC\_POLICY allows for the specification of rules for binding device ports (typically HBA ports) to specific switch ports. DCC policies ensure that whenever a device performs a fabric login (FLOGI) request, the World Wide Name (WWN) specified in the FLOGI is validated to be connected to the authorized port. Enforcement for private loop devices not performing FLOGI is done through the name server.

**Recommended Action** No action is required.

## FW-1338

**Message** <Label>, is above high boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the number of Device Connection Control (DCC) violations has risen above the high boundary. DCC violations indicate that an unauthorized device tried to join the fabric. The DCC\_POLICY allows for the specification of rules for binding device ports (typically HBA ports) to specific switch ports. DCC policies ensure that whenever a device performs a fabric login (FLOGI) request, the World Wide Name (WWN) specified in the FLOGI is validated to be connected to the authorized port. Enforcement for private loop devices not performing FLOGI is done through the name server.

**Recommended Action** Execute the **errShow** command to determine the device WWN, switch WWN, and switch port. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1339

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of Device Connection Control (DCC) violations has changed from a value outside of the acceptable range to a value within the acceptable range. DCC violations indicate that an unauthorized device tried to join the fabric. The DCC_POLICY allows for the specification of rules for binding device ports (typically HBA ports) to specific switch ports. DCC policies ensure that whenever a device performs a fabric login (FLOGI) request, the World Wide Name (WWN) specified in the FLOGI is validated to be connected to the authorized port. Enforcement for private loop devices not performing FLOGI is done through the name server.
<b>Recommended Action</b>	No action is required.

## FW-1340

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of login violations has changed. Login violations indicate that a login failure has been detected.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the IP location of the login attempt. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1341

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of login violations has fallen below the low boundary. Login violations indicate that a login failure has been detected.
<b>Recommended Action</b>	No action is required.

## FW-1342

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of login violations has risen above the high boundary. Login violations indicate that a login failure has been detected.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to determine the IP location of the login attempt. Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1343

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of login violations has changed from a value outside of the acceptable range to a value within the acceptable range. Login violations indicate that a login failure has been detected.
<b>Recommended Action</b>	No action is required.

## FW-1344

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of invalid timestamps has changed. Invalid timestamp violations indicate that a packet with an invalid timestamp has been received from the primary fabric configuration server (FCS). When the primary FCS downloads a new configuration to other switches in the fabric, the packet is tagged with a timestamp. The receiving switch compares this timestamp to its current time. If the difference is too great, it rejects the packet. This counter keeps track of packets rejected due to invalid timestamps.
<b>Recommended Action</b>	Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

**FW-1345**

**Message** <Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of invalid timestamps has fallen below the low boundary. Invalid timestamp violations indicate a packet with an invalid timestamp has been received from the primary fabric configuration server (FCS). When the primary FCS downloads a new configuration to other switches in the fabric, the packet is tagged with a timestamp. The receiving switch compares this timestamp to its current time. If the difference is too great, it rejects the packet. This counter keeps track of packets rejected due to invalid timestamps.

**Recommended Action** No action is required.

**FW-1346**

**Message** <Label>, is above high boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the number of invalid timestamps has risen above the high boundary. Invalid timestamp violations indicate a packet with an invalid timestamp has been received from the primary fabric configuration server (FCS). When the primary FCS downloads a new configuration to other switches in the fabric, the packet is tagged with a timestamp. The receiving switch compares this timestamp to its current time. If the difference is too great, it rejects the packet. This counter keeps track of packets rejected due to invalid timestamps.

**Recommended Action** Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1347

**Message** <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of invalid timestamps has changed from a value outside of the acceptable range to a value within the acceptable range. Invalid timestamp violations indicate a packet with an invalid timestamp has been received from the primary fabric configuration server (FCS). When the primary FCS downloads a new configuration to other switches in the fabric, the packet is tagged with a timestamp. The receiving switch compares this timestamp to its current time. If the difference is too great, it rejects the packet. This counter keeps track of packets rejected due to invalid timestamps.

**Recommended Action** No action is required.

## FW-1348

**Message** <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of invalid signatures has changed. Invalid signature violations indicate that a packet with an invalid signature has been received from the primary fabric configuration server (FCS). When the primary FCS downloads a new configuration to the other switches in the fabric, the packet is signed using the private key of the primary FCS. The receiving switch must verify this signature with the public key of the primary FCS switch. If verification fails, it rejects the packet. This counter keeps track of the number of packets received with invalid signatures.

**Recommended Action** Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

**FW-1349**

**Message** <Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of invalid signatures has fallen below the low boundary. Invalid signature violations indicate that a packet with an invalid signature has been received from the primary fabric configuration server (FCS). When the primary FCS downloads a new configuration to the other switches in the fabric, the packet is signed using the private key of the primary FCS. The receiving switch must verify this signature with the public key of the primary FCS switch. If verification fails, it rejects the packet. This counter keeps track of the number of packets received with invalid signatures.

**Recommended Action** No action is required.

**FW-1350**

**Message** <Label>, is above high boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the number of invalid signatures has risen above the high boundary. Invalid signature violations indicate that a packet with an invalid signature has been received from the primary fabric configuration server (FCS). When the primary FCS downloads a new configuration to the other switches in the fabric, the packet is signed using the private key of the primary FCS. The receiving switch must verify this signature with the public key of the primary FCS switch. If verification fails, it rejects the packet. This counter keeps track of the number of packets received with invalid signatures.

**Recommended Action** Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.



## FW-1351

**Message** <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of invalid signatures has changed from a value outside of the acceptable range to a value within the acceptable range. Invalid signature violations indicate that a packet with an invalid signature has been received from the primary fabric configuration server (FCS). When the primary FCS downloads a new configuration to the other switches in the fabric, the packet is signed using the private key of the primary FCS. The receiving switch must verify this signature with the public key of the primary FCS switch. If verification fails, it rejects the packet. This counter keeps track of the number of packets received with invalid signatures.

**Recommended Action** No action is required.

## FW-1352

**Message** <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of invalid certificates has changed. This violation indicates that a packet with an invalid certificate has been received from the primary fabric configuration server (FCS). Before a new primary FCS switch sends any configuration data to any switch in the fabric, it first sends its certificate to all the switches in the fabric. The receiving switch must verify that the sender is the primary FCS switch and its certificate is signed by the Root CA recognized by the receiving switch. This counter keeps track of the number of packets received with invalid certificates.

**Recommended Action** Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1353

**Message** <Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of invalid certificates has fallen below the low boundary. This violation indicates that a packet with an invalid certificate has been received from the primary fabric configuration server (FCS). Before a new primary FCS switch sends any configuration data to any switch in the fabric, it first sends its certificate to all the switches in the fabric. The receiving switch must verify that the sender is the primary FCS switch and its certificate is signed by the Root CA recognized by the receiving switch. This counter keeps track of the number of packets received with invalid certificates.

**Recommended Action** No action is required.

## FW-1354

**Message** <Label>, is above high boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the number of invalid certificates has risen above the high boundary. This violation indicates that a packet with an invalid certificate has been received from the primary fabric configuration server (FCS). Before a new primary FCS switch sends any configuration data to any switch in the fabric, it first sends its certificate to all the switches in the fabric. The receiving switch must verify that the sender is the primary FCS switch and its certificate is signed by the Root CA recognized by the receiving switch. This counter keeps track of the number of packets received with invalid certificates.

**Recommended Action** Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1355

**Message** <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of invalid certificates has changed from a value outside of the acceptable range to a value within the acceptable range. This violation indicates that a packet with an invalid certificate has been received from the primary fabric configuration server (FCS). Before a new primary FCS switch sends any configuration data to any switch in the fabric, it first sends its certificate to all the switches in the fabric. The receiving switch has to verify that the sender is the primary FCS switch and its certificate is signed by the Root CA recognized by the receiving switch. This counter keeps track of the number of packets received with invalid certificates.

**Recommended Action** No action is required.

## FW-1356

**Message** <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of authentication failures has changed. Authentication failures can occur for many reasons. The switch on the other side may not support the protocol, have an invalid certificate, not be signed properly, or send unexpected packets. The port where authentication fails is segmented. This counter keeps track of the number of authentication failures.

**Recommended Action** Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1357

**Message** <Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of authentication failures has fallen below the low boundary. Authentication failures can occur for many reasons. The switch on the other side may not support the protocol, have an invalid certificate, not be signed properly, or send unexpected packets. The port where authentication fails is segmented. This counter keeps track of the number of authentication failures.

## 5 FW-1358

**Recommended Action** No action is required.

### FW-1358

**Message** <Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the number of authentication failures has risen above the high boundary. Authentication failures can occur for many reasons. The switch on the other side may not support the protocol, have an invalid certificate, not be signed properly, or send unexpected packets. The port where authentication fails is segmented. This counter keeps track of the number of authentication failures.

**Recommended Action** Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

### FW-1359

**Message** <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of authentication failures has changed from a value outside of the acceptable range to a value within the acceptable range. Authentication failures can occur for many reasons. The switch on the other side might not support the protocol, have an invalid certificate, not be signed properly, or send unexpected packets. The port where authentication fails is segmented. This counter keeps track of the number of authentication failures.

**Recommended Action** No action is required.

### FW-1360

**Message** <Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of Switch Link Authentication Protocol (SLAP) faulty packets has changed. This counter keeps track of the number of unexpected SLAP packets and SLAP packets with faulty transmission IDs.

**Recommended Action** Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1361

**Message** <Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of switch link authentication protocol (SLAP) faulty packets has fallen below the low boundary. This counter keeps track of the number of unexpected SLAP packets and SLAP packets with faulty transmission IDs.

**Recommended Action** No action is required.

## FW-1362

**Message** <Label>, is above high boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the number of Switch Link Authentication Protocol (SLAP) faulty packets has risen above the high boundary. This counter keeps track of the number of unexpected SLAP packets and SLAP packets with faulty transmission IDs.

**Recommended Action** Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1363

**Message** <Label>, is between high and low boundaries (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of Switch Link Authentication Protocol (SLAP) faulty packets has changed from a value outside of the acceptable range to a value within the acceptable range. This counter keeps track of the number of unexpected SLAP packets and SLAP packets with faulty transmission IDs.

**Recommended Action** No action is required.

**FW-1364**

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of time service (TS) out-of-sync violations has changed.
<b>Recommended Action</b>	Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

**FW-1365**

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of time service (TS) out-of-sync violations has fallen below the low boundary.
<b>Recommended Action</b>	No action is required.

**FW-1366**

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of time service (TS) out-of-sync violations has risen above the high boundary.
<b>Recommended Action</b>	Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1367

<b>Message</b>	<Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of time service (TS) out-of-sync violations has changed from a value outside of the acceptable range to a value within the acceptable range.
<b>Recommended Action</b>	No action is required.

## FW-1368

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of no-FCS violations has changed. This counter records how often the switch loses contact with the primary fabric configuration server (FCS) switch. When the primary FCS switch in the fabric sends its certificate to a switch, the receiving switch saves the World Wide Name (WWN) of that primary FCS switch. If a secure switch finds that there are no FCSs in the fabric, but it still has the WWN of the last primary FCS switch, it increments this counter and resets the WWN of the primary FCS to all zeroes.
<b>Recommended Action</b>	Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1369

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of no-FCS violations has fallen below the low boundary. This counter records how often the switch loses contact with the primary fabric configuration server (FCS) switch. When the primary FCS switch in the fabric sends its certificate to a switch, the receiving switch saves the World Wide Name (WWN) of that primary FCS switch. If a secure switch finds that there are no FCSs in the fabric, but it still has the WWN of the last primary FCS switch, it increments this counter and resets the WWN of the primary FCS to all zeroes.

## 5 FW-1370

**Recommended Action** No action is required.

### FW-1370

**Message** <Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the number of no-FCS violations has risen above the high boundary. This counter records how often the switch loses contact with the primary fabric configuration server (FCS) switch. When the primary FCS switch in the fabric sends its certificate to a switch, the receiving switch saves the World Wide Name (WWN) of that primary FCS switch. If a secure switch finds that there are no FCSs in the fabric, but it still has the WWN of the last primary FCS switch, it increments this counter and resets the WWN of the primary FCS to all zeroes.

**Recommended Action** Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

### FW-1371

**Message** <Label>, is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of no-FCS violations has changed from a value outside of the acceptable range to a value within the acceptable range. This counter records how often the switch loses contact with the primary fabric configuration server (FCS) switch. When the primary FCS switch in the fabric sends its certificate to a switch, the receiving switch saves the World Wide Name (WWN) of that primary FCS switch. If a secure switch finds that there are no FCSs in the fabric, but it still has the WWN of the last primary FCS switch, it increments this counter and resets the WWN of the primary FCS to all zeroes.

**Recommended Action** No action is required.



## FW-1372

<b>Message</b>	<Label>, value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of incompatible security database violations has changed. This violation indicates the number of secure switches with different version stamps have been detected. When a switch is in secure mode, it connects only to another switch that is in secure mode and has a compatible security database. A compatible security database means that the version stamp and fabric configuration server (FCS) policy matches exactly.
<b>Recommended Action</b>	Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1373

<b>Message</b>	<Label>, is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of incompatible security database violations has fallen below the low boundary. This violation indicates the number of secure switches with different version stamps have been detected. When a switch is in secure mode, it connects only to another switch that is in secure mode and has a compatible security database. A compatible security database means that the version stamp and fabric configuration server (FCS) policy matches exactly.
<b>Recommended Action</b>	No action is required.

## FW-1374

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the number of incompatible security database violations has risen above the high boundary. This violation indicates the number of secure switches with different version stamps have been detected. When a switch is in secure mode, it connects only to another switch that is in secure mode and has a compatible security database. A compatible security database means that the version stamp and fabric configuration server (FCS) policy matches exactly.

## 5 FW-1375

**Recommended Action** Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

### FW-1375

**Message** <Label>, is between high and low boundaries (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of incompatible security database violations has changed from a value outside of the acceptable range to a value within the acceptable range. This violation indicates the number of secure switches with different version stamps that have been detected. When a switch is in secure mode, it connects only to another switch that is in secure mode and has a compatible security database. A compatible security database means that the version stamp and fabric configuration server (FCS) policy matches exactly.

**Recommended Action** No action is required.

### FW-1376

**Message** <Label>, value has changed (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of illegal commands has changed. This counter tracks how many times commands allowed only on the primary fabric configuration server (FCS) switch have been executed on a non-primary FCS switch. There are many commands that can be executed only on the primary FCS switch, as well as one security command that can be executed only on a backup FCS switch. The counter increments every time someone issues one of these commands on a switch where it is not allowed.

**Recommended Action** Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

## FW-1377

**Message** <Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of illegal commands has fallen below the low boundary. This counter tracks how many times commands allowed only on the primary fabric configuration server (FCS) switch have been executed on a non-primary FCS switch. There are many commands that can be executed only on the primary FCS switch, as well as one security command that can be executed only on a backup FCS switch. The counter increments every time someone issues one of these commands on a switch where it is not allowed.

**Recommended Action** No action is required.

## FW-1378

**Message** <Label>, is above high boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the number of illegal commands has risen above the high boundary. This counter tracks how many times commands allowed only on the primary fabric configuration server (FCS) switch have been executed on a non-primary FCS switch. There are many commands that can be executed only on the primary FCS switch, as well as one security command that can be executed only on a backup FCS switch. The counter increments every time someone issues one of these commands on a switch where it is not allowed.

**Recommended Action** Responses to security-class messages depend on user policies. Consult your security administrator for response strategies and policies.

**FW-1379**

**Message** <Label>, is between high and low boundaries (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of illegal commands has changed from a value outside of the acceptable range to a value within the acceptable range. This counter tracks how many times commands allowed only on the primary fabric configuration server (FCS) switch have been executed on a non-primary FCS switch. There are many commands that can be executed only on the primary FCS switch, as well as one security command that can be executed only on a backup FCS switch. The counter increments every time someone issues one of these commands on a switch where it is not allowed.

**Recommended Action** No action is required.

**FW-1400**

**Message** <Label>, value has changed (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the flash memory usage percentage has changed. Flash memory increases and decreases slightly with normal operation of the switch.

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1401**

**Message** <Label>, is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the flash memory usage percentage has fallen below the low boundary. Flash memory increases and decreases slightly with normal operation of the switch.

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1402

<b>Message</b>	<Label>, is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FW
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the flash memory usage percentage has risen above the high boundary. Flash memory increases and decreases slightly with normal operation of the switch.
<b>Recommended Action</b>	Remove some unwanted files to create some flash space. Execute the <b>supportSave</b> command to remove files from the kernel space.

## FW-1403

<b>Message</b>	<Label>,is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the CPU or memory usage is between the boundary limits.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1404

<b>Message</b>	<Label>,is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FW
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the CPU or memory usage is above its threshold. If this RASLOG pertains to memory usage, then the usage is above the middle memory threshold.
<b>Recommended Action</b>	No action is required.

## FW-1405

<b>Message</b>	<Label>, is above high boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FW
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the memory usage is below the low memory threshold.
<b>Recommended Action</b>	No action is required.

## FW-1406

<b>Message</b>	<Label>, is above high boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FW
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the memory usage is above the high memory threshold.
<b>Recommended Action</b>	No action is required.

## FW-1407

<b>Message</b>	<Label>, is between high and low boundaries (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the memory usage is between the high and middle memory thresholds.
<b>Recommended Action</b>	No action is required.

## FW-1408

<b>Message</b>	<Label>, is between high and low boundaries (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the memory usage is between the low and high or middle memory thresholds.
<b>Recommended Action</b>	No action is required.

## FW-1424

<b>Message</b>	Switch status changed from <Previous state> to <Current state>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because of a policy violation.
<b>Recommended Action</b>	Execute the <b>switchStatusShow</b> command to determine the policy violation.

## FW-1425

<b>Message</b>	Switch status changed from <Bad state> to HEALTHY.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the switch status has changed to a healthy state. This occurred because a policy is no longer violated.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1426**

<b>Message</b>	Switch status change contributing factor Power supply: <Number Bad> bad, <Number Missing> absent.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because the number of faulty or missing power supplies is greater than or equal to the policy set by the <b>switchStatusPolicySet</b> command.
<b>Recommended Action</b>	Replace the faulty or missing power supply.

**FW-1427**

<b>Message</b>	Switch status change contributing factor Power supply: <Number Bad> bad.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because the number of faulty power supplies is greater than or equal to the policy set by the <b>switchStatusPolicySet</b> command.
<b>Recommended Action</b>	Replace the faulty power supply.

**FW-1428**

<b>Message</b>	Switch status change contributing factor Power supply: <Number Missing> absent.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because the number of missing power supplies is greater than or equal to the policy set by the <b>switchStatusPolicySet</b> command.
<b>Recommended Action</b>	Replace the missing power supply.



## FW-1429

<b>Message</b>	Switch status change contributing factor: Power supplies are not redundant.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because the power supplies are not in the correct slots for redundancy.
<b>Recommended Action</b>	Rearrange the power supplies so that one is in an odd slot and another in an even slot to make them redundant.

## FW-1430

<b>Message</b>	Switch status change contributing factor <string>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because the number of faulty temperature sensors is greater than or equal to the policy set by the <b>switchStatusPolicySet</b> command. A temperature sensor is faulty when the sensor value is not in the acceptable range or is faulty.
<b>Recommended Action</b>	Replace the field-replaceable unit (FRU) with the faulty temperature sensor.

## FW-1431

<b>Message</b>	Switch status change contributing factor Fan: <Number Bad> bad.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because the number of faulty fans is greater than or equal to the policy set by the <b>switchStatusPolicySet</b> command. A fan is faulty when the value is not in the acceptable range or is faulty.
<b>Recommended Action</b>	Replace the faulty or deteriorating fan field-replaceable units (FRUs).

**FW-1432**

<b>Message</b>	Switch status change contributing factor WWN: <Number Bad> bad.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because the number of faulty World Wide Name (WWN) cards is greater than or equal to the policy set by the <b>switchStatusPolicySet</b> command.
<b>Recommended Action</b>	Replace the faulty WWN card.

**FW-1433**

<b>Message</b>	Switch status change contributing factor CP: CP non-redundant (<CP Number>) faulty.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because the number of faulty CPs is greater than or equal to the policy set by the <b>switchStatusPolicySet</b> command. The CPs are not redundant.  If you power cycle a chassis in dual-domain configuration, and then reset the micro-switch of the active CP before the heartbeat is up, this will cause both CPs to come up in a non-redundant state.
<b>Recommended Action</b>	Execute the <b>firmwareShow</b> command to verify if both the CPs have compatible firmware levels. Execute the <b>firmwareDownload</b> command to install the same level of firmware to both CPs. Replace any faulty CPs.  If you reset the micro-switch (the latch on the CP blade) on the active CP before the heartbeat was up on a power cycle, and the CPs came up non-redundant, then you should reboot the CPs again to clear the problem.

**FW-1434**

<b>Message</b>	Switch status change contributing factor Blade: <Number Bad> blade failures (<Blade Numbers>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because the number of blade failures is greater than or equal to the policy set by the <b>switchStatusPolicySet</b> command.
<b>Recommended Action</b>	Replace the faulty blade.

## FW-1435

<b>Message</b>	Switch status change contributing factor Flash: usage out of range.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because the flash memory usage is out of range. The policy was set using the <b>switchStatusPolicySet</b> command.
<b>Recommended Action</b>	Execute the <b>supportSave</b> command to clear out the kernel flash.

## FW-1436

<b>Message</b>	Switch status change contributing factor Marginal ports: <Number of marginal ports> marginal out of <Total number of ports> ports:config(<Percentage configured> percent,<Actual threshold limit>). (Port(s) <port list>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because the number of marginal ports is greater than or equal to the policy set using the <b>switchStatusPolicySet</b> command. A port is faulty when the port value is Link Loss, Synchronization Loss, Signal Loss, Invalid word, Protocol error, CRC error, Port state change, or Buffer Limited Port is above the high boundary.
<b>Recommended Action</b>	Replace the faulty or deteriorating small form-factor pluggable (SFP). Execute the <b>fwportdetailshow</b> command to know the reason for marginal ports.

## FW-1437

<b>Message</b>	Switch status change contributing factor Faulty ports: <Number of faulty ports> faulty out of <Total number of ports> ports:config(<Percentage configured> percent,<Actual threshold limit>). (Port(s) <port list>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because the number of faulty ports is greater than or equal to the policy set by the <b>switchStatusPolicySet</b> command. A port is considered faulty due to hardware failure such as a faulty small form-factor pluggable (SFP) or port.
<b>Recommended Action</b>	Replace any faulty or deteriorating SFPs.

## FW-1438

<b>Message</b>	Switch status change contributing factor Missing SFPs: <Number of missing SFPs> missing SFPs out of <Total number of SFPs> SFPs:config(<Percentage configured> percent,<Actual threshold limit>). (Port(s) <port list>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because the number of missing small form-factor pluggable (SFPs) is greater than or equal to the policy set by the <b>switchStatusPolicySet</b> command.
<b>Recommended Action</b>	Execute the <b>switchStatusPolicySet</b> command to modify the SFP policy or to add SFPs to the empty ports.

## FW-1439

<b>Message</b>	Switch status change contributing factor Switch offline.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because the switch is offline.
<b>Recommended Action</b>	Execute the <b>switchEnable</b> command.

## FW-1440

<b>Message</b>	<FRU label> state has changed to <FRU state>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the state of the specified field-replaceable unit (FRU) has changed to absent.
<b>Recommended Action</b>	Verify that the event was planned.

## FW-1441

<b>Message</b>	<FRU label> state has changed to <FRU state>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the state of the specified field-replaceable unit (FRU) has changed to inserted. This means that a FRU is inserted but not powered on.
<b>Recommended Action</b>	Verify that the event was planned.

## FW-1442

<b>Message</b>	<FRU label> state has changed to <FRU state>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the state of the specified field-replaceable unit (FRU) has changed to on.
<b>Recommended Action</b>	Verify that the event was planned.

## FW-1443

<b>Message</b>	<FRU label> state has changed to <FRU state>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the state of the specified field-replaceable unit (FRU) has changed to off.
<b>Recommended Action</b>	Verify that the event was planned.

## FW-1444

<b>Message</b>	<FRU label> state has changed to <FRU state>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the state of the specified field-replaceable unit (FRU) has changed to faulty.

## 5 FW-1445

**Recommended Action** Replace the FRU.

### FW-1445

**Message** Four power supplies are now required for 2X redundancy, Switch Status Policy values changed.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the switch requires four power supplies and the prior Switch Status Policy parameters will be overwritten to reflect this. The presence of an AP blade means that more than one power supply may be required to provide adequate power. So (even if the AP blade is powered down or removed) the Switch Status Policy values will now reflect the need for four power supplies to maintain full (2X) redundancy.

**Recommended Action** No action required unless there are fewer than four power supplies active in the chassis. If there are fewer than four, insert additional power supplies so that there are four active power supplies.

### FW-1446

**Message** Four power supplies now required for 2X redundancy, not enforced by Fabric Watch due to Switch Status Policy overridden by User.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the switch now requires four power supplies for full (2X) redundancy, but the user has previously overridden the Switch Status Policy values pertaining to the number of power supplies. So those values will not be automatically changed.

With no AP blades, the default value is 3 (out of service), indicating switch status is down or 0 indicating no checking for switch status marginal.

When an AP blade is or has been present, the default value is 2 (out of service) indicating switch status is down or 1 (out of service) indicating switch status is marginal.

**Recommended Action** To maintain full (2X) redundancy and proper monitoring by Fabric Watch, supply four active power supplies and enter the default values associated with the presence of an AP blade using the **switchStatusPolicySet** command.

## FW-1447

<b>Message</b>	Switch status change contributing factor Core Blade: <Number Bad> Core blade failures (<Switch State>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because the number of core blade failures is greater than or equal to the policy set by the <b>switchStatusPolicySet</b> command.
<b>Recommended Action</b>	Replace the faulty core blade.

## FW-1448

<b>Message</b>	Switch status change contributing factor Error ports: <Number of Error ports> Error out of <Total number of ports> ports:config(<Percentage configured> percent,<Actual threshold limit>). (Port(s) <port list>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is not in a healthy state. This occurred because the number of faulty ports is greater than or equal to the policy set by the <b>switchStatusPolicySet</b> command. A port is faulted because of port segmentation or port disable.
<b>Recommended Action</b>	Execute the <b>switchShow</b> command to know the reason for port segmentation and port disable. Take the necessary action to bring the port up.

## FW-1500

<b>Message</b>	Mail overflow - Alerts being discarded.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the mail alert overflow condition has occurred.
<b>Recommended Action</b>	Resolve or disable the mail alert using the <b>fwMailCfg</b> command.

## FW-1501

<b>Message</b>	Mail overflow cleared - <Mails discarded> alerts discarded.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the mail overflow condition has cleared.
<b>Recommended Action</b>	No action is required.

## FW-1502

<b>Message</b>	Invalid Email address <Invalid address> is configured from pre-7.0.0 config file.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the configuration file has invalid e-mail addresses.
<b>Recommended Action</b>	Reconfigure a valid e-mail address.

## FW-1510

<b>Message</b>	<Area string> threshold exceeded(High=<Threshold high>). Current value is <Current value>: Port <Port number> disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified port is now disabled because the link on this port had multiple link failures that exceeded the Fabric Watch threshold on the port. Both physical and hardware problems can cause link failures. Link failures frequently occur due to a loss of synchronization. Link failures also occur due to hardware failures, a defective small form-factor pluggable (SFP), or a faulty cable.  Protocol errors indicates CRC sum disparity. Occasionally, these errors occur due to software glitches. Persistent errors occur due to hardware problems.
<b>Recommended Action</b>	Check for concurrent loss of synchronization errors. Check the SFP and the cable. Then, enable the port using the <b>portEnable</b> command.



**FW-1511**

<b>Message</b>	<Port Name> <Label>, has crossed lower threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of link failures that the port experiences has changed and crossed the lower threshold boundary to a value within the acceptable range. Link loss errors occur when a link experiences a loss of signal and fails. Both physical and hardware problems can cause link loss errors. Link loss errors frequently occur due to a loss of synchronization. Check for concurrent loss of synchronization errors and, if applicable, troubleshoot them.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1512**

<b>Message</b>	<Port Name> <Label>, has dropped below upper threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of link failures that the port experiences has changed and dropped below the upper threshold boundary to a value within the acceptable range. Link loss errors occur when a link experiences a loss of signal and fails. Both physical and hardware problems can cause link loss errors. Link loss errors frequently occur due to a loss of synchronization. Check for concurrent loss of synchronization errors and, if applicable, troubleshoot them.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1513**

<b>Message</b>	<Port Name> <Label>, has crossed lower threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of synchronization losses that the port experiences has changed and crossed the lower threshold boundary to a value within the acceptable range. Loss of synchronization errors frequently occur due to a faulty small form-factor pluggable (SFP) or cable. Signal losses often create synchronization losses.

## 5 FW-1514

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

### FW-1514

**Message** <Port Name> <Label>, has dropped below upper threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of synchronization losses that the port experiences has changed and dropped below the upper threshold boundary to a value within the acceptable range. Loss of synchronization errors frequently occur due to a faulty small form-factor pluggable (SFP) or cable. Signal losses often create synchronization losses.

**Recommended Action** No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

### FW-1515

**Message** <Port Name> <Label>, has crossed lower threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of signal losses that the port experiences has changed and crossed the lower threshold boundary to a value within the acceptable range. Loss of signal generally indicates a physical problem.

**Recommended Action** Frequent loss of signal generally indicates a physical problem. Check both ends of your cable connection. Verify that the cable and small form-factor pluggables (SFPs) are not faulty.

### FW-1516

**Message** <Port Name> <Label>, has dropped below upper threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the number of signal losses that the port experiences has changed and dropped below the upper threshold boundary to a value within the acceptable range. Loss of signal generally indicates a physical problem.

**Recommended Action** Frequent loss of signal generally indicates a physical problem. Check both ends of your cable connection. Verify that the cable and small form-factor pluggables (SFPs) are not faulty.

**FW-1517**

<b>Message</b>	<Port Name> <Label>, has crossed lower threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of protocol errors that the port experiences has changed and crossed the lower threshold boundary to a value within the acceptable range. Occasional protocol errors occur due to software glitches. Persistent protocol errors occur due to hardware problems.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1518**

<b>Message</b>	<Port Name> <Label>, has dropped below upper threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of protocol errors that the port experiences has changed and dropped below the upper threshold boundary to a value within the acceptable range. Occasional protocol errors occur due to software glitches. Persistent protocol errors occur due to hardware problems.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1519**

<b>Message</b>	<Port Name> <Label>, has crossed lower threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of invalid words that the port experiences has changed and crossed the lower threshold boundary to a value within the acceptable range. Invalid words usually indicate a hardware problem with a small form-factor pluggable (SFP) or cable.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1520**

<b>Message</b>	<Port Name> <Label>, has dropped below upper threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of invalid words that the port experiences has changed and dropped the below upper threshold boundary to a value within the acceptable range. Invalid words usually indicate a hardware problem with a small form-factor pluggable (SFP) or cable.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1521**

<b>Message</b>	<Port Name> <Label>, has crossed lower threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of invalid cyclic redundancy checks (CRCs) that the port experiences crossed the lower threshold boundary to a value within the acceptable range.
<b>Recommended Action</b>	Frequent fluctuations in CRC errors generally indicate an aging fabric. Check your small form-factor pluggables (SFPs), cables, and connections for faulty hardware. Verify that all optical hardware is clean.

**FW-1522**

<b>Message</b>	<Port Name> <Label>, has dropped below upper threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of invalid cyclic redundancy checks (CRCs) that the port experiences has dropped below the upper threshold boundary to a value within the acceptable range.
<b>Recommended Action</b>	Frequent fluctuations in CRC errors generally indicate an aging fabric. Check your small form-factor pluggables (SFPs), cables, and connections for faulty hardware. Verify that all optical hardware is clean.

## FW-1523

<b>Message</b>	<Port Name> <Label>, has crossed lower threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the percentage of incoming traffic that the port experiences has changed and crossed the lower threshold boundary to a value within the acceptable range.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1524

<b>Message</b>	<Port Name> <Label>, has dropped below upper threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the percentage of incoming traffic that the port experiences has changed and dropped below the upper threshold boundary to a value within the acceptable range.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-1525

<b>Message</b>	<Port Name> <Label>, has crossed lower threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the percentage of outgoing traffic that the port experiences has changed and crossed the lower threshold boundary to a value within the acceptable range.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1526**

<b>Message</b>	<Port Name> <Label>, has dropped below upper threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the percentage of outgoing traffic that the port experiences has changed and dropped below the upper threshold boundary to a value within the acceptable range.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1527**

<b>Message</b>	<Port Name> <Label>, has crossed lower threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of state changes that the port experiences has changed and crossed the lower threshold boundary to a value within the acceptable range. The state of the port has changed for one of the following reasons: the port has gone offline, has come online, is testing, is faulty, has become an E_Port, has become an F_Port, has segmented, or has become a trunk port.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1528**

<b>Message</b>	<Port Name> <Label>, has dropped below upper threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of state changes that the port experiences has changed and dropped below the upper boundary to a value within the acceptable range. The state of the port has changed for one of the following reasons: the port has gone offline, has come online, is testing, is faulty, has become an E_Port, has become an F_Port, has segmented, or has become a trunk port.
<b>Recommended Action</b>	No action is required. Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1529**

<b>Message</b>	<Port Name> <Label>, has crossed lower threshold boundary to in between (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of link resets that the port experiences has changed and crossed the lower threshold boundary to a value within the acceptable range. Link resets occur due to link timeout errors that indicate no frame activity at all. Both physical and hardware problems can cause link resets to increase.
<b>Recommended Action</b>	Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1530**

<b>Message</b>	<Port Name> <Label>, has dropped below upper threshold boundary to in between (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of link resets that the port experiences has changed and dropped below the upper threshold boundary to a value within the acceptable range. Link resets occur due to link timeout errors that indicate no frame activity. Both physical and hardware problems can cause link resets to increase.
<b>Recommended Action</b>	Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-1531**

<b>Message</b>	<Port Name> <Label>, has crossed lower threshold boundary to in between (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of C3 transmit timeout frames has crossed the lower threshold boundary and is in between the low and high thresholds.
<b>Recommended Action</b>	Check the target device; it could be slow.

**FW-1532**

<b>Message</b>	<Port Name> <Label>, has dropped below upper threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the number of C3 transmit timeout frames has dropped below the upper threshold boundary and is in between the low and high thresholds.
<b>Recommended Action</b>	Check the target device; it could be slow.

**FW-1533**

<b>Message</b>	<Port Name> <Label> has crossed lower threshold boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the trunk utilization crossed the lower threshold boundary to in between the low and high thresholds.
<b>Recommended Action</b>	No action is required.

**FW-1534**

<b>Message</b>	<Port Name> <Label> has dropped below threshold upper boundary to in between(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the trunk utilization has dropped below the upper threshold boundary to in between the low and high thresholds.
<b>Recommended Action</b>	No action is required.



## FW-1535

<b>Message</b>	Fabric Watch has stopped portfencing feature for <Area String> loss area in <Port Name> class since FOS6.3. Disabling port fencing feature for this.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that Port Fencing is configured for link loss and synchronization loss in previous versions, but upgrading to a new version resets the bit because Port Fencing is not supported.
<b>Recommended Action</b>	No action is required. You are informed that the Port Fencing bit is reset.

## FW-2000

<b>Message</b>	FW Monitoring is disabled since MAPS is enabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that Fabric Watch is not monitoring the switch because MAPS is enabled.
<b>Recommended Action</b>	Verify that the event was planned.

## FW-3001

<b>Message</b>	Event: <Event Name>, Status: success, Info:<Event Related Info>.
<b>Message Type</b>	AUDIT
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that Port Fencing was enabled or disabled successfully.
<b>Recommended Action</b>	No action is required.

## FW-3010

<b>Message</b>	<Port Name> <Label> value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the circuit utilization has changed.
<b>Recommended Action</b>	Respond to this message as is appropriate to the particular policy of the end-user installation.

## FW-3011

<b>Message</b>	<Port Name> <Label> is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the circuit utilization is below the low boundary threshold.
<b>Recommended Action</b>	No action is required.

## FW-3012

<b>Message</b>	<Port Name> <Label> is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the circuit utilization is above the high boundary threshold.
<b>Recommended Action</b>	No action is required.

**FW-3013**

<b>Message</b>	<Port Name> <Label> is between high and low boundaries (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the circuit utilization is between the high and low boundary thresholds.
<b>Recommended Action</b>	No action is required.

**FW-3014**

<b>Message</b>	<Port Name> <Label> value has changed (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the packet loss that the circuit experiences has changed.
<b>Recommended Action</b>	Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-3015**

<b>Message</b>	<Port Name> <Label> is below low boundary (High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the packet loss that the circuit experiences is below the low boundary threshold.
<b>Recommended Action</b>	No action is required.

## FW-3016

<b>Message</b>	<Port Name> <Label> is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the packet loss that the circuit experiences is above the high boundary threshold.
<b>Recommended Action</b>	No action is required.

## FW-3017

<b>Message</b>	<Port Name> <Label> is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the packet loss that the circuit experiences is between the low and high boundary thresholds.
<b>Recommended Action</b>	No action is required.

## FW-3018

<b>Message</b>	<Port Name> <Label> value has changed(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the number of state changes that the circuit experiences has changed. The state of the circuit has changed because the circuit has gone offline or the circuit has come online.
<b>Recommended Action</b>	Respond to this message as is appropriate to the particular policy of the end-user installation.

**FW-3019**

<b>Message</b>	<Port Name> <Label> is below low boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the number of state changes that the circuit experiences is below the low boundary level. The state of the circuit has changed because the circuit has gone offline or the circuit has come online.
<b>Recommended Action</b>	No action is required.

**FW-3020**

<b>Message</b>	<Port Name> <Label> is above high boundary(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the number of state changes that the circuit experiences has increased above the high boundary threshold. The state of the circuit has changed because the circuit has gone offline, the circuit has come online, or the circuit is testing.
<b>Recommended Action</b>	No action is required.

**FW-3021**

<b>Message</b>	<Port Name> <Label> is between high and low boundaries(High=<High value>, Low=<Low value>). Current value is <Value> <Unit>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the number of state changes that the circuit experiences has increased above the high boundary threshold. The state of the circuit has changed because the circuit has gone offline, the circuit has come online, or the circuit is testing.
<b>Recommended Action</b>	No action is required.

## FW-3022

<b>Message</b>	Timebase for <Key> is changed to Minute as Seconds is not supported.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the timebase for the class is changed implicitly to minutes because a seconds timebase is not supported.
<b>Recommended Action</b>	No action is required.

## HAM Messages

### HAM-1001

<b>Message</b>	Standby CP is not healthy, device <device name> status BAD, Severity = <severity level>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	<p>Indicates that a standby control processor (CP) device error is reported by the high availability manager (HAM) health monitor, with the specified device and severity level. The severity level can be critical, major, or minor.</p> <p>The active CP will continue to function normally. Because the standby CP is not healthy, non-disruptive failover is not possible.</p>
<b>Recommended Action</b>	Restart the standby CP blade by ejecting the card and reseating it. If the problem persists, replace the standby CP.

### HAM-1002

<b>Message</b>	Standby CP is healthy.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that all standby control processor (CP) devices monitored by the high availability manager (HAM) health monitor reported no error.
<b>Recommended Action</b>	No action is required.

### HAM-1004

<b>Message</b>	Processor rebooted - <Reboot Reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	<p>Indicates that the switch has been restarted because of a user action or an error. The switch restart can be initiated by the <b>firmwareDownload</b>, <b>fastBoot</b>, <b>haFailover</b>, and <b>reboot</b> commands. Some examples of errors that may initiate this message are hardware errors, software errors, compact flash errors, or memory errors. The <i>Reboot Reason</i> variable can be one of the following:</p> <ul style="list-style-type: none"> <li>• Hafailover</li> <li>• Reset</li> </ul>

## 5 HAM-1005

- Fastboot
- Giveup Master:SYSM
- CP Faulty:SYSM
- FirmwareDownload
- ConfigDownload:MS
- ChangeWWN:EM
- Reboot:WebTool
- Fastboot:WebTool
- Software Fault:Software Watchdog
- Software Fault:Kernel Panic
- Software Fault:ASSERT
- Reboot:SNMP
- Fastboot:SNMP
- Reboot
- Chassis Config
- Reboot:API
- Reboot:HAM
- EMFault:EM

**Recommended Action** Execute the **errShow** command on both control processors (CPs) to view the error log for additional messages that may indicate reason for the switch restart.

### HAM-1005

**Message** HeartBeat Miss reached threshold.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that either the active CP Ethernet Media Access Controller (EMAC) or the standby CP is down. The active CP will run a diagnostic test on EMAC and will wait for the standby CP to reset it if it is down.

**Recommended Action** No action is required.



## HAM-1006

<b>Message</b>	EMAC controller for Active CP is BAD.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the local Ethernet Media Access Controller (EMAC) on the active CP has been marked BAD as determined by the diagnostic test run by the high availability manager (HAM) module.
<b>Recommended Action</b>	The standby CP will take over and reset the active CP. The system will be non-redundant because the standby CP becomes the active CP.

## HAM-1007

<b>Message</b>	Need to reboot the system for recovery, reason: <reason name>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the switch in current condition needs to be restarted to achieve a reliable recovery. The reasons can be one of the following: <ul style="list-style-type: none"> <li>• The standby CP was not ready when failover occurred.</li> <li>• The failover occurred when the last logical switch (LS) transaction was incomplete.</li> <li>• The switch failed when timeout occurred at certain stage.</li> <li>• The cold or warm recovery has failed.</li> </ul>
<b>Recommended Action</b>	If auto-reboot is enabled, the switch will automatically restart. Otherwise, execute the <b>reboot</b> command to manually restart the switch.

## HAM-1008

<b>Message</b>	Rebooting the system for recovery - auto-reboot is enabled.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the recovery by auto-reboot is enabled, and therefore the switch automatically restarts. This message is displayed if the event logged in HAM-1007 has occurred and auto-reboot is enabled.
<b>Recommended Action</b>	Wait until the switch is up to perform any operations.

## HAM-1009

<b>Message</b>	Need to MANUALLY REBOOT the system for recovery - auto-reboot is disabled.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the recovery by auto-restart is disabled, therefore the switch needs to be manually restarted for recovery. This message is displayed if the event logged in HAM-1007 has occurred and auto-reboot is disabled.
<b>Recommended Action</b>	Execute the <b>reboot</b> command to restart the switch manually.

## HAM-1010

<b>Message</b>	Maunually trigger haReboot/reboot for recovery from OOM when appropriate.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that out of memory (OOM) condition has been detected when the switch was not ready for warm recovery.
<b>Recommended Action</b>	Manually trigger the switch restart for cold recovery, if needed; or wait until switch is ready for warm recovery and execute the <b>haReboot</b> or <b>haFailover</b> command.

## HAM-1011

<b>Message</b>	haReboot is automatically triggered for warm recovery from OOM.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that out of memory (OOM) condition has been detected when switch was ready for warm recovery. The <b>haReboot</b> is automatically triggered.
<b>Recommended Action</b>	No action is required. The <b>haReboot</b> is automatically triggered to recover from the OOM condition.

## HAM-1013

<b>Message</b>	<error message>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the software watchdog has detected termination of a restartable daemon, but could not restart the daemon.
<b>Recommended Action</b>	Manually initiate a restart or failover, if needed.

## HAM-1014

<b>Message</b>	<error message>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the software watchdog has detected termination of a restartable daemon and needs to restart or initiate a failover.
<b>Recommended Action</b>	Execute the <b>reboot</b> command to restart the system or initiate a failover by using the <b>haFailover</b> command.

## HAM-1015

<b>Message</b>	<info message>.
<b>Message Type</b>	AUDIT
<b>Class</b>	RAS
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a terminated software component has been restarted.
<b>Recommended Action</b>	No action is required.

## HAMK Messages

### HAMK-1001

<b>Message</b>	Warm Recovery Failed.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the switch failed during the warm recovery.
<b>Recommended Action</b>	This event triggers the switch restart automatically and attempts a cold recovery. Execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

### HAMK-1002

<b>Message</b>	Heartbeat down.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the active control processor (CP) blade determined that the standby CP blade is down. This can be a result of a user-initiated action such as firmware download, the standby CP blade being reset or removed, or an error in the standby CP blade.
<b>Recommended Action</b>	Monitor the standby CP blade for a few minutes. If this message is due to a standby CP restart, the HAMK-1003 message will display after the standby CP is restarted.  If the standby CP does not connect to the active CP after 10 minutes, restart the standby CP blade by ejecting the blade and reseating it.

### HAMK-1003

<b>Message</b>	Heartbeat up.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the active control processor (CP) blade detected the standby CP blade. This means that the standby CP blade is available to take over in case a failure happens in the active CP blade. Typically, this message is displayed when the standby CP blade restarts.
<b>Recommended Action</b>	No action is required.

## HAMK-1004

<b>Message</b>	Resetting standby CP (double reset may occur).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the standby control processor (CP) is being reset due to a loss of heartbeat. Typically, this message is displayed when the standby CP has been restarted. Note that in certain circumstances, a CP may experience a double reset and restart twice. A CP can recover automatically even if it has restarted twice.
<b>Recommended Action</b>	No action is required.

## HIL Messages

### HIL-1101

<b>Message</b>	Slot <slot number> faulted, <nominal voltage> (<measured voltage>) is above threshold.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the blade voltage is above threshold.
<b>Recommended Action</b>	Replace the faulty blade or switch (for non-bladed switches).

### HIL-1102

<b>Message</b>	Slot <slot number> faulted, <nominal voltage> (<measured voltage>) is below threshold.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the blade voltage is below threshold.
<b>Recommended Action</b>	Replace the faulty blade or switch (for non-bladed switches).

### HIL-1103

<b>Message</b>	Blower <blower number> faulted, <nominal voltage> (<measured voltage>) is above threshold.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the fan voltage is above threshold.
<b>Recommended Action</b>	Run the <b>psShow</b> command to verify the power supply status. Try to reseat the faulty fan field-replaceable units (FRUs) and power supply FRU to verify that they are seated properly. If the problem persists, replace the fan FRU or the power supply FRU as necessary.

## HIL-1104

<b>Message</b>	Blower <blower number> faulted, <nominal voltage> (<measured voltage>) is below threshold.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the fan voltage is below threshold.
<b>Recommended Action</b>	Run the <b>psShow</b> command to verify the power supply status. Try to reseat the faulty fan field-replaceable units (FRUs) and power supply FRU to verify that they are seated properly. If the problem persists, replace the fan FRU or the power supply FRU as necessary.

## HIL-1105

<b>Message</b>	Switch error, <nominal voltage> (<measured voltage>) above threshold.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the switch voltage is above threshold. This message is specific to non-bladed switches.
<b>Recommended Action</b>	For switches that do not have field-replaceable units (FRUs), replace the entire switch. If the 12 volt level is faulty, replace one or both power supplies; if any other voltage is faulty, replace the entire switch.

## HIL-1106

<b>Message</b>	Switch error, <nominal voltage> (<measured voltage>) below threshold.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the switch voltage is below threshold. This message is specific to non-bladed switches.
<b>Recommended Action</b>	For switches that do not have field-replaceable units (FRUs), replace the entire switch. If the 12 volt level is faulty, replace one or both power supplies; if any other voltage is faulty, replace the entire switch.

## HIL-1107

<b>Message</b>	Switch faulted, <nominal voltage> (<measured voltage>) above threshold. System preparing for reset.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the switch voltage is above threshold. This message is specific to non-bladed switches.
<b>Recommended Action</b>	For switches that do not have field-replaceable units (FRUs), replace the entire switch. If the 12 volt level is faulty, replace one or both power supplies; if any other voltage is faulty, replace the entire switch.

## HIL-1108

<b>Message</b>	Switch faulted, <nominal voltage> (<measured voltage>) below threshold. System preparing for reset.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the switch voltage is below threshold. This message is specific to non-bladed switches.
<b>Recommended Action</b>	For switches that do not have field-replaceable units (FRUs), replace the entire switch. If the 12 volt level is faulty, replace one or both power supplies; if any other voltage is faulty, replace the entire switch.

## HIL-1201

<b>Message</b>	Blower <blower number>, speed (<measured speed> RPM) above threshold.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the fan speed (in RPM) has risen above the maximum threshold. A high speed does not necessarily mean that the fan is faulty.
<b>Recommended Action</b>	Run the <b>tempShow</b> command to verify that the switch temperatures are within operational ranges. Refer to the hardware reference manual for the temperature range of your switch. Make sure that the area is well-ventilated and that the room temperature is within the operational range of your switch. Refer to the hardware reference manual for your switch for the operational temperature range. Run the <b>fanShow</b> command to monitor the speed of the fan generating this error. If the fan continues to generate this message, replace the fan FRU.



## HIL-1202

<b>Message</b>	Blower <blower number> faulted, speed (<measured speed> RPM) below threshold.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified fan speed (in RPM) has fallen below the minimum threshold.
<b>Recommended Action</b>	Replace the fan FRU.

## HIL-1203

<b>Message</b>	Fan <fan number> faulted, speed (<measured speed> RPM) above threshold.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified fan speed (in RPM) has risen above the maximum threshold. A high speed does not necessarily mean that the fan is faulty.
<b>Recommended Action</b>	<p>Run the <b>tempShow</b> command to verify that the switch temperatures are within operational ranges. Refer to the hardware reference manual for the temperature range of your switch.</p> <p>Make sure that the area is well-ventilated and that the room temperature is within the operational range of your switch. Refer to the hardware reference manual for your switch for the operational temperature range.</p> <p>Run the <b>fanShow</b> command to monitor the speed of the fan generating this error.</p> <p>If the fan continues to generate this message, replace the fan FRU.</p>

## HIL-1204

<b>Message</b>	Fan <fan number> faulted, speed (<measured speed> RPM) below threshold.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified fan speed (in RPM) has fallen below the minimum threshold. This message is specific to non-bladed switches.
<b>Recommended Action</b>	<p>Replace the fan field-replaceable unit (FRU).</p> <p>For switches that do not have FRUs, replace the entire switch.</p>

## HIL-1206

<b>Message</b>	Fan <fan number> sensor <sensor number> , speed (<measured speed> RPM) below threshold.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified fan speed (in RPM) has fallen below the minimum threshold. This problem can quickly cause the switch to overheat. This message is specific to non-bladed switches.
<b>Recommended Action</b>	Replace the fan field-replaceable unit (FRU).

## HIL-1207

<b>Message</b>	Fan <fan number> is faulty.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the fan is faulty.
<b>Recommended Action</b>	<p>Use the <b>tempShow</b> command to verify that the switch temperatures are within operational ranges. Refer to the hardware reference manual for the temperature range of your switch.</p> <p>Make sure that the area is well-ventilated and that the room temperature is within the operational range of your switch. Refer to the hardware reference manual for your switch for the operational temperature range.</p> <p>Use the <b>fanShow</b> command to monitor the status of the fan generating this error.</p> <p>If the fan continues to generate this message, replace the switch because the fan is not field-replaceable.</p>

## HIL-1208

<b>Message</b>	Fan <fan number> is not faulty.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the fan is not faulty.
<b>Recommended Action</b>	<p>This can only occur on switches with non-removable fans. It follows a previous indication of faultiness.</p> <p>If the fan continues to generate this message, it indicates oscillation between faulty and non-faulty behavior. Replace the switch because the fan is not field-replaceable.</p>

## HIL-1301

<b>Message</b>	1 blower failed or missing. Replace failed or missing blower assembly immediately.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a fan field-replaceable unit (FRU) has failed or has been removed. This message is often preceded by a low speed error message. This problem can cause the switch to overheat.
<b>Recommended Action</b>	Replace the affected fan FRU immediately.

## HIL-1302

<b>Message</b>	<count> blowers failed or missing. Replace failed or missing blower assemblies immediately.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that multiple fan field-replaceable units (FRUs) have failed or are missing on a switch. This message is often preceded by a low fan speed message.
<b>Recommended Action</b>	Replace the affected fan FRUs immediately.

## HIL-1303

<b>Message</b>	One fan failed. Replace failed fan FRU immediately.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a fan field-replaceable unit (FRU) has failed. This message is often preceded by a low fan speed message.
<b>Recommended Action</b>	Replace the faulty fan FRU immediately.

## HIL-1304

<b>Message</b>	Two fans failed. Replace failed fan FRUs immediately.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that multiple fan field-replaceable units (FRUs) have failed. This message is often preceded by a low fan speed message.
<b>Recommended Action</b>	Replace the faulty fan FRUs immediately.

## HIL-1305

<b>Message</b>	One or two fans failed. Replace failed fan FRUs immediately.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that multiple fan field-replaceable units (FRUs) have failed. This message is often preceded by a low fan speed message.
<b>Recommended Action</b>	Replace the faulty fan FRUs immediately.

## HIL-1306

<b>Message</b>	Three fans failed. Replace failed fan FRUs immediately.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that three fan field-replaceable units (FRUs) have failed. This message is often preceded by a low fan speed message.
<b>Recommended Action</b>	Replace the faulty fan FRUs immediately.

## HIL-1307

<b>Message</b>	Four or five fans failed. Replace failed fan FRUs immediately.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that multiple fan field-replaceable units (FRUs) have failed. This message is often preceded by a low fan speed message.
<b>Recommended Action</b>	Replace the faulty fan FRUs immediately.

## HIL-1308

<b>Message</b>	All fans failed. Replace failed fan FRUs immediately.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that all fans have failed. This message is often preceded by a low fan speed message.
<b>Recommended Action</b>	Replace the faulty fan field-replaceable units (FRUs) immediately.

## HIL-1309

<b>Message</b>	<count> fan FRUs failed. Replace failed fan FRUs immediately.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that multiple fans have failed. This message is often preceded by a low fan speed message.
<b>Recommended Action</b>	Replace the faulty fan field-replaceable units (FRUs) immediately.

## HIL-1310

<b>Message</b>	<count> fan(s) faulty.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that multiple fans have failed. This message is often preceded by a low fan speed message.

## 5 HIL-1311

**Recommended Action** Because the fans are not field-replaceable, replace the switch if the temperature is high.

### HIL-1311

**Message** No fans are faulty.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates recovery from an earlier condition of one or more fans having failed.

**Recommended Action** This can only occur on switches with non-removable fans. It follows a previous indication of faultiness. If the fan continues to generate this message, it indicates oscillation between faulty and non-faulty behavior. Replace the switch because the fan is not field-replaceable.

### HIL-1401

**Message** One fan FRU missing. Install fan FRU immediately.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that a fan field-replaceable unit (FRU) has been removed.

**Recommended Action** Install the missing fan FRU.

### HIL-1402

**Message** Two fan FRUs missing. Install fan FRUs immediately.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that two fan field-replaceable units (FRUs) have been removed.

**Recommended Action** Install the missing fan FRUs immediately.

## HIL-1403

<b>Message</b>	All fan FRUs missing. Install fan FRUs immediately.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that all fan field-replaceable units (FRUs) have been removed.
<b>Recommended Action</b>	Install the missing fan FRUs immediately.

## HIL-1404

<b>Message</b>	<count> fan FRUs missing. Install fan FRUs immediately.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that one or more fan field-replaceable units (FRUs) have been removed.
<b>Recommended Action</b>	Install the missing fan FRUs immediately.

## HIL-1501

<b>Message</b>	Slot <slot number>, high temperature (<measured temperature>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the temperature of this blade has risen above the warning threshold.
<b>Recommended Action</b>	Run the <b>fanShow</b> command to verify all the fans are working properly. Make sure that the area is well-ventilated and that the room temperature is within operational range of your switch. Refer to the hardware reference manual for your switch for the operational temperature range.

## HIL-1502

<b>Message</b>	Slot <slot number>, high temperature (<measured temperature>). Unit will be shut down in 2 minutes if temperature remains high.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the temperature of this blade has risen above the critical threshold. This usually follows a high-temperature message.
<b>Recommended Action</b>	Run the <b>fanShow</b> command to verify all the fans are working properly. Make sure that the area is well-ventilated and that the room temperature is within operational range of your switch. Refer to the hardware reference manual for your switch for the operational temperature range. If the message persists, replace the blade.

## HIL-1503

<b>Message</b>	Slot <slot number>, unit shutting down.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the temperature of this blade has been above the maximum threshold for at least two minutes. The blade is shut down to prevent damage. This usually follows a high-temperature warning message.
<b>Recommended Action</b>	Run the <b>fanShow</b> command to verify all the fans are working properly. Make sure that the area is well-ventilated and that the room temperature is within the operational range of your switch. Refer to the hardware reference manual for your switch for the operational temperature range. If the message persists, replace the faulty blade.

## HIL-1504

<b>Message</b>	System within normal temperature specifications (<measured temperature> C).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that temperatures in the system have returned to normal.
<b>Recommended Action</b>	No action is required.



## HIL-1505

<b>Message</b>	High temperature (<measured temperature> C), fan speed increasing per environmental specifications.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that temperatures in the system have risen above the warning threshold and that the fan speed is being increased.
<b>Recommended Action</b>	Run the <b>fanShow</b> command to verify all the fans are working properly. Make sure that the area is well-ventilated and that the room temperature is within the operational range of your switch. Refer to the hardware reference manual for your switch for the operational temperature range.

## HIL-1506

<b>Message</b>	High temperature (<measured temperature> C) exceeds system temperature limit. System will shut down within 2 minutes.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that temperatures in the system have risen above the critical threshold.
<b>Recommended Action</b>	Run the <b>fanShow</b> command to verify that all fans are working properly. Replace any deteriorating fan field-replaceable units (FRUs). Make sure that the area is well-ventilated and that the room temperature is within the operational range of your switch. Refer to the hardware reference manual for your switch for the operational temperature range.

## HIL-1507

<b>Message</b>	High temperature warning time expired. System preparing for shutdown.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that temperatures in the system have risen above the critical threshold.
<b>Recommended Action</b>	To avoid causing damage to the switch, the system shuts down automatically. To help prevent future problems, make sure that all the fans are working properly. Make sure that the area is well-ventilated and that the room temperature is within the operational range of your switch. Refer to the hardware reference manual for your switch for the operational temperature range.

## HIL-1508

<b>Message</b>	Fan faulty warning time expired. System preparing for shutdown.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that temperatures in the system have remained above the critical threshold too long.
<b>Recommended Action</b>	To avoid causing damage to the switch, the system shuts down automatically. To help prevent future problems, make sure that all the fans are working properly. Make sure that the area is well-ventilated and that the room temperature is within the operational range of your switch. Refer to the hardware reference manual for your switch for the operational temperature range.

## HIL-1509

<b>Message</b>	High temperature (<measured temperature> C). Warning time expired. System preparing for shutdown.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that temperatures in the system have risen above the critical threshold.
<b>Recommended Action</b>	To avoid causing damage to the switch, the system shuts down automatically. To help prevent future problems, make sure that all the fans are working properly. Make sure that the area is well-ventilated and that the room temperature is within the operational range of your switch. Refer to the hardware reference manual for your switch for the operational temperature range.

## HIL-1510

<b>Message</b>	Current temperature (<measured temperature> C) is below shutdown threshold. System shutdown canceled.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that temperatures in the system have dropped below the critical threshold; the system can continue operation.
<b>Recommended Action</b>	To help prevent future problems, make sure that all the fans are working properly. Make sure that the area is well-ventilated and that the room temperature is within the operational range of your switch. Refer to the hardware reference manual for your switch for the operational temperature range.

## HIL-1511

<b>Message</b>	Fan speed increasing per environmental specifications.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that temperatures in the system have risen above the warning threshold and that the fan speed is being increased.
<b>Recommended Action</b>	Run the <b>fanShow</b> command to verify all the fans are working properly. Make sure that the area is well-ventilated and that the room temperature is within the operational range of your switch. Refer to the hardware reference manual for your switch for the operational temperature range.

## HIL-1601

<b>Message</b>	Using backup temperature sensor. Attention needed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that temperature readings from the primary sensor are out of range.
<b>Recommended Action</b>	Run the <b>fanShow</b> command to verify that all fans are operating correctly. Replace any deteriorating fan field-replaceable units (FRUs). Run the <b>tempShow</b> command to verify temperature values. If any sensor is too high, monitor the switch. Try rebooting or power cycling the switch.

## HIL-1602

<b>Message</b>	Multiple temperature sensors failed. Service immediately.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that temperature readings from multiple sensors are out of range.
<b>Recommended Action</b>	Run the <b>fanShow</b> command to verify that all fans are operating correctly. Replace any deteriorating fan field-replaceable units (FRUs). Run the <b>tempShow</b> command to verify temperature values. If any sensor is too high, monitor the switch. Try rebooting or power cycling the switch.

## HIL-1603

<b>Message</b>	<failure count> fans out of service. System is shutting down immediately.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the total fan failure count is greater than or equal to two.
<b>Recommended Action</b>	To avoid causing damage to the switch, the system shuts down automatically. To help prevent future problems, make sure that all the fans are working properly.

## HIL-1605

<b>Message</b>	High temperature (<measured temperature> C), fan speed increasing per environmental specifications.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that temperatures in the system have risen above the threshold and that the fan speed is being increased.
<b>Recommended Action</b>	No action is required.

## HIL-1610

<b>Message</b>	Fan/PS unit <Combo fan/power supply unit number> not supplying power, fan speeds may not be available. Please ensure that the unit has power and the switch is on.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the power supply is not connected to a power source, is not switched on, or the unit is faulty. This message is applicable only to the Brocade 5100.
<b>Recommended Action</b>	Ensure the power cord is connected to the unit with a valid power source and then switch on the unit. If the problem persists, try reseating the unit. If the problem still persists, replace the FRU.

## HIL-1611

<b>Message</b>	MISMATCH in PSU-FAN Air Flow direction. Replace PSU with fan air flows in same direction. System will be shut down in 2 minutes.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the airflows of the power supply and fan assemblies are moving in the reverse or opposite direction, which could overheat the system. The airflow of the power supply and fan assemblies must move in the same direction or the system will shut down in two minutes. This message is applicable only to the Brocade 6510.
<b>Recommended Action</b>	Use the <b>chassisShow</b> command to check the airflow directions of the power supply and fan assemblies. Ensure that the airflows run in the same direction.

## HIL-1612

<b>Message</b>	MISMATCH in PSU-FAN Air Flow direction. System shut down.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the airflows of the power supply and fan assemblies are moving in the reverse or opposite direction. The system will shut down immediately. This message is applicable only to the Brocade 6510.
<b>Recommended Action</b>	Ensure that the airflows of the power supply and fan assemblies run in the same direction.

## HIL-1613

<b>Message</b>	PSU-FAN FRUS Air Flow matched. System shutdown canceled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the airflows of the power supply and fan assemblies have changed to move in the same direction. The system continues to operate. This message is applicable only to the Brocade 6510.
<b>Recommended Action</b>	Ensure that the airflows of the power supply and fan assemblies run in the same direction.

## HIL-1650

<b>Message</b>	Unable to detect both WWN cards in chassis. Access to WWN halted.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that one or both of the World Wide Name (WWN) cards is missing. Both WWN cards must be present for normal operation.
<b>Recommended Action</b>	Make sure both WWN cards are inserted.

## HLO Messages

### HLO-1001

<b>Message</b>	Incompatible Inactivity timeout <dead timeout> from port <port number>, correct value <value>.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	ERROR
<b>Probable Cause</b>	<p>Indicates that the hello (HLO) message was incompatible with the value specified in the fabric shortest path first (FSPF) protocol. The Brocade switch will not accept FSPF frames from the remote switch.</p> <p>In Fabric OS, the HLO dead timeout value is not configurable, so this error can only occur when the Brocade switch is connected to a switch from another manufacturer.</p>
<b>Recommended Action</b>	The dead timeout value of the remote switch must be compatible with the value specified in the FSPF protocol. Refer to the documentation for the other manufacturer's switch to change this value.

### HLO-1002

<b>Message</b>	Incompatible Hello timeout <HLO timeout> from port <port number>, correct value <correct value>.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	ERROR
<b>Probable Cause</b>	<p>Indicates that the hello (HLO) message was incompatible with the value specified in the fabric shortest path first (FSPF) protocol. The Brocade switch will not accept FSPF frames from the remote switch.</p> <p>In Fabric OS, the HLO timeout value is not configurable, so this error can only occur when the Brocade switch is connected to a switch from another manufacturer.</p>
<b>Recommended Action</b>	The HLO timeout value of the remote switch must be compatible with the value specified in the FSPF protocol. Refer to the documentation for the other manufacturer's switch to change this value.

## HLO-1003

**Message** Invalid Hello received from port <port number>, Domain = <domain ID>, Remote Port = <remote port ID>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the hello (HLO) message received was invalid and the frame was dropped. The Brocade switch will not accept fabric shortest path first (FSPF) frames from the remote switch.  
The switch has received an invalid HLO because either the domain or port number in the HLO message has an invalid value. This error can only occur when the Brocade switch is connected to a switch from another manufacturer.

**Recommended Action** The HLO message of the remote switch must be compatible with the value specified in the FSPF protocol. Refer to the documentation for the other manufacturer's switch to change this value.



## HMON Messages

### HMON-1001

<b>Message</b>	<Failure description>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that there was a problem reading an essential file containing configuration information from the nonvolatile storage device. This could be the result of a missing file or a corrupt file system.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware to your switch. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## HSL Messages

### HSL-1000

<b>Message</b>	HSL initialization failed.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates a hardware subsystem layer (HSL) initialization failure. This error is caused by other system errors.
<b>Recommended Action</b>	Execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

### HSL-1001

<b>Message</b>	Failed to acquire system MAC address pool.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates failure to acquire the system address. This error is caused by other system errors.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to view the error log for other system errors, and take appropriate corrective actions.

### HSL-1002

<b>Message</b>	SFP for interface <InterfaceName> is inserted.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a small form-factor pluggable (SFP) transceiver has been inserted in the specified interface.
<b>Recommended Action</b>	No action is required.

## HSL-1003

<b>Message</b>	SFP for interface <InterfaceName> is removed.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a small form-factor pluggable (SFP) transceiver has been removed from the specified interface.
<b>Recommended Action</b>	No action is required.

## HSL-1004

<b>Message</b>	Incompatible SFP for interface <InterfaceName> is detected.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that an incompatible small form-factor pluggable (SFP) transceiver for the interface has been inserted.
<b>Recommended Action</b>	Disable the interface using the <b>shutdown</b> command and insert an SFP transceiver that is supported on the interface. After the SFP transceiver is inserted, re-enable the interface using the <b>no shutdown</b> command.

## HSL-1005

<b>Message</b>	Failed to initialize with FSS.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates a failure to initialize the Fabric OS State Synchronization (FSS) service. This error is caused by other system errors.
<b>Recommended Action</b>	Execute the <b>errShow</b> command to view the error log for other system errors, and take appropriate corrective actions.

## HSL-1006

<b>Message</b>	Failed to get kernel page size <PageSize> bytes for mmap.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that there is not enough contiguous kernel memory.
<b>Recommended Action</b>	Install more memory on the board.

## HSL-1007

<b>Message</b>	Failed to read SFP for interface <InterfaceName>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates failure to read the small form-factor pluggable (SFP) transceiver on the specified interface.
<b>Recommended Action</b>	Disable the interface using the <b>shutdown</b> command and re-insert the SFP transceiver. After the SFP transceiver is inserted, re-enable the interface using the <b>no shutdown</b> command. If the problem persists, contact your switch service provider.

## HTTP Messages

### HTTP-1001

<b>Message</b>	Switch PID format has changed to <current PID format>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the port ID (PID) format was changed.
<b>Recommended Action</b>	No action is required. For more information on PID format, refer to the <i>Fabric OS Administrator's Guide</i> .

### HTTP-1002

<b>Message</b>	Zoning transaction initiated by User: <User Name>, Role: <User Role> completed successfully.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	ZONE
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the zoning database has been changed.
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

### HTTP-1003

<b>Message</b>	Zoning transaction initiated by User: <User Name>, Role: <User Role> could not be completed successfully - <Reason Message>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	ZONE
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an error in completing the zoning transaction because of the specified reason.
<b>Recommended Action</b>	Check the ZONE events in the error message log by using the <b>errShow</b> command, and take appropriate corrective actions.

## IBD Messages

### IBD-1000

<b>Message</b>	Slot <slot number> Port GE<port number>: Maximum attempts to restart failed. Disabling port.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified port has crashed unexpectedly and restarting attempts have failed.
<b>Recommended Action</b>	Power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands.

## IPAD Messages

### IPAD-1000

<b>Message</b>	<Type of managed entity>/<Instance number of managed entity> <Type of network interface>/<Instance number of network interface> <Protocol address family> <Source of address change> <Value of address and prefix> DHCP <DHCP enabled or not>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the local IP address has been changed manually or it was reconfigured automatically by the Dynamic Host Configuration Protocol (DHCP) server.
<b>Recommended Action</b>	No action is required.

### IPAD-1001

<b>Message</b>	<Type of managed entity>/<Instance number of managed entity> <Protocol address family> <Source of address change> <Value of address> DHCP <DHCP enabled or not>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the gateway IP address has been changed manually or it was reconfigured automatically by the Dynamic Host Configuration Protocol (DHCP) server.
<b>Recommended Action</b>	No action is required.

### IPAD-1002

<b>Message</b>	Switch name has been successfully changed to <Switch name>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the switch name has been changed.
<b>Recommended Action</b>	No action is required.

## IPAD-1003

<b>Message</b>	DNS parameters saved successfully.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Domain Name System (DNS) parameters are saved successfully.
<b>Recommended Action</b>	No action is required.

## IPAD-1004

<b>Message</b>	DNS parameters removed successfully.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Domain Name System (DNS) parameters are removed successfully.
<b>Recommended Action</b>	No action is required.



## IPS Messages

### IPS-1001

<b>Message</b>	<code>&lt;message&gt; FTR_AFA/FTR_AE License Not Installed (&lt;error&gt;).</code>
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that either Advanced FICON Acceleration (FTR_AFA) or Advanced Extension (FTR_AE) license is not installed or assigned to the slot.
<b>Recommended Action</b>	Run the <b>licenseShow</b> command to verify the slot-based licenses are installed on the switch. Contact your switch supplier for an appropriate slot-based license. Run the <b>licenseAdd</b> and <b>licenseSlotCfg</b> commands to add the license to your switch and activate it.

### IPS-1002

<b>Message</b>	<code>Failed to initialize &lt;module&gt; rc = &lt;error&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the initialization of a module within the IPS daemon failed.
<b>Recommended Action</b>	Download a new firmware version using the <b>firmwareDownload</b> command.

### IPS-1003

<b>Message</b>	<code>&lt;function name&gt;: Failed to allocate memory while performing &lt;message&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that memory resources are low. This may be a transient problem.
<b>Recommended Action</b>	Check the memory usage on the switch using the <b>memShow</b> command. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

**IPS-1004**

<b>Message</b>	Port Config Mode Mismatch slot (<slot>) port(ge<port>): current mode is (<current mode>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that configured port mode is different from the intended use.
<b>Recommended Action</b>	Change the port configuration (by deleting configured FCIP tunnels or iSCSI sessions) to return the port mode to neutral before attempting to configure the port for a different mode or use.

**IPS-1005**

<b>Message</b>	Tunnel Authorization Failure for slot (<slot>) port(ge<port>) tunnel ID(<tunnel number>) reason (<reason>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that tunnel setup failed because of an authorization failure from the remote side. A reason for such a failure could be a WWN mismatch.
<b>Recommended Action</b>	Change the tunnel configuration on one side of the tunnel to authorize the remote side to set up the tunnel.

**IPS-1006**

<b>Message</b>	Tunnel Configuration Mismatch for slot (<slot>) port(<port>) tunnel ID(<tunnel number>) reason (<reason>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that tunnel setup failed because of a configuration mismatch between the two ends. The <i>reason</i> field indicates the cause for configuration mismatch.
<b>Recommended Action</b>	Change the tunnel configuration on one side of the tunnel to match that of the other side to set up the tunnel.

## IPS-1007

<b>Message</b>	FX8-24 blade (<slot>) is not at the correct revision. Unable to use IPSec on FCIP Tunnel (<port>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the tunnel configuration failed because the FX8-24 blade is not at the correct revision to support IPSec enabled tunnels on VEs 22-31.
<b>Recommended Action</b>	Contact your switch vendor to acquire the correct hardware revision blade.

## ISNS Messages

### ISNS-1001

<b>Message</b>	Configuration peering with external iSNS server <New config iSNS server IP address> slot/port <New config Slot number>/ge<New config port number> (current <Current iSNS server IP address> <Current slot number>/ge<Current port number>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a user has issued the <b>isnscCfg</b> command.
<b>Recommended Action</b>	No action is required.

### ISNS-1002

<b>Message</b>	Start peering with external iSNS server <iSNS server IP address> slot/port <Slot number>/ge<Port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that peering has started with the specified external Internet Storage Name Service (iSNS) server.
<b>Recommended Action</b>	No action is required.

### ISNS-1003

<b>Message</b>	Peering with external iSNS server is disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the IP address of the Internet Storage Name Service (iSNS) server is zero. Therefore, peering is disabled.
<b>Recommended Action</b>	If you wish to enable the iSNS server, use the <b>isnscCfg</b> command to show or set the server IP address; otherwise, no action is required.

## ISNS-1004

<b>Message</b>	Timeout refreshing iSNS database with iSNS server <iSNS server IP address> slot/port <Slot number>/ge<Port number> Reg-Period <Registration-Period in seconds>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Internet Storage Name Service (iSNS) client fails to receive a successful response for a DevAttrQry within the specified registration period.
<b>Recommended Action</b>	Verify the connection of the iSNS server to the slot and port.

## ISNS-1005

<b>Message</b>	User request re-register with external iSNS server <iSNS server IP address> slot/port <Slot number>/ge<Port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a user has requested to re-register with the specified external Internet Storage Name Service (iSNS) server.
<b>Recommended Action</b>	No action is required.

## ISNS-1006

<b>Message</b>	Start re-register with external iSNS server <iSNS server IP address> slot/port <Slot number>/ge<Port number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the re-register with the specified external Internet Storage Name Service (iSNS) server has started.
<b>Recommended Action</b>	No action is required.

## ISNS-1008

<b>Message</b>	Peering with external iSNS server <iSNS server IP address> not started because configuration unchanged.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that peering with the external Internet Storage Name Service (iSNS) server was already started with the same configuration.
<b>Recommended Action</b>	No action is required. You may change the configuration and retry the peering with the external iSNS server.

## ISNS-1009

<b>Message</b>	Peering with external iSNS server <iSNS server IP address> not started because no virtual targets found.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that no virtual targets were found, and therefore peering was not started.
<b>Recommended Action</b>	No action is required. Peering will resume automatically when virtual targets are detected.

## ISNS-1010

<b>Message</b>	Slot/port <Slot>/ge<Port> is out of range.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the slot or port is out of range.
<b>Recommended Action</b>	Retry with a valid slot and port. Refer to the appropriate hardware reference manual for valid slot and port ranges.

## ISNS-1011

<b>Message</b>	iSNS Client Service is <iSNS client State (enabled/disabled)>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the current state of the Internet Storage Name Service (iSNS) client is enabled or disabled.
<b>Recommended Action</b>	No action is required. Use the <b>fosConfig</b> command to display, enable, or disable the iSNS client service.

## ISNS-1013

<b>Message</b>	iSNS server connection failure.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Internet Storage Name Service (iSNS) client failed to establish a connection with the iSNS server.
<b>Recommended Action</b>	Verify the connection of the iSNS server to the slot and port. Use the <b>isnscCfg</b> command to display or correct the server IP address.

## ISNS-1014

<b>Message</b>	Start peering with external iSNS server <iSNS server IP address> on management port.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that peering has started with the specified external Internet Storage Name Service (iSNS) on the management port.
<b>Recommended Action</b>	No action is required.

## KAC Messages

### KAC-1002

<b>Message</b>	KAC (<Key Vault Type>) communication Error: Error connecting to <Backup or Primary>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Key Archive Client (KAC) is unable to communicate with the primary or backup key vault.
<b>Recommended Action</b>	Determine whether the configured key vault is operational; if not, change the switch key vault settings or resolve the operational problem at the key vault.

### KAC-1004

<b>Message</b>	KAC <Operation Description> to Key Vault failed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Key Archive Client (KAC) is unable to do the specified operation to the primary or backup key vault.
<b>Recommended Action</b>	Determine whether the configured key vault is operational; if not, change the switch key vault settings or resolve the operational problem at the key vault.

### KAC-1006

<b>Message</b>	Switch to Key Vault trustee link was not established.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the trustee link was not established between the switch and the key vault.
<b>Recommended Action</b>	Establish a trustee link between the switch and the key vault. Refer to the <i>Fabric OS Encryption Administrator's Guide</i> for instructions to establish a trusted link.



## KAC-1007

<b>Message</b>	KAC key archival operation to Key Vault failed, LUN=<LUN Number>, keyID=<Key ID Value>, errno=<Error Number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Key Archive Client (KAC) is unable to archive the key to primary or backup key vault.
<b>Recommended Action</b>	Determine whether the configured key vault is operational; if not, change the switch key vault settings or resolve the operational problem at the key vault.

## KAC-1008

<b>Message</b>	Putting of TEP failed. Check if there is already an unapproved TEP, then delete it. Error code=<Error code from LKM>, string=<Error string>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that there was already a pending unapproved Trusted link Establishment Package (TEP) at the Lifetime Key Manager (LKM).
<b>Recommended Action</b>	Log in to LKM and delete the unapproved TEP.

## KAC-1009

<b>Message</b>	Primary(<Primary Keyvault IP Address>) and Backup(<Backup Keyvault IP Address>) Key Vaults are not in sync. Detected key mismatch with KeyID = <KeyID>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the primary and backup key vault contents are not in sync.
<b>Recommended Action</b>	Synchronize the contents of the primary and backup key vaults using instructions provided by the key vault provider.

## KAC-1010

<b>Message</b>	Archival for KeyID <KeyID> failed to <Keyvault IP Address>. Error code=<Error code>, string=<Error string>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that archiving of Data Encryption Key (DEK) to the key vault failed.
<b>Recommended Action</b>	No action is required.

## KAC-1011

<b>Message</b>	Archival of Dummy DEK to the KV <Keyvault IP Address> failed. Dummy DEK: <Dummy Key Id>, KeyCount: <Key Count>. Error code=<Error code>, string=<Error string>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that archiving of dummy Data Encryption Key (DEK) to the key vault failed.
<b>Recommended Action</b>	No action is required.

## KAC-1012

<b>Message</b>	Retrieval of Dummy DEK from the KV <Keyvault IP Address> failed. Dummy DEK: <Dummy Key Id>, KeyCount: <Key Count>. Error code=<Error code>, string=<Error string>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that retrieving of dummy Data Encryption Key (DEK) from the key vault failed.
<b>Recommended Action</b>	No action is required.

## KAC-1013

<b>Message</b>	Archival of the Actual DEK to the KV <Keyvault IP Address> failed. Actual Key: <Actual Key Id>. Error code=<Error code>, string=<Error string>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that archiving of actual Data Encryption Key (DEK) to the key vault failed.
<b>Recommended Action</b>	No action is required.

## KAC-1014

<b>Message</b>	Retrieval of Actual DEK from the KV <Keyvault IP Address> failed. Actual Key: <Actual Key Id>. Error code=<Error code>, string=<Error string>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that retrieving of actual Data Encryption Key (DEK) from the key vault failed.
<b>Recommended Action</b>	No action is required.

## KAC-1015

<b>Message</b>	KAC(<Key Vault Type>) communication Error: Error connecting to <Key Vault IP>. Error code=<Error code>, string=<Error string>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Key Archive Client (KAC) is unable to communicate with the primary or backup key vault.
<b>Recommended Action</b>	Change the switch key vault settings and make sure the configured key vault is operational.

## KAC-1016

<b>Message</b>	Error: Key ID mismatched in request/response. Requested key ID <Key ID in response> and key in response <Requested Key Id>. Error code=<Error code>, string=<Error string>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a mismatch between the requested key ID and the key in the response from the key vault.
<b>Recommended Action</b>	Determine whether the configured key vault is operational; if not, change the switch key vault settings or resolve the operational problem at the key vault.

## KAC-1017

<b>Message</b>	Error: KV parameter [<param name>] configured on BES is not supported by the Key Vault. Please fix the configuration of the parameter to ensure key operations function as expected.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a mismatch between the configured key vault parameters on the Brocade Encryption Switch (BES) and the functionality supported by the key vault.
<b>Recommended Action</b>	De-register the key vaults, set the correct value for key vault parameter, and re-register the key vaults.

## KSWD Messages

### KSWD-1001

<b>Message</b>	<Software component>:<Software component Process ID> failed to refresh (<Current time>:<Refresh time>).
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that one of the critical daemons is found to be unresponsive. An abort signal is sent.
<b>Recommended Action</b>	Copy the warning message along with any core file information and contact your switch service provider.

### KSWD-1002

<b>Message</b>	Detected termination of process <Software component>:<Software component Process ID>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a process on the switch has ended unexpectedly.
<b>Recommended Action</b>	Copy the warning message along with any core file information and contact your switch service provider.

## KTRC Messages

### KTRC-1001

<b>Message</b>	Dump memory size exceeds dump file size.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the dump memory size has exceeded the dump file size.
<b>Recommended Action</b>	Execute the <b>supportSave</b> command and reload the switch. If the problem persists, contact your switch service provider.

### KTRC-1002

<b>Message</b>	Concurrent trace dumping.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the initial background dump has not completed.
<b>Recommended Action</b>	No action is required.

### KTRC-1003

<b>Message</b>	Cannot open ATA dump device.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the advanced technology attachment (ATA) dump driver is not initialized properly.
<b>Recommended Action</b>	Execute the <b>supportSave</b> command and reload the switch. If the problem persists, contact your switch service provider.

## KTRC-1004

<b>Message</b>	Cannot write to ATA dump device.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the write boundary in the advanced technology attachment (ATA) dump device has exceeded.
<b>Recommended Action</b>	Execute the <b>supportSave</b> command and reload the switch. If the problem persists, contact your switch service provider.

## KTRC-1005

<b>Message</b>	Trace initialization failed. <Reason initialization failed>. <Internal error code>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that trace was unable to initialize.
<b>Recommended Action</b>	Execute the <b>supportSave</b> command and reload the switch. If the problem persists, contact your switch service provider.

## L2SS Messages

### L2SS-1001

<b>Message</b>	Linux socket error - error reason: <reason>, socket name: <socketname>, error name: <errorname>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that an error has occurred in the Linux socket.
<b>Recommended Action</b>	Reboot or power cycle the switch.

### L2SS-1002

<b>Message</b>	Initialization error: <reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Layer 2 system (L2SYS) encountered an error during initialization.
<b>Recommended Action</b>	Reboot or power cycle the switch.

### L2SS-1003

<b>Message</b>	Message Queue Error: Message queue create failed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Layer 2 system (L2SYS) encountered system service manager (SSM) message queue errors.
<b>Recommended Action</b>	Reboot or power cycle the switch.



## L2SS-1004

<b>Message</b>	FDB error: Error in creating AVL tree.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Layer 2 system (L2SYS) has encountered an error while initializing the AVL tree.
<b>Recommended Action</b>	Reboot or power cycle the switch.

## L2SS-1005

<b>Message</b>	MAC-address-table hash failed even after two attempts for slot <slot> chip <chip>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the media access control (MAC) address table hash failed even after two hash changes on the specified chip.
<b>Recommended Action</b>	Reboot or power cycle the switch.

## L2SS-1006

<b>Message</b>	MAC-address-table table on slot <Slot_id> chip <Chip_id> is 95 percent full.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the media access control (MAC) address table on the chip is 95 percent full.
<b>Recommended Action</b>	Clear some of the entries using the <b>no mac-address-table static</b> command or wait until the old entries age out.

## L2SS-1007

<b>Message</b>	MAC-address-table on slot <Slot_id> chip <Chip_id> is less than 90 percent full.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the media access control (MAC) address table on the specified chip is less than 90 percent full.
<b>Recommended Action</b>	No action is required. The Layer 2 system (L2SYS) starts learning the entries.

## L2SS-1008

<b>Message</b>	Hardware GID limit reached on chip <Chip_id>, GID limit at <Max_gid>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that all dynamic group IDs (GIDs) are allocated.
<b>Recommended Action</b>	Clear some of the ACL entries using the <b>clear counters access-list mac</b> command.

## L3SS Messages

### L3SS-1004

<b>Message</b>	<Function Name>, <Line No>: HW/Driver Error (possibly the CAM is full): <HW Error Message>, rc=<Error Code>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an error in the hardware or the driver of the Layer 3 subsystem (L3SS). L3SS may have passed invalid parameters or the hardware Content Addressable Memory (CAM) may be full.
<b>Recommended Action</b>	Retry or clear the CAM.

## LACP Messages

### LACP-1001

<b>Message</b>	<module> Error opening socket (<error>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that initialization of the specified module within the Link Aggregation Control Protocol (LACP) daemon has failed.
<b>Recommended Action</b>	Download a new firmware using the <b>firmwareDownload</b> command.

### LACP-1002

<b>Message</b>	<msg>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that some of the fields received in the Link Aggregation Control Protocol Data Unit (LACPDU) are invalid.
<b>Recommended Action</b>	No action is required.

## LANCE Messages

### LANCE-1000

<b>Message</b>	Slot <slot number> Port GE<port number>: Maximum attempts to restart failed. Disabling port.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified port has crashed unexpectedly and restarting attempts have failed.
<b>Recommended Action</b>	Power cycle the blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands.

## LFM Messages

### LFM-1001

<b>Message</b>	The Logical Fabric Manager service is disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Logical Fabric Manager service is disabled. Note that the Logical Fabric Manager service is enabled by the factory setting and it is not user-configurable.
<b>Recommended Action</b>	No action is required.

### LFM-1002

<b>Message</b>	The Logical Fabric Manager service is enabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Logical Fabric Manager service is enabled. Note that the Logical Fabric Manager service is enabled by the factory setting and it is not user-configurable.
<b>Recommended Action</b>	No action is required.

### LFM-1003

<b>Message</b>	The Logical Fabric Manager configuration is set to default.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Logical Fabric Manager configuration is set to default. This will remove all prior Logical Fabric Manager configurations. This operation is not supported currently.
<b>Recommended Action</b>	No action is required.

## LFM-1004

<b>Message</b>	HA is out of sync for opcode <HA_OPCODE>, error value <error value>.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates loss of high availability (HA) sync with remote control processor (CP).
<b>Recommended Action</b>	Collect the supportsave information using the <b>supportsave</b> command and contact the Brocade technical support.

## LFM-1005

<b>Message</b>	Logical port <portnum> disabled with reason <reason code>(<reason string>)
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified logical port is disabled for an internal logging purpose. This could be due to port segmentation.
<b>Recommended Action</b>	Check the reason for port disable using the <b>switchShow</b> command, and take appropriate corrective action.

## LFM-1006

<b>Message</b>	The switch with domain <domain> with firmware version <version> has joined the FID <FID> fabric and may not be compatible with XISL use.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the firmware version on the specified switch is not compatible with XISL.
<b>Recommended Action</b>	Check the release notes to verify if this firmware is compatible with XISL. If it is not, remove the switch from the fabric.

## LOG Messages

### LOG-1000

<b>Message</b>	Previous message repeated <repeat count> time(s).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the previous message was repeated the specified number of times.
<b>Recommended Action</b>	No action is required.

### LOG-1001

<b>Message</b>	A log message was dropped.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a log message was dropped. A trace dump file has been created.
<b>Recommended Action</b>	Execute the <b>reboot</b> command for non-bladed switches or the <b>haFailover</b> command on bladed switches. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

### LOG-1002

<b>Message</b>	A log message was dropped.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a message was not recorded by the error logging system. A trace dump file has been created. The message may still be visible through Simple Network Management Protocol (SNMP) or other management tools.
<b>Recommended Action</b>	Execute the <b>reboot</b> command for non-bladed switches or the <b>haFailover</b> command on bladed switches. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.



## LOG-1003

<b>Message</b>	The log has been cleared.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the persistent error log has been cleared.
<b>Recommended Action</b>	No action is required.

## LOG-1004

<b>Message</b>	Log message <Log message that has been blocked> flooding detected and blocked.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a message has been flooding and was blocked.
<b>Recommended Action</b>	Execute the <b>reboot</b> command. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## LOG-1005

<b>Message</b>	Log message <Log message that has been disabled> has been disabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	RAS
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified message has been disabled from logging.
<b>Recommended Action</b>	No action is required.

## LOG-1006

<b>Message</b>	Log message <Log message that has been enabled> has been enabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	RAS
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified message has been enabled for logging.
<b>Recommended Action</b>	No action is required.

## LOG-1007

<b>Message</b>	Log Module <Log Module that has been disabled> has been disabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	RAS
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified module has been disabled from logging.
<b>Recommended Action</b>	No action is required.

## LOG-1008

<b>Message</b>	Log Module <Log Module that has been enabled> has been enabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	RAS
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified module has been enabled for logging.
<b>Recommended Action</b>	No action is required.

## LOG-1009

<b>Message</b>	Internal Log message <Log message that has been enabled to be sent to syslog server> has been enabled for syslog logging.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified internal message has been enabled for syslog logging.
<b>Recommended Action</b>	No action is required.

## LOG-1010

<b>Message</b>	Internal Log message <Log message that has been disabled from being sent to syslog server> has been disabled from syslog logging.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified internal message has been disabled from syslog logging.
<b>Recommended Action</b>	No action is required.

## LOG-1011

<b>Message</b>	Log Message <Log Message Id> severity has been changed to <Severity>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	RAS
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the severity level of the specified log message has been changed.
<b>Recommended Action</b>	No action is required.

## LSDB Messages

### LSDB-1001

<b>Message</b>	Link State ID <link state ID> out of range.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified link state ID is out of the acceptable range. The valid link state ID is the same as the valid domain ID, with a range from 1 through 239. The switch will discard the record because it is not supported.
<b>Recommended Action</b>	No action is required.

### LSDB-1002

<b>Message</b>	Local Link State Record reached max incarnation.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the local link state record (LSR) reached the maximum number of incarnations. An "incarnation" is a progressive number that identifies the most recent version of the link state record (LSR). The switch generates its local LSR when first enabled. The incarnation number will begin again at 0x80000001 after reaching 0x7FFFFFFF.
<b>Recommended Action</b>	No action is required.

### LSDB-1003

<b>Message</b>	No database entry for local Link State Record, domain <local domain>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that there is no local link state record (LSR) entry in the link state database (LSDB). The switch should always generate its own local entry when starting up. An "incarnation" is a progressive number that identifies the most recent version of the LSR. The switch generates its local LSR when first enabled. By disabling and enabling the switch, a new local LSR is generated.

**Recommended Action** Run the **switchDisable** and **switchEnable** commands. A new local LSR is generated during the switch enable.

## LSDB-1004

**Message** No Link State Record for domain <local domain>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that there is no link state record (LSR) for the specified local domain.

**Recommended Action** No action is required. The other switch will pass the LSR after the fabric is stable.

## MCAST\_SS Messages

### MCAST\_SS-1001

<b>Message</b>	Socket Error: <op> (<reason>) for socket <sockname> the error code <errorname>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that an error has occurred in the Linux socket.
<b>Recommended Action</b>	Restart the multicast subsystem (MCAST_SS) daemon.

### MCAST\_SS-1002

<b>Message</b>	Socket Error: <op> sock name <sock> Error <error> type <type> seq <seq> pid <pid>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the error has occurred while processing the hardware abstraction layer (HAL) message.
<b>Recommended Action</b>	Restart the multicast subsystem (MCAST_SS) daemon.

### MCAST\_SS-1003

<b>Message</b>	Learning error: <op> (<reason>) - VLAN <vid> MAC/group <address>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the multicast subsystem (MCAST_SS) has encountered an error while learning the media access control (MAC) addresses.
<b>Recommended Action</b>	Restart the MCAST_SS daemon.

## MCAST\_SS-1004

<b>Message</b>	NSM error: <op> (<reason>) for VLAN <vid> port <port>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the multicast subsystem (MCAST_SS) has encountered an error during a network service module (NSM) event.
<b>Recommended Action</b>	Restart the MCAST_SS daemon.

## MCAST\_SS-1005

<b>Message</b>	Message error: Invalid message type <type> expecting <value1> or <value2> or <value3>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the type of the message received from the driver is invalid.
<b>Recommended Action</b>	Restart the MCAST_SS daemon.

## MCAST\_SS-1006

<b>Message</b>	Message error: <op> (<reason>) Invalid message length <length> expecting <length1>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that length of the message received from the driver is invalid.
<b>Recommended Action</b>	Restart the MCAST_SS daemon.

## MCAST\_SS-1007

<b>Message</b>	Initialization error: <op> (<reason>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the multicast subsystem (MCAST_SS) has encountered an error during initialization.
<b>Recommended Action</b>	Restart the MCAST_SS daemon.

## MCAST\_SS-1008

<b>Message</b>	HAL error: <op> (<reason>) - VLAN <vid> MAC/group <address>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the multicast subsystem (MCAST_SS) has encountered the hardware abstraction layer (HAL) errors.
<b>Recommended Action</b>	Restart the MCAST_SS daemon.

## MCAST\_SS-1009

<b>Message</b>	L2SS error : <op> (<reason>) VLAN <vid> MAC <mac address>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the multicast subsystem (MCAST_SS) has encountered the Layer 2 subsystem (L2SS) related errors.
<b>Recommended Action</b>	Restart the MCAST_SS daemon.



## MCAST\_SS-1010

<b>Message</b>	Message Queue error: <op> (<reason>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the multicast subsystem (MCAST_SS) has encountered the message queue errors.
<b>Recommended Action</b>	Restart the MCAST_SS daemon.

## MCAST\_SS-1011

<b>Message</b>	IDB error: <op> (<reason>) port id <portid> not found.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified port ID is invalid.
<b>Recommended Action</b>	Restart the MCAST_SS daemon.

## MCAST\_SS-1012

<b>Message</b>	IDB error: <op> (<reason>) VLAN VID <vid> not found.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified VLAN ID (VID) is invalid.
<b>Recommended Action</b>	Restart the MCAST_SS daemon.

## MCAST\_SS-1013

<b>Message</b>	Snooping DB error: <op> (<reason>) Group Not found - VLAN <vid> group <group address>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the group address lookup for the specified VLAN has failed.

## 5 MCAST\_SS-1014

**Recommended Action** Restart the MCAST\_SS daemon.

### MCAST\_SS-1014

**Message** Snooping DB error: <op> (<reason>) MAC Not found - VLAN <vid> MAC-addr <mac address>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the media access control (MAC) address lookup for the specified VLAN has failed.

**Recommended Action** Restart the MCAST\_SS daemon.

### MCAST\_SS-1015

**Message** HSL error: <op> (<reason>) failed for message <message> VLAN <vid> MAC <mac address> mgid <mgid> CPU <cpu>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the specified hardware subsystem layer (HSL) related operation has failed.

**Recommended Action** Restart the MCAST\_SS daemon.

### MCAST\_SS-1016

**Message** Message error: <op> (<reason>) <length>(<length1>).

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the length of the message received from the driver is invalid.

**Recommended Action** Restart the MCAST\_SS daemon.

## MCAST\_SS-1017

<b>Message</b>	Learning error: <op> (<reason>) Invalid number <port> for ifindex <ifindex>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the multicast subsystem (MCAST_SS) has encountered an error while learning the media access control (MAC) addresses.
<b>Recommended Action</b>	Restart the MCAST_SS daemon.

## MCAST\_SS-1018

<b>Message</b>	Memory Alloc Error: <op> (<reason>) type <memtype>/<memsize>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the multicast subsystem (MCAST_SS) has encountered an error during the memory allocation.
<b>Recommended Action</b>	Restart the MCAST_SS daemon.

## MCAST\_SS-1019

<b>Message</b>	Ptree Error: <op> (<reason>) VLAN <vid> MAC/group <address>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the multicast subsystem (MCAST_SS) has encountered an error during the Ptree operation.
<b>Recommended Action</b>	Restart the MCAST_SS daemon.

## 5 MCAST\_SS-1020

### MCAST\_SS-1020

<b>Message</b>	List Error: <op> (<reason>) VLAN <vid> MAC <mac address> group <group address>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the multicast subsystem (MCAST_SS) has encountered an error during the List operation.
<b>Recommended Action</b>	Restart the MCAST_SS daemon.

## MFIC Messages

### MFIC-1001

<b>Message</b>	<code>failure at sysmod_scn registry rc= &lt;failure reason&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the system is temporarily out of resources.
<b>Recommended Action</b>	No action is required; this message is often transitory. If the message persists, run the <b>reboot</b> or the <b>haFailover</b> command (if applicable). If the message persists, run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

### MFIC-1002

<b>Message</b>	Chassis FRU header not programmed for switch NID, using defaults (applies only to FICON environments).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that custom switch node descriptor (NID) fields have not been programmed in nonvolatile storage. The default values are used. The Switch NID is used only in the following SB ELS frames: Request Node Identification Data (RNID) and Registered Link Incident Record (RLIR). The use of SB-3 link incident registration and reporting is typically limited to FICON environments.
<b>Recommended Action</b>	No action is required if SB-3 link incident registration and reporting is not used by the host or if default values are desired for the switch node descriptor fields.

### MFIC-1003

<b>Message</b>	Effective Insistent domain ID for the fabric changed from <state> to <state>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that one or more switches joined the fabric with an insistent domain ID (IDID) mode setting that is different from the current effective IDID mode for the fabric. This message also occurs when the IDID for the fabric has been turned on or off. The possible values for the state are "On" and "Off".

## 5 MFIC-1003

**Recommended Action** IDID mode is a fabric-wide mode; make sure that any switches added to the fabric are configured with the same IDID mode as the fabric. If you are enabling or disabling IDID mode, this message is for information purposes only, and no action is required. IDID mode can be set using the **configure** command in the CLI or checking the Advanced Web Tools **Switch Admin > Configure > Fabric > Insistent Domain ID Mode** check box. The switch must be disabled to change the IDID mode.

## MM Messages

### MM-1001

<b>Message</b>	VPD block 0 CRC is bad.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that CRC in the VPD block 0 is bad. This could indicate corruption or tampering.
<b>Recommended Action</b>	Execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## MPTH Messages

### MPTH-1001

<b>Message</b>	Null parent, lsId = <number>.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a null parent was reported. The minimum cost path (MPATH) uses a tree structure in which the parent is used to connect to the root of the tree.
<b>Recommended Action</b>	No action is required.

### MPTH-1002

<b>Message</b>	Null lsrP, lsId = <ls ID number>.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a link state record (LSR) is null.
<b>Recommended Action</b>	No action is required.

### MPTH-1003

<b>Message</b>	No minimum cost path in candidate list.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the fabric shortest path first (FSPF) module has determined that there is no minimum cost path (MPATH) available in the candidate list.
<b>Recommended Action</b>	No action is required.



## MQ Messages

### MQ-1004

<b>Message</b>	<code>mqRead, queue = &lt;queue name&gt;, queue ID = &lt;queue ID&gt;, type = &lt;message type&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	<p>Indicates an unexpected message has been received in the specified message queue. The <i>queue name</i> value is always <code>fspf_q</code>. The <i>queue ID</i> and <i>message type</i> values can be any of the following:</p> <ul style="list-style-type: none"> <li>• 2 - MSG_TX</li> <li>• 3 - MSG_INTR</li> <li>• 4 - MSG_STR</li> <li>• 6 - MSG_ASYNC_IU</li> <li>• 7 - MSG_LINIT_IU</li> <li>• 8 - MSG_RSCN</li> <li>• 9 - MSG_IOCTL</li> <li>• 10 - MSG_ACCEPT</li> <li>• 11 - MSG_IU_FREE</li> <li>• 12 - MSG_US</li> <li>• 13 - MSG_EXT_RSCN</li> <li>• 14 - MSG_RDTS_START</li> <li>• 15 - MSG_RDTS_SENDEFP</li> <li>• 16 - MSG_RDTS_RESET</li> </ul>
<b>Recommended Action</b>	No action is required.

### MQ-1005

<b>Message</b>	<code>queue &lt;queue name&gt;: queue full (miss=&lt;miss count&gt;).</code>
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified message queue is full.
<b>Recommended Action</b>	No action is required.

## 5 MQ-1006

### MQ-1006

<b>Message</b>	queue <queue name>: msg too long (<number of bytes>:<message queue size>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the incoming message size is larger than the message queue size.
<b>Recommended Action</b>	No action is required.

## MS Messages

### MS-1001

<b>Message</b>	MS Platform Segmented port= <code>&lt;port number&gt; (0x&lt;port number (hex)&gt;)</code> ( <code>&lt;reason for segmentation&gt; &lt;domain&gt; (0x&lt;domain (hex)&gt;)</code> ).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Management Server (MS) has segmented from another switch domain at the specified port because of errors or inconsistencies defined in the MS platform service.
<b>Recommended Action</b>	Reboot or power cycle the switch.

### MS-1002

<b>Message</b>	MS Platform Service Unstable( <code>&lt;message string&gt;&lt;domain number&gt;</code> ).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	<p>Indicates that the Management Server (MS) platform service is unstable.</p> <p>The <i>message string</i> value can be one of the following:</p> <ul style="list-style-type: none"> <li>No Resp for GCAP from: The switch did not respond to a request for a GCAP (MS Get Capabilities) command.</li> <li>GCAP sup but not PL by: GCAP is supported but the flag for MS platform service is not set.</li> <li>GCAP Rejected (reason =BUSY) by: GCAP is not supported by another switch.</li> <li>Reject EXGPLDB from: The request to the exchange platform database was rejected. The remote switch may be busy.</li> </ul> <p>The <i>domain number</i> is the target domain that caused the error.</p>
<b>Recommended Action</b>	<p>The recommended actions are as follows:</p> <ul style="list-style-type: none"> <li>No Resp for GCAP from: No action is required.</li> <li>GCAP sup but not PL by: Set the flag for the MS platform service.</li> <li>GCAP Rejected (reason =BUSY) by: Execute the <b>firmwareDownload</b> command to upgrade the firmware level on the switch to a level that supports reliable commit service (RCS). RCS is supported in Fabric OS v2.6, v3.1 and later, and v4.1 and later.</li> <li>Reject EXGPLDB from: Wait a few minutes and try the command again.</li> </ul>

## MS-1003

<b>Message</b>	MS detected Unstable Fabric(<message string><domain number>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	<p>Indicates that the Management Server (MS) detected an unstable fabric; the command or operation may not be successfully completed. This message is often transitory.</p> <p>The <i>message string</i> value can be one of the following:</p> <ul style="list-style-type: none"> <li>• DOMAIN_INVALID for a req from: The domain is invalid for a request.</li> <li>• No WWN for: Unable to acquire the World Wide Name (WWN) for the corresponding domain.</li> </ul> <p>The <i>domain number</i> is the target domain that caused error.</p>
<b>Recommended Action</b>	<p>The fabric may be reconfiguring, forming, or merging. Wait a few minutes and try the operation again.</p> <p>Execute the <b>fabricShow</b> command or the <b>secFabricShow</b> command to verify that the number of domains matches the Management Server known domains.</p> <p>If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.</p>

## MS-1004

<b>Message</b>	MS detected ONLY 1 Domain(d=<domain in local resource>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Management Server (MS) detected an unstable count of domains in its own local resource. This message is often transitory.
<b>Recommended Action</b>	<p>The fabric may be reconfiguring, forming, or merging. Wait a few minutes and try the operation again.</p> <p>Execute the <b>fabricShow</b> command or the <b>secFabricShow</b> command to verify that the number of domains matches the Management Server known domains.</p> <p>If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.</p>

## MS-1005

<b>Message</b>	MS Invalid CT Response from d=<domain>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Management Server (MS) received an invalid common transport (CT) response from the switch domain. MS expects either a CT accept IU or a reject IU; the MS received neither response, which violates the Fibre Channel - Generic Services (FS-GS) specification.
<b>Recommended Action</b>	Check the integrity of the FC switch at the specified domain. It is not sending correct MS information as defined by the Fibre Channel - Framing and Signaling (FC-FS) standard.

## MS-1006

<b>Message</b>	MS Unexpected iu_data_sz=<number of bytes>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Management Server (MS) received an information unit (IU) data of unexpected size. The IU payload and the IU size may be inconsistent with each other or with the command that is currently being processed.
<b>Recommended Action</b>	Wait a few minutes and try the operation again. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## MS-1008

<b>Message</b>	MS Failure while initializing <action>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Management Server (MS) failed while initializing the specified action. This message is often transitory. The <i>action</i> can be one of the following: <ul style="list-style-type: none"> <li>• while writing to ms_els_q: MS is unable to write a message to the MS Extended Link Service Queue.</li> <li>• while inserting timer to timer list: MS is unable to add a timer to a resource.</li> </ul>
<b>Recommended Action</b>	If the error persists, check the available memory on the switch using the <b>memShow</b> command.

## MS-1009

<b>Message</b>	RLIR event. Slot/Port <slot number>/<port number> (0x<PID (hex)>). Device Port Tag is 0x<port tag>. <message text>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a registered link incident record (RLIR) has been generated for one of the actions indicated by the <i>message</i> value. The <i>message</i> value can be one of the following: <ul style="list-style-type: none"> <li>• Exceeded bit error rate threshold</li> <li>• Loss of signal or synchronization</li> <li>• Not operational seq recognized</li> <li>• Primitive sequence timeout</li> <li>• Unrecognized link incident</li> </ul>
<b>Recommended Action</b>	Persistent RLIR incidents are likely the result of SAN hardware problems such as bad cables or small form-factor pluggable (SFP) transceivers. If the message persists, replace hardware.

## MS-1021

<b>Message</b>	MS WARMBOOT failure(FSS_MS_WARMINIT failed. Reason=<failure reason>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Fabric OS state synchronization (FSS) warm recovery failed during the WARM INIT phase of a reboot.
<b>Recommended Action</b>	If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## MS-1022

<b>Message</b>	Management Server Platform Service <Activated or Deactivated>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Management Server (MS) platform service is being activated or deactivated.
<b>Recommended Action</b>	No action is required.

## MS-1023

<b>Message</b>	Management Server Topology Discovery Service <Enabled or Disabled>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Management Server (MS) topology discovery service is being enabled or disabled.
<b>Recommended Action</b>	No action is required.

## MS-1024

<b>Message</b>	Management Server Access Control List is Updated.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Management Server (MS) Access Control List (ACL) is saved to nonvolatile storage.
<b>Recommended Action</b>	No action is required.

## MS-1025

<b>Message</b>	Possible Failover could have occurred while enabling MS Platform Service.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a failover occurred when Management Server (MS) platform service was being enabled. This can leave the fabric in an inconsistent state.
<b>Recommended Action</b>	If any inconsistency in MS platform service exists within the fabric, enable MS platform service.

## MS-1026

<b>Message</b>	MS Platform disabled port <port number> domain <domain> to block enabling Platform service through merge operation.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Management Server (MS) has disabled the specified E_Port connected to the specified domain because an implicit enable operation of the MS platform service has been blocked.
<b>Recommended Action</b>	Enable MS platform service on the switch and re-enable the port to join the fabric.

## MS-1027

<b>Message</b>	Fabric Name - <fabric_name> configured.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified fabric name is configured or renamed.
<b>Recommended Action</b>	No action is required.

## MS-1028

<b>Message</b>	Fabric Name - <fabric_name> Cleared.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified fabric name is cleared.
<b>Recommended Action</b>	No action is required.



## MS-1029

<b>Message</b>	Duplicate Fabric Name - <fabric_name> matching with FID <Fabric ID>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FABRIC
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the configured fabric name is already used for another partition.
<b>Recommended Action</b>	Select a different fabric name and reconfigure.

## MS-1030

<b>Message</b>	Fabric Name - <fabric_name> <cmd> Failed for domain <domain>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FABRIC
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that fabric name configure or clear operation failed in Fibre Channel Router (FCR).
<b>Recommended Action</b>	Wait for fabric to stabilize and retry the operation.

## MSTP Messages

### MSTP-1001

**Message** <message>: <message>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the system has failed to allocate memory.

**Recommended Action** Check the memory usage on the switch using the **memShow** command.  
Restart or power cycle the switch.

### MSTP-1002

**Message** <message>: <message>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the system has failed to initialize.

**Recommended Action** Restart or power cycle the switch.

### MSTP-1003

**Message** <message>: <message>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates a connection, transfer, or receiving error in the socket.

**Recommended Action** If this is a bladed switch, execute the **haFailover** command. If the problem persists or if this is a non-bladed switch, download a new firmware version using the **firmwareDownload** command.

## MSTP-2001

<b>Message</b>	<message>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the multiple spanning tree protocol (MSTP) bridge mode has changed.
<b>Recommended Action</b>	No action is required.

## MSTP-2002

<b>Message</b>	<Bridge mode information>. My Bridge ID: <Bridge ID> Old Root: <Old Root ID> New Root: <New Root ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the multiple spanning tree protocol (MSTP) bridge or bridge instance root has been changed.
<b>Recommended Action</b>	No action is required.

## MSTP-2003

<b>Message</b>	MSTP instance <instance> is created.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified multiple spanning tree protocol (MSTP) instance has been created.
<b>Recommended Action</b>	No action is required.

## MSTP-2004

<b>Message</b>	MSTP instance <instance> is deleted.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified multiple spanning tree protocol (MSTP) instance has been deleted.
<b>Recommended Action</b>	No action is required.

## MSTP-2005

<b>Message</b>	VLAN <vlan_ids> is <action> on MSTP instance <instance>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified multiple spanning tree protocol (MSTP) instance has been modified.
<b>Recommended Action</b>	No action is required.

## MSTP-2006

<b>Message</b>	MSTP instance <instance> bridge priority is changed from <priority_old> to <priority_new>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified multiple spanning tree protocol (MSTP) instance priority has been modified.
<b>Recommended Action</b>	No action is required.

## NBFS Messages

### NBFS-1001

<b>Message</b>	Duplicate E_Port SCN from port <portnumber> in state <state change name> (<state change number>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a duplicate E_Port state change notification (SCN) was reported. The neighbor finite state machine (NBFSM) states are as follows: <ul style="list-style-type: none"> <li>• 0 - Down</li> <li>• 1 - Init</li> <li>• 2 - Database Exchange</li> <li>• 3 - Database Acknowledge Wait</li> <li>• 4 - Database Wait</li> <li>• 5 - Full</li> </ul>
<b>Recommended Action</b>	No action is required.

### NBFS-1002

<b>Message</b>	Wrong input: <state name> to neighbor FSM, state <current state name>, port <portnumber>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the wrong input was sent to the neighbor finite state machine (NBFSM). NBFSM states are as follows: <ul style="list-style-type: none"> <li>• 0 - Down</li> <li>• 1 - Init</li> <li>• 2 - Database Exchange</li> <li>• 3 - Database Acknowledge Wait</li> <li>• 4 - Database Wait</li> <li>• 5 - Full</li> </ul> <p>If this error occurs repeatedly, then there is a problem in the protocol implementation between two switches.</p>
<b>Recommended Action</b>	Run the <b>nbrStateShow</b> command to check the neighbor state of the port listed in the message. If it is Full, then this message can safely be ignored. Otherwise, run the <b>portDisable</b> and <b>portEnable</b> commands to refresh the port.

## NBFS-1003

<b>Message</b>	DB_XMIT_SET flag not set in state <current state name>, input <state name>, port <portnumber>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the database transmit set flag was not set for the specified input state on the specified port. Neighbor finite state machine (NBFSM) states are as follows: <ul style="list-style-type: none"> <li>• 0 - Down</li> <li>• 1 - Init</li> <li>• 2 - Database Exchange</li> <li>• 3 - Database Acknowledge Wait</li> <li>• 4 - Database Wait</li> <li>• 5 - Full</li> </ul>
<b>Recommended Action</b>	No action is required. The Fabric OS automatically recovers from this problem.

## NBFS-1004

<b>Message</b>	Wrong input: <state name> to neighbor FSM, state <current state name>, port <portnumber>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the wrong input was sent to the neighbor finite state machine (NBFSM). NBFSM states are as follows: <ul style="list-style-type: none"> <li>• 0 - Down</li> <li>• 1 - Init</li> <li>• 2 - Database Exchange</li> <li>• 3 - Database Acknowledge Wait</li> <li>• 4 - Database Wait</li> <li>• 5 - Full</li> </ul> <p>If this error occurs repeatedly, then there is a problem in the protocol implementation between two switches.</p>
<b>Recommended Action</b>	Run the <b>nbrStateShow</b> command to check the neighbor state of the port listed in the message. If it is Full, then this message can safely be ignored. Otherwise, run the <b>portDisable</b> and <b>portEnable</b> commands to refresh the port.

## NS Messages

### NS-1001

<b>Message</b>	The response for request 0x<CT command code> from remote switch 0x<Domain Id> is larger than the max frame size the remote switch can support.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the response payload exceeds the maximum frame size the remote switch can handle.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to upgrade the remote switch with Fabric OS v4.3 or later, or Fabric OS v3.2 or later, as appropriate for the switch type, so that it can support GMI to handle frame fragmentation and reassembly.  You can also reduce the number of devices connected to the local switch.

### NS-1002

<b>Message</b>	Remote switch 0x<Domain Id> has firmware revision lower than 2.2: <Firmware Revision 1st character><Firmware Revision 2nd character><Firmware Revision 3rd character><Firmware Revision 4th character> which is not supported.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the local switch cannot interact with the remote switch because of incompatible or obsolete firmware.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to upgrade the remote switch to the latest level of firmware.

### NS-1003

<b>Message</b>	Number of local devices <Current local device count>, exceeds the standby can support <Local device count that standby can support>, can't send update.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Name Server on the standby control processor (CP) has a lower supported capability than the active CP because of different firmware versions running on the active and standby CPs. This means that the active and standby CPs are out of sync. Any execution of the <b>haFailover</b> or <b>firmwareDownload</b> commands will be disruptive.

## 5 NS-1004

**Recommended Action** To avoid disruption of traffic in the event of an unplanned failover, schedule a firmware download so that the active and standby CPs have the same firmware version.  
Reduce the local device count to follow the capability of the earliest version of firmware.

### NS-1004

**Message** Number of local devices <Current local device count>, exceeds the standby can support <Local device count that standby can support>, can't sync.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the Name Server on the standby control processor (CP) has a lower supported capability than the active CP because of different firmware versions running on the active and standby CPs. This means that the active and standby CPs are out of sync. Any execution of the **haFailover** or **firmwareDownload** commands will be disruptive.

**Recommended Action** To avoid disruption of traffic in the event of an unplanned failover, schedule a firmware download so that the active and standby CPs have the same firmware version.  
Reduce the local device count to follow the capability of the earliest version of firmware.

### NS-1005

**Message** Zone size of <Effective Zone Size> has over the supporting limit of <Support Zone Size> for the remote switch domain ID <Remote Switch Domain ID>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates the effective zone size has exceeded the limit that a remote switch can support. The oversized portion will be truncated.

**Recommended Action** Reduce the zone size to 1024 or smaller, or upgrade the software of the remote switch to support 2048 zones.

### NS-1006

**Message** Duplicate WWN was detected with PID 0x<existing device PID> and 0x<new device PID>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that an existing device has the same World Wide Name (WWN) as that of a new device that has come online.



**Recommended Action** The switch will process the new process ID (PID) and leave the existing PID intact. Subsequent switch operations will clean up the obsolete PID. However, it is recommended that administrators remove devices with a duplicate WWN.

## NS-1007

**Message** NS has detected a logical ISL port <LISL port number> in TI zone <TI zone name> in fabric <Fabric ID>. Routing may not be setup correctly.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that a logical inter-switch link (LISL) is detected in a traffic isolation (TI) zone.

**Recommended Action** Remove the LISL port from the TI zone because the routing may not be set up correctly.

## NS-1008

**Message** Open FR license not installed.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that Open FR license is not installed and therefore local devices involved in Open FR will not function.

**Recommended Action** Install the Open FR license or relocate Open FR devices to a licensed switch.

## NS-1009

**Message** NS has detected a device with Node WWN as zero, pid 0x<device PID>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that a device has logged in with node World Wide Node Name (WWNN) as zero. Brocade Network Advisor (BNA) will not show the port connectivity.

**Recommended Action** Check the device that logged in. The device could be faulty.

## NS-1010

<b>Message</b>	CSCTL mode enabled on port <csctlport> QoS zoning will be ignored for devices on this port.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that class-specific control (CS_CTL) mode has been enabled on the specified port that has devices as members of a quality of service (QoS) zone.
<b>Recommended Action</b>	Remove the CS_CTL configured devices from the QoS zone.

## NS-1011

<b>Message</b>	NS has detected a failover flag disabled TI zone in a base switch <Domain Id> in fabric ID <Fabric ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a failover-disabled traffic isolation (TI) zone has been detected in a base switch fabric.
<b>Recommended Action</b>	Enable the failover flag or remove the TI zone with the disabled failover flag because the routing may not be set up correctly.

## NS-1012

<b>Message</b>	Detected duplicate WWPN [<WWPN>] - devices removed with PID 0x<existing device PID> and 0x<new device PID>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the devices with the same World Wide Port Name (WWPN) have been removed from the Name Server database.
<b>Recommended Action</b>	Verify the device reported with duplicate WWPN.

## NSM Messages

### NSM-1001

**Message**     Interface <InterfaceName> is online.

**Message Type**   LOG

**Severity**        INFO

**Probable Cause**   Indicates that the specified interface has come online after the protocol dependencies are resolved.

**Recommended Action**   No action is required.

### NSM-1002

**Message**     Interface <InterfaceName> is protocol down.

**Message Type**   LOG

**Severity**        INFO

**Probable Cause**   Indicates that the specified interface has gone offline because one of the protocol dependencies is unresolved.

**Recommended Action**   Check for the reason codes using the **show interface** command and resolve the protocol dependencies. The following are the possible reason codes:

- Admin down
- Link protocol down
- DOT1x authenticating
- Minimum member links not UP (applicable only for port-channel interfaces)
- DOT1x authentication failed
- BRCD remote link negotiation failed/LLDP disabled
- LAG negotiating/failed
- LAG admin state is down
- UNKNOWN

## NSM-1003

<b>Message</b>	Interface <InterfaceName> is link down.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified interface has gone offline because the link is down.
<b>Recommended Action</b>	Check whether the connectivity between the peer ports is proper, and the remote link is up using the <b>show interface</b> command.

## NSM-1004

<b>Message</b>	Interface <InterfaceName> is created.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified logical interface has been created.
<b>Recommended Action</b>	No action is required.

## NSM-1005

<b>Message</b>	The FCoE VLAN: <VlanName> is in use. Therefore, cannot disable the FCoE VLAN.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified Fibre Channel over Ethernet (FCoE) VLAN is used in the FCoE daemon (fcoed) and therefore cannot be disabled.
<b>Recommended Action</b>	Remove all the FCoE sessions from the FCoE VLAN member ports and then disable the FCoE VLAN.

## NSM-1006

<b>Message</b>	FCoE on VLAN: <VlanName> has been disabled successfully.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that FCoE has been disabled on the specified VLAN.

**Recommended Action** No action is required.

## NSM-1007

**Message** Chassis is <status>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the chassis has been enabled or disabled.

**Recommended Action** No action is required.

## NSM-1008

**Message** Blade (<slot number>) is <status>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified blade has been enabled or disabled.

**Recommended Action** No action is required.

## NSM-1009

**Message** Interface <InterfaceName> is deleted.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified logical interface has been deleted.

**Recommended Action** No action is required.

## NSM-1010

<b>Message</b>	InterfaceMode changed from <Mode_old> to <Mode_new> for interface <InterfaceName>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the interface mode has been changed.
<b>Recommended Action</b>	No action is required.

## NSM-1011

<b>Message</b>	OperationalEndpointMode changed from <Mode_old> to <Mode_new> for interface <InterfaceName>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the interface operational endpoint mode has been changed.
<b>Recommended Action</b>	No action is required.

## NSM-1012

<b>Message</b>	VLAN classifier group <group_id> is created.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified VLAN classifier group has been created.
<b>Recommended Action</b>	No action is required.

## NSM-1013

<b>Message</b>	VLAN classifier group <group_id> is deleted.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified VLAN classifier group has been deleted.
<b>Recommended Action</b>	No action is required.

## NSM-1014

<b>Message</b>	VLAN classifier rule <rule_id> is created.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified VLAN classifier rule has been created.
<b>Recommended Action</b>	No action is required.

## NSM-1015

<b>Message</b>	VLAN classifier rule <rule_id> is deleted.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified VLAN classifier rule has been deleted.
<b>Recommended Action</b>	No action is required.

## NSM-1016

<b>Message</b>	VLAN classifier rule <rule_id> is <action> on VLAN classifier group <group_id>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified VLAN classifier group has been modified.

## 5 NSM-1017

**Recommended Action** No action is required.

### NSM-1017

**Message** Interface <InterfaceName> is <action> on interface <Logical\_InterfaceName>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the logical interface member list has been changed.

**Recommended Action** No action is required.

### NSM-1018

**Message** <count> VLANs <except> will be allowed on interface <Logical\_InterfaceName>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the VLAN membership has been changed for the specified interface.

**Recommended Action** No action is required.

### NSM-1019

**Message** Interface <InterfaceName> is administratively up.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the administrative status of the specified interface has changed to up.

**Recommended Action** No action is required.



## NSM-1020

<b>Message</b>	Interface <InterfaceName> is administratively down.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the administrative status of the specified interface has changed to down.
<b>Recommended Action</b>	No action is required.

## ONMD Messages

### ONMD-1000

<b>Message</b>	LLDP is enabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the link layer discovery protocol (LLDP) is enabled globally.
<b>Recommended Action</b>	No action is required.

### ONMD-1001

<b>Message</b>	LLDP is disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the link layer discovery protocol (LLDP) is disabled globally.
<b>Recommended Action</b>	No action is required.

### ONMD-1002

<b>Message</b>	LLDP global configuration is changed.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the link layer discovery protocol (LLDP) global configuration has been changed.
<b>Recommended Action</b>	No action is required.

## ONMD-1003

<b>Message</b>	LLDP is enabled on interface <InterfaceName>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the link layer discovery protocol (LLDP) is enabled on the specified interface.
<b>Recommended Action</b>	No action is required.

## ONMD-1004

<b>Message</b>	LLDP is disabled on interface <InterfaceName>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the link layer discovery protocol (LLDP) is disabled on the specified interface.
<b>Recommended Action</b>	No action is required.

## ONMD-1005

<b>Message</b>	Using auto-sense on interface <InterfaceName> to update DCBX version.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the auto-sense feature is used to detect the Data Center Bridging eXchange (DCBX) version on the specified interface. The DCBX version field will be automatically updated between the Converged Enhanced Ethernet (CEE) version and the pre-CEE version depending on the link neighbor.
<b>Recommended Action</b>	No action is required.

## PDM Messages

### PDM-1001

<b>Message</b>	<code>Failed to parse the pdm config.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Parity Data Manager (PDM) process could not parse the configuration file. This may be caused by a missing configuration file during the installation.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

### PDM-1002

<b>Message</b>	<code>ipcInit failed.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Parity Data Manager (PDM) process could not initialize the inter-process communication (IPC) mechanism.
<b>Recommended Action</b>	If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

### PDM-1003

<b>Message</b>	<code>pdm [-d] -S &lt;service&gt; -s &lt;instance&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a syntax error occurred when trying to launch the Parity Data Manager (PDM) process.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## PDM-1004

<b>Message</b>	PDM memory shortage.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Parity Data Manager (PDM) process ran out of memory.
<b>Recommended Action</b>	Reboot or power cycle the switch. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## PDM-1005

<b>Message</b>	FSS register failed.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Parity Data Manager (PDM) failed to register with the Fabric OS synchronization service (FSS).
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## PDM-1006

<b>Message</b>	Too many files in sync.conf.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the sync.conf configuration file contains too many entries.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## PDM-1007

<b>Message</b>	File not created: <file name>. errno=<errno>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Parity Data Manager (PDM) process failed to create the specified file.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## PDM-1008

<b>Message</b>	Failed to get the number of U_Ports.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Parity Data Manager (PDM) system call to getCfg failed.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## PDM-1009

<b>Message</b>	Can't update Port Config Data.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Parity Data Manager (PDM) system call to setCfg failed.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## PDM-1010

<b>Message</b>	File open failed: <file name>, errno=<errno>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Parity Data Manager (PDM) process could not open the specified file.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## PDM-1011

<b>Message</b>	File read failed: <file name>, Length(read=<Number of character read>, expected=<Number of characters expected>), errno=<errno returned by read>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Parity Data Manager (PDM) process could not read data from the specified file.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## PDM-1012

<b>Message</b>	File write failed: <file name>. Length(read=<Number of character read>, write=<Number of characters written>), errno=<errno returned by write>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Parity Data Manager (PDM) process could not write data to the specified file.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## PDM-1013

<b>Message</b>	File empty: <File Name>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch configuration file <code>/etc/fabos/fabos.[0 1].conf</code> is empty.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## PDM-1014

<b>Message</b>	Access sysmod failed.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a system call to sysMod failed.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## PDM-1017

<b>Message</b>	System (<Error Code>): <Command>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the specified system call failed.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.



## PDM-1019

<b>Message</b>	File path or trigger too long.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that one line of the pdm.conf file is too long.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## PDM-1020

<b>Message</b>	Long path name (<Path>/<File Name>), Skip.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified file path name is too long. The maximum character limit is 49 characters.
<b>Recommended Action</b>	Use path names not exceeding 49 characters in length for the files to be replicated.

## PDM-1021

<b>Message</b>	Failed to download area port map.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a system call failed.
<b>Recommended Action</b>	Execute the <b>firmwareDownload</b> command to reinstall the firmware. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## PDM-1022

<b>Message</b>	The switch is configured only with IPv6 addresses.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Parity Data Manager (PDM) cannot synchronize with its peer because the firmware does not support IPv6.
<b>Recommended Action</b>	Configure the local switch with IPv4 addresses.

## PDM-1023

<b>Message</b>	RADIUS is configured with IPv6 addresses.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Parity Data Manager (PDM) cannot synchronize with its peer because the remote access dial-in user server (RADIUS) is configured with IPv6 addresses. IPv6 is not supported by older firmware.
<b>Recommended Action</b>	Configure RADIUS with IPv4 addresses.

## PDM-1024

<b>Message</b>	DNS is configured with IPv6 addresses.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Parity Data Manager (PDM) cannot synchronize with its peer because the Domain Name Service (DNS) is configured with IPv6 addresses. IPv6 is not supported by older firmware.
<b>Recommended Action</b>	Configure DNS with IPv4 addresses.

## PDM-1025

<b>Message</b>	LDAP is configured with IPv6 addresses.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Parity Data Manager (PDM) cannot synchronize with its peer because the Lightweight Directory Access Protocol (LDAP) server is configured with IPv6 addresses. IPv6 is not supported by older firmware.
<b>Recommended Action</b>	Configure the LDAP server with IPv4 addresses.

## PDM-1026

<b>Message</b>	User defined roles configured.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Parity Data Manager (PDM) cannot synchronize with its peer because the user-defined roles are configured. User-defined roles are not supported by older firmware.
<b>Recommended Action</b>	Remove user-defined roles configuration.

## PDTR Messages

### PDTR-1001

<b>Message</b>	<informational message>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that information has been written to the panic dump files. The watchdog register codes are as follows: <ul style="list-style-type: none"><li>• 0x10000000 - The watchdog timer (WDT) forced a core reset.</li><li>• 0x20000000 - The WDT forced a chip reset.</li><li>• All other code values are reserved.</li></ul>
<b>Recommended Action</b>	Run the <b>pdShow</b> command to view the panic dump and core dump files.

### PDTR-1002

<b>Message</b>	<informational message>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that information has been written to the panic dump and core dump files and a trap has been generated. The watchdog register codes are as follows: <ul style="list-style-type: none"><li>• 0x10000000 - The watchdog timer (WDT) forced a core reset.</li><li>• 0x20000000 - The WDT forced a chip reset.</li><li>• All other code values are reserved.</li></ul>
<b>Recommended Action</b>	Run the <b>pdShow</b> command to view the panic dump and core dump files.

## PLAT Messages

### PLAT-1000

<b>Message</b>	<Function name> <Error string>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that nonrecoverable peripheral component interconnect (PCI) errors have been detected.
<b>Recommended Action</b>	The system will be faulted and may automatically reboot. If the system does not reboot automatically, reboot the system manually using the <b>reboot</b> command. Execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

### PLAT-1001

<b>Message</b>	CP<Identifies which CP (0 or 1) is doing the reset> resetting other CP (double reset may occur).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the other control processor (CP) is being reset. This message is typically generated by a CP that is in the process of becoming the active CP. Note that in certain circumstances a CP may experience a double reset and reboot twice. A CP can recover automatically even if it has rebooted twice.
<b>Recommended Action</b>	No action is required.

### PLAT-1002

<b>Message</b>	CP<Identifies which CP (0 or 1) is generating the message>: <Error message> CP Fence 0x<CP Fence register. Contents (2 bytes) are platform-specific> 0x<CP Error register. Contents are platform-specific> CP Error 0x<Write control flag. Contents are platform-specific>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the control processor (CP) cannot access the inter-integrated circuit (I2C) subsystem because of an error condition or because of being fenced or isolated from the I2C bus.
<b>Recommended Action</b>	Reboot the CP if it does not reboot automatically. Reseat the CP if rebooting does not solve the problem. If the problem persists, replace the CP.

**PLAT-1003**

<b>Message</b>	<Info message> Slot <Blade Slot number> C/BE: 0x<Captured Command/Byte-Enables data> ADBUS: 0x<Captured AD bus data> misc_intr 0x<Bridge reset interrupts>.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that peripheral component interconnect (PCI) bus hang was detected.
<b>Recommended Action</b>	Replace the field-replaceable unit (FRU).

**PLAT-1004**

<b>Message</b>	Switch has older FPGA rev 0x<FPGA version already installed in HW>. Upgrade to newer rev 0x<FPGA version which Fabric OS carries> using the fpga_update command.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that Fabric OS has older field-programmable gate array (FPGA) version. This message is applicable only to Brocade 5470.
<b>Recommended Action</b>	Upgrade FPGA to new version.

**PLAT-1072**

<b>Message</b>	The chassis is disabled because no Core Blades are available. Insert/replace one or both Core Blades and run chassisenable.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the chassis has been disabled because of the unavailability of the core blades. There must be at least one core blade in enabled state for the chassis to be considered ready. All core blades are either missing, faulted, or powered off. This results in all logical switches (and ports) being disabled.
<b>Recommended Action</b>	Make sure that all core blade slots have core blades inserted and their ejector switches are closed. Power on core blades that are powered off, and power cycle or replace the core blades that are faulted. Run the <b>chassisenable</b> command to re-enable the ports. Running the <b>fastboot</b> or <b>reboot</b> command will also result in enabling the logical switches and ports.

## PMGR Messages

### PMGR-1001

<b>Message</b>	Attempt to create switch <FID> succeeded.
<b>Message Type</b>	LOG   AUDIT
<b>Class</b>	LS
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the switch with the specified fabric ID (FID) was successfully created.
<b>Recommended Action</b>	No action is required.

### PMGR-1002

<b>Message</b>	Attempt to create switch <FID> failed. Error message: <Error Message>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch with the specified fabric ID (FID) was not created.
<b>Recommended Action</b>	Refer to the <i>Error Message</i> string displayed in the message for possible action.

### PMGR-1003

<b>Message</b>	Attempt to delete switch <FID> succeeded.
<b>Message Type</b>	LOG   AUDIT
<b>Class</b>	LS
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the switch with the specified fabric ID (FID) was successfully deleted.
<b>Recommended Action</b>	No action is required.

## PMGR-1004

<b>Message</b>	Attempt to delete switch <FID> failed. Error message: <Error Message>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch with the specified fabric ID (FID) was not deleted.
<b>Recommended Action</b>	Refer to the <i>Error Message</i> string displayed in the message for possible action.

## PMGR-1005

<b>Message</b>	Attempt to move port(s) to switch <FID> succeeded.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a successful attempt to move the ports to the specified switch.
<b>Recommended Action</b>	No action is required.

## PMGR-1006

<b>Message</b>	Attempt to move port(s) <Ports> on slot <Slot> to switch <FID> failed. Error message: <Error Message>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an unsuccessful attempt to move the ports to the specified switch.
<b>Recommended Action</b>	Refer to the <i>Error Message</i> string displayed in the message for possible action.

## PMGR-1007

<b>Message</b>	Attempt to change switch <FID> to switch <New FID> succeeded.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates successful change of the switch fabric ID (FID).



**Recommended Action** No action is required.

## PMGR-1008

**Message** Attempt to change switch <FID> to switch <New FID> failed. Error message: <Error Message>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates a failed attempt to change the switch fabric ID (FID).

**Recommended Action** Refer to the *Error Message* string displayed in the message for possible action.

## PMGR-1009

**Message** Attempt to change the base switch to switch <FID> succeeded.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates successful change of the base switch.

**Recommended Action** No action is required.

## PMGR-1010

**Message** Attempt to change the base switch to switch <FID> failed. Error message: <Error Message>

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates a failed attempt to change the base switch.

**Recommended Action** Refer to the *Error Message* string displayed in the message for possible action.

## PMGR-1011

<b>Message</b>	Attempt to move port(s) to switch <FID> succeeded.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a successful attempt to move the ports to the specified switch.
<b>Recommended Action</b>	No action is required.

## PORT Messages

### PORT-1003

<b>Message</b>	Port <port number> Faulted because of many Link Failures.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the specified port is now disabled because the link on this port had multiple failures that exceeded an internally set threshold on the port. This problem is typically related to hardware.
<b>Recommended Action</b>	<p>Check and replace (if necessary) the hardware attached to both ends of the specified port number, including:</p> <ul style="list-style-type: none"><li>• The media (SFPs)</li><li>• The cable (fiber optic or copper inter-switch link (ISL))</li><li>• The attached devices</li></ul> <p>After checking the hardware, execute the <b>portEnable</b> command to re-enable the port.</p>

### PORT-1004

<b>Message</b>	Port <port number> (0x<port number (hex)>) could not be enabled because it is disabled due to long distance.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified port is not enabled because other ports in the same group have used the buffers for this port group. This happens when other ports were configured to be long distance.
<b>Recommended Action</b>	<p>To enable this port, perform one of the following actions:</p> <ul style="list-style-type: none"><li>• Reconfigure the other E_Ports so they are not long distance.</li><li>• Change the other E_Ports so they are not E_Ports.</li></ul> <p>This will free some buffers and allow this port to be enabled.</p>

## PORT-1005

<b>Message</b>	Slot <slot number> port <port on slot> does not support configured L_Port. Issue portCfgLport to clear configuration.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the specified port is configured to be an L_Port, but the port does not support L_Port. If an L_Port is connected, then the port will be disabled because the port does not support L_Port. If an E_Port or F_Port is connected, then the port will not come up because it is configured to be an L_Port.
<b>Recommended Action</b>	Execute the <b>portCfgLport</b> command to clear the L_Port configuration.

## PORT-1006

<b>Message</b>	Configuration changed for port (ID: <port number>) in No_Module or No_Light state.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the configuration changes were made to an offline port in the No_Module or No_Light state.
<b>Recommended Action</b>	No action is required.

## PORT-1007

<b>Message</b>	Port (ID: <port number>) has been renamed to (<port name>).
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a port has been reconfigured with a different name.
<b>Recommended Action</b>	No action is required.

## PORT-1008

<b>Message</b>	GigE Port (ID: <port number>) has been enabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a Gigabit Ethernet port has been enabled.
<b>Recommended Action</b>	No action is required.

## PORT-1009

<b>Message</b>	GigE Port (ID: <port number>) has been disabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a Gigabit Ethernet port has been disabled.
<b>Recommended Action</b>	No action is required.

## PORT-1010

<b>Message</b>	Port (ID: <port number>) QoS is disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the port quality of service (QoS) is disabled due to the best effort setting on the 4 Gbps or 8 Gbps long distance platform.
<b>Recommended Action</b>	No action is required.

## PS Messages

### PS-1000

<b>Message</b>	Failed to initialize Advanced Performance Monitoring.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that an unexpected software error has occurred in Advanced Performance Monitoring. The Performance Monitor has failed to initialize.
<b>Recommended Action</b>	The control processor (CP) will reboot or failover automatically. If it does not, reboot or power cycle the switch to reinitiate the firmware.

### PS-1001

<b>Message</b>	Advanced Performance Monitoring configuration updated due to change in PID format.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the port ID (PID) format was changed.
<b>Recommended Action</b>	No action is required. Refer to the <i>Fabric OS Administrator's Guide</i> for more information about the PID format.

### PS-1002

<b>Message</b>	Failed to initialize the tracing system for Advanced Performance Monitoring.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that an unexpected software error has occurred in Advanced Performance Monitoring. The Performance Monitor tracing system has failed to initialize.
<b>Recommended Action</b>	Tracing will not be available for Advanced Performance Monitoring, but other functions will function normally. To activate tracing, reboot or failover the control processor (CP).

## PS-1003

<b>Message</b>	Failed to set end-to-end monitoring mask on ISL ports.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the restoring configuration has attempted to set the end-to-end monitoring mask on at least one inter-switch link (ISL) port.
<b>Recommended Action</b>	No action is required. End-to-end monitoring is not supported on ISL ports when ISL monitoring is enabled. ISL monitoring can only be disabled through the Fabric Access API.

## PS-1004

<b>Message</b>	Failed to add end-to-end monitors on port <port> which is an ISL port.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the restoring configuration has attempted to add end-to-end monitors on at least one inter-switch link (ISL) port.
<b>Recommended Action</b>	No action is required. End-to-end monitoring is not supported on ISL ports when ISL monitoring is enabled. ISL monitoring can only be disabled through the Fabric Access API.

## PS-1005

<b>Message</b>	ISL monitor on port <port> stopped counting because no hardware resources are available.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that inter-switch link (ISL) and end-to-end monitors have used up all the hardware resources.
<b>Recommended Action</b>	To resume counting, delete some end-to-end monitors sharing the same hardware resource pool by using the <b>perfDeIEEMonitor</b> command.

## PS-1006

<b>Message</b>	Failed to add fabricmode toptalker monitors on domain=<domain id>, because end-to-end monitors are configured on this switch.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that end-to-end monitors are configured on the switch.
<b>Recommended Action</b>	Delete end-to-end monitors on the switch and re-install the fabric mode Top Talker monitor. End-to-end monitors and fabric mode Top Talker monitors are mutually exclusive.

## PS-1007

<b>Message</b>	Failed to add Fabricmode Top Talker on domain=<domain id>. <function name>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that FC Routing (FCR) is enabled on the specified fabric.
<b>Recommended Action</b>	Top Talker cannot be installed on a fabric with FCR service enabled. In case Top Talker must be installed on a fabric, disable FCR using the <b>fosconfig --disable fcr</b> command.

## PS-1008

<b>Message</b>	Failed to delete fabricmode Top Talker monitor on domain <domain id>, Failure reason: <error code>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the fabric is not stable, the domain is not reachable, or the resource is not available.
<b>Recommended Action</b>	Wait for the fabric to become stable and then execute the <b>perfttmon --delete fabricmode</b> command.



## PS-1009

<b>Message</b>	Failed to add the device updates in condb database.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the fabric has more than the allowed number of devices.
<b>Recommended Action</b>	Reduce the number of devices configured in the fabric to be within the allowed limit. The maximum number of devices that can be configured in a fabric is 940.

## PS-1010

<b>Message</b>	Removed <Toptaker mode> Top Talker on port <Port no>. Reason: <Reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that Top Talker on the specified port has been removed due to memory allocation failure.
<b>Recommended Action</b>	Install Top Talker again on the specified port using the <b>perfttmon --add</b> command.

## PSWP Messages

### PSWP-1001

**Message** PID for port <wwn name corresponding to source port> and port <wwn name corresponding to destination port> are swapped. New PID for port <wwn name corresponding to source port> is 0x<wwn name corresponding to destination port> and port <new area corresponding to source wwn> is 0x<new area corresponding to destination wwn>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates the **portSwap** command has been issued.

**Recommended Action** No action is required.

### PSWP-1002

**Message** Port Swap feature enabled.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates the port swap feature has been enabled in the switch.

**Recommended Action** No action is required.

### PSWP-1003

**Message** Port Swap feature disabled.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates the port swap feature has been disabled in the switch.

**Recommended Action** No action is required.

## PSWP-1004

<b>Message</b>	Blade Swap complete for slots <slot number corresponding to the source blade> and <slot number corresponding to the destination blade>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the <b>bladeSwap</b> command has been issued.
<b>Recommended Action</b>	No action is required.

## PSWP-1005

<b>Message</b>	Blade Swap undo failed with error code <error code from undoBladeSwap>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the <b>bladeSwap</b> command has not been undone.
<b>Recommended Action</b>	Use the <b>portSwapShow</b> command to display a list of currently swapped ports; then use the <b>portSwap</b> command to achieve the desired result.

## PSWP-1006

<b>Message</b>	Blade Swap failed on configInit with error code <error code from configInit> in switch number <current switch number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the <b>bladeSwap</b> command failed on access to configuration data.
<b>Recommended Action</b>	Retry the command. If the failure persists, contact your switch service provider.

## PSWP-1007

**Message** Blade Swap failed on fabosInit with error code <error code from fabosInit> in switch number <current switch number>.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates the **bladeSwap** command failed on access to switch context.

**Recommended Action** Retry the command. If the failure persists, contact your switch service provider.

## RAS Messages

### RAS-1001

<b>Message</b>	First failure data capture (FFDC) event occurred.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a first failure data capture (FFDC) event occurred and the failure data has been captured.
<b>Recommended Action</b>	Execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

### RAS-1002

<b>Message</b>	First failure data capture (FFDC) maximum storage size (<log size limit> MB) was reached.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the storage size for first failure data capture (FFDC) data has reached the maximum.
<b>Recommended Action</b>	Execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

### RAS-1004

<b>Message</b>	Software 'verify' error detected.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an internal software error.
<b>Recommended Action</b>	Execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## RAS-1005

<b>Message</b>	Software 'assert' error detected.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an internal software error.
<b>Recommended Action</b>	Execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## RAS-1006

<b>Message</b>	Support data file (<Uploaded file name>) automatically transferred to remote address ' <Remote target designated by user> '.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the support data was automatically transferred from the switch to the configured remote server.
<b>Recommended Action</b>	No action is required.

## RAS-1007

<b>Message</b>	System is about to reboot.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a system restart was initiated.
<b>Recommended Action</b>	No action is required.

## RAS-2001

<b>Message</b>	Audit message log is enabled.
<b>Message Type</b>	LOG   AUDIT
<b>Class</b>	RAS
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the audit message log has been enabled.
<b>Recommended Action</b>	No action is required.

## RAS-2002

<b>Message</b>	Audit message log is disabled.
<b>Message Type</b>	LOG   AUDIT
<b>Class</b>	RAS
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the audit message log has been disabled.
<b>Recommended Action</b>	No action is required.

## RAS-2003

<b>Message</b>	Audit message class configuration has been changed to <New audit class configuration>.
<b>Message Type</b>	LOG   AUDIT
<b>Class</b>	RAS
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the audit event class configuration has been changed.
<b>Recommended Action</b>	No action is required.

## RAS-3001

<b>Message</b>	USB storage device plug-in detected.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the USB storage device plug-in has been detected.
<b>Recommended Action</b>	No action is required.

## RAS-3002

<b>Message</b>	USB storage device enabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the USB storage device has been enabled.
<b>Recommended Action</b>	No action is required.

## RAS-3003

<b>Message</b>	USB storage device was unplugged before it was disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the USB storage device was unplugged before it was disabled.
<b>Recommended Action</b>	No action is required. It is recommended to disable the USB storage device using the <b>usbstorage -d</b> command before unplugging it from the system.

## RAS-3004

<b>Message</b>	USB storage device disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the USB storage device has been disabled.



**Recommended Action** No action is required.

## RAS-3005

**Message** CLI: <CLI command>.

**Message Type** AUDIT

**Class** CLI

**Severity** INFO

**Probable Cause** Indicates that the specified command was executed on console.

**Recommended Action** No action is required.

## RCS Messages

### RCS-1001

<b>Message</b>	RCS has been disabled. Some switches in the fabric do not support this feature.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the reliable commit service (RCS) feature has been disabled on the local switch because not all switches in the fabric support RCS or the switch is in non-native mode.
<b>Recommended Action</b>	Run the <b>rclInfoShow</b> command to view RCS capability on the fabric. RCS is supported in Fabric OS v2.6, v3.1 and later, and v4.1 and later.  Run the <b>firmwareDownload</b> command to upgrade the firmware for any switches that do not support RCS.

### RCS-1002

<b>Message</b>	RCS has been enabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the reliable commit service (RCS) feature has been enabled. RCS must be capable on all switches in the fabric to be enabled. If all switches are capable, it is automatically enabled.
<b>Recommended Action</b>	No action is required.

### RCS-1003

<b>Message</b>	Failed to allocate memory: (<function name>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified reliable commit service (RCS) function has failed to allocate memory.
<b>Recommended Action</b>	This message is usually transitory. Wait for few minutes and retry the command. Check memory usage on the switch using the <b>memShow</b> command. Reboot or power cycle the switch.

## RCS-1004

<b>Message</b>	Application(<application name>) not registered.(<error string>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified application did not register with reliable commit service (RCS).
<b>Recommended Action</b>	<p>Run the <b>haShow</b> command to view the HA state.</p> <p>Run the <b>haDisable</b> and <b>haEnable</b> commands.</p> <p>Run the <b>rcsInfoShow</b> command to view RCS capability on the fabric. RCS is supported in Fabric OS v2.6, v3.1 and later, and v4.1 and later.</p> <p>Run the <b>firmwareDownload</b> command to upgrade the firmware for any switches that do not support RCS.</p>

## RCS-1005

<b>Message</b>	Phase <RCS phase>, <Application Name> Application returned <Reject reason>, 0x<Reject code>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a receiving switch is rejecting the specified reliable commit service (RCS) phase.
<b>Recommended Action</b>	<p>If the reject is in the acquire change authorization (ACA) phase, wait for several minutes and then retry the operation from the sender switch.</p> <p>If the reject is in the stage fabric configuration (SFC) phase, check if the application license exists for the local domain and if the application data is compatible.</p>

## RCS-1006

<b>Message</b>	State <RCS phase>, Application <Application Name> AD<Administrative Domain>, RCS CM. Domain <Domain ID that sent the reject> returned 0x<Reject code>. App Response Code <Application Response Code>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	<p>Indicates that the specified domain rejected a reliable commit service (RCS) phase initiated by an application on the local switch.</p> <ul style="list-style-type: none"> <li>• If the reject phase is acquire change authorization (ACA), the remote domain may be busy and could not process the new request.</li> <li>• If the reject phase is stage fabric configuration (SFC), the data sent by the application may not be compatible or the domain does not have the license to support that application.</li> </ul>

## 5 RCS-1007

**Recommended Action** If the reject is in the ACA phase, wait for several minutes and then retry the operation.  
If the reject is in the SFC phase, check if the application license exists for the remote domain and if the application data is compatible.

### RCS-1007

**Message** Zone DB size and propagation overhead exceeds domain <domain number>'s maximum supported Zone DB size <max zone db size>. Retry after reducing Zone DB size.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the specified domain cannot handle the zone database being committed.

**Recommended Action** Reduce the zone database size.

### RCS-1008

**Message** Domain <domain number> Lowest Max Zone DB size.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates the specified domain has the lowest memory available for the zone database in the fabric. The zone database must be smaller than the memory available on this domain.

**Recommended Action** Reduce the zone database size.

### RCS-1009

**Message** Request remote domain <domain number> offline because it does not support RCS.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified remote domain is requested to go offline to take it out of the fabric because it does not support reliable commit service (RCS).

**Recommended Action** Run the **fabricShow** command to verify that the remote domain is out of the fabric.

## RCS-1010

<b>Message</b>	Domain <domain number> is RCS-incapable. Disabled <Number of E_ports disabled> E_Port(s) connected to this domain.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified remote domain is RCS-incapable, or the RCS-capable information could not be retrieved for the specified remote domain due to some potential routing issues.
<b>Recommended Action</b>	Run the <b>rcsInfoShow</b> command to view RCS capability of the switch. Investigate for routing issue or check the cabling, and re-enable the disabled E_Ports to attempt another exchange of RCS-capable information.

## RCS-1011

<b>Message</b>	Remote domain <domain number> is RCS-incapable. Configure this domain as RCS-capable.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified remote domain is RCS-incapable, or the RCS-capable information could not be retrieved for the specified remote domain due to some potential routing issues.
<b>Recommended Action</b>	Run the <b>rcsInfoShow</b> command to view RCS capability of the switch. Investigate for routing issue or check the cabling, and re-enable the disabled E_Ports to attempt another exchange of RCS-capable information.

## RCS-1012

<b>Message</b>	Local domain is RCS incapable (ForceDisabled is <Flag which denotes whether switch is RCS capable or not>), hence reject the RCS_INFO request from domain <domain number>.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified domain is RCS-incapable.
<b>Recommended Action</b>	Execute the <b>supportSave</b> command and contact your switch service provider.

## RCS-1013

<b>Message</b>	Remote domain <domain number> is RCS incapable.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified remote domain is RCS-incapable.
<b>Recommended Action</b>	Execute the <b>supportSave</b> command and contact your switch service provider.

## RKD Messages

### RKD-1001

<b>Message</b>	<Re-key type (First time encryption/Rekey/Write Metadata)> operation <Re-key action (started/completed/cancelled)>. Target: <Target physical WWN>, Initiator: <Initiator physical WWN>, LUN ID: <LUN ID>. SessionId:<Session ID>/<Session MN>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a first-time encryption, re-key, or write metadata operation was started, completed, or canceled.
<b>Recommended Action</b>	No action is required.

### RKD-1002

<b>Message</b>	Could not start <Re-key type (First time encryption/Rekey/Write Metadata)> operation. <I/T/L String>. No response from cluster member WWN: <EE WWN> Slot: <EE Slot Number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a first-time encryption, re-key, or write metadata operation was not started.
<b>Recommended Action</b>	Correct the cluster Ethernet link error and try to start the re-key operation again.

### RKD-1003

<b>Message</b>	<Re-key type (First time encryption/Rekey/Write Metadata)> encountered a FATAL SCSI error and will be suspended. <I/T/L String>. Command: <Read/Write>; LBA: <LBA String>; Num Blocks: 0x<Num of Blocks>; Error: <Error String>; SK/ASC: <SCSI Sense Key>/<SCSI ASC>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that a first-time encryption, re-key, or write metadata operation encountered a fatal SCSI error and was suspended.
<b>Recommended Action</b>	Correct the error and resume the re-key operation.

## RKD-1004

<b>Message</b>	Message: <Generic re-key message>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the generic re-key message.
<b>Recommended Action</b>	No action is required.

## RKD-1005

<b>Message</b>	LUN with LSN: <LUN LSN> does not have metadata. Make note of key ID <Key ID for encrypt/decrypt> that will be used for encryption/decryption of the LUN.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates uncompressible data on blocks 1 through 16 of the LUN.
<b>Recommended Action</b>	Migrate the data on this LUN to a larger LUN and add it to the container using the <b>-newLUN</b> option.



## RMON Messages

### RMON-1001

<b>Message</b>	RMON rising threshold alarm from SNMP OID <oid>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the threshold level was exceeded for the sample type of the remote monitoring (RMON) alarm.
<b>Recommended Action</b>	Check the traffic on the interface using the <b>show interface</b> command. Note that you can use the <b>show interface</b> command to check the traffic on the interface, provided the statistics on the interface are not cleared using the <b>clear counters</b> command.

### RMON-1002

<b>Message</b>	RMON falling threshold alarm from SNMP OID <oid>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the threshold level has come down for the sample type of the remote monitoring (RMON) alarm.
<b>Recommended Action</b>	Check the traffic on the interface using the <b>show interface</b> command. Note that you can use the <b>show interface</b> command to check the traffic on the interface, provided the statistics on the interface are not cleared using the <b>clear counters</b> command.

## RPCD Messages

### RPCD-1001

<b>Message</b>	Authentication Error: client \"<IP address>\" has bad credentials: <bad user name and password pair>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an authentication error was reported. The specified client IP address has faulty credentials.
<b>Recommended Action</b>	Enter the correct user name and password from the Fabric Access API host.

### RPCD-1002

<b>Message</b>	Missing certificate file. Secure RPCd is disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a Secure Sockets Layer (SSL) certificate is missing.
<b>Recommended Action</b>	To enable remote procedure call daemon (RPCD) in secure mode, install a valid SSL certificate on the switch.

### RPCD-1003

<b>Message</b>	Permission denied accessing certificate file. Secure RPCd is disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the Secure Sockets Layer (SSL) certificate file configured on the switch could not be accessed because root did not have read-level access.
<b>Recommended Action</b>	Change the file system access level for the certificate file to have root read-level access.

## RPCD-1004

<b>Message</b>	Invalid certificate file. Secure RPCd is disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the Secure Sockets Layer (SSL) certificate file has been corrupted.
<b>Recommended Action</b>	To enable remote procedure call daemon (RPCD) in secure mode, install a valid SSL certificate on the switch.

## RPCD-1005

<b>Message</b>	Missing private key file. Secure RPCd is disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the private key file is missing.
<b>Recommended Action</b>	Run the <b>secCertUtil</b> command to install a valid private key file.

## RPCD-1006

<b>Message</b>	Permission denied accessing private key file. Secure RPCd is disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the private key file configured on the switch could not be accessed because the root did not have read-level access.
<b>Recommended Action</b>	Change the file system access level for the private key file to have root read-level access.

## RPCD-1007

<b>Message</b>	Invalid private file. Secure RPCd is disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the private key file has been corrupted.

## 5 RPCD-1007

**Recommended Action** Run the **secCertUtil** command to install a valid private key file.

## RTE Messages

### RTE-1001

<b>Message</b>	Detected route inconsistency. It may cause connectivity issues. If such issues arise, bounce all ISLs and ICLs on this chassis.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the constraints that are used to determine the paths for Dynamic Path Selection (DPS) are not synchronized from active control processor (CP) to standby CP during the failover. This event causes route inconsistencies.
<b>Recommended Action</b>	Reset all E_ports on the chassis using the <b>portDisable</b> and <b>portEnable</b> commands.

## RTWR Messages

### RTWR-1001

<b>Message</b>	RTWR <routine: error message> 0x<detail 1>, 0x<detail 2>, 0x<detail 3>, 0x<detail 4>, 0x<detail 5>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	<p>Indicates that an error occurred in Reliable Transport With Response (RTWR) due to one of the following reasons:</p> <ul style="list-style-type: none"> <li>• The system ran out of memory.</li> <li>• The domain may be unreachable</li> <li>• The frame transmission failed.</li> <li>• An internal error or failure occurred.</li> </ul> <p>The message contains the name of the routine that has an error and other error-specific information. Refer to values in details 1 through 5 for more information.</p>
<b>Recommended Action</b>	Restart the switch.

### RTWR-1002

<b>Message</b>	RTWR <error message: maximum retries exhausted> 0x<port>, 0x<domain ID>, 0x<retry count>, 0x<status>, 0x<process ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that Reliable Transport With Response (RTWR) has exhausted the maximum number of retries for sending data to the specified domain.
<b>Recommended Action</b>	<p>Execute the <b>fabricShow</b> command to verify that the specified domain ID is online.</p> <p>If the switch with the specified domain ID is offline, enable the switch using the <b>switchEnable</b> command.</p> <p>If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.</p>

## RTWR-1003

<b>Message</b>	<module name>: RTWR retry <number of times retried> to domain <domain ID>, iu_data <first word of iu_data>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the number of times Reliable Transport With Response (RTWR) has failed to get a response and retried.
<b>Recommended Action</b>	Execute the <b>fabricShow</b> command to verify that the specified domain ID is reachable. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## SCN Messages

### SCN-1001

**Message** SCN queue overflow for process <daemon name>.

**Message Type** FFDC | LOG

**Severity** CRITICAL

**Probable Cause** Indicates that an attempt to write a state change notification (SCN) message to a specific queue has failed because the SCN queue for the specified daemon is full. This may be caused by the daemon hanging or the system being busy.

The following are some valid values for the *daemon name*:

- fabricd
- asd
- evmd
- fcpd
- webd
- msd
- nsd
- psd
- snmpd
- zoned
- fspf
- tsd

**Recommended** If this message is caused by the system being busy, the condition is temporary.

**Action**

If this message is caused by a hung daemon, the software watchdog will cause the daemon to dump the core and reboot the switch. In this case, execute the **supportSave** command to send the core files using FTP to a secure server location.

If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.



## SCN-1002

<b>Message</b>	SCN queue overflow for process <daemon name>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	<p>Indicates that an attempt to write a state change notification (SCN) message to a specific queue has failed because the SCN queue for the specified daemon is full. This may be caused by the daemon hanging or the system being busy.</p> <p>The following are some of the valid values for the <i>daemon name</i>:</p> <ul style="list-style-type: none"><li>• fabricd</li><li>• asd</li><li>• evmd</li><li>• fcpd</li><li>• webd</li><li>• msd</li><li>• nsd</li><li>• psd</li><li>• snmpd</li><li>• zoned</li><li>• fspfd</li><li>• tsd</li></ul>
<b>Recommended Action</b>	<p>If this message is caused by the system being busy, the condition is temporary.</p> <p>If this message is caused by a hung daemon, the software watchdog will cause the daemon to dump the core and reboot the switch. In this case, execute the <b>supportSave</b> command to send the core files using FTP to a secure server location.</p> <p>If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.</p>

## SEC Messages

### SEC-1001

<b>Message</b>	RCS process fails: <reason code>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the reliable commit service (RCS) process failed to complete. RCS is a mechanism for transferring data from one switch to other switches within the fabric. RCS ensures that either all or none of the switches commit to the database. RCS can fail if one switch in the fabric is busy or in an error state that prevents it from accepting the database.
<b>Recommended Action</b>	<p>RCS is evoked when the security database is modified by a security command (for example, <b>secPolicySave</b>, <b>secPolicyActivate</b>, or <b>distribute</b>). If the switch is busy, the command may fail the first time. Retry the command.</p> <p>Run the <b>rclsInfoShow</b> command to view RCS capability on the fabric. RCS must be capable on all switches in the fabric to be enabled. If all switches are capable, it is automatically enabled.</p> <p>If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.</p>

### SEC-1002

<b>Message</b>	Security data fails: <Reason Text>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the receiving switch fails to validate the security database sent from the primary fabric configuration server (FCS) switch. This may be caused by several factors: the data package may be corrupted, the time stamp on the package may be out of range as a result of replay attack or out-of-sync time service, or the signature verification failed. Signature verification failure may result from an internal error, such as losing the primary public key or an invalid database.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that switch. The error may also be a result of an internal corruption or a hacker attack to the secure fabric. If you have reason to believe that the error is the result of a possible security breach, take appropriate action as defined by your enterprise security policy.

## SEC-1003

<b>Message</b>	Fail to download security data to domain <Domain number> after <Number of retries> retries.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the specified domain failed to download security data after the specified number of attempts, and that the failed switch encountered an error accepting the database download. The primary switch will segment the failed switch after 30 tries.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state.  If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## SEC-1005

<b>Message</b>	Primary FCS receives data request from domain <Domain number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the primary fabric configuration server (FCS) received a data request from the specified domain. For example, if the switch fails to update the database or is attacked (data injection), a message is generated to the primary FCS to try to correct and resynchronize with the rest of the switches in the fabric.
<b>Recommended Action</b>	Use the <b>secFabricShow</b> command to check whether any of the switches in the fabric encountered an error. If one or more of the switches is not in the ready state, and you have reason to believe that the error is the result of a possible security breach, take appropriate action as defined by your enterprise security policy.

## SEC-1006

<b>Message</b>	Security statistics error: Failed to reset due to invalid <data>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that invalid data has been received for any statistic-related command for security ( <b>secStatsShow</b> or <b>secStatsReset</b> ). The counter is updated automatically when a security violation occurs. This message may also occur if the updating counter fails.
<b>Recommended Action</b>	If the message is the result of a user command, retry the statistic command.  If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## SEC-1007

<b>Message</b>	Security violation: Unauthorized host with IP address <IP address of the violating host> tries to establish API connection.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a security violation was reported. The IP address of the unauthorized host is displayed in the message.
<b>Recommended Action</b>	Check for unauthorized access to the switch through the API connection.

## SEC-1008

<b>Message</b>	Security violation: Unauthorized host with IP address <IP address of the violating host> tries to establish HTTP connection.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a security violation was reported. The IP address of the unauthorized host is displayed in the message.
<b>Recommended Action</b>	Check for unauthorized access to the switch through the HTTP connection.

## SEC-1009

<b>Message</b>	Security violation: Unauthorized host with IP address <IP address of the violating host> tries to establish TELNET connection.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a security violation was reported. The IP address of the unauthorized host is displayed in the message.
<b>Recommended Action</b>	Check for unauthorized access to the switch through the Telnet connection.

## SEC-1010

<b>Message</b>	RCS rejected: <Reason String>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Trying to distribute the database from a non-primary switch.
<b>Recommended Action</b>	Resolve the specified error by executing the command only from the primary FCS.

## SEC-1016

<b>Message</b>	Security violation: Unauthorized host with IP address <IP address of the violating host> tries to establish SSH connection.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a security violation was reported. The IP address of the unauthorized host is displayed in the message.
<b>Recommended Action</b>	Check for unauthorized access to the switch through the SSH connection.

## SEC-1022

<b>Message</b>	Failed to <operation> PKI objects.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the fabric failed to generate or validate either the public or private key pair or the certificate signing request (CSR).
<b>Recommended Action</b>	Run the <b>secCertUtil show -fcapall</b> command and verify that all public key infrastructure (PKI) objects exist on the switch. If the private key does not exist, follow the steps for re-creating PKI objects outlined in the <i>Fabric OS Administrator's Guide</i> . If a certificate does not exist or is invalid, install the certificate by following the field upgrade process.

## SEC-1024

<b>Message</b>	The <DB name> security database is too large to fit in flash.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the size of the security database is too large for the flash memory. The size of the security database increases with the number of entries in each policy.
<b>Recommended Action</b>	Reduce the size of the security database by reducing the number of entries within each policy.

## SEC-1025

<b>Message</b>	Invalid IP address (<IP address>) detected.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can occur only when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1026

<b>Message</b>	Invalid format or character in switch member <switch member ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can occur only when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1028

<b>Message</b>	No name is specified.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can occur only when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1029

<b>Message</b>	Invalid character in <policy name>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can occur only when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1030

<b>Message</b>	The length of the name is invalid.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can occur only when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1031

<b>Message</b>	Current security policy DB cannot be supported by standby. CPs will go out of sync.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the security database size is not supported by the standby control processor (CP).
<b>Recommended Action</b>	Reduce the security policy size by deleting entries within a policy or by deleting some policies.

## SEC-1032

<b>Message</b>	Empty FCS list is not allowed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1033

<b>Message</b>	Invalid character used in member parameter to add switch to SCC policy; command terminated.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a member parameter in the <b>secPolicyAdd</b> command is invalid (for example, it may include an invalid character, such as an asterisk). A valid switch identifier (a WWN, a domain ID, or a switch name) must be provided as a member parameter in the <b>secPolicyAdd</b> command. Only the <b>secPolicyCreate</b> command supports use of the asterisk for adding switches to policies.
<b>Recommended Action</b>	Run the <b>secPolicyAdd</b> command using a valid switch identifier (WWN, domain ID, or switch name) to add specific switches to the Switch Connection Control (SCC) policy.



## SEC-1034

<b>Message</b>	Invalid member <policy member>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the input list has an invalid member.
<b>Recommended Action</b>	Verify the member names, and input the correct information.

## SEC-1035

<b>Message</b>	Invalid device WWN <device WWN>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the specified World Wide Name (WWN) is invalid.
<b>Recommended Action</b>	Enter the correct WWN value.

## SEC-1036

<b>Message</b>	Device name <device name> is invalid due to a missing colon.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates one or more device names mentioned in the <b>secPolicyCreate</b> or <b>secPolicyAdd</b> commands does not have the colon character (:) as required.
<b>Recommended Action</b>	Run the <b>secPolicyCreate</b> or <b>secPolicyAdd</b> command with a properly formatted device name parameter.

## SEC-1037

<b>Message</b>	Invalid WWN format <invalid WWN>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the WWN entered in the policy member list has an invalid format.

## 5 SEC-1038

**Recommended Action** Run the command again using the standard WWN format; 16 hexadecimal digits grouped as 8 colon-separated pairs, for example, 50:06:04:81:D6:F3:45:42.

### SEC-1038

**Message** Invalid domain <domain ID>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates an invalid domain ID was entered.

**Recommended Action** Verify that the domain ID is correct. If it is not, re-run the command using the correct domain ID.

### SEC-1039

**Message** <message>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates the domain ID entered is out of range.

**Recommended Action** Verify that the domain ID is correct. If it is not, re-run the command using the correct domain ID.

### SEC-1040

**Message** Invalid portlist (<port list>). Cannot combine \* with port member in the same portlist.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates the port list contains the wildcard asterisk (\*) character. You cannot use the asterisk in a port list.

**Recommended Action** Enter the port list values without any wildcard characters.

## SEC-1041

<b>Message</b>	Invalid port member <port member> in portlist (<port list>). <Reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the port member is invalid for one of the following reasons: <ul style="list-style-type: none"><li>• The value is not a number.</li><li>• The value is too long. Valid numbers must be between one and three characters long.</li><li>• The value cannot be parsed due to invalid characters.</li></ul>
<b>Recommended Action</b>	Use valid syntax when entering port members.

## SEC-1042

<b>Message</b>	Invalid index/area member <port member> in portlist (<Port list>). Out of range (<Minimum value> - <Maximum value>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the specified index or area member is not within the minimum and maximum range.
<b>Recommended Action</b>	Use valid syntax when entering index or area numbers.

## SEC-1043

<b>Message</b>	Invalid port range <Minimum> - <Maximum>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the specified port is not within the minimum and maximum range.
<b>Recommended Action</b>	Use valid syntax when entering port ranges.

**SEC-1044**

<b>Message</b>	Duplicate member <member ID> in (<List>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the specified member is a duplicate in the input list. The list can be a policy list or a switch member list.
<b>Recommended Action</b>	Do not specify any duplicates.

**SEC-1045**

<b>Message</b>	Too many port members.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

**SEC-1046**

<b>Message</b>	Empty list.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1049

<b>Message</b>	<code>Invalid switch name &lt;switch name&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1050

<b>Message</b>	<code>There are more than one switches with the same name &lt;switch name&gt; in the fabric.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1051

<b>Message</b>	<code>Missing brace for port list &lt;port list&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1052

<b>Message</b>	Invalid input.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1053

<b>Message</b>	Invalid pFCS list <pFCS list>
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds these error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1054

<b>Message</b>	Invalid FCS list length <list length>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1055

<b>Message</b>	Invalid FCS list <WWN list>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1056

<b>Message</b>	Invalid position <New position>. Only <Number of members in FCS list> members in list.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1057

<b>Message</b>	No change. Both positions are the same.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1059

<b>Message</b>	Fail to <operation, e.g., save, delete, etc.,> <named item> to flash.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the operation failed when writing to flash memory.
<b>Recommended Action</b>	Run the <b>supportFtp - e</b> command to FTP files from the switch and remove them from the flash memory.

## SEC-1062

<b>Message</b>	Invalid number of Domains in Domain List.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that either no domains or domains more than the maximum number supported are specified.
<b>Recommended Action</b>	Enter the correct number of domains.

## SEC-1063

<b>Message</b>	Failed to reset statistics.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that either the type or the domains specified are invalid.
<b>Recommended Action</b>	Enter valid input.

## SEC-1064

<b>Message</b>	Failed to sign message.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the public key infrastructure (PKI) objects on the switch are not in a valid state and the signature operation failed.



**Recommended Action** Run the **secCertUtil show -fcapall** command to verify that all PKI objects are valid. If PKI objects are not valid, generate the PKI objects and install the certificate by following the field upgrade process.

## SEC-1065

**Message** Invalid character in list.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates the input list has an invalid character.

**Recommended Action** Enter valid input.

## SEC-1069

**Message** Security Database is corrupted.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates the security database is corrupted for unknown reasons.

**Recommended Action** Execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

## SEC-1071

**Message** No new security policy data to apply.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that no changes in the defined security policy database need to be activated at this time.

**Recommended Action** Verify that the security event was planned. First change some policy definitions, and then run the **secPolicyActivate** command to activate the policies.

## SEC-1072

<b>Message</b>	<Policy type> Policy List is Empty.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the specific policy type is empty. The security database is corrupted for unknown reasons.
<b>Recommended Action</b>	Execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## SEC-1073

<b>Message</b>	No FCS policy in list.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the specific policy type is empty. The security database is corrupted for unknown reasons.
<b>Recommended Action</b>	Execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## SEC-1074

<b>Message</b>	Cannot execute the command on this switch. Please check the secure mode and FCS status.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a security command was run on a switch that is not allowed to run it either because it is in non-secure mode or because it does not have the required fabric configuration server (FCS) privilege.
<b>Recommended Action</b>	If a security operation that is not allowed in non-secure mode is attempted, do not perform the operation in non-secure mode. In secure mode, run the command from a switch that has the required privilege; that is, either a backup FCS or primary FCS.

## SEC-1075

<b>Message</b>	Fail to <operation> new policy set on all switches.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1076

<b>Message</b>	NoNodeWWNZoning option has been changed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the NoNodeWWNZoning option has been changed. If the option is turned on, a zone member can be added using node WWNs, but the member will not be able to communicate with others nodes in the zone.
<b>Recommended Action</b>	Re-enable the current zone configuration for the change to take effect.

## SEC-1077

<b>Message</b>	Failed to activate new policy set on all switches.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the policy could not be activated. Possible reasons that the policy could not be activated include not enough memory or a busy switch.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that all switches in the fabric are in the ready state. Retry the command when all switches are ready.

## SEC-1078

<b>Message</b>	No new data to abort.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates there are no new changes in the defined security policy database that can be aborted.
<b>Recommended Action</b>	Verify the security event was planned. Verify if there were really any changes to the defined policy database that can be aborted.

## SEC-1079

<b>Message</b>	The policy name <policy name> is invalid.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the policy name entered in the <b>secPolicyCreate</b> , <b>secPolicyActivate</b> , <b>secPolicyAdd</b> , or <b>secPolicyDelete</b> command was invalid.
<b>Recommended Action</b>	Run the command again using a valid policy name.

## SEC-1080

<b>Message</b>	Operation denied. Please use <code>secPolicyActivate</code> or <code>distribute</code> commands.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>fabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1081

<b>Message</b>	Entered a name for a DCC policy ID that was not unique.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the Device Connection Control (DCC) policy name given in the <b>secPolicyCreate</b> command was the same as another DCC policy.
<b>Recommended Action</b>	Make sure that the DCC policy name has a unique alphanumeric string, and run the <b>secPolicyCreate</b> command again.

## SEC-1082

<b>Message</b>	Failed to create <policy name> policy.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the security policy was not created because of faulty input or low resources.
<b>Recommended Action</b>	Use proper syntax when creating policies. If the security database is too large, you must delete other members within the database before adding new members to a policy.

## SEC-1083

<b>Message</b>	Name already exists.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>fabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1084

<b>Message</b>	Name exists for different type <Policy name>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the specified policy already exists.
<b>Recommended Action</b>	No action is required.

## SEC-1085

<b>Message</b>	Failed to create <policy name>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the security policy was not created.
<b>Recommended Action</b>	Check that the current policy configuration is valid. For example, the RSNMP policy cannot exist without the WSNMP policy.

## SEC-1086

<b>Message</b>	The security database is too large to fit in flash.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the security database has more data than the flash memory can accommodate.
<b>Recommended Action</b>	Reduce the number of entries in some policies to decrease the security database size.

## SEC-1087

<b>Message</b>	The security database is larger than the data distribution limit of fabric <fabric data distribution limit> bytes.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the security database has more data than can be distributed to some of the switches in the fabric.
<b>Recommended Action</b>	Reduce the number of entries in the security policies to decrease the security database size.

## SEC-1088

<b>Message</b>	Cannot execute the command. Please try later.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>fabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1089

<b>Message</b>	Policy name <policy name> was not found.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the security policy name in the <b>secPolicyAdd</b> command does not exist.
<b>Recommended Action</b>	Create the appropriate security policy first, and then use its name in the <b>secPolicyAdd</b> command to add new members.

**SEC-1090**

<b>Message</b>	SCC list contains FCS member. Please remove member from the FCS policy first.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>fabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

**SEC-1091**

<b>Message</b>	No policy to remove.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the specified policy member does not exist or the policy itself does not exist.
<b>Recommended Action</b>	Verify that the security policy name or member ID is correct.

**SEC-1092**

<b>Message</b>	<Policy name> Name not found.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>fabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.



## SEC-1093

<b>Message</b>	New FCS list must have at least one member in common with current FCS list.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the new fabric configuration server (FCS) list does not have a common member with the existing FCS list.
<b>Recommended Action</b>	Resubmit the command with at least one member of the new FCS list in common with the current FCS list.

## SEC-1094

<b>Message</b>	Policy member not found.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds that there is an error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>fabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1095

<b>Message</b>	Deleting FCS policy is not allowed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>fabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1096

<b>Message</b>	Failed to delete <policy name> because <reason text>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a policy cannot be removed because deleting it would result in an invalid security policy configuration.
<b>Recommended Action</b>	Verify the security policy configuration requirements and remove any policies that require the policy you want to be removed first.

## SEC-1097

<b>Message</b>	Cannot find <active or defined> policy set.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the specified policy could not be found.
<b>Recommended Action</b>	If the message persists, run <b>supportFtp</b> (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

## SEC-1098

<b>Message</b>	No <active or defined> FCS list.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the specified policy could not be found.
<b>Recommended Action</b>	Execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## SEC-1099

**Message** Please enable your switch before running secModeEnable.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.

**Recommended Action** Run the **fabricShow** command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1100

**Message** FCS switch present. Command terminated.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.

**Recommended Action** Run the **fabricShow** command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1101

**Message** Failed to enable security on all switches. Please retry later.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates the security enable failed on the fabric because one or more switches in the fabric are busy.

**Recommended Action** Verify that the security event was planned. If the security event was planned, run the **secFabricShow** command to verify that all switches in the fabric are in the ready state. When all switches are in the ready state, retry the operation.

## SEC-1102

<b>Message</b>	Fail to download <security data>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the switch failed to download a certificate, security database, or policies. This can happen when the switch does not get enough resources to complete the operation, the fabric has not stabilized, or the policy database is an invalid format.
<b>Recommended Action</b>	Wait for the fabric to become stable and then retry the operation. If the policy database is in an illegal format (with <b>configDownload</b> command), correct the format and retry the operation.

## SEC-1104

<b>Message</b>	Fail to get primary <Certificate or public key>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the switch failed to get either the primary certificate or a primary public key.
<b>Recommended Action</b>	Verify the primary switch has a valid certificate installed and retry the operation. If a valid certificate is not installed, install a certificate by following the procedure specified in the <i>Fabric OS Administrator's Guide</i> .

## SEC-1105

<b>Message</b>	Fail to disable secure mode on all switches.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the switch failed to disable security in the fabric. This could happen if the switch cannot get the required resources to complete the command, and sending to a remote domain fails or the remote domain returns an error.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> to verify that all switches in the fabric are in the ready state. Retry the command when all switches are ready.

## SEC-1106

<b>Message</b>	Failed to sign message data.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that some public key infrastructure (PKI) objects on the switch are not in a valid state, and a signature operation failed.
<b>Recommended Action</b>	Run the <b>secCertUtil show -fcapall</b> command and verify that all PKI objects exist on the switch. If a failure to validate PKI objects occurs, follow the steps for re-creating PKI objects outlined in the <i>Fabric OS Administrator's Guide</i> .

## SEC-1107

<b>Message</b>	Stamp is 0.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1108

<b>Message</b>	Fail to reset stamp on all switches.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a version reset operation failed either because the switch could not get all the required resources to perform the operation or because it failed to send the message to all switches in the fabric.
<b>Recommended Action</b>	Verify that the security event was planned. If the security event was planned, run the <b>secFabricShow</b> command to verify that all switches in the fabric are in the ready state. When all switches are in the ready state, retry the operation.

## SEC-1110

<b>Message</b>	FCS list must be the first entry in the [Defined Security policies] section. Fail to download defined database.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a security policy download was attempted with a defined policy that does not have the fabric configuration server (FCS) policy as the first policy. The FCS policy is required to be the first policy in the defined security database.
<b>Recommended Action</b>	Download a correct configuration with the fabric configuration server (FCS) policy as the first policy in the defined security database.

## SEC-1111

<b>Message</b>	New defined FCS list must have at least one member in common with current active FCS list. Fail to download defined database.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the defined and active fabric configuration server (FCS) policy list failed to have at least one member in common.
<b>Recommended Action</b>	A new FCS policy list must have at least one member in common with the previous FCS policy.

## SEC-1112

<b>Message</b>	FCS list must be the first entry in the Active Security policies, and the same as the current active FCS list in the switch.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates either a security policy download was attempted with an active policy that does not have the fabric configuration server (FCS) policy as the first policy, or the FCS policy is not the same as the current FCS policy on the switch.
<b>Recommended Action</b>	Make sure that the new FCS policy is the same as the current FCS policy on the switch.

## SEC-1113

<b>Message</b>	<Key> [ <Feature> license ] going to expire in <Expiry_days> day(s).
<b>Message Type</b>	LOG   AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the license period will expire soon.
<b>Recommended Action</b>	Get a new license for this feature.

## SEC-1114

<b>Message</b>	<Key> [ <Feature> license ] has expired.
<b>Message Type</b>	LOG   AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the license period has expired.
<b>Recommended Action</b>	Get a new license for this feature.

## SEC-1115

<b>Message</b>	No primary FCS to failover.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that during an attempted <b>secFcsFailover</b> , no primary FCS is present in the fabric.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that all switches in the fabric are in the ready state. When all switches are in the ready state, retry the operation.

**SEC-1116**

<b>Message</b>	Fail to commit failover.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

**SEC-1117**

<b>Message</b>	Fail to set <data>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the switch failed to save the data received by the primary fabric configuration server (FCS) switch. This data can be an FCS password, a non-FCS password, SNMP data, or multiple user authentication data.
<b>Recommended Action</b>	Run the <b>fabricShow</b> command to verify that all switches in the fabric are in the ready state. When all switches are in the ready state, retry the operation.

**SEC-1118**

<b>Message</b>	Fail to set SNMP string.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the SNMP string could not be set. Usually this problem is transient.
<b>Recommended Action</b>	Retry the command.



## SEC-1119

<b>Message</b>	Secure mode has been enabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the secure Fabric OS was enabled by the <b>secModeEnable</b> command.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, there is no action required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-1121

<b>Message</b>	Time is out of range when <text>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the time on the switch is not synchronized with the primary fabric configuration server (FCS), the data packet is corrupted, or a replay attack is launched on the switch.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, verify that all switches in the fabric are in time synchronization with the primary FCS and that no external entity is trying to access the fabric. When verification is complete, retry the operation.

## SEC-1122

<b>Message</b>	Error code: <Domain ID>, <Error message>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that one of the switches in the fabric could not communicate with the primary fabric configuration server (FCS).
<b>Recommended Action</b>	Run the <b>fabricShow</b> command to verify that all switches in the fabric are in the ready state. When all switches are in the ready state, retry the operation.

## SEC-1123

<b>Message</b>	Security database downloaded by Primary FCS.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the security database was successfully downloaded from the primary fabric configuration server (FCS).
<b>Recommended Action</b>	No action is required.

## SEC-1124

<b>Message</b>	Secure Mode is off.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a secure mode disable is attempted in a non-secure fabric.
<b>Recommended Action</b>	No action is required.

## SEC-1126

<b>Message</b>	Secure mode has been disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a secure mode disable operation completed successfully.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-1130

<b>Message</b>	The Primary FCS has failed over to a new switch.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a fabric configuration server (FCS) failover operation was completed successfully.

**Recommended Action** Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-1135

**Message** `Secure fabric version stamp has been reset.`

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates the version stamp of the secure fabric is reset.

**Recommended Action** Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-1136

**Message** `Failed to verify signature <data type, MUA, policy, etc.,>.`

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates the receiving switch failed to validate the security database sent from the primary fabric configuration server (FCS) switch. This message usually indicates that the data package is corrupted, the time stamp on the package is out of range as a result of a replay attack or out-of-sync time service, or the signature verification failed. Signature verification failure indicates either an internal error (such as losing the primary public key) or an invalid database.

**Recommended Action** Run the **secFabricShow** command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that switch. This message may also be the result of an internal corruption or a hacker attack to the secure fabric.

## SEC-1137

**Message** `No signature in <data type, MUA, policy, etc.,>.`

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates the receiving switch failed to validate the security database sent from the primary fabric configuration server (FCS) switch. This message usually indicates that the data package is corrupted, the time stamp on the package is out of range as a result of a replay attack or out-of-sync time service, or the signature verification failed. Signature verification failure indicates either an internal error (such as losing the primary public key) or an invalid database.

**Recommended Action** Run the **secFabricShow** command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that switch. This message may also be the result of an internal corruption or a hacker attack to the secure fabric.

**SEC-1138**

<b>Message</b>	Security database download received from Primary FCS.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a non-primary fabric configuration server (FCS) switch received a security database download.
<b>Recommended Action</b>	Verify that the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

**SEC-1139**

<b>Message</b>	The RSNMP_POLICY cannot exist without the WSNMP_POLICY.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the receiving switch failed to validate the security database sent from the primary fabric configuration server (FCS) switch. This message usually indicates that the data package is corrupted, the time stamp on the package is out of range as a result of a replay attack or out-of-sync time service, or the signature verification failed. Signature verification failure indicates either an internal error (such as losing the primary public key) or an invalid database.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that switch. This message may also be the result of an internal corruption or a hacker attack to the secure fabric.

**SEC-1142**

<b>Message</b>	Reject new policies. <reason text>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the new polices are rejected because of the reason specified.
<b>Recommended Action</b>	Use proper syntax when entering policy information.

## SEC-1145

<b>Message</b>	A security admin event has occurred. This message is for information purpose only. The message for individual event is: <Event specific data>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates one of the following has occurred: <ul style="list-style-type: none"> <li>• The names for the specified policies have changed.</li> <li>• The passwords have changed for the specified accounts.</li> <li>• The SNMP community strings have been changed.</li> </ul>
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-1146

<b>Message</b>	PID changed: <State>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the PID format of the switch was changed either to extended-edge PID or from extended-edge PID. If the Device Connection Control (DCC) polices existed, all index/area ID values either increased or decreased by 16. The values wrap around after 128. If a DCC policy contains an index/area of 127 before changing to extended-edge PID, then the new index/area is 15, because of the wraparound.
<b>Recommended Action</b>	No action is required.

## SEC-1153

<b>Message</b>	Error in RCA: RCS is not supported.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that reliable commit service (RCS) is not supported.
<b>Recommended Action</b>	Run the <b>rclsInfoShow</b> command to view RCS capability on the fabric. RCS must be capable on all switches in the fabric to be enabled. If all switches are capable, it is automatically enabled.  For any switch that does not support RCS, obtain the latest firmware version from your switch supplier, and run the <b>firmwareDownload</b> command to upgrade the firmware.  If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

**SEC-1154**

<b>Message</b>	PID change failed: <Reason> <defined status> <active status>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that either the defined or the active policy could not be updated. If the policy database is very large, it might not be able to change the index/area because the new policy database exceeds the maximum size. This message can also be caused when the switch is short of memory. The status values can be either defined, active, or both. A negative value means that a policy set was failed by the daemon.
<b>Recommended Action</b>	Reduce the size of the policy database.

**SEC-1155**

<b>Message</b>	PID change failed: <Reason> <defined status> <active status>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that either the defined or active policy was too large after modifying the index/area ID. The status values can be either defined, active, or both. A negative value means that a policy set was failed by the daemon.
<b>Recommended Action</b>	Reduce the size of the specified policy database.

**SEC-1156**

<b>Message</b>	Change failed: <Reason> <defined status> <active status>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the security daemon is busy. The status values can be defined, active, or both. A negative value means that a policy set was failed by the daemon.
<b>Recommended Action</b>	For the first reject, wait a few minutes and then resubmit the transaction. Fabric-wide commands may take a few minutes to propagate throughout the fabric. Make sure to wait a few minutes between executing commands so that your commands do not overlap in the fabric.

## SEC-1157

<b>Message</b>	PID Change failed: <Reason> <defined status> <active status>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the provisioning resources for a security policy failed because of low memory or internal error. The status values can be defined, active, or both. A negative value means that a policy set was failed by the daemon.
<b>Recommended Action</b>	Retry the failed command. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## SEC-1158

<b>Message</b>	Invalid name <Policy or Switch name>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified name is invalid. The name can be a policy name or a switch name.
<b>Recommended Action</b>	Enter a valid name.

## SEC-1159

<b>Message</b>	Non_Reachable domain <Domain ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

**SEC-1160**

<b>Message</b>	Duplicate port <port ID> in port list (<port list>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a duplicate port member exists in the specified port list.
<b>Recommended Action</b>	Verify that there is no duplicate port member in the port list.

**SEC-1163**

<b>Message</b>	System is already in secure mode. Lockdown option cannot be applied.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the lockdown option was attempted while the fabric is in secure mode.
<b>Recommended Action</b>	Do not use the lockdown option with the <b>secModeEnable</b> command when a switch is already in secure mode.

**SEC-1164**

<b>Message</b>	Lockdown option cannot be applied on a non-FCS switch.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the attempt to enable security is made on a switch that is not present in the fabric configuration server (FCS) list.
<b>Recommended Action</b>	Add the switch to the FCS policy list when using the lockdown option to enable security.

**SEC-1165**

<b>Message</b>	Low memory, failed to enable security on all switches.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the system is low on memory.



**Recommended Action** Wait a few minutes and try the command again.

## SEC-1166

**Message** Non FCS tries to commit failover.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.

**Recommended Action** Run the **secFabricShow** command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1167

**Message** Another FCS failover is in process. Command terminated.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that because another failover is already in progress, this failover attempt cannot proceed.

**Recommended Action** Verify the security event was planned. If the security event was planned, retry fabric configuration server (FCS) failover after the current failover has completed, if this switch should become the primary FCS. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-1168

**Message** Primary FCS failover is busy. Please retry later.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.

**Recommended Action** Run the **secFabricShow** command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

**SEC-1170**

<b>Message</b>	This command must be executed on the Primary FCS switch, the first reachable switch in the FCS list.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

**SEC-1171**

<b>Message</b>	Disabled secure mode due to invalid security object.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the switch is segmented, and secure mode is disabled on the switch because there was no license present or no public key infrastructure (PKI) objects.
<b>Recommended Action</b>	Run the <b>secCertUtil show -fcapall</b> command to determine whether all PKI objects exist. If they do not exist, run the <b>secCertUtil</b> command to create them for the switch. Run the <b>licenseAdd</b> command to install the required license key. Contact your switch supplier to obtain a license if you do not have one.

**SEC-1172**

<b>Message</b>	Failed to identify role.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the switch is unable to determine its role (primary FCS or backup FCS) in the secure fabric.
<b>Recommended Action</b>	Verify all switches in the fabric are in time synchronization with the primary FCS and that no external entity is trying to access the fabric. When verification is complete, retry the operation.

## SEC-1173

<b>Message</b>	Lost contact with Primary FCS switch.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the switch has lost contact with the primary fabric configuration server (FCS) switch in the secure fabric. This could result from the primary FCS being disabled.
<b>Recommended Action</b>	If the primary FCS was disabled intentionally, no action is required; if not, check the primary FCS.

## SEC-1174

<b>Message</b>	Failed to set <FCS or non-FCS> password.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the fabric configuration server (FCS) or non-FCS password could not be set.
<b>Recommended Action</b>	Verify all switches in the fabric are in time synchronization with the primary FCS and that no external entity is trying to access the fabric. When verification is complete, retry the operation.

## SEC-1175

<b>Message</b>	Failed to install zone data.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the zone database could not be installed on the switch.
<b>Recommended Action</b>	Verify all switches in the fabric are in time synchronization with the primary FCS and that no external entity is trying to access the fabric. When verification is complete, retry the operation.

## SEC-1176

<b>Message</b>	Failed to generate new version stamp.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the primary fabric configuration server (FCS) failed to generate a new version stamp because the fabric was not stable.
<b>Recommended Action</b>	Verify all switches in the fabric are in time synchronization with the primary FCS and that no external entity is trying to access the fabric. When verification is complete, retry the operation.

## SEC-1180

<b>Message</b>	Added account <user name> with <role name> authorization.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified new account has been created.
<b>Recommended Action</b>	No action is required.

## SEC-1181

<b>Message</b>	Deleted account <user name>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified account has been deleted.
<b>Recommended Action</b>	No action is required.

## SEC-1182

<b>Message</b>	Recovered <number of> accounts.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified number of accounts has been recovered from backup.

**Recommended Action** No action is required.

## SEC-1183

**Message** Policy to binary conversion error: Port <port number> is out range.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates a security database conversion has failed because of an invalid value.

**Recommended Action** Retry the command with a valid value.  
If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

## SEC-1184

**Message** <Security server (RADIUS/LDAP/TACACS+)> configuration change, action <action>, server ID <server name>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates the specified action is applied to the specified remote authentication dial-in user service (RADIUS/LDAP/TACACS+) server configuration. The possible actions are ADD, REMOVE, CHANGE, and MOVE.

**Recommended Action** No action is required.

## SEC-1185

**Message** <action> switch DB.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates the switch database was enabled or disabled as the secondary authentication, accounting, and authorization (AAA) mechanism when the remote authentication dial-in user service (RADIUS/LDAP/TACACS+) is the primary AAA mechanism.

**Recommended Action** No action is required.

**SEC-1186**

<b>Message</b>	<Security server (RADIUS/LDAP/TACACS+)> <action> Configuration.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the RADIUS, LDAP, or TACACS+ configuration was enabled or disabled as the primary authentication, accounting, and authorization (AAA) mechanism.
<b>Recommended Action</b>	No action is required.

**SEC-1187**

<b>Message</b>	Security violation: Unauthorized switch <switch WWN> tries to join fabric.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a Switch Connection Control (SCC) security violation was reported. The specified unauthorized switch attempts to join the fabric.
<b>Recommended Action</b>	Check the SCC policy to verify the switches allowed in the fabric. If the switch should be allowed in the fabric but it is not included in the SCC policy, add the switch to the policy. If the switch is not allowed access to the fabric, this is a valid violation message and an unauthorized entity is trying to access your fabric. Take appropriate action, as defined by your enterprise security policy.

**SEC-1188**

<b>Message</b>	Security violation: Unauthorized device <device node name> tries to FLOGI to index/area <port number> of switch <switch WWN>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a Device Connection Control (DCC) security violation was reported. The specified device attempted to log in using fabric login (FLOGI) to an unauthorized port. The DCC policy correlates specific devices to specific port locations. If the device changes the connected port, the device will not be allowed to log in.
<b>Recommended Action</b>	Check the DCC policy and verify the specified device is allowed in the fabric and is included in the DCC policy. If the specified device is not included in the policy, add it to the policy. If the host is not allowed access to the fabric, this is a valid violation message and an unauthorized entity is trying to access your fabric. Take appropriate action, as defined by your enterprise security policy.

## SEC-1189

<b>Message</b>	Security violation: Unauthorized host with IP address <IP address> tries to do SNMP write operation.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an SNMP security violation was reported. The specified unauthorized host attempted to perform a write SNMP operation.
<b>Recommended Action</b>	Check the WSNMP policy and verify which hosts are allowed access to the fabric through SNMP. If the host is allowed access to the fabric but is not included in the policy, add the host to the policy. If the host is not allowed access to the fabric, this is a valid violation message and an unauthorized entity is trying to access your fabric. Take appropriate action, as defined by your enterprise security policy.

## SEC-1190

<b>Message</b>	Security violation: Unauthorized host with IP address <IP address> tries to do SNMP read operation.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an SNMP security violation was reported. The specified unauthorized host attempted to perform a read SNMP (RSNMP) operation.
<b>Recommended Action</b>	Check the RSNMP policy to verify the hosts allowed access to the fabric through SNMP read operations are included in the RSNMP policy. If the host is allowed access but is not included in the RSNMP policy, add the host to the policy. If the host is not allowed access to the fabric, this is a valid violation message and an unauthorized entity is trying to access your fabric. Take appropriate action, as defined by your enterprise security policy.

## SEC-1191

<b>Message</b>	Security violation: Unauthorized host with IP address <Ip address> tries to establish HTTP connection.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an HTTP security violation was reported. The specified unauthorized host attempted to establish an HTTP connection.
<b>Recommended Action</b>	Determine whether the host IP address specified in the message can be used to manage the fabric through an HTTP connection. If so, add the host IP address to the HTTP policy of the fabric. If the host is not allowed access to the fabric, this is a valid violation message and an unauthorized entity is trying to access your fabric. Take appropriate action, as defined by your enterprise security policy.

**SEC-1192**

<b>Message</b>	Security violation: Login failure attempt via <connection method>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a serial or modem login security violation was reported. The wrong password was used while trying to log in through a serial or modem connection; the login failed.
<b>Recommended Action</b>	Use the correct password.

**SEC-1193**

<b>Message</b>	Security violation: Login failure attempt via <connection method>. IP Addr: <IP address>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a specified login security violation was reported. The wrong password was used while trying to log in through the specified connection method; the login failed.
<b>Recommended Action</b>	The error message lists the violating IP address. Verify that this IP address is being used by a valid switch admin. Use the correct password.

**SEC-1194**

<b>Message</b>	This switch does not have all the required PKI objects correctly installed.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.



## SEC-1195

<b>Message</b>	This switch has no <component> license.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1196

<b>Message</b>	Switch does not have all default account names.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the default switch accounts admin and user do not exist on the switch when enabling security.
<b>Recommended Action</b>	Reset the default admin and user account names on the switch that reported the warning and retry enabling security.

## SEC-1197

<b>Message</b>	Changed account <user name>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified account has changed.
<b>Recommended Action</b>	No action is required.

**SEC-1198**

<b>Message</b>	Security violation: Unauthorized host with IP address <IP address> tries to establish API connection.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an API security violation was reported. The specified unauthorized host attempted to establish an API connection.
<b>Recommended Action</b>	Check to see if the host IP address specified in the message can be used to manage the fabric through an API connection. If so, add the host IP address to the API policy of the fabric. If the host is not allowed access to the fabric, this is a valid violation message and an unauthorized entity is trying to access your fabric. Take appropriate action, as defined by your enterprise security policy.

**SEC-1199**

<b>Message</b>	Security violation: Unauthorized access to serial port of switch <switch instance>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a serial connection policy security violation was reported. An attempt was made to access the serial console on the specified switch instance when it is disabled.
<b>Recommended Action</b>	Check to see if an authorized access attempt is being made on the console. If so, add the switch WWN to the serial policy. If the host is not allowed access to the fabric, this is a valid violation message and an unauthorized entity is trying to access your fabric. Take appropriate action, as defined by your enterprise security policy.

**SEC-1200**

<b>Message</b>	Security violation: MS command is forwarded from non-primary FCS switch.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a management server (MS) forward security violation was reported. A management server command was forwarded from a non-primary fabric configuration server (FCS) switch.
<b>Recommended Action</b>	Check the MS policy and verify that the connection is allowed. If the connection is allowed but not specified, enable the connection in the MS policy. If the MS policy does not allow the connection, this is a valid violation message and an unauthorized entity is trying to access your fabric. Take appropriate action, as defined by your enterprise security policy.

## SEC-1201

<b>Message</b>	Security violation: MS device <device WWN> operates on non-primary FCS switch.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a management server (MS) operation security violation was reported. An MS device operation occurred on a non-primary fabric configuration server (FCS) switch.
<b>Recommended Action</b>	Check the management server policy and verify the connection is allowed. If the connection is allowed but not specified, enable the connection in the MS policy. If the MS policy does not allow the connection, this is a valid violation message and an unauthorized entity is trying to access your fabric. Take appropriate action, as defined by your enterprise security policy.

## SEC-1202

<b>Message</b>	Security violation: Unauthorized access from MS device node name <device node name>, device port name <device port name>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a management server (MS) security violation was reported. The unauthorized device specified in the message attempted to establish a connection.
<b>Recommended Action</b>	Check the MS server policy and verify that the connection is allowed. If the connection is allowed but not specified, enable the connection in the MS policy. If the MS policy does not allow the connection, this is a valid violation message and an unauthorized entity is trying to access your fabric. Take appropriate action, as defined by your enterprise security policy.

## SEC-1203

<b>Message</b>	Login information: Login successful via TELNET/SSH/RSH. IP Addr: <IP address>
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the IP address of the remote station logging in.
<b>Recommended Action</b>	No action is required.

## SEC-1250

<b>Message</b>	DCC enforcement API failed: <failed action> err=<status>, key=<data>
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an internal error caused the Device Connection Control (DCC) policy enforcement to fail.
<b>Recommended Action</b>	Retry the failed security command. If the message persists, run <b>supportFtp</b> (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

## SEC-1251

<b>Message</b>	Policy to binary conversion error: <text message> <value>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the security database conversion failed because of invalid values. The reason is specified in the <i>text message</i> variable and the faulty value is printed in the <i>value</i> variable.
<b>Recommended Action</b>	Retry the failed security command. If the message persists, run <b>supportFtp</b> (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

## SEC-1253

<b>Message</b>	Bad DCC interface state during <Phase>, state=<state>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal error has caused the Device Connection Control (DCC) policy update to fail in the provision, commit, or cancel phases.
<b>Recommended Action</b>	Retry the failed security command. If the message persists, run <b>supportFtp</b> (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

## SEC-1300

<b>Message</b>	This switch is in VcEncode mode. Security is not supported.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the switch is set up with VC-encoded mode.
<b>Recommended Action</b>	Turn off VC-encoded mode before enabling security.

## SEC-1301

<b>Message</b>	This switch is in interop mode. Security is not supported.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the switch is enabled in interop mode.
<b>Recommended Action</b>	Disable interop mode using the <b>interopMode</b> command before enabling the Secure Fabric OS feature.

## SEC-1302

<b>Message</b>	This switch does not have all the required PKI objects correctly installed.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify that the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1303

<b>Message</b>	This software version does not support security.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the currently installed software version does not support the Brocade Secure Fabric OS feature.
<b>Recommended Action</b>	Run the <b>firmwareDownload</b> command to update the firmware to the latest version for your specific switch. Verify the firmware you are installing supports the Brocade Secure Fabric OS feature.

## SEC-1304

<b>Message</b>	This switch has no security license.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and then local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1305

<b>Message</b>	This switch has no zoning license.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a corruption occurred during the distribution of the security database. This can only occur when the primary fabric configuration server (FCS) distributes the security database to the other switches in the fabric, and the local validation finds the error in the security database. This is a rare occurrence.
<b>Recommended Action</b>	Run the <b>secFabricShow</b> command to verify the fabric is still consistent. All the switches should be in the ready state. If a switch is in the error state, the database may not be correctly updated for that specific switch.

## SEC-1306

<b>Message</b>	Failed to verify certificate with root CA.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the certificate could not be verified with root certificate authority (CA). This could happen if an unauthorized switch tries to access the fabric that is not certified by a trusted root CA or a root CA certificate does not exist on the switch.
<b>Recommended Action</b>	Run the <b>secCertUtil show -fcapall</b> command and verify that all public key infrastructure (PKI) objects exist on the switch. If a failure to validate PKI objects occurs, follow the steps for re-creating PKI objects outlined in the <i>Fabric OS Administrator's Guide</i> . If PKI objects are valid, verify that an unauthorized switch is not trying to access the fabric.

## SEC-1307

<b>Message</b>	<Security server (RADIUS/LDAP/TACACS+)> server <Server name> authenticated user account '<username>'.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that after some servers timed out, the specified RADIUS, LDAP, or TACACS+ server responded to a switch request.
<b>Recommended Action</b>	If the message appears frequently, move the responding server to the top of the RADIUS/LDAP/TACACS+ server configuration list using the <b>aaaConfig</b> command.

## SEC-1308

<b>Message</b>	All <Radius/LDAP/TACACS+ server identity> servers failed to authenticate user account '<username>'.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that all servers in the RADIUS, LDAP, or TACACS+ configuration have failed to respond to a switch request within the specified timeout.
<b>Recommended Action</b>	Verify the switch has proper network connectivity to the specified RADIUS, LDAP, or TACACS+s servers, and the servers are correctly configured.

## SEC-1309

<b>Message</b>	Waiting for RCS transaction to complete: <Wait time in seconds> secs
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that Fabric OS is still waiting for the reliable commit service (RCS) transaction to complete.
<b>Recommended Action</b>	Verify if there are any reliable commit service (RCS) or Reliable Transport With Response (RTWR) errors. If not, the transaction is still in progress.

## SEC-1310

<b>Message</b>	Unable to determine data distribution limit of fabric. Please retry later.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the data distribution limit could not be obtained from all switches in the fabric. This may happen if the fabric is reconfiguring or a new domain joined the fabric.
<b>Recommended Action</b>	Retry the command when the fabric is stable.

## SEC-1311

<b>Message</b>	Security mode cannot be enabled because one or more of the password policies is not set to default value.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the security enable failed on the fabric because one or more switches in the fabric have password policies that are not set to the default values.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, run the <b>passwdCfg --setdefault</b> command on each switch in the fabric to set the password policies to the default values. Then verify with the <b>passwdCfg --show</b> command that password policies are set to the default values on all switches and retry the <b>secModeEnable</b> command.



## SEC-1312

<b>Message</b>	<MSG Message>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the password configuration parameters changed.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-1313

<b>Message</b>	The passwdcfg parameters were set to default values.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the password configuration parameters were set to default values.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-1314

<b>Message</b>	Reading <IP Address Description> IP address from EM failed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the call to the environment monitor (EM) module to retrieve the IP address failed.
<b>Recommended Action</b>	Reboot the system to fix this error. If the problem persists, contact your switch service provider.

## SEC-1315

<b>Message</b>	<Name of command> command failed -<List of databases rejecting distribution> db(s) configured for rejection on this switch.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates there was an attempt to distribute databases to a switch that was configured not to accept distributions from the fabric.
<b>Recommended Action</b>	Verify the accept distribution configuration for the listed databases. Use the <b>remoteeCfg</b> command to verify and correct the configuration if necessary.

## SEC-1316

<b>Message</b>	<Policy Name> policy WWN List is conflicting with domain <Domain Number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the newly added switches to the fabric, as specified by domain number, have a conflicting policy with the local switch.
<b>Recommended Action</b>	Check the conflicting policy and make the new switches and the local switch policies the same.

## SEC-1317

<b>Message</b>	Inconsistent fabric, rejecting transaction
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that either this domain is performing FDD merge or matched domains are not the same as what CM sees.
<b>Recommended Action</b>	If a policy conflict exists, resolve it, and then wait for the fabric to become stable. Retry the distribution.

## SEC-1318

<b>Message</b>	Transaction rejected due to inconsistent fabric.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that some domains detected an inconsistent fabric.
<b>Recommended Action</b>	Resolve the policy conflict, if there is one, and then wait for the fabric to stabilize. Retry the distribution.

## SEC-1319

<b>Message</b>	<Event name> updated<Datasets updated> dbs(s).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified event has occurred.
<b>Recommended Action</b>	Verify the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-1320

<b>Message</b>	Non-acl domain <Domain Number> tries to join a fabric with strict fabric wide policy.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a domain not supporting an access control list (ACL) policy tried to join a fabric with the strict fabric-wide policy.
<b>Recommended Action</b>	No action is required. The domain is denied by disallowing all its E_Ports from connecting to the fabric.

## SEC-1321

<b>Message</b>	Failed secure mode enable command. Reason: <Reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the security enable failed on the fabric because the switch has a conflicting configuration such as fabric-wide consistency configuration or AD configuration.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, run the <b>fddCfg --fabwideset</b> command or <b>ad --clear</b> command to clear the fabric wide consistency configuration or AD configuration and retry the <b>secModeEnable</b> command.

## SEC-1322

<b>Message</b>	Some DCC policy is too large, distribution cancelled.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates this fabric is not able to support a Device Connection Control (DCC) policy with more than 256 ports.
<b>Recommended Action</b>	Reconfigure any policy that includes more than 256 ports in its member list, and then save the policy configuration changes.

## SEC-1323

<b>Message</b>	Key(s) \<"<Key Name>>" ignored during configdownload.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified key is ignored during configuration download.
<b>Recommended Action</b>	Verify the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-1324

<b>Message</b>	Fabric transaction failure. RCS error: <Error code>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the reliable commit service (RCS) transaction failed with the specified reason code.
<b>Recommended Action</b>	Verify the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-1325

<b>Message</b>	Security enforcement: Switch <switch WWN> connecting to port <Port number> is not authorized to stay in fabric.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that because of a Switch Connection Control (SCC) policy violation, the switch is being disabled on the specified port.
<b>Recommended Action</b>	No action is required unless the switch must remain in the fabric. If the switch must remain in the fabric, add the switch World Wide Name (WWN) to the SCC policy, and then attempt to join the switch with the fabric.

## SEC-1326

<b>Message</b>	Event: fddcfg --fabwideset, Status: success, Info: Fabric wide configuration set to <Fabric-wide configuration set by user>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified event has occurred.
<b>Recommended Action</b>	Verify the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-1327

<b>Message</b>	Strict <Policy Name> policy WWN List is conflicting with domain <Domain Number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the policy is conflicting with the domain.
<b>Recommended Action</b>	No action is required. The domain is denied by disallowing all its E_Ports connected to the fabric. If the domain should be allowed to merge with the fabric, then resolve the issue by making the conflicting policies the same.

## SEC-1328

<b>Message</b>	Attempt to enable secure mode failed. Reason: <Reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the <b>secModeEnable</b> command failed on the fabric because the Authentication Policy is enabled on the switch.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, run the <b>authUtil --policy passive</b> command to disable the Authentication Policy and retry the <b>secModeEnable</b> command.

## SEC-1329

<b>Message</b>	IPFilter enforcement:Failed to enforce ipfilter policy of <Policy Type> type because of <Error code>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the IP filter policy enforcement failed because of an internal system failure.
<b>Recommended Action</b>	Execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## SEC-1330

<b>Message</b>	<Name of command> command failed -<List of databases rejecting distribution> db(s) are coming from a non-Primary switch.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an attempt was made to distribute databases either from a backup fabric configuration server (FCS) switch or a non-FCS switch.
<b>Recommended Action</b>	Verify the distribution is initiated by the FCS switch. Use the <b>secPolicyShow</b> command to verify and correct the configuration if necessary.

## SEC-1331

<b>Message</b>	Attempt to enable secure mode failed. Reason: <Reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the <b>secModeEnable</b> command failed on the fabric because default IP filter policies are not active on the switch, or an active transaction exists on IP filter policies.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, run the <b>ipfilter --activate default_ipv4</b> command or the <b>ipfilter --activate default_ipv6</b> command to activate default IP filter policies. Use the <b>ipfilter --save</b> or <b>ipfilter --transabort</b> commands to save or abort the active transaction on IP filter policies. Then retry the <b>secModeEnable</b> command.

## SEC-1332

<b>Message</b>	Fabric wide policy is conflicting as <Policy Name> is present in the fabric wide policy and 5.3 or 5.2 switches present in the fabric.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the fabric-wide policy is conflicting.
<b>Recommended Action</b>	Remove either the FCS from the fabric-wide policy, or remove Fabric OS v5.3 or Fabric OS v5.2 switches from the fabric, or set the fabric-wide mode for FCS as strict.

## SEC-1333

<b>Message</b>	<Name of command> command failed. There are VF enabled switch(s) in fabric. <List of databases rejecting distribution> db(s) distribution is blocked.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates there was an attempt to distribute PWD or IPFILTER databases from the fabric to a switch that is VF-enabled
<b>Recommended Action</b>	Disable VF on all the switches that have VF-enabled if PWD or IPFILTER databases need to be distributed.

## SEC-1334

<b>Message</b>	SSH Daemon is restarted.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the Secure Shell (SSH) daemon was not running and it was restarted.
<b>Recommended Action</b>	No action is required.

## SEC-1335

<b>Message</b>	Strict <Policy Name> policy is conflicting with domain <Domain Number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the policy is conflicting with the domain.
<b>Recommended Action</b>	No action is required. The domain is denied by disallowing all its E_Ports connected to the fabric. If the domain should be allowed to merge with the fabric, then resolve the issue by making the conflicting policies the same.



## SEC-1336

<b>Message</b>	<Policy Name> policy is conflicting with domain <Domain Number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the newly added switches to the fabric, as specified by domain number, have a conflicting policy with the local switch.
<b>Recommended Action</b>	Check the conflicting policy and make the new switches and the local switch policies the same.

## SEC-1337

<b>Message</b>	Plain-text password is sent during console login
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that plain-text password is sent during console login
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-1338

<b>Message</b>	<MSG Message>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the password configuration parameters changed.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

**SEC-1339**

<b>Message</b>	Distribute command failed. There are Inflight encryption enabled switch(s) in fabric. Auth db(s) distribution is blocked
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates there was an attempt to distribute AUTH databases with switch policy (Off/Passive) from the fabric to a switch that has Inflight Encryption enabled
<b>Recommended Action</b>	Disable or enable Inflight encryption in all the switches in the fabric

**SEC-3001**

<b>Message</b>	Event: <Event Name>, Status: success, Info: Security mode <State change: Enabled or Disabled> on the fabric.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the security mode of the fabric was either enabled or disabled.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

**SEC-3002**

<b>Message</b>	Event: <Event Name>, Status: success, Info: <Event Related Info>.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified security event has occurred. The event can be one of the following: <ul style="list-style-type: none"> <li>• There has been a fabric configuration server (FCS) failover.</li> <li>• A security policy has been activated.</li> <li>• A security policy has been saved.</li> <li>• A security policy has been aborted.</li> <li>• A non-FCS password has changed.</li> </ul>

**Recommended Action** Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3003

**Message** Event: <Event Name>, Status: success, Info: Created <Policy Name> policy, with member(s) <Member List> .

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates a new security policy with entries has been created. When you use a wildcard (for example, an asterisk) in creating a policy, the audit report displays the wildcard in the event information field.

**Recommended Action** Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3004

**Message** Event: <Event Name>, Status: success, Info: Created <Policy name> policy.

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates a new security policy has been created. When you use a wildcard (for example, an asterisk) in creating a member for a policy, the audit report displays the wildcard in the event information field.

**Recommended Action** Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3005

**Message** Event: <Event Name>, Status: success, Info: Added member(s) <Members added> to policy <Policy name>.

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates new members have been added to a security policy. If you use a wildcard (for example, an asterisk) in adding members to a policy, the audit report displays the wildcard in the event information field.

## 5 SEC-3006

**Recommended Action** Verify the addition of members to the policy was planned. If the addition of members was planned, no action is required. If the addition of members was not planned, take appropriate action as defined by your enterprise security policy.

### SEC-3006

**Message** Event: <Event Name>, Status: success, Info: Removed member(s) <Members removed> from policy <Policy name>.

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates a user has removed the specific members from the security policy. When you use a wildcard (for example, an asterisk) in removing members from a policy, the audit report displays the wildcard in the event information field.

**Recommended Action** Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

### SEC-3007

**Message** Event: <Event Name>, Status: success, Info: Deleted policy <Deleted policy name>.

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates the specified security policy was deleted.

**Recommended Action** Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

### SEC-3008

**Message** Event: <Event Name>, Status: success, Info: FCS member moved from position <Old FCS position> to <New FCS position>.

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates the fabric configuration server (FCS) list has been modified. One of the members of the list has been moved to a new position in the list.

**Recommended Action** Verify the modification was planned. If the modification was planned, no action is required. If the modification was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3009

**Message** Event: <Event Name>, Status: success, Info: Security Transaction aborted.

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates the pending security transaction is aborted.

**Recommended Action** Verify the security transaction was intentionally aborted. If the security transaction was intentionally aborted, no action is required. If the security transaction was not intentionally aborted, take appropriate action as defined by your enterprise security policy.

## SEC-3010

**Message** Event: <Event Name>, Status: success, Info: Reset [<Name of security stat(s) reset>] security stat(s).

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates a user has reset all the security statistics.

**Recommended Action** Verify the security statistics were intentionally reset. If the security statistics were intentionally reset, no action is required. If the security statistics were not intentionally reset, take appropriate action as defined by your enterprise security policy.

## SEC-3011

**Message** Event: <Event Name>, Status: success, Info: Reset [<Stat name>] statistics on domain(s) [<Domain IDs>].

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates a user has reset a security statistic on the specified domains.

**Recommended Action** Verify the security statistics were intentionally reset. If the security statistics were intentionally reset, no action is required. If the security statistics were not intentionally reset, take appropriate action as defined by your enterprise security policy.

## SEC-3012

**Message** Event: <Event Name>, Status: success, Info: Temp Passwd <Password Set or Reset> on domain [<Domain ID>] for account [<Account name>].

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates a user has reset the password for the specified user accounts.

**Recommended Action** Verify the password was intentionally reset. If the password was intentionally reset, no action is required. If the password was not intentionally reset, take appropriate action as defined by your enterprise security policy.

## SEC-3013

**Message** Event: <Event Name>, Status: success, Info: Security Version stamp is reset.

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates a user has reset the security version stamp.

**Recommended Action** Verify the security version stamp was intentionally reset. If the security event was planned, no action is required. If the security version stamp was not intentionally reset, take appropriate action as defined by your enterprise security policy.

## SEC-3014

**Message** Event: <Event Name>, Status: success, Info: <Event related info> <Security server> server <Server Name> for AAA services.

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates a user has changed the RADIUS, LDAP, or TACACS+ configuration.

**Recommended Action** Verify the RADIUS configuration was changed intentionally. If the RADIUS configuration was changed intentionally, no action is required. If the RADIUS configuration was not changed intentionally, take appropriate action as defined by your enterprise security policy.

## SEC-3015

**Message** Event: <Event Name>, Status: success, Info: Moved <Event option> server <Server name> to position <New position>.

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates a user has changed the position of the RADIUS, LDAP, or TACACS+ server.

**Recommended Action** Verify the remote server position was intentionally changed. If the remote server position was intentionally changed, no action is required. If the remote server position was not intentionally changed, take appropriate action as defined by your enterprise security policy.

## SEC-3016

**Message** Event: <Event Name>, Status: success, Info: Attribute [<Attribute Name>] of <Security server> server <server ID> changed <Attribute related info, if any>.

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates a user has changed the specified attribute of the RADIUS, LDAP, and TACACS+ server.

**Recommended Action** Verify the RADIUS/LDAP/TACACS+ attribute was intentionally changed. If the RADIUS attribute was intentionally changed, no action is required. If the RADIUS/LDAP/TACACS+ attribute was not intentionally changed, take appropriate action as defined by your enterprise security policy.

## SEC-3017

**Message** Event: <Event Name>, Status: success, Info: <Event Related Info>.

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates a user has changed the RADIUS, LDAP, and TACACS+ configuration.

## 5 SEC-3018

**Recommended Action** Verify the RADIUS/LDAP/TACACS+ configuration was intentionally changed. If the RADIUS/LDAP/TACACS+ configuration was intentionally changed, no action is required. If the RADIUS/LDAP/TACACS+ configuration was not intentionally changed, take appropriate action as defined by your enterprise security policy.

### SEC-3018

**Message** Event: <Event Name>, Status: success, Info: Parameter [<Parameter Name>] changed from [<Old Value>] to [<New Value>].

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates the specified password configuration parameter is changed.

**Recommended Action** Verify the password configuration parameter was intentionally changed. If the password configuration parameter was intentionally changed, no action is required. If the password configuration parameter was not intentionally changed, take appropriate action as defined by your enterprise security policy.

### SEC-3019

**Message** Event: <Event Name>, Status: success, Info: Passwdcfg parameters set to default values.

**Message Type** AUDIT

**Class** SECURITY

**Severity** INFO

**Probable Cause** Indicates the password configuration parameters are set to default values.

**Recommended Action** Verify the password configuration parameter was intentionally set to default values. If the password configuration parameter was intentionally set to default values, no action is required. If the password configuration parameter was not intentionally set to default values, take appropriate action as defined by your enterprise security policy.



## SEC-3020

<b>Message</b>	Event: <Event Name>, Status: success, Info: Successful login attempt via <connection method and IP Address>.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a successful login occurred. An IP address is displayed when the login occurs over a remote connection.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3021

<b>Message</b>	Event: <Event Name>, Status: failed, Info: Failed login attempt via <connection method and IP Address>.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a failed login attempt occurred.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3022

<b>Message</b>	Event: <Event Name>, Status: success, Info: Successful logout by user [<User>].
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified user has successfully logged out.
<b>Recommended Action</b>	No action is required.

## SEC-3023

<b>Message</b>	Event: <Event Name>, Status: failed, Info: Account [<User>] locked, failed password attempts exceeded.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that failed password attempts exceeded the allowed limit; the account has been locked.
<b>Recommended Action</b>	The account may automatically unlock after the lockout duration has expired or an administrator may manually unlock the account.

## SEC-3024

<b>Message</b>	Event: <Event Name>, Status: success, Info: User account [<User Name>], password changed.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the user's password was changed.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3025

<b>Message</b>	Event: <Event Name>, Status: success, Info: User account [<User Name>] added. Role: [<Role Type>], Password [<Password Expired or not>], Home Context [<Home AD>], AD/VF list [<AD membership List>].
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a new user account was created.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3026

<b>Message</b>	Event: <Event Name>, Status: success, Info: User account [<User Name>], role changed from [<Old Role Type>] to [<New Role Type>].
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a user account role was changed.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3027

<b>Message</b>	Event: <Event Name>, Status: success, Info: User account [<User Name>] [<Changed Attributes>].
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates user account properties were changed.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3028

<b>Message</b>	Event: <Event Name>, Status: success, Info: User account [<User Name>] deleted.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified user account was deleted.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

**SEC-3029**

<b>Message</b>	Event: <Event Name>, Status: success, Info: Backup user account \"<User Account Name>\" recovered.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that backup user accounts were recovered.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

**SEC-3030**

<b>Message</b>	Event: <Event Name>, Status: success, Info: <Event Specific Info>.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified <b>secCertUtil</b> operation was performed.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

**SEC-3031**

<b>Message</b>	Event: <Event Name>, Status: success, Info: Distributed<List of Databases> db(s) to <Number of domains> domain(s), dom-id(s)<List of Domains>.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified event has occurred.
<b>Recommended Action</b>	Verify the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3032

<b>Message</b>	Event: <Event Name>, Status: success, Info: Switch is configured to <accept or reject> <Database name> database.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified event has occurred to accept or reject a certain database.
<b>Recommended Action</b>	Verify the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3033

<b>Message</b>	Event: fddcfg --fabwideset, Status: success, Info: Fabric wide configuration set to <Fabric-wide configuration set by user>.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified event has occurred.
<b>Recommended Action</b>	Verify the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3034

<b>Message</b>	Event: aaaconfig, Status: success, Info: Authentication configuration changed from <Previous Mode> to <Current Mode> <Exisisting sessions are terminated or not>.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an authentication configuration has changed.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

**SEC-3035**

<b>Message</b>	Event: ipfilter, Status: success, Info: <IP Filter Policy> ipfilter policy(ies) saved.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified IP filter policies has been saved.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

**SEC-3036**

<b>Message</b>	Event: ipfilter, Status: failed, Info: Failed to save changes for <IP Filter Policy> ipfilter policy(s).
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified IP filter policies have not been saved.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

**SEC-3037**

<b>Message</b>	Event: ipfilter, Status: success, Info: <IP Filter Policy> ipfilter policy activated.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified IP filter policy has been activated.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3038

<b>Message</b>	Event: ipfilter, Status: failed, Info: Failed to activate <IP Filter Policy> ipfilter policy.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified IP filter policy failed to activate.
<b>Recommended Action</b>	Verify the security event was planned. If the event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3039

<b>Message</b>	Event:Security Violation , Status: failed, Info: Unauthorized host with IP address <IP address of the violating host> tries to establish connection using <Protocol Connection Type>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a security violation was reported. The IP address of the unauthorized host is displayed in the message.
<b>Recommended Action</b>	Check for unauthorized access to the switch through the specified protocol connection.

## SEC-3044

<b>Message</b>	The FIPS mode has been changed to <Fips Mode>.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates there was a change in the Federal Information Processing Standards (FIPS) mode.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3045

<b>Message</b>	Zeroization has been executed on the system.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the system has been zeroized.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3046

<b>Message</b>	The FIPS Self Tests mode has been set to <Self Test Mode>.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates there was a change in the Federal Information Processing Standards (FIPS) Self Test mode.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3047

<b>Message</b>	Info: RBAC permission for a CLI command: <Cmd Name> is failed.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the user does not have permission to execute this command.
<b>Recommended Action</b>	Verify the user has the required permission to execute this command.



## SEC-3048

<b>Message</b>	FIPS mode has been enabled in the system using force option.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the system has been forced to Federal Information Processing Standards (FIPS) mode.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy. Look for the status of the prerequisites that did not conform to FIPS mode.

## SEC-3049

<b>Message</b>	Status of bootprom access is changed using fipscfg CLI to : <Access Status>.
<b>Message Type</b>	AUDIT
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the status of boot PROM access has changed using the <b>fipsCfg</b> command.
<b>Recommended Action</b>	No action is required.

## SEC-3050

<b>Message</b>	Event: <Event Name>, Status: success, Info: <Event Specific Info>
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified Secure Shell (SSH) utility operation was performed.
<b>Recommended Action</b>	Verify the security event was planned. If the security event was planned, no action is required. If the security event was not planned, take appropriate action as defined by your enterprise security policy.

## SEC-3051

<b>Message</b>	The license key <Key> is <Action>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a license key is added or removed.
<b>Recommended Action</b>	No action is required.

## SEC-3061

<b>Message</b>	Role '<Role Name>' is created.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified role name has been created.
<b>Recommended Action</b>	No action is required.

## SEC-3062

<b>Message</b>	Role '<Role Name>' is deleted.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified role name has been deleted.
<b>Recommended Action</b>	No action is required.

## SEC-3063

<b>Message</b>	Role '<Role Name>' is copied from '<Source Role>'.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified role name has been copied from the source role.
<b>Recommended Action</b>	No action is required.

## SEC-3064

<b>Message</b>	Permission to the RBAC class(es) '<RBAC Class Names>' is changed for the role '<Role Name>'.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the permission to the Role-Based Access Control (RBAC) class is changed for the specified role name.
<b>Recommended Action</b>	No action is required.

## SEC-3065

<b>Message</b>	Configuration of user-defined roles is uploaded.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the configuration of user-defined roles has been uploaded.
<b>Recommended Action</b>	No action is required.

## SEC-3066

<b>Message</b>	Configuration of user-defined roles is downloaded.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the configuration of user-defined roles has been downloaded.
<b>Recommended Action</b>	No action is required.

## SEC-3067

<b>Message</b>	Invalid Cipher list <Cipher List>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the input cipher list is an invalid string.
<b>Recommended Action</b>	Invalid cipher list input, therefore reverted to previous cipher list.

## SEC-4001

<b>Message</b>	Client logged in. <IP Address>, <User Account>, <Application>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the client has logged in.
<b>Recommended Action</b>	No action is required.

## SFLO Messages

### SFLO-1001

<b>Message</b>	sFlow is <state> globally.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that sFlow is globally enabled or disabled.
<b>Recommended Action</b>	No action is required.

### SFLO-1002

<b>Message</b>	sFlow is <state> for port <name>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that sFlow is enabled or disabled on the specified port.
<b>Recommended Action</b>	No action is required.

### SFLO-1003

<b>Message</b>	Global sFlow sampling rate is changed to <sample_rate>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the global sFlow sampling rate has been changed to the specified value.
<b>Recommended Action</b>	No action is required.

## SFLO-1004

<b>Message</b>	Global sFlow polling interval is changed to <polling_intvl>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the global counter sampling interval has been changed to the specified value.
<b>Recommended Action</b>	No action is required.

## SFLO-1005

<b>Message</b>	sFlow sampling rate on port <name> is changed to <sample_rate>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the sFlow sampling rate has been changed on the specified port.
<b>Recommended Action</b>	No action is required.

## SFLO-1006

<b>Message</b>	sFlow polling interval on port <name> is changed to <poling_intvl>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the polling interval has been changed on the specified port.
<b>Recommended Action</b>	No action is required.

## SFLO-1007

<b>Message</b>	<name> is <state> as sFlow collector.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the sFlow collector is configured or not configured.

**Recommended Action** No action is required.

## SFLO-1008

**Message** All the sFlow collectors are unconfigured.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that none of the sFlow collectors are configured.

**Recommended Action** No action is required.

## SNMP Messages

### SNMP-1001

<b>Message</b>	SNMP service is not available <Reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Simple Network Management Protocol (SNMP) service could not be started because of the specified reason. Therefore, you will not be able to query the switch through SNMP.
<b>Recommended Action</b>	Verify that the IP address for the Ethernet and Fibre Channel interface is set correctly. If the specified reason is an initialization failure, restart the switch using the <b>reboot</b> command.

### SNMP-1002

<b>Message</b>	SNMP <Error Details> initialization failed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the initialization of the SNMP service failed and therefore you will not be able to query the switch through SNMP.
<b>Recommended Action</b>	Restart or power cycle the switch. This will automatically initialize SNMP.

### SNMP-1003

<b>Message</b>	Distribution of Community Strings to Secure Fabric failed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the changes in the SNMP community strings could not be propagated to other switches in the secure fabric.
<b>Recommended Action</b>	Retry changing the SNMP community strings on the primary switch.



## SNMP-1004

<b>Message</b>	Incorrect SNMP configuration.
<b>Message Type</b>	AUDIT   FFDC   LOG
<b>Class</b>	CFG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the SNMP configuration is incorrect and therefore the SNMP service will not work correctly.
<b>Recommended Action</b>	Change the SNMP configuration to the default using the <b>snmpConfig --default</b> command.

## SNMP-1005

<b>Message</b>	SNMP configuration attribute, <Changed attribute>, has changed from <Old Value> to <New Value>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the SNMP configuration has changed. The modified parameter and the old and new parameter values are displayed in the message.
<b>Recommended Action</b>	Execute the <b>snmpConfig --show</b> command to view the new SNMP configuration.

## SNMP-1006

<b>Message</b>	<SNMP Configuration group> configuration was reset to default.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified SNMP configuration group was reset to the factory default.
<b>Recommended Action</b>	Execute the <b>snmpConfig --show</b> command for the group to view the new SNMP configuration.

## SNMP-1009

<b>Message</b>	Port traps are <blocked state> on port <port>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the blocked or unblocked status of the port traps on the specified port.
<b>Recommended Action</b>	Execute the <b>snmpTraps --show</b> command to view the current status of the port.

## SPC Messages

### SPC-1001

<b>Message</b>	S<slot number containing Encryption Engine>, Cryptographic operation enabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the cryptographic operation is enabled on an encryption engine.
<b>Recommended Action</b>	No action is required.

### SPC-1002

<b>Message</b>	S<slot number containing Encryption Engine>, Cryptographic operation disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the cryptographic operation is disabled on an encryption engine.
<b>Recommended Action</b>	No action is required.

### SPC-1003

<b>Message</b>	S<slot number containing Encryption Engine>, Security Processor faulted.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the security processor is faulted because of an internal error. Cryptographic operations are affected.
<b>Recommended Action</b>	To recover a bladed system, execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands on the blade. To recover a non-bladed system, execute the <b>fastboot</b> command on the switch.

## SPC-2001

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: Crypto error asserted by Vader/OB1 0x<Reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that Crypto error is asserted by the Field-Programmable Gate Array (FPGA).
<b>Recommended Action</b>	No action is required.

## SPC-2002

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: Tamper Event: Crypto subsystem cover tampered.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the Crypto subsystem cover is tampered. The encryption engine is zeroized.
<b>Recommended Action</b>	Execute the <b>cryptocfg --initEE</b> and <b>cryptocfg --regEE</b> commands.

## SPC-2003

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: Data Disable status: 0x<DisableStatus>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the data disable signal status.
<b>Recommended Action</b>	No action is required.

## SPC-2004

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: FPGA firmware download failed: 0x<Reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that FPGA download has failed.
<b>Recommended Action</b>	No action is required.

## SPC-2005

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: FPGA firmware download success.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that FPGA download was successful.
<b>Recommended Action</b>	No action is required.

## SPC-2006

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: Crypto post tests failed: 0x<Reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that Crypto Power-On Self-Test (POST) tests have failed.
<b>Recommended Action</b>	No action is required.

## SPC-2007

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: Crypto post tests success: 0x<Reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that Crypto Power-On Self-Test (POST) has passed successfully.
<b>Recommended Action</b>	No action is required.

## SPC-2008

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: Vader/OB1 recovered from error.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Crypto error from FPGA is de-asserted.
<b>Recommended Action</b>	No action is required.

## SPC-2009

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: Tamper event: User zeroization.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the tamper event triggered due to a user zeroize request. The encryption engine is zeroized.
<b>Recommended Action</b>	Execute the <b>cryptocfg --initEE</b> and <b>cryptocfg --regEE</b> commands.

## SPC-2010

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: Crypto subsystem cover is open.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the Crypto subsystem cover is open.
<b>Recommended Action</b>	Close the Crypto subsystem cover properly.

## SPC-2011

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: OBl crypto BIST success.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the FPGA built-in self-test (BIST) was successful.
<b>Recommended Action</b>	No action is required.

## SPC-2012

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: User zeroization command completed successfully. Tamper INT status <Status>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the user zeroization command has completed successfully. The encryption engine is zeroized.
<b>Recommended Action</b>	Execute the <b>cryptocfg --initEE</b> and <b>cryptocfg --regEE</b> commands.

**SPC-2013**

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: Oscillator Failure Detected.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates hardware failure.
<b>Recommended Action</b>	The shelf life of the system may be reduced. Contact the vendor for further instructions.

**SPC-2014**

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: Low Battery Level Detected.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the battery is depleted.
<b>Recommended Action</b>	System operation will be unaffected while the facility power is present. Schedule battery replacement with the vendor.

**SPC-2040**

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: SPD Device minorNum <MinorNum> is already open. state <State>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Security Policy Database (SPD) device has already opened or is busy for sysctrlr or keyappd.
<b>Recommended Action</b>	No action is required.



## SPC-2041

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: Alloc freemsg block failed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an allocation failure for the pool of SB message.
<b>Recommended Action</b>	No action is required.

## SPC-2042

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: Alloc msg - no free sbmsgs.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates no free message buffer in the free pool.
<b>Recommended Action</b>	No action is required.

## SPC-2043

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: Destination device read queue overflow <Device minor>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the device read queue has overflowed.
<b>Recommended Action</b>	No action is required.

## SPC-2044

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: Read - device not open <Device minor number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the SPD device is not opened.
<b>Recommended Action</b>	No action is required.

## SPC-3001

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: No input KEK for DEK inject, DEK: <DEK octet 1> <DEK octet 2> <DEK octet 3> <DEK octet 4>, KEK: <KEK octet 1> <KEK octet 2> <KEK octet 3> <KEK octet 4>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the wrapping key encryption key (KEK) for the data encryption key (DEK) to be injected does not exist within the encryption engine CryptoModule.
<b>Recommended Action</b>	For opaque key vaults such as DPM, recover the missing master key to the current or alternate position.

## SPC-3002

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: No input KEK for DEK rewrap, DEK: <DEK octet 1> <DEK octet 2> <DEK octet 3> <DEK octet 4>, KEK: <KEK octet 1> <KEK octet 2> <KEK octet 3> <KEK octet 4>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the input wrapping key encryption key (KEK) for the data encryption key (DEK) to be rewrapped does not exist within the encryption engine CryptoModule.
<b>Recommended Action</b>	For opaque key vaults such as DPM, recover the missing master key to the current or alternate position.

## SPC-3003

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: No output KEK for DEK rewrap, DEK: <DEK octet 1> <DEK octet 2> <DEK octet 3> <DEK octet 4>, KEK: <KEK octet 1> <KEK octet 2> <KEK octet 3> <KEK octet 4>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the output wrapping key encryption key (KEK) for the data encryption key (DEK) to be rewrapped does not exist within the encryption engine CryptoModule.
<b>Recommended Action</b>	No action is required. The KEK will be recovered automatically.

## SPC-3004

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: No output KEK for DEK create, KEK: <KEK octet 1> <KEK octet 2> <KEK octet 3> <KEK octet 4>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates the output wrapping key encryption key (KEK) for the data encryption key (DEK) to be created does not exist within the encryption engine CryptoModule.
<b>Recommended Action</b>	For opaque key vaults such as DPM, recover the missing master key to the current or alternate position.

## SPC-3005

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: DEK inject error: <SP status code>, DEK: <DEK octet 1 or other info> <DEK octet 2> <DEK octet 3> <DEK octet 4>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an error in injecting data encryption key (DEK) into encryption engine. The <i>SP status code</i> variable specifies the cause of the error: <ul style="list-style-type: none"> <li>• 14 - Invalid input DEK format</li> <li>• 32 - DEK could not be unwrapped</li> <li>• 33 - FGPA error upon inject</li> <li>• 73 - Invalid key encryption key (KEK) format</li> </ul>
<b>Recommended Action</b>	Contact your switch service provider for assistance.

## SPC-3006

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: DEK rewrap error: <SP status code>, DEK: <DEK octet 1 or other info> <DEK octet 2> <DEK octet 3> <DEK octet 4>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates data encryption key (DEK) rewrap error. The <i>SP status code</i> variable specifies the cause of the error: <ul style="list-style-type: none"> <li>• 2 - Invalid input data encryption key (DEK) format</li> <li>• 14 - Rewrapping not allowed: primary key encryption key (KEK) generation is in progress</li> <li>• 31 - DEK could not be wrapped</li> <li>• 32 - DEK could not be unwrapped</li> <li>• 33 - FGPA error upon inject</li> <li>• 73 - Invalid KEK format</li> </ul>
<b>Recommended Action</b>	For status code 14, complete primary KEK generation; otherwise, contact your switch service provider.

## SPC-3007

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: DEK create error: <SP status code>, info: <other info>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an error in creating data encryption key (DEK). The <i>SP status code</i> variable specifies the cause of the error: <ul style="list-style-type: none"> <li>• 2 - Invalid input data encryption key (DEK) specification</li> <li>• 14 - Creation not allowed: primary key encryption key (KEK) generation is in progress</li> <li>• 21 - No primary KEK exists with which to wrap the DEK</li> <li>• 31 - DEK could not be wrapped</li> <li>• 73 - Invalid KEK format</li> <li>• other - Internal error</li> </ul>
<b>Recommended Action</b>	For status code 14, complete primary KEK generation; otherwise, contact your switch service provider.

## SPC-3008

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: SP crypto got READY notification.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the key application (KPD) within the CryptoModule of the encryption engine has been started.
<b>Recommended Action</b>	No action is required.

## SPC-3009

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: FIPS certificate mismatch, certificate: <FIPS certificate is CO-0 or User-1>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Federal Information Protection Standard (FIPS) certificate within the CryptoModule does not match that of the node.
<b>Recommended Action</b>	Zeroize the encryption engine (after backing up any needed primary or secondary KEK), then execute the <b>cryptocfg --initEE</b> and <b>cryptocfg --regEE</b> commands.

## SPC-3010

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: SEK integrity failure during initialization.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the CryptoModule internal Secret Encryption Key has been corrupted or has not been initialized.
<b>Recommended Action</b>	Execute the <b>cryptocfg --initEE</b> and <b>cryptocfg --regEE</b> commands.

**SPC-3011**

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: Persistent data storage error: <SP status code>, KEK: <KEK octet 1> <KEK octet 2> <KEK octet 3> <KEK octet 4>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that an attempt to store CryptoModule internal data using the Secret Encryption Key failed; most likely, the encryption engine has been zeroized or tampered with.
<b>Recommended Action</b>	Execute the <b>cryptocfg --initEE</b> and <b>cryptocfg --regEE</b> commands, and then recover or restore the needed primary and secondary KEKs.

**SPC-3012**

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: Persistent data retrieval error: <SP status code>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that an attempt to read CryptoModule internal data using the Secret Encryption Key failed; most likely, the encryption engine has been zeroized or tampered with.
<b>Recommended Action</b>	Execute the <b>cryptocfg --initEE</b> and <b>cryptocfg --regEE</b> commands, and then recover or restore the needed primary and secondary KEKs.

**SPC-3013**

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: SEK generation failure: <SP status code>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the CryptoModule internal Secret Encryption Key could not be generated.
<b>Recommended Action</b>	Contact your switch service provider for assistance.

## SPC-3014

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: RNG compare failure: successive values match.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the CryptoModule internal random number generator has failed.
<b>Recommended Action</b>	Contact your switch service provider for assistance.

## SPC-3015

<b>Message</b>	S<slot number containing Encryption Engine>, <module name>: RSA pairwise key generation test failure.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the CryptoModule could not generate its internal key pair.
<b>Recommended Action</b>	Contact your switch service provider for assistance.

## SPM Messages

### SPM-1001

<b>Message</b>	Init fails: <Reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the security processor management (SPM) failed to initialize.
<b>Recommended Action</b>	Check the system resources and restart the switch.

### SPM-1002

<b>Message</b>	Generic SPM Warning: <Reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates an security processor management (SPM) warning based on the reason displayed.
<b>Recommended Action</b>	Execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

### SPM-1003

<b>Message</b>	Set New Group Cfg SC Enable <SC_Enable> KV Type <KV_Type>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a new group has been configured.
<b>Recommended Action</b>	No action is required.



## SPM-1004

<b>Message</b>	Initialize Node.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a node initialization.
<b>Recommended Action</b>	No action is required.

## SPM-1005

<b>Message</b>	Set EE Control slot <slot> action <action>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates specified control action is taken on encryption engine in specified slot.
<b>Recommended Action</b>	No action is required.

## SPM-1006

<b>Message</b>	Registered Certificate of type <cert_type>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a certificate registration.
<b>Recommended Action</b>	No action is required.

## SPM-1007

<b>Message</b>	Deregistered Certificate cid [<cert_id>] type <cert_type> idx <qc_idx>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a certificate de-registration.

## 5 SPM-1008

**Recommended Action** No action is required.

### SPM-1008

**Message** Deregistered SP Certificate in slot <slot>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates an security processor (SP) certificate de-registration.

**Recommended Action** No action is required.

### SPM-1009

**Message** <cert> Certificate is missing.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the specified certificate is missing.

**Recommended Action** Execute the **cryptocfg --initnode** command.

### SPM-1010

**Message** <cert> Key Vault Certificate is missing.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the specified key vault certificate is missing.

**Recommended Action** Deregister and register the key vault.

## SPM-1011

<b>Message</b>	Group Cfg Changed Quorum Size <qc_size>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a group configuration has changed the quorum size.
<b>Recommended Action</b>	No action is required.

## SPM-1012

<b>Message</b>	Authentication Context: <established>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an authentication context.
<b>Recommended Action</b>	No action is required.

## SPM-1013

<b>Message</b>	Security database is out of sync.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a failure to distribute security database.
<b>Recommended Action</b>	Execute the <b>cryptocfg --sync -securitydb</b> command to manually sync the security database.

## SPM-1014

<b>Message</b>	Warning: Configdownload may change key vault configuration and result in EE going to Operational; Need Valid KEK state.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the master keys downloaded will not be effective unless imported because the encryption engine may have different master key configured.
<b>Recommended Action</b>	Import required master keys using the <b>cryptocfg --recovermasterkey</b> command to bring the encryption engine online.

## SPM-1015

<b>Message</b>	Security database may be out of sync.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a failure to distribute the security database.
<b>Recommended Action</b>	Use the <b>cryptocfg --sync -securitydb</b> command to manually sync security database.

## SPM-1016

<b>Message</b>	Security database is out of sync. This warning can be ignored if the nodes in the EG are running different versions of FOS.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a failure to distribute the security database.
<b>Recommended Action</b>	Use the <b>cryptocfg --sync -securitydb</b> command to manually sync security database.

## SPM-3001

<b>Message</b>	Event: cryptocfg Status: success, Info: Node [<wnstr>] initialized.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a node was initialized.
<b>Recommended Action</b>	No action is required.

## SPM-3002

<b>Message</b>	Event: cryptocfg Status: success, Info: EE in slot <slot> initialized.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an encryption engine was initialized.
<b>Recommended Action</b>	No action is required.

## SPM-3003

<b>Message</b>	Event: cryptocfg Status: success, Info: EE in slot <slot> registered.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an encryption engine was registered.
<b>Recommended Action</b>	No action is required.

## SPM-3004

<b>Message</b>	Event: cryptocfg Status: success, Info: EE in slot <slot> enabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an encryption engine was enabled.
<b>Recommended Action</b>	No action is required.

## SPM-3005

<b>Message</b>	Event: cryptocfg Status: success, Info: EE in slot <slot> disabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an encryption engine was disabled.
<b>Recommended Action</b>	No action is required.

## SPM-3006

<b>Message</b>	Event: cryptocfg Status: success, Info: <sourceFile> file exported via scp: <hostUsername>[<hostIP>]:<hostPath>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a file was exported through SCP protocol.
<b>Recommended Action</b>	No action is required.

## SPM-3007

<b>Message</b>	Event: cryptocfg Status: success, Info: File imported via scp: <hostUsername>[<hostIP>]:<hostPath>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a file was imported through SCP protocol
<b>Recommended Action</b>	No action is required.

## SPM-3008

<b>Message</b>	Event: cryptocfg Status: success, Info: DH challenge generated for vault IP <vaultIP>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a DH challenge was generated for a key vault.
<b>Recommended Action</b>	No action is required.

## SPM-3009

<b>Message</b>	Event: cryptocfg Status: success, Info: DH response accepted.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a DH response was accepted.
<b>Recommended Action</b>	No action is required.

## SPM-3010

<b>Message</b>	Event: cryptocfg Status: success, Info: EE in slot <slot> zeroized.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an encryption engine was zeroized.
<b>Recommended Action</b>	No action is required.

## SPM-3011

<b>Message</b>	Event: cryptocfg Status: success, Info: Local file \"<filename>\" deleted.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a locally stored file was deleted.
<b>Recommended Action</b>	No action is required.

## SPM-3012

<b>Message</b>	Event: cryptocfg Status: success, Info: <primaryOrSecondary> key vault registered. Certificate label: \"<certLabel>\" Certificate file: \"<certFilename>\" IP address: <IPAddress>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a key vault was registered.
<b>Recommended Action</b>	No action is required.



## SPM-3013

<b>Message</b>	Event: cryptocfg Status: success, Info: Key vault with certificate label \"<certLabel>\" deregistered.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a key vault was deregistered.
<b>Recommended Action</b>	No action is required.

## SPM-3014

<b>Message</b>	Event: cryptocfg Status: success, Info: Key archive client registered with certificate file \"<certFilename>\".
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a key archive client (KAC) certificate was registered.
<b>Recommended Action</b>	No action is required.

## SPM-3015

<b>Message</b>	Event: cryptocfg Status: success, Info: Key vault type set to <keyVaultType>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the key vault type was set.
<b>Recommended Action</b>	No action is required.

## SPM-3016

<b>Message</b>	Event: cryptocfg Status: success, Info: Master key generated.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a master key was generated
<b>Recommended Action</b>	No action is required.

## SPM-3017

<b>Message</b>	Event: cryptocfg Status: success, Info: Master key exported.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a master key was exported.
<b>Recommended Action</b>	No action is required.

## SPM-3018

<b>Message</b>	Event: cryptocfg Status: success, Info: <currentOrAlternate> master key recovered.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a master key was recovered.
<b>Recommended Action</b>	No action is required.

**SPM-3019**

<b>Message</b>	Event: cryptocfg Status: success, Info: System card registered. Certificate label: \ \"<certLabel>\" Certificate file: \ \"<certFilename>\".
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a system card was registered.
<b>Recommended Action</b>	No action is required.

**SPM-3020**

<b>Message</b>	Event: cryptocfg Status: success, Info: System card with certificate label \"<certLabel>\" deregistered.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a system card was deregistered.
<b>Recommended Action</b>	No action is required.

**SPM-3021**

<b>Message</b>	Event: cryptocfg Status: success, Info: Authentication card registered. Certificate label: \ \"<certLabel>\" Certificate file: \ \"<certFilename>\".
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an authentication card was registered.
<b>Recommended Action</b>	No action is required.

## SPM-3022

<b>Message</b>	Event: cryptocfg Status: success, Info: Authentication card with certificate label \"<certLabel>\" deregistered.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an authentication card was deregistered.
<b>Recommended Action</b>	No action is required.

## SPM-3023

<b>Message</b>	Event: cryptocfg Status: success, Info: System card <enabledOrDisabled>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates use of the system card was enabled or disabled.
<b>Recommended Action</b>	No action is required.

## SPM-3024

<b>Message</b>	Event: cryptocfg Status: success, Info: Quorum size set to <quorumsize>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the quorum size was set.
<b>Recommended Action</b>	No action is required.

## SPM-3025

<b>Message</b>	Event: cryptocfg Status: success, Info: File imported via USB: Source: <sourcePath> Destination: <destinationFilename>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a file was imported through a USB device.
<b>Recommended Action</b>	No action is required.

## SPM-3026

<b>Message</b>	Event: cryptocfg Status: success, Info: File exported via usb: Source: <sourcePath> Destination: <destinationFilename>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a file was exported through a USB device
<b>Recommended Action</b>	No action is required.

## SPM-3027

<b>Message</b>	Event: cryptocfg Status: success, Info: Recovery card registered. Certificate label: \"<certLabel>\" Certificate file: \"<certFilename>\".
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a recovery card was registered.
<b>Recommended Action</b>	No action is required.

## SPM-3028

<b>Message</b>	Event: SPM-EE state changed, Info: EE State: <EE Status>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates an encryption engine state has changed.
<b>Recommended Action</b>	No action is required.

## SPM-3029

<b>Message</b>	Event: KeyVault Connection Status: <status>, Info: KAC_Connect: <kac status>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	SECURITY
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the status of key vault.
<b>Recommended Action</b>	No action is required.

## SS Messages

### SS-1000

<b>Message</b>	supportSave has uploaded support information to the host with IP address <host ip>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>supportSave</b> command was used to transfer support information to a remote location.
<b>Recommended Action</b>	No action is required.

### SS-1001

<b>Message</b>	supportSave's upload operation to host IP address <host ip> aborted.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a file copy error occurred during execution of the <b>supportSave</b> command. Complete error information cannot always be displayed in this message because of possible errors in subcommands being executed by the <b>supportSave</b> command.
<b>Recommended Action</b>	Check and correct the remote server settings and configuration. Execute the <b>supportFtp</b> command (as needed) to set the FTP or SCP parameters. After the problem is corrected, execute the <b>supportSave</b> command again.

### SS-1002

<b>Message</b>	supportSave has stored support information to the USB storage device.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>supportSave</b> command was used to transfer support information to an attached USB storage device.
<b>Recommended Action</b>	No action is required.

## SS-1003

<b>Message</b>	supportSave's operation to USB storage device aborted.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a USB operation error occurred during execution of the <b>supportSave</b> command. Complete error information cannot always be displayed in this message because of possible errors in subcommands being executed by the <b>supportSave</b> command.
<b>Recommended Action</b>	Execute the <b>usbstorage</b> command to check the USB storage device settings. After the USB problem is corrected, execute the <b>supportSave</b> command again.

## SS-1004

<b>Message</b>	One or more modules timed out during supportsave. Retry supportsave with -t option to collect all logs.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a timeout in modules during the execution of the <b>supportSave</b> command.
<b>Recommended Action</b>	Execute the <b>supportSave -t [2-5]</b> command to collect all logs.

## SS-1005

<b>Message</b>	supportsave failed for the slot <Slot Number>. Reason: No IP connection.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that there is no IP connection between the active control processor (CP) and the blade in the specified slot.
<b>Recommended Action</b>	Check for the IP connection between the active CP and the blade in the specified slot. After the IP connection is established, execute the <b>supportSave</b> command again.



## SS-1006

<b>Message</b>	supportsave not collected for slot <Slot Number>. Reason: blade was not available to accept a supportsave request.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the supportsave request was not sent to the blade in the specified slot.
<b>Recommended Action</b>	Restart the switch using the <b>reboot</b> command and then execute the <b>supportSave</b> command.

## SS-1007

<b>Message</b>	supportsave failed for the slot <Slot Number>. Reason: No response from the blade in the specified slot for the given supportsave request.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that there was no response from the blade in the specified slot for the given supportsave request.
<b>Recommended Action</b>	Restart the switch using the <b>reboot</b> command and then execute the <b>supportSave</b> command.

## SS-1008

<b>Message</b>	supportsave failed for the slot <Slot Number>. Reason: BP supportsave timeout.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified slot has taken more time than expected to collect the supportsave logs.
<b>Recommended Action</b>	Execute the <b>supportSave</b> command again.

## SS-1009

<b>Message</b>	<slot number and its node name(BP/DP)> supportsave failed. Reason:No ISC connection for <slot number and its node name(BP/DP)>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that there is no Inter-Subsystem Communication (ISC) connection for the specified node slot.
<b>Recommended Action</b>	Restart the switch using the <b>reboot</b> command and then execute the <b>supportSave</b> command.

## SS-1010

<b>Message</b>	CORE/FFDC files have been uploaded to the host with IP address <host ip>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>supportSave</b> command was used to transfer core and first failure data capture (FFDC) files to a remote location.
<b>Recommended Action</b>	No action is required.

## SS-1011

<b>Message</b>	CORE/FFDC files have been transferred to the USB storage device.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>supportSave</b> command was used to transfer core and first failure data capture (FFDC) files to a USB storage Device.
<b>Recommended Action</b>	No action is required.

## SS-1012

<b>Message</b>	BP supportsave failed. The /mnt of Active CP does not have enough disk space to collect BP supportsave files.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a chassis with the blade processor (BP) does not have enough disk space in the secondary partition of the active CP to save the supportsave files, before uploading them to the remote host.
<b>Recommended Action</b>	Manually clean up the secondary partition of the active CP to collect the supportsave files.

## SSMD Messages

### SSMD-1001

<b>Message</b>	Failed to allocate memory: (<function name>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified function has failed to allocate memory.
<b>Recommended Action</b>	Check the memory usage on the switch using the <b>memShow</b> command. Restart or power cycle the switch.

### SSMD-1002

<b>Message</b>	Failed to initialize <module> rc = <error>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the initialization of a module within System Services Manager (SSM) has failed.
<b>Recommended Action</b>	Download a new firmware using the <b>firmwareDownload</b> command.

### SSMD-1003

<b>Message</b>	Failed to lock semaphore mutex: (<function name>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified function has failed to lock the mutex (semaphore).
<b>Recommended Action</b>	Restart or power cycle the switch.

## SSMD-1004

<b>Message</b>	Failed to unlock semaphore mutex: (<function name>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified function failed to unlock the mutex (semaphore).
<b>Recommended Action</b>	Restart or power cycle the switch.

## SSMD-1005

<b>Message</b>	SSM start up failed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that Data Center Ethernet (DCE) SSM encountered an unexpected severe error during basic startup and initialization.
<b>Recommended Action</b>	Restart or power cycle the switch. If the problem persists, download a new firmware using the <b>firmwareDownload</b> command.

## SSMD-1006

<b>Message</b>	Error while configuring ACL <ACL name> on interface <Interface name>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that an error occurred while programming a Ternary Content Addressable Memory (TCAM) entry on the specified interface.
<b>Recommended Action</b>	Try again after some time. If the problem persists, execute the <b>supportSave</b> command and then restart or power cycle the switch.

## SSMD-1007

<b>Message</b>	Error while removing ACL <ACL name> from interface <Interface name>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that an error occurred while programming a TCAM entry on the specified interface.
<b>Recommended Action</b>	Try again after some time. If the problem persists, execute the <b>supportSave</b> command and then restart or power cycle the switch.

## SSMD-1008

<b>Message</b>	Apptype TCAM Table full for Slot:<slot number> chip:<Chip number in the slot>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the application type TCAM table is full on the specified chip.
<b>Recommended Action</b>	Remove the unused protocol-based VLAN classifiers and Layer 2 extended access control lists (ACLs).

## SSMD-1200

<b>Message</b>	QoS failed programming ASIC <ASIC slot number>/<ASIC chip number> Multicast Rate Limit.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in programming the dataplane application-specific integrated circuit (ASIC) for enforcing the Multicast Rate Limit feature.
<b>Recommended Action</b>	Delete and reapply the Quality of Service (QoS) Multicast Rate Limit policy using the <b>qos rcv-queue multicast rate-limit</b> command. If the problem persists, restart or power cycle the switch.

## SSMD-1201

<b>Message</b>	QoS failed programming ASIC <ASIC slot number>/<ASIC chip number> Multicast Tail Drop.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in programming the dataplane ASIC for enforcing the Multicast Tail Drop feature.
<b>Recommended Action</b>	Delete and reapply the QoS Multicast Tail Drop policy using the <b>qos rcv-queue multicast threshold</b> command. If the problem persists, restart or power cycle the switch.

## SSMD-1202

<b>Message</b>	QoS failed programming interface 0x<Interface ID> 802.3x Pause flow control.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in programming the dataplane ASIC for enforcing interface 802.3x Pause flow control feature.
<b>Recommended Action</b>	Delete and reapply the QoS 802.3x Pause flow control policy using the <b>qos flowcontrol</b> command. If the problem persists, restart or power cycle the switch.

## SSMD-1203

<b>Message</b>	QoS failed programming interface 0x<Interface ID> PFC flow control.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in programming the dataplane ASIC for enforcing interface Priority-based Flow Control (PFC) flow control feature.
<b>Recommended Action</b>	Delete and reapply the QoS PFC flow control policy using the <b>qos flowcontrol pfc</b> command. If the problem persists, restart or power cycle the switch.

## SSMD-1204

<b>Message</b>	QoS failed initializing ASIC <ASIC slot number>/<ASIC chip number>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in initializing the dataplane ASIC QoS infrastructure.
<b>Recommended Action</b>	Restart or power cycle the switch.

## SSMD-1205

<b>Message</b>	CEE failed programming ETS policy for CEE Map <CEE Map name>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in programming the dataplane ASIC for enforcing the Converged Enhanced Ethernet (CEE) Map Enhanced Transmission Selection (ETS) feature.
<b>Recommended Action</b>	Delete and reapply the CEE Map ETS policy using the <b>cee-map default</b> command. If the problem persists, restart or power cycle the switch.

## SSMD-1206

<b>Message</b>	CEE failed programming CoS to PGID policy for CEE Map <CEE Map name>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in programming the dataplane ASIC for enforcing the CEE Map Class of Service (CoS) to Priority Group ID (PGID) mapping feature.
<b>Recommended Action</b>	Delete and reapply the CEE Map CoS to PGID policy using the <b>cee-map default</b> command. If the problem persists, restart or power cycle the switch.



## SSMD-1207

<b>Message</b>	QoS failed programming interface 0x<Interface ID> Default CoS.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in programming the dataplane ASIC for enforcing the interface Default CoS feature.
<b>Recommended Action</b>	Delete and reapply the QoS interface Default CoS policy using the <b>qos cos</b> command. If the problem persists, restart or power cycle the switch.

## SSMD-1208

<b>Message</b>	QoS failed programming interface 0x<Interface ID> Trust.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in programming the dataplane ASIC for enforcing the interface Trust feature.
<b>Recommended Action</b>	Delete and reapply the QoS interface Trust policy using the <b>qos trust cos</b> command. If the problem persists, restart or power cycle the switch.

## SSMD-1209

<b>Message</b>	QoS failed programming interface 0x<Interface ID> CoS Mutation map.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in programming the dataplane ASIC for enforcing the interface CoS Mutation mapping feature.
<b>Recommended Action</b>	Delete and reapply the QoS interface CoS Mutation policy using the <b>qos cos-mutation</b> command. If the problem persists, restart or power cycle the switch.

**SSMD-1210**

<b>Message</b>	QoS failed programming interface 0x<Interface ID> CoS to Traffic Class map.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in programming the dataplane ASIC for enforcing the CoS to Traffic Class mapping feature.
<b>Recommended Action</b>	Delete and reapply the QoS interface CoS to Traffic Class policy using the <b>qos cos-traffic-class</b> command. If the problem persists, restart or power cycle the switch.

**SSMD-1211**

<b>Message</b>	QoS failed programming ASIC <ASIC slot number>/<ASIC chip number> Scheduler Control.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in programming the dataplane ASIC for enforcing the packet Scheduler Control feature.
<b>Recommended Action</b>	Delete and reapply the QoS packet Scheduler Control policy using the <b>qos queue scheduler</b> command. If the problem persists, restart or power cycle the switch.

**SSMD-1212**

<b>Message</b>	QoS failed programming ASIC <ASIC slot number>/<ASIC chip number> Multicast Scheduler Control.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in programming the dataplane ASIC for enforcing the multicast packet Scheduler Control feature.
<b>Recommended Action</b>	Delete and reapply the QoS multicast packet Scheduler Control policy using the <b>qos queue multicast scheduler</b> command. If the problem persists, restart or power cycle the switch.

## SSMD-1213

<b>Message</b>	QoS failed programming interface 0x<Interface ID> CoS Tail Drop Threshold.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in programming the dataplane ASIC for enforcing the interface CoS Tail Drop Threshold feature.
<b>Recommended Action</b>	Delete and reapply the QoS CoS Tail Drop Threshold policy using the <b>qos rcv-queue</b> command. If the problem persists, restart or power cycle the switch.

## SSMD-1214

<b>Message</b>	QoS failed programming interface 0x<Interface ID> CoS Tail Drop Threshold.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in programming the dataplane ASIC for enforcing the interface CoS Tail Drop Threshold feature.
<b>Recommended Action</b>	Delete and reapply the QoS CoS Tail Drop Threshold policy using the <b>qos rcv-queue</b> command. If the problem persists, restart or power cycle the switch.

## SSMD-1215

<b>Message</b>	QoS failed programming interface 0x<Interface ID> CoS Tail Drop Threshold.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in programming the dataplane ASIC for enforcing the interface CoS Tail Drop Threshold feature.
<b>Recommended Action</b>	Delete and reapply the QoS CoS Tail Drop Threshold policy using the <b>qos rcv-queue</b> command. If the problem persists, restart or power cycle the switch.

## SSMD-1216

<b>Message</b>	QoS failed programming interface 0x<Interface ID> Pause.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM encountered an unexpected error in programming the dataplane ASIC for enforcing the interface Pause feature.
<b>Recommended Action</b>	Delete and reapply the QoS Pause policy. If the message persists, restart or power cycle the switch.

## SSMD-1217

<b>Message</b>	QoS CEE could not comply with FCoE scheduler policy for CEE Map <CEE Map name>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that DCE SSM was unable to translate the CEE Map and Fibre Channel over Ethernet (FCoE) configuration into an ETS scheduler policy implementable by the dataplane ASIC.
<b>Recommended Action</b>	Redefine CEE Map and FCoE into a configuration that translates into an ETS scheduler policy requiring eight or fewer traffic classes.

## SSMD-1300

<b>Message</b>	CEE Map <ceemap> is created with precedence <precedence>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified CEE Map has been created.
<b>Recommended Action</b>	No action is required.

## SSMD-1301

<b>Message</b>	CEE Map <ceemap> is deleted.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified CEE Map has been deleted.
<b>Recommended Action</b>	No action is required.

## SSMD-1302

<b>Message</b>	CEE Map <ceemap> priority table <pg_ids> are <action>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the priority groups have been added to or removed from the specified CEE Map.
<b>Recommended Action</b>	No action is required.

## SSMD-1303

<b>Message</b>	CEE Map <ceemap> priority group <pg_id> with weight <PGID_weight> is created with PFC <pfc>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified priority group has been created.
<b>Recommended Action</b>	No action is required.

## SSMD-1304

<b>Message</b>	CEEM Map <ceemap> priority group <pg_id> is deleted.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified priority group has been deleted.

## 5 SSMD-1305

**Recommended Action** No action is required.

### SSMD-1305

**Message** CEE Map <ceemap> priority group <pg\_id> weight is changed from <PGID\_weight\_new> to <PGID\_weight\_old>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified priority group weight has been changed.

**Recommended Action** No action is required.

### SSMD-1306

**Message** CEE Map <ceemap> priority group <pg\_id> is PFC <pfc\_status>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified priority group PFC status has been changed.

**Recommended Action** No action is required.

### SSMD-1307

**Message** <acl\_type> access list <acl\_name> is created.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified access list has been created.

**Recommended Action** No action is required.

## SSMD-1308

<b>Message</b>	<code>&lt;acl_type&gt; access list &lt;acl_name&gt; is deleted.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified access list has been deleted.
<b>Recommended Action</b>	No action is required.

## SSMD-1309

<b>Message</b>	<code>&lt;acl_type&gt; access list &lt;acl_name&gt; rule sequence number &lt;rule_sq_no&gt; is &lt;action&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified access list rules were added to or removed from an existing policy.
<b>Recommended Action</b>	No action is required.

## SSMD-1310

<b>Message</b>	<code>ACL &lt;acl_name&gt; configured on interface &lt;InterfaceName&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified access list has been configured on the interface.
<b>Recommended Action</b>	No action is required.

## SSMD-1311

<b>Message</b>	<code>ACL &lt;acl_name&gt; is removed from interface &lt;InterfaceName&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified access list has been removed from the interface.

## 5 SSMD-1312

**Recommended Action** No action is required.

### SSMD-1312

**Message** <map\_type> <map\_name> assigned to interface <InterfaceName>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified user profile map has been assigned to the interface.

**Recommended Action** No action is required.

### SSMD-1313

**Message** <map\_type> <map\_name> removed from interface <InterfaceName>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified user profile map has been removed from the interface.

**Recommended Action** No action is required.

### SSMD-1314

**Message** CEE Map <ceemap> precedence changed from <precedence\_old> to <precedence\_new>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that precedence of the specified CEE Map has been changed.

**Recommended Action** No action is required.



## SSMD-1315

<b>Message</b>	CEE Map <ceemap> is incompatible with current firmware. Resetting it to default.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified CEE Map is incompatible with the current firmware and therefore it is reset to the default.
<b>Recommended Action</b>	No action is required.

## SSMD-1316

<b>Message</b>	CEE Map <ceemap> is reset to default configuration.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified CEE Map is reset to the default using the <b>no cee-map name</b> command.
<b>Recommended Action</b>	No action is required.

## SSMD-1317

<b>Message</b>	ACL <acl_name> is being configured on interface <InterfaceName>. This operation could take a long time.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified access list is being configured on the interface.
<b>Recommended Action</b>	No action is required.

## SSMD-1318

**Message** ACL <acl\_name> is being removed from interface <InterfaceName>. This operation could take a long time.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified access list is being removed from the interface.

**Recommended Action** No action is required.

## SULB Messages

### SULB-1001

<b>Message</b>	<code>Firmwaredownload</code> command has started.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FIRMWARE
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the <b>firmwareDownload</b> command has been entered. This process should take approximately 17 minutes. The process is set to time out after 30 minutes.
<b>Recommended Action</b>	Do not fail over or power down the system during firmware upgrade. Allow the <b>firmwareDownload</b> command to continue without disruption. No action is required. Run the <b>firmwareDownloadStatus</b> command for more information.

### SULB-1002

<b>Message</b>	<code>Firmwaredownload</code> command has completed successfully.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FIRMWARE
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>firmwareDownload</b> command has completed successfully and switch firmware has been updated.
<b>Recommended Action</b>	No action is required. The <b>firmwareDownload</b> command has completed as expected. Run the <b>firmwareDownloadStatus</b> command for more information. Run the <b>firmwareShow</b> command to verify the firmware versions.

### SULB-1003

<b>Message</b>	<code>Firmwarecommit</code> has started.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FIRMWARE
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>firmwareCommit</b> command has been entered.

## 5 SULB-1004

**Recommended Action** No action is required. Run the **firmwareDownloadStatus** command for more information.

### SULB-1004

**Message** `Firmwarecommit has completed.`

**Message Type** AUDIT | LOG

**Class** FIRMWARE

**Severity** INFO

**Probable Cause** Indicates that the **firmwareCommit** command has completed successfully.

**Recommended Action** No action is required. Run the **firmwareDownloadStatus** command for more information.

### SULB-1005

**Message** `Current Active CP is preparing to failover.`

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the active control processor (CP) is about to reboot. The standby CP is taking over as the active CP.

**Recommended Action** No action is required. The **firmwareDownload** command is progressing as expected. Run the **firmwareDownloadStatus** command for more information.

### SULB-1006

**Message** `Forced failover succeeded. New Active CP is running new firmware.`

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the previous standby control processor (CP) has now become the active CP and is running the new firmware version.

**Recommended Action** No action is required. The **firmwareDownload** command is progressing as expected. Run the **firmwareDownloadStatus** command for more information.

## SULB-1007

<b>Message</b>	Standby CP reboots.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the standby control processor (CP) is rebooting with new firmware.
<b>Recommended Action</b>	No action is required. The <b>firmwareDownload</b> command is progressing as expected. Run the <b>firmwareDownloadStatus</b> command for more information.

## SULB-1008

<b>Message</b>	Standby CP booted successfully with new firmware.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the standby control processor (CP) has rebooted successfully.
<b>Recommended Action</b>	No action is required. The <b>firmwareDownload</b> command is progressing as expected. Run the <b>firmwareDownloadStatus</b> command for more information.

## SULB-1009

<b>Message</b>	Firmwaredownload command failed. Status: 0x<status code>, error: 0x<error code>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FIRMWARE
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>firmwareDownload</b> command failed. The additional <i>status code</i> and <i>error code</i> values provide debugging information.

The following table lists **firmwareDownload** status messages and status codes. Some of them will not be displayed in this RASLog message and are listed for completeness.

**TABLE 7** Status messages and status codes

Status message	Status code
"Firmware download sanity check failed."	0x30
"Sanity check failed because system is non-redundant."	0x31
"Sanity check failed because firmware download is already in progress."	0x32
"Sanity check failed because Fabric OS is disabled on active CP."	0x33

**TABLE 7** Status messages and status codes (Continued)

Status message	Status code
"Sanity check failed because HAMD is disabled on active CP."	0x34
"Sanity check failed because firmware download process is already in progress."	0x35
"Sanity check failed because Fabric OS is disabled on standby CP."	0x36
"Sanity check failed because HAMD is disabled on standby CP."	0x37
"Firmware download failed on standby CP."	0x40
"Firmware download failed on standby CP."	0x41
"Firmware download failed on standby CP."	0x42
"Firmware commit failed on standby CP."	0x43
"Firmware download failed."	0x44
"Firmware download failed due to IPC error."	0x50
"Unable to check the firmware version on standby CP due to IPC error."	0x51
"Firmware download failed due to IPC error."	0x52
"Firmware download failed due to IPC error."	0x53
"Standby CP failed to reboot due to IPC error."	0x54
"Firmware commit operation failed due to IPC error."	0x55
"Unable to check the firmware version on standby CP due to IPC error."	0x56
"Unable to restore the original firmware due to standby CP timeout."	0x57
"Standby CP failed to reboot and was not responding."	0x58
"Unable to check the firmware version on standby CP due to IPC error."	0x59
"Sanity check failed because the firmware download operation is already in progress."	0x60
"Sanity check failed because the firmware download operation is already in progress."	0x61
NOT USED	0x62
"System error."	0x63
"Active CP forced failover succeeded. Now the standby CP becomes active CP."	0x64
"Standby CP booted up."	0x65
"Active and standby CP failed to gain HA synchronization within 10 minutes."	0x66
"Standby CP rebooted successfully."	0x67
"Standby CP failed to reboot."	0x68
"Firmware commit has started to restore the secondary partition."	0x69
"Local CP is restoring its secondary partition."	0x6a
"Unable to restore the secondary partition. Run the <b>firmwareDownloadStatus</b> and <b>firmwareShow</b> commands to see firmware status."	0x6b
"Firmware download has started on standby CP. It might take up to 10 minutes."	0x6c
"Firmware download has completed successfully on standby CP."	0x6d
"Standby CP reboots."	0x6e

**TABLE 7** Status messages and status codes (Continued)

Status message	Status code
"Standby CP failed to boot up."	0x6f
"Standby CP booted up with new firmware."	0x70
"Standby CP failed to boot up with new firmware."	0x71
"Firmware download has completed successfully on standby CP."	0x72
"Firmware download has started on standby CP. It might take up to 10 minutes. "	0x73
"Firmware download has completed successfully on standby CP."	0x74
"Standby CP reboots."	0x75
"Standby CP failed to reboot."	0x76
"Firmware commit has started on standby CP."	0x77
"Firmware commit has completed successfully on standby CP."	0x78
"Standby CP booted up with new firmware."	0x79
"Standby CP failed to boot up with new firmware."	0x7a
"Firmware commit has started on both active and standby CPs."	0x7b
"Firmware commit has completed successfully on both active and standby CPs."	0x7c
"Firmware commit failed on active CP."	0x7d
"The original firmware has been restored successfully on standby CP."	0x7e
"Unable to restore the original firmware on standby CP."	0x7f
"Standby CP reboots."	0x80
"Standby CP failed to reboot."	0x81
"Standby CP booted up with new firmware."	0x82
"Standby CP failed to boot up with new firmware."	0x83
"There was an unexpected reboot during the firmware download operation. The command is aborted."	0x84
"Standby CP was not responding. The command is aborted."	0x85
"Firmware commit has started on both active and standby CPs. Run the <b>firmwareDownloadStatus</b> and <b>firmwareShow</b> commands to see the firmware status."	0x86
"Firmware commit has started on the local CP. Run the <b>firmwareDownloadStatus</b> and <b>firmwareShow</b> commands to see the firmware status."	0x87
"Firmware commit has started on the remote CP. Run the <b>firmwareDownloadStatus</b> and <b>firmwareShow</b> commands to see the firmware status."	0x88
"Run the <b>firmwareDownloadStatus</b> and <b>firmwareShow</b> commands to see the firmware status."	0x89
"The <b>firmwareDownload</b> command has completed successfully."	0x8a
"The original firmware has been restored successfully."	0x8b
"Remote CP is restoring its secondary partition."	0x8c
"Local CP is restoring its secondary partition."	0x8d

**TABLE 7** Status messages and status codes (Continued)

Status message	Status code
"Remote CP is restoring its secondary partition."	0x8e
"Firmware download has started."	0x8f
"Firmware commit has started."	0x90
"Firmware download has completed successfully."	0x91
"Firmware commit has completed successfully."	0x92
"Firmware commit has started to restore the secondary partition."	0x93
"Firmware commit failed."	0x94
"The secondary partition has been restored successfully."	0x95
"Firmware is being downloaded to the blade. This step may take up to 10 minutes."	0xa0
"Firmware download timed out."	0xa1
"Reboot occurred during firmware download. Firmware commit will be started to recover the blade."	0xa2
"Blade rebooted during firmware commit. The operation will be restarted."	0xa3
"Firmware has been downloaded successfully. Blade is rebooting with the new firmware."	0xa4
"Blade has rebooted successfully."	0xa5
"New firmware failed to boot up. Run the <b>firmwareDownload</b> command again."	0xa6
"Firmware commit has started on the blade. This may take up to 10 minutes."	0xa7
"The <b>firmwareRestore</b> command is entered. System will reboot and a firmware commit operation will start upon bootup."	0xa8
"Switch is relocating the AP image."	0xa9
"The AP image is relocated successfully."	0xaa
"Switch reboots during relocating the AP image. The operation will be restarted."	0xab
"Blade failed to reboot with the original image. The <b>firmwareRestore</b> command failed."	0xac

The following table lists additional **firmwareDownload** error messages and error codes. The error code provide more details on the reason for firmware download failure.

**TABLE 8** Error messages and error codes

Error message	Error code
"Image is up-to-date. No need to download the same version of firmware."	0xF
"Upgrade is inconsistent."	0x10
"OSRootPartition is inconsistent. For example: swap OSRootPartitions and reboot."	0x11
"Unable to access the required package list file. Check whether the switch is supported by the requested firmware. Also check the <b>firmwareDownload</b> help page for other possible failure reasons."	0x12
"The RPM package database is inconsistent. Contact your switch service provider for recovery."	0x13



**TABLE 8** Error messages and error codes (Continued)

Error message	Error code
"Out of memory."	0x14
"Failed to download RPM package."	0x15
"Unable to create firmware version file."	0x16
"Unexpected system error."	0x17
"Error in getting lock device for firmware download."	0x18
"Error in releasing lock device for firmware download."	0x19
"Firmware commit failed."	0x1a
"Firmware directory structure is not compatible. Check whether the firmware is supported on this platform."	0x1b
"Failed to load the Linux kernel image."	0x1c
"OSLoader is inconsistent."	0x1d
"New image has not been committed. Run the <b>firmwareCommit</b> or <b>firmwareRestore</b> command and then run the <b>firmwareDownload</b> command."	0x1e
"Firmware restore failed."	0x1f
"Both images are mounted to the same device."	0x20
"Unable to uninstall old packages."	0x21
"Firmware download is already in progress."	0x22
"Firmware download timed out."	0x23
"Out of disk space."	0x24
"Primary filesystem is inconsistent. Run the <b>firmwareRestore</b> command to restore the original firmware, or contact your switch service provider for recovery."	0x25
"The post-install script failed."	0x26
"Unexpected reboot."	0x27
"Primary kernel partition is inconsistent. Contact your switch service provider for recovery."	0x28
"The pre-install script failed."	0x29
"The platform option is not supported."	0x2a
"Failed to install RPM package."	0x2b
"Cannot downgrade directly to this version. Downgrade to an intermediate version and then download the desired version."	0x2c
"Invalid RPM package. Reload firmware packages on the file server."	0x2e
"Cannot downgrade due to presence of blade type 17. Remove or power off these blades before proceeding."	0x2f
"Cannot downgrade due to presence of blade type 24. Remove or power off these blades before "	0x30
"Cannot downgrade due to presence of long-distance ports in LS mode. Remove these settings before proceeding."	0x31
"Network is not reachable. Verify the IP address of the server is correct."	0x32

The following descriptions explain the causes of some common error messages:

- 0x15 - "Failed to download RPM package." If this error occurs immediately after firmware download is started, the firmware on the switch may be two releases older than the requested firmware. The firmware download operation supports firmware upgrades within two feature releases (a feature release is indicated by a major number and a minor number; for example, X.Y). In this case, you will need to upgrade to an intermediate version before downloading the desired version. If this error occurs in the middle of a firmware download, the firmware in the file server may be corrupted or there may be a temporary network issue. In this case, retry the **firmwareDownload** command. If the problem persists, contact your system administrator.
- 0x18 - "Error in getting lock device for firmware download". This error can be due to another firmware download is already in progress. Run the **firmwareDownloadStatus** command to verify that this is the case. Wait for the current session to finish before proceeding.
- 0x23 - "Firmware download timed out." This error may occur because the **firmwareDownloadStatus** command has not completed within the predefined timeout period. It is most often caused by network issues. If the problem persists, contact your system administrator.
- 0x24 - "Out of disk space." This error may occur because some core dump files have not been removed from the filesystem and are using up disk space. Remove these core dump files by using the **supportSave** command before proceeding.
- 0x29 - "The pre-install script failed." This error may be caused by an unsupported blade type. Remove or power off the unsupported blades before proceeding.
- 0x2e - "Invalid RPM package." This error may be caused by an inconsistent firmware image loaded on the file server. It may also be caused by temporary networking issues. Reload the firmware packages on the file server and then retry the **firmwareDownload** command. If the problem persists, contact your system administrator.

The following table lists the **firmwareDownload** state names and code values. They indicate where in the **firmwareDownload** process the error occurred.

**TABLE 9** Upgrade state and code value

Upgrade state	Code
SUS_PEER_CHECK_SANITY	0x21
SUS_PEER_FWDL_BEGIN	0x22
SUS_SBY_FWDL_BEGIN	0x23
SUS_PEER_REBOOT	0x24
SUS_SBY_REBOOT	0x25
SUS_SBY_FABOS_OK	0x26
SUS_PEER_FS_CHECK	0x27
SUS_SELF_FAILOVER	0x28
SUS_SBY_FWDL1_BEGIN	0x29
SUS_SELF_FWDL_BEGIN	0x2a
SUS_SELF_COMMIT	0x2b
SUS_SBY_FWC_BEGIN	0x2c
SUS_SBY_COMMIT	0x2d
SUS_SBY_FS_CHECK	0x2e

**TABLE 9** Upgrade state and code value (Continued)

Upgrade state	Code
SUS_ACT_FWC_BEGIN	0x2f
SUS_PEER_RESTORE_BEGIN	0x30
SUS_SBY_RESTORE_BEGIN	0x31
SUS_PEER_FWC_BEGIN	0x32
SUS_PEER_FS_CHECK1	0x33
SUS_FINISH	0x34
SUS_COMMIT	0x35

**Recommended Action**

Run the **firmwareDownloadStatus** command for more information.

In a modular switch, when the **firmwareDownload** command fails, the command will synchronize the firmware on the two partitions of each CP by starting a firmware commit operation. Wait until this operation completes (about 10 minutes) before attempting another firmware download.

In a modular switch, when the **firmwareDownload** command fails, the two CPs may end up with different versions of firmware and they may not gain high availability (HA) sync. In this case, run the **firmwareDownload -s** command to upgrade the firmware on the standby CP to the same version as the active CP. Then retry the **firmwareDownload** command to download the desired version of firmware onto the CPs.

Refer to the *Fabric OS Troubleshooting Guide* for troubleshooting information.

**SULB-1010**

**Message** `Firmwarecommit failed (status=0x<error code>).`

**Message Type** AUDIT | LOG

**Class** FIRMWARE

**Severity** INFO

**Probable Cause** Indicates that the **firmwareCommit** command failed. The error code provides debugging information.

**Recommended Action** If the failure is caused by an inconsistent filesystem, contact your switch service provider.

**SULB-1011**

**Message** `Firmwaredownload command failed. <error string>.`

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the **firmwareDownload** command failed. The *error string* value indicates the reason for failure.

## 5 SULB-1017

**Recommended Action** Run the **firmwareDownloadStatus** command for more information.  
Refer to the *Fabric OS Troubleshooting Guide* for troubleshooting information.

### SULB-1017

**Message** Firmwaredownload failed in slot <Slot number>.

**Message Type** AUDIT | LOG

**Class** FIRMWARE

**Severity** ERROR

**Probable Cause** Indicates that the **firmwareDownload** command failed on the specified blade. The error may be caused by the inconsistent application processor (AP) blade firmware stored on the active CP. It may also be caused by an internal Ethernet issue or by a persistent storage hardware failure.

**Recommended Action** Run the **slotShow** command. If the blade is in the FAULTY state, run the **slotPowerOff** and **slotPowerOn** commands to trigger another firmware download. If the blade is stuck in the LOADING state, remove and re-insert the blade to trigger another firmware download. If the problem persists, contact your switch service provider.

### SULB-1018

**Message** Firmwaredownload timed out in slot <Slot number>.

**Message Type** AUDIT | LOG

**Class** FIRMWARE

**Severity** ERROR

**Probable Cause** Indicates that there may be error caused by the blade initialization issue after the new firmware is downloaded and the blade is rebooted. The error may also be caused by an internal Ethernet issue or by a persistent storage hardware failure.

**Recommended Action** Run the **slotShow** command. If the blade is in the FAULTY state, run the **slotPowerOff** and **slotPowerOn** commands to trigger another firmware download to the blade. If the blade is stuck in the LOADING state, remove and re-insert the blade to trigger another firmware download. If the problem persists, contact your switch service provider.

## SULB-1020

<b>Message</b>	New firmware failed to boot in slot <Slot number>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FIRMWARE
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the BP blade is still running the old image even though it should reboot with the new image. This error may indicate that the new image has not been loaded correctly to the specified blade.
<b>Recommended Action</b>	Run the <b>slotShow</b> command. If the blade is in a FAULTY state, run the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands to trigger another firmware download to the blade. If the blade is stuck in LOADING state, remove and re-insert the blade to trigger another firmware download. If the problem persists, contact your switch service provider.

## SULB-1021

<b>Message</b>	Firmware is being downloaded to the blade in slot <Slot number>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FIRMWARE
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the firmware is being loaded to the specified blade.
<b>Recommended Action</b>	Run the <b>firmwareDownloadStatus</b> command to monitor the firmware download progress. After it finishes, run the <b>firmwareShow</b> command to verify the firmware versions.

## SULB-1022

<b>Message</b>	The blade in slot <Slot number> has rebooted successfully with new firmware.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the blade in the specified slot has rebooted with new firmware. This is a normal step in the firmware download process.
<b>Recommended Action</b>	Run the <b>firmwareDownloadStatus</b> command to monitor the firmware download progress.

## SULB-1023

<b>Message</b>	The blade in slot <Slot number> has rebooted during firmwaredownload.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FIRMWARE
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that there may be an error caused by an unexpected disruption of the <b>firmwareDownload</b> command; for example, powering off and on of the indicated BP blade in the middle of a firmware download. The error may also be caused by persistent storage hardware failure or by a software error.
<b>Recommended Action</b>	The <b>firmwareCommit</b> command will be started automatically after the blade boots up to repair the secondary partition. If at the end of the firmware commit, the blade firmware version is still inconsistent with the active CP firmware, firmware download will be restarted automatically on the blade. Run the <b>firmwareDownloadStatus</b> command to monitor the progress. If the problem persists, contact your switch service provider.

## SULB-1024

<b>Message</b>	Firmware commit has completed on the blade in slot <Slot number>.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FIRMWARE
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the <b>firmwareCommit</b> command has completed on the specified blade.
<b>Recommended Action</b>	Run the <b>firmwareShow</b> command to verify the firmware versions. If the blade firmware is the same as the active CP firmware, the <b>firmwareDownload</b> command has completed successfully on the blade. However, if the firmware commit operation has been started to repair the secondary partition, at the end of the firmware commit, the blade firmware version may still be inconsistent with the active CP firmware. In this case, firmware download will automatically be restarted on the blade. Run the <b>firmwareDownloadStatus</b> command to monitor the progress.

## SULB-1025

<b>Message</b>	The blade in slot <Slot number> will reboot with the new firmware.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that new firmware has been downloaded to the specified application processor (AP) blade and the AP blade will reboot to activate it.

**Recommended Action** Wait for the blade to reboot.

## SULB-1026

**Message** `Firmware commit operation started on the blade in slot <Slot number>.`

**Message Type** AUDIT | LOG

**Class** FIRMWARE

**Severity** WARNING

**Probable Cause** Indicates that the **firmwareCommit** command has started on the specified blade. The operation may be a normal part of firmware download, or it may have started to repair the secondary partition of the blade if the secondary partition is corrupted.

**Recommended Action** Wait for the firmware commit operation to complete.

## SULB-1030

**Message** `The switch has rebooted during relocating the internal firmware image.`

**Message Type** AUDIT | LOG

**Class** FIRMWARE

**Severity** WARNING

**Probable Cause** Indicates that there may be an error caused by an unexpected disruption of the **firmwareDownload** command; for example, by powering the switch off and on in the middle of a firmware download. The error may also be caused by persistent storage hardware failure or by a software error.

**Recommended Action** The **firmwareDownload** command will continue after the switch has rebooted. Run the **firmwareDownloadStatus** command to monitor progress. If the problem persists, contact your switch service provider.

## SULB-1031

**Message** `The switch is relocating an internal firmware image.`

**Message Type** AUDIT | LOG

**Class** FIRMWARE

**Severity** WARNING

**Probable Cause** Indicates that the switch has rebooted with the new firmware and is relocating the application processor (AP) firmware.

## 5 SULB-1032

**Recommended Action** Wait for the operation to complete.

### SULB-1032

**Message** Relocating an internal firmware image on the CP.

**Message Type** AUDIT | LOG

**Class** FIRMWARE

**Severity** WARNING

**Probable Cause** Indicates that the switch has started firmware download to the co-CPU.

**Recommended Action** Wait for the operation to complete.

### SULB-1033

**Message** Switch has completed relocating the internal firmware image.

**Message Type** AUDIT | LOG

**Class** FIRMWARE

**Severity** WARNING

**Probable Cause** Indicates that the firmware download process has completed normally on the switch.

**Recommended Action** Run the **firmwareShow** command to verify the firmware versions. Run the **switchShow** command to make sure the switch is enabled.

### SULB-1034

**Message** Relocation of internal image timed out.

**Message Type** AUDIT | LOG

**Class** FIRMWARE

**Severity** ERROR

**Probable Cause** Indicates that there may be an error caused by the switch initialization issue after the internal image is relocated. It may also be caused by an internal Ethernet issue or by a persistent storage hardware failure.

**Recommended Action** Reboot the switch. This will cause the internal image to be relocated again. Use the **firmwareDownloadStatus** command to monitor the progress. If the problem persists, contact your switch service provider.



## SULB-1035

<b>Message</b>	An error has occurred during relocation of the internal image.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FIRMWARE
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that an error has occurred during the relocation of the internal image. The error may be caused by inconsistent internal firmware image. It may also be caused by an internal Ethernet issue or a persistent storage hardware failure.
<b>Recommended Action</b>	Reset the switch. This will cause the internal image to be relocated again. If the problem persists, contact your switch service provider.

## SULB-1036

<b>Message</b>	<The Version being logged><Version String>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the version running in the system. This is generally logged before download and after download of the firmware to store version information.
<b>Recommended Action</b>	No action is required.

## SULB-1037

<b>Message</b>	HCL failed. Reboot the switch manually using the reboot command. However, it will disrupt the FC traffic.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FIRMWARE
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that Hot Code Load (HCL) has failed. Many reasons, such as a domain not confirmed, can cause this failure.
<b>Recommended Action</b>	Run the <b>reboot</b> command to reboot the switch manually.

## SULB-1038

<b>Message</b>	Co-CPU has not booted up properly. Skip the <code>firmwaredownload</code> command on the co-CPU.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FIRMWARE
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the main CPU cannot access the co-CPU to update the firmware on the co-CPU or run any other firmware download command on the co-CPU. If the <b>firmwareDownload</b> command is in progress, it will continue without updating the co-CPU firmware.
<b>Recommended Action</b>	After the firmware download completes, reboot the CP manually to bring up the co-CPU and run the <b>firmwareDownload</b> command again. If the problem persists, your switch service provider.

## SULB-1039

<b>Message</b>	CP has completed relocating the internal firmware image.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FIRMWARE
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the firmware download process has completed normally on the control processor (CP).
<b>Recommended Action</b>	Run the <b>firmwareShow</b> command to verify the firmware versions.

## SULB-1040

<b>Message</b>	An error has occurred during relocation of the internal image on the CP.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FIRMWARE
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an error has occurred during the relocation of the internal image. The error may be caused by an inconsistent internal firmware image. It may also be caused by an internal Ethernet failure.
<b>Recommended Action</b>	Run the <b>firmwareShow</b> command to verify the firmware versions. Run the <b>firmwareDownload</b> command again if the firmware is not updated.  This will cause the internal image to be relocated again. If the problem persists, contact your switch service provider.

## SULB-1041

<b>Message</b>	<code>Firmware has been activated successfully on standby CP.</code>
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FIRMWARE
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>firmwareActivate</b> command has completed successfully on the standby control processor (CP).
<b>Recommended Action</b>	No action is required. The <b>firmwareActivate</b> command has completed on the standby CP as expected. Run the <b>firmwareShow</b> command to verify the firmware versions.

## SULB-1042

<b>Message</b>	<code>Firmwareactivate command has completed successfully.</code>
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	FIRMWARE
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>firmwareActivate</b> command has completed successfully and the switch firmware has been updated.
<b>Recommended Action</b>	No action is required. The <b>firmwareActivate</b> command has completed as expected. Run the <b>firmwareShow</b> command to verify the firmware versions.

## SULB-1043

<b>Message</b>	<code>Firmwareactivate command failed. &lt;error string&gt;.</code>
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>firmwareActivate</b> command failed. The <i>error string</i> value indicates the reason for failure.
<b>Recommended Action</b>	Run the <b>firmwareShow</b> command to verify the firmware versions.

## SULB-1044

<b>Message</b>	Firmwaredownload to secondary partition has completed successfully.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>firmwareDownload</b> command to the secondary partition has completed successfully and the switch will come up with the updated firmware on reboot.
<b>Recommended Action</b>	No action is required. The switch will auto-reboot with the downloaded firmware.

## SWCH Messages

### SWCH-1001

**Message** Switch is not in ready state - Switch enable failed, switch status= 0x<switch status>, c\_flags = 0x<switch control flags>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the switch is enabled before it is ready.

**Recommended Action** If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

### SWCH-1002

**Message** Security violation: Unauthorized device <wwn name of device> tries to flogin to port <port number>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified device is not present in the authorized profile list.

**Recommended Action** Verify that the device is authorized to log in to the switch. If the device is authorized, execute the **secPolicyDump** command to verify whether the World Wide Name (WWN) of the specified device is listed. If it is not listed, execute the **secPolicyAdd** command to add this device to an existing policy.

### SWCH-1003

**Message** Slot ENABLED but Not Ready during recovery, disabling slot = <slot number>(<return value>).

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the slot state has been detected as inconsistent during failover or recovery.

**Recommended Action** For a bladed switch, execute the **slotPowerOff** and **slotPowerOn** commands to power cycle the blade.  
For a non-bladed switch, reboot or power cycle the switch.

**SWCH-1004**

<b>Message</b>	Blade attach failed during recovery, disabling slot = <slot number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified blade has failed during failover or recovery.
<b>Recommended Action</b>	For a bladed switch, execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands to power cycle the blade. For a non-bladed switch, reboot or power cycle the switch.

**SWCH-1005**

<b>Message</b>	Diag attach failed during recovery, disabling slot = <slot number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the diagnostic blade attach operation has failed during failover or recovery.
<b>Recommended Action</b>	For a bladed switch, execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands to power cycle the blade. For a non-bladed switch, reboot or power cycle the switch.

**SWCH-1006**

<b>Message</b>	HA state out of sync: Standby CP (ver = <standby SWC version>) does not support NPIV functionality. (active ver = <active SWC version>, NPIV devices = <'1' if NPIV devices exist; Otherwise '0'>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the standby control processor (CP) does not support N_Port ID Virtualization (NPIV) functionality, but the switch has some NPIV devices logged in to the fabric.
<b>Recommended Action</b>	Load a firmware version on a standby CP that supports NPIV functionality using the <b>firmwareDownload</b> command.

**SWCH-1007**

<b>Message</b>	Switch port <port number> disabled due to \"<disable reason>\".
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch port is disabled due to the reason displayed in the message.
<b>Recommended Action</b>	Based on the disable reason displayed, take appropriate action to restore the port. If the disable reason is "Insufficient frame buffers", reduce the distance or speed settings for the port to reduce the buffer requirement of the link. Alternatively, one or more ports in the port group must be disabled to make more buffers available for the link. Refer to the <i>Fabric OS Administrator's Guide</i> for more information.

**SWCH-1008**

<b>Message</b>	<area string> are port swapped on ports that do not support port swap. Slot <slot number> will be faulted.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the blade enabled with the port configuration that does not support port swap.
<b>Recommended Action</b>	Replace the blade with ports that support port swap. Then swap ports back to the port's default area. Refer to the <i>Fabric OS Administrator's Guide</i> for more information on port swapping.

**SWCH-1009**

<b>Message</b>	Shared area having Trunk Area (TA) enabled on slot <slot number>. Shared areas that have TA enabled will be persistently disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the blade is enabled with a port configuration that had Trunk Area previously enabled on the shared area port.
<b>Recommended Action</b>	Disable Trunk Area on ports that had Trunk Area enabled previously. Refer to the <i>Fabric OS Administrator's Guide</i> for more information.

## SWCH-1010

<b>Message</b>	Trunk Area (TA) enabled on slot <slot number> with switch not in PID format 1. TA enabled ports will be persistently disabled.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the blade is enabled with the port configuration that had Trunk Area enabled previously.
<b>Recommended Action</b>	Disable Trunk Area on ports that had Trunk Area enabled previously. Refer to the <i>Fabric OS Administrator's Guide</i> for more information.

## SWCH-1011

<b>Message</b>	HA out of sync: Stby CP (ver=<standby SWC version>) doesn't support Trunk Area functionality. (active ver=<active SWC version>, TA enabled on sw=<'1' if Trunk Area ports exist; Otherwise '0'>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the standby control processor (CP) does not support Trunk Area functionality, but the switch has some ports with Trunk Area enabled.
<b>Recommended Action</b>	Load a firmware version on standby CP that supports Trunk Area functionality by using the <b>firmwareDownload</b> command.

## SWCH-1012

<b>Message</b>	Trunk Area (<trunk area>) has been enabled for one or more ports.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a Trunk Area has been enabled for one or more ports and the configuration file has been updated.
<b>Recommended Action</b>	No action is required.



## SWCH-1013

<b>Message</b>	Trunk Area has been disabled for one or more ports.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a Trunk Area assignment has been disabled for one or more ports and the configuration file has been updated.
<b>Recommended Action</b>	No action is required.

## SWCH-1014

<b>Message</b>	All Trunk Areas have been disabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that all Trunk Areas have been disabled and the configuration file has been updated.
<b>Recommended Action</b>	No action is required.

## SWCH-1015

<b>Message</b>	<Function name> <Description of problem>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an internal problem has been detected by the software. This is usually an internal Fabric OS problem or due to file corruption.
<b>Recommended Action</b>	Reboot or power cycle the switch. If the message persists, execute the <b>firmwareDownload</b> command to update the firmware.

**SWCH-1016**

<b>Message</b>	Device <wwn name of device> FDISC to port <port number>. Static persistent PID set and area requested not assigned to the device. Reject FDISC.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the static persistent port ID (PID) is set and the area requested is not assigned to the device.
<b>Recommended Action</b>	This is an N_Port ID virtualization (NPIV) device and the static persistent PID is set on it, though the area cannot be assigned as requested. Remove the static binding to have the device come up with a different area by using the <b>wwnaddress --unbind</b> command.

**SWCH-1017**

<b>Message</b>	Device <wwn name of device> tries to FLOGI to port <port number>, reject FLOGI as persistent PID is set on the Loop device.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates persistent port ID (PID) is set and static persistent PID is not supported on loop device.
<b>Recommended Action</b>	Remove the WWN-PID binding using the <b>wwnaddress --unbind</b> command and re-enable the port.

**SWCH-1018**

<b>Message</b>	Device <wwn name of device> FLOGI to port <port number>, Static persistent PID set, Requested area <area> user bound to another port. Reject FLOGI.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a WWN-PID and port address binding collision.
<b>Recommended Action</b>	The persistent PID is set on the device and the requested area cannot be assigned because it is user bound to a different port. Remove the WWN-PID binding using the <b>wwnaddress --unbind</b> command or remove the port address binding using the <b>portaddress --unbind</b> command and then re-enable the port.

## SWCH-1019

<b>Message</b>	Device <wwn name of device> tries to FLOGI, reject FLOGI as persistent PID is set on device and port <port number> has user area <area> bound to it.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a WWN-PID and port address binding collision.
<b>Recommended Action</b>	The persistent PID is set on the device and the requested area cannot be assigned because the port it is trying to log in through has a different area bound to it. Remove the WWN-PID binding using the <b>wwnaddress --unbind</b> command or remove the port address binding using the <b>portaddress --unbind</b> command and then re-enable the port.

## SWCH-1020

<b>Message</b>	HA state out of sync: Standby CP (ver = <standby SWC version>) does not support QoS links to AG(Active CP version = <active SWC version>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the standby control processor (CP) does not support links to Access Gateway running quality of service (QoS).
<b>Recommended Action</b>	Load a firmware version on the standby CP that supports QoS links to Access Gateway by using the <b>firmwareDownload</b> command.

## SWCH-1021

<b>Message</b>	HA state out of sync: Standby CP (ver = <standby SWC version>) does not support Dynamic area on default switch (Active CP version = <active SWC version>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the standby control processor (CP) does not support dynamic area on the default switch.
<b>Recommended Action</b>	Load a firmware version on the standby CP that supports dynamic area on the default switch by using the <b>firmwareDownload</b> command.

## SWCH-1022

<b>Message</b>	Port:<port number> has been disabled due to port address conflict while enabling FMS mode.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch has ports with FICON Management Server (FMS) reserved areas (0xFE, 0xFF) that are not supported in FMS mode.
<b>Recommended Action</b>	No action required. Refer to the <i>FICON Administrator's Guide</i> for more information.

## SWCH-1023

<b>Message</b>	HA state out of sync: Standby CP (ver = <standby SWC version>) does not support XISL use while fmsmode and/or lossless are enabled (Active CP version =<active SWC version>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the standby control processor (CP) does not support extended inter-switch link (XISL) while FICON Management Server (FMS) mode and Lossless are enabled.
<b>Recommended Action</b>	Load a firmware version on standby CP that supports both XISL use and FMS mode and Lossless at the same time by using the <b>firmwareDownload</b> command.

## SWCH-1024

<b>Message</b>	HA state out of sync: Standby CP (ver = <standby SWC version>) does not support active's enforce_login policy (Active CP version =<active SWC version>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the standby control processor (CP) does not enforce login policy of the active CP.
<b>Recommended Action</b>	Configure the enforce login policy to a value that the standby CP supports.

## SWCH-1025

<b>Message</b>	This Logical Switch has ports other than 16 Gbps-capable FC ports. Edge Hold Time for these ports is unchanged and is <Edge Hold Time>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the edge hold time for the non 16 Gbps-capable FC ports is not the same as 16 Gbps-capable FC ports in the logical switch. The non 16 Gbps-capable FC ports use the edge hold time configured on the default switch.
<b>Recommended Action</b>	To know the edge hold time configured for non 16 Gbps-capable FC ports, go to the default switch and execute the <b>configShow</b> command.

## SWCH-1026

<b>Message</b>	HA state out of sync: Standby CP (ver = <standby SWC version>) does not support auto csctl_mode (Active CP version = <active SWC version>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the standby control processor (CP) does not support auto class-specific control (CS_CTL) mode.
<b>Recommended Action</b>	Upgrade the standby CP firmware version to same level as active CP.

## SYSC Messages

### SYSC-1001

<b>Message</b>	Failed to run <Name of program that could not be run (string)>:<System internal error message (string)>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that one of the programs would not run on the system during the boot sequence.
<b>Recommended Action</b>	<p>If the message is reported during a reboot after new firmware has been loaded, try reloading the firmware using the <b>firmwareDownload</b> command.</p> <p>If the message persists, there may be a conflict between the two versions of firmware or the nonvolatile storage may be corrupted.</p> <p>If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.</p>

### SYSC-1002

<b>Message</b>	Switch bring-up timed out.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the system timed out during a reboot or failover sequence, waiting for one or more programs to register with system services or to fail over to active status.
<b>Recommended Action</b>	The switch is in an inconsistent state and can be corrected only by a reboot or power cycle. Before rebooting the chassis, record the firmware version on the switch or control processor (CP) and run the <b>haDump</b> command. If this is a dual-CP switch, gather the output from the CP in which this log message appeared.

### SYSC-1004

<b>Message</b>	Daemon <Daemon name to restart> restart successful.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a terminated daemon is restarted by the system automatically.
<b>Recommended Action</b>	Execute the <b>supportSave</b> command to gather troubleshooting data. No further action is required.

## SYSC-1005

<b>Message</b>	Daemon <Daemon name to restart> is not restarted (Reason: <Restart failure reason>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a terminated daemon is not restarted, either because a restart limit is reached or a restart action fails.
<b>Recommended Action</b>	Execute the <b>supportSave</b> command to gather troubleshooting data. Execute the <b>reboot</b> or <b>haFailover</b> command to recover the system.

## SYSM Messages

### SYSM-1001

<b>Message</b>	No memory.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates the switch has run out of system memory.
<b>Recommended Action</b>	Run the <b>memShow</b> command to view the switch memory usage. Reboot or power cycle the switch. Run the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then run the <b>supportSave</b> command and contact your switch service provider.

### SYSM-1002

<b>Message</b>	<number>, Switch: <Switch number>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates a user has executed either the <b>switchShutdown</b> or <b>switchReboot</b> command. All services are brought down for a logical switch.
<b>Recommended Action</b>	No action is required if the <b>switchShutdown</b> or <b>switchReboot</b> command was executed intentionally. If the <b>switchShutdown</b> command was run, you must run the <b>switchStart</b> command to restart traffic on the logical switch.

### SYSM-1003

<b>Message</b>	<number>, Switch: <start reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the user executed the <b>switchStart</b> or <b>switchReboot</b> command. All services are brought back up after a temporary shutdown of the logical switch.
<b>Recommended Action</b>	No action is required if the <b>switchStart</b> command was executed intentionally. Because reinitializing a switch is a disruptive operation and can stop I/O traffic, you may have to stop and restart the traffic during this process.



## SYSM-1004

<b>Message</b>	Failed to retrieve current chassis configuration option, ret=<Unknown>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates there was a failure to read configuration data from the World Wide Name (WWN) card.
<b>Recommended Action</b>	Verify that the WWN card is present and operational and the affected control processor (CP) is properly seated in its slot.

## SYSM-1005

<b>Message</b>	CP blade in slot <Slot number> failed to retrieve current chassis type.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates there was a failure to read the chassis type from the system.
<b>Recommended Action</b>	Verify the control processor (CP) blade is operational and is properly seated in its slot.

## SYSM-1006

<b>Message</b>	CP blade in slot <Slot number> is incompatible with the chassis type.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates this chassis type is not compatible with the control processor (CP) blade.
<b>Recommended Action</b>	Use the CP blade on a compatible chassis.

## SYSM-1007

**Message** PERMITTING USE OF INCOMPATIBLE CHASSIS FOR CP IN SLOT <Slot number>. DATA ERRORS MAY RESULT.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates an override of the incompatible control processor (CP) or chassis check. This message is for engineering use only.

**Recommended Action** Delete the /var/chassis\_backplane\_override file and reboot the CP.

## TAPE Messages

### TAPE-1001

<b>Message</b>	Key acquisition for <Pool or Container> <Begins or Complete>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the key acquisition for the pool or the container has begun or is complete.
<b>Recommended Action</b>	No action is required.

## TRCE Messages

### TRCE-1001

<b>Message</b>	Trace dump available<slot on which the trace dump occurs>! (reason: <cause of trace dump: PANIC DUMP, WATCHDOG EXPIRED, MANUAL, TRIGGER>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that trace dump files have been generated on the switch or the specified slot. The cause for the dump can be one of the following: <ul style="list-style-type: none"> <li>• PANICDUMP: Generated by panic dump.</li> <li>• WATCHDOG EXPIRED: Generated by hardware watchdog expiration.</li> <li>• MANUAL: Generated manually by issuing the <b>tracedump -n</b> command.</li> <li>• TRIGGER: Triggered by a specific Message ID generated by CRITICAL RASLog message.</li> </ul>
<b>Recommended Action</b>	Execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

### TRCE-1002

<b>Message</b>	Trace dump<slot on which the trace dump occurs> automatically transferred to address ' <FTP target designated by user> '.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a trace dump has occurred on the switch or the specified slot, and the trace dump files were automatically transferred from the switch to the specified FTP server.
<b>Recommended Action</b>	No action is required.

### TRCE-1003

<b>Message</b>	Trace dump<slot on which the trace dump occurs> was not transferred due to FTP error.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that a trace dump has occurred on the switch or the specified slot, but the trace dump files were not automatically transferred from the switch because of an FTP error such as a wrong FTP address, FTP site is down, and network is down.

**Recommended Action** If the message persists, execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

## TRCE-1004

**Message** Trace dump<slot on which the trace dump occurs> was not transferred because trace auto-FTP disabled.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that trace dump files have been created on the switch or the specified slot, but the trace dump files were not automatically transferred from the switch because auto-FTP is disabled.

**Recommended Action** Execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

## TRCE-1005

**Message** FTP Connectivity Test failed due to error.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the connectivity test to the FTP host failed because of reasons such as a wrong FTP address, FTP site is down, network is down, and so on.

**Recommended Action** Execute the **supportFtp** command (as needed) to set up automatic FTP transfers; then execute the **supportSave** command and contact your switch service provider.

## TRCE-1006

**Message** FTP Connectivity Test succeeded to FTP site ' <FTP target configured by users> '.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that a connectivity test to the FTP host has succeeded. This feature is enabled using the **supportftp -t** command.

**Recommended Action** No action is required.

## TRCE-1007

<b>Message</b>	Notification of this CP has failed. Parameters temporarily out of synch with other CP.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the active control processor (CP) is unable to alert the standby CP of a change in trace status. This message is only applicable to bladed switches.
<b>Recommended Action</b>	This message is often transitory. Wait a few minutes and try the command again. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## TRCE-1008

<b>Message</b>	Unable to load trace parameters.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the active control processor (CP) is unable to read the stored trace parameters.
<b>Recommended Action</b>	Reboot the CP (dual-CP system) or restart the switch. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## TRCE-1009

<b>Message</b>	Unable to alert active CP that a dump has occurred.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the standby control processor (CP) is unable to communicate trace information to active CP. This message is only applicable to bladed switches.
<b>Recommended Action</b>	Execute the <b>haShow</b> command to verify that the current CP is standby and the other CP is active. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

**TRCE-1010**

<b>Message</b>	Traced fails to start.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the trace daemon (traced), which is used for transferring trace files has failed to start. The trace capability within the switch is unaffected. The system automatically restarts the traced facility after a brief delay.
<b>Recommended Action</b>	Reboot the CP (dual-CP system) or restart the switch. If the message persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

**TRCE-1011**

<b>Message</b>	Trace dump manually transferred to target ' <optional string to indicate which slot the trace dump is transferred> ': <result>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the trace dump files were manually transferred to the specified slot.
<b>Recommended Action</b>	No action is required.

**TRCE-1012**

<b>Message</b>	The system was unable to retrieve trace information from slot <Slot number of the blade on which the attempt was made>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the system was unable to retrieve trace information from the specified slot because there is no communication between the main system and the specified slot.
<b>Recommended Action</b>	Make sure the blade is enabled and retry the command. If the blade is already enabled, execute the <b>supportSave</b> command and contact your switch service provider.

## TRCE-1013

<b>Message</b>	Trace dump <slot on which the trace dump occurs> was not transferred as FIPS mode is enabled.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a trace dump has occurred on the switch or the specified slot, but the trace dump files were not automatically transferred from the switch because FIPS mode is enabled on the switch.
<b>Recommended Action</b>	No action is required.



## TRCK Messages

### TRCK-1001

<b>Message</b>	Successful login by user <User>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the track change feature recorded a successful login.
<b>Recommended Action</b>	No action is required.

### TRCK-1002

<b>Message</b>	Unsuccessful login by user <User> after <login_fail_cnt> overall login failure attempts.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the track change feature recorded a failed login. This occurs if the user name or password is entered incorrectly.
<b>Recommended Action</b>	Normally, this message indicates a typing error by an authorized user. If this message occurs repeatedly, it may indicate an unauthorized user trying to gain access to a switch. When secure mode is enabled on the fabric, the IP address of a failed login is reported to the error log.

### TRCK-1003

<b>Message</b>	Logout by user <User>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the track change feature recorded a successful logout.
<b>Recommended Action</b>	No action is required.

**TRCK-1004**

<b>Message</b>	Config file change from task:<task>
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the track change feature recorded a configuration change for the switch. The track change feature records any change to the configuration file in nonvolatile memory, including a configuration download. This message is not generated for a configuration upload. All configuration changes occur through the parity data manager (PDM) server, so the PDMIPC is the only task possible.
<b>Recommended Action</b>	No action is required. Run the <b>configShow</b> command to view the configuration file.

**TRCK-1005**

<b>Message</b>	Track-changes on.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the track change feature has been enabled.
<b>Recommended Action</b>	No action is required. Run the <b>trackChangesSet 0</b> command if you want to disable the track change feature.

**TRCK-1006**

<b>Message</b>	Track-changes off.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the track change feature has been disabled.
<b>Recommended Action</b>	No action is required. Run the <b>trackChangesSet 1</b> command if you want to enable the track changes feature.

## TS Messages

### TS-1001

<b>Message</b>	NTP Query failed: <error code>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	<p>Indicates that a Network Time Protocol (NTP) query to the configured external clock server failed. Local clock time on the principal or primary fabric configuration server (FCS) switch is used for fabric synchronization.</p> <p>This message may be logged during temporary operational issues such as IP network connection issues to the external clock server. If the message does not recur, it can be ignored.</p>
<b>Recommended Action</b>	Execute the <b>tsClockServer</b> command to verify that the configured external clock server is available and functional. If that external clock server is not available, choose another clock server.

### TS-1002

<b>Message</b>	<Type of clock server used> Clock Server used instead of <Type of clock server configured>: locl: 0x<Reference ID of LOCL> remote: 0x<Reference ID of external clock server>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	<p>Indicates the fabric time synchronization was sourced from an alternate clock server instead of the configured clock server. The clock server used can be one of the following type:</p> <ul style="list-style-type: none"> <li>• LOCL - Local clock on the principal or primary FCS switch.</li> <li>• External - External Network Time Protocol (NTP) server address configured.</li> </ul> <p>This message may be logged during temporary operational issues such as IP network connection issues to the external clock server or the fabric is configured for external time synchronization but the principal or primary fabric configuration server (FCS) does not support the feature. If the message does not recur, it can be ignored.</p>
<b>Recommended Action</b>	Execute the <b>tsClockServer</b> command to verify that the principal or primary FCS switch has the clock server IP configured correctly, and the configured clock server is accessible to the switch and functional. If the principal or primary FCS does not support the feature, either choose a different switch for the role or reset the clock server to LOCL.

## TS-1006

<b>Message</b>	<message> .
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a time service event is occurring or has failed. The message can be one of the following: <ul style="list-style-type: none"> <li>• Init failed. Time Service exiting - Initialization error, but the time server exits.</li> <li>• Synchronizing time of day clock - Usually logged during temporary operational issues when the clock goes out of synchronization. For example, when a time update packet is missed due to fabric reconfiguration or role change of the principal or primary fabric configuration server (FCS) switch. If the message does not recur, it can be ignored.</li> <li>• Validating time update - Usually logged during temporary operational issues when a time update packet cannot be validated in a secure fabric. For example, during fabric reconfiguration or role change of the primary FCS switch. If the message does not recur, it can be ignored.</li> </ul>
<b>Recommended Action</b>	No action is required.

## TS-1007

<b>Message</b>	<message> .
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a switch is trying to set the clock server, which is not the primary fabric configuration server (FCS) across the fabric. A consistent FCS policy must be implemented across the fabric.
<b>Recommended Action</b>	Execute the <b>secPolicyShow</b> command to verify that the FCS policy is consistent across the fabric.

## TS-1008

<b>Message</b>	<New clock server used> Clock Server used instead of <Old server configured> .
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the source of fabric time synchronization distributed from the principal or primary fabric configuration server (FCS) switch was changed to another configured clock server. This happens when the Network Time Protocol (NTP) query to the current active external clock server failed.

**Recommended  
Action**      No action is required.

## UCST Messages

### UCST-1003

<b>Message</b>	Duplicate Path to Domain <domain ID>, Output Port = <port number>, PDB pointer = 0x<value>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that duplicate paths were reported to the specified domain from the specified output port. The <i>PDB pointer</i> value displayed in the message is the address of the path database and provides debugging information.
<b>Recommended Action</b>	No action is required.

### UCST-1007

<b>Message</b>	Inconsistent route detected: Port = <port number>, should be <port number>.
<b>Message Type</b>	FFDC   LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates that the switch detected an inconsistency in the routing database between the routing protocol and the hardware configuration. The first port number displayed is what the hardware has configured and the second port number displayed is what the protocol is using.
<b>Recommended Action</b>	Run the <b>switchDisable</b> command and then the <b>switchEnable</b> command to reset the routing database. Run the <b>uRouteShow</b> command to display the new routing tables.

### UCST-1020

<b>Message</b>	Static route (input-area: <port number>, domain: <domain ID> output-area: <port number>) has been ignored due to platform limitation.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the configured static route cannot be applied to the routing database because of a platform limitation.
<b>Recommended Action</b>	No action is required.

## UCST-1021

<b>Message</b>	In-order delivery option has been enabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that in-order delivery (IOD) option has been enabled on the switch. This option guarantees in-order delivery of frames during fabric topology changes.
<b>Recommended Action</b>	No action is required.

## UCST-1022

<b>Message</b>	In-order delivery option has been disabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that in-order delivery (IOD) option has been disabled on the switch. This may cause out-of-order delivery of frames during fabric topology changes.
<b>Recommended Action</b>	No action is required.

## UCST-1023

<b>Message</b>	Dynamic Load Sharing option has been enabled
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that Dynamic Load Sharing (DLS) option has been enabled on the switch. This will move existing routes to a new redundant path when this path becomes available.
<b>Recommended Action</b>	No action is required.

## UCST-1024

<b>Message</b>	Dynamic Load Sharing option has been disabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that Dynamic Load Sharing (DLS) option has been disabled on the switch.
<b>Recommended Action</b>	No action is required.

## UCST-1026

<b>Message</b>	LossLess-DLS option has been enabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the NoFrameDrop option has been enabled. This will help minimize frame loss during fabric topology changes.
<b>Recommended Action</b>	No action is required.

## UCST-1027

<b>Message</b>	LossLess-DLS option has been disabled.
<b>Message Type</b>	AUDIT   LOG
<b>Class</b>	CFG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the NoFrameDrop option has been disabled. This may cause higher frame loss during fabric topology changes.
<b>Recommended Action</b>	No action is required.



## UPTH Messages

### UPTH-1001

<b>Message</b>	No minimum cost path in candidate list.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the switch is unreachable because no minimum cost path (MPATH) exists in the candidate list (domain ID list).
<b>Recommended Action</b>	No action is required. This error will end the current shortest path first (SPF) computation.

### UPTH-1002

<b>Message</b>	Domain <domain ID> is unreachable because the enabled TI zone is not compatible with the fabric configuration.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified switch is unreachable because the traffic isolation (TI) zone and the fabric configuration are incompatible.
<b>Recommended Action</b>	Clear all TI zones and then create a valid TI zone for your fabric configuration. Refer to the <i>Fabric OS Administrator's Guide</i> for more information on TI zoning.

## VDR Messages

### VDR-2001

<b>Message</b>	<message> .
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Field-Programmable Gate Array (FPGA) parity error threshold exceeded.
<b>Recommended Action</b>	Power cycle the switch.

## VS Messages

### VS-1001

<b>Message</b>	No virtual PWWN assignment for the device <Login device PWWN>, port <Switch port> or (AG <AG NWWN> port <AG port>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the device with the virtual Port World Wide Name (PWWN) feature enabled tried to log in but there is no mapping for the device, port, or Access Gateway (AG) port.
<b>Recommended Action</b>	Execute the <b>fapwwn</b> command to map the device, port, or AG port. You can ignore this message if the virtual PWWN is not required.

### VS-1002

<b>Message</b>	The Virtual PWWN assignment for the device <Login device PWWN>, port <Switch port> (AG <AG NWWN> port <AG port>) is timed out.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the virtual Port World Wide Name (PWWN) association has timed out.
<b>Recommended Action</b>	No action is required.

### VS-1003

<b>Message</b>	Could not find Virtual PWWN config file for the switch.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the configuration file is corrupted or accidentally removed.
<b>Recommended Action</b>	Restart the switch and download the configuration using the <b>configDownload</b> command.

## VS-1004

<b>Message</b>	Could not find Virtual PWWN config file for the switch.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the virtual Port World Wide Name (PWWN) feature has been enabled for the first time on the switch or the configuration file was corrupted or accidentally removed.
<b>Recommended Action</b>	Creating a new default configuration file. Execute the <b>configDownload</b> command to download any of your earlier configurations for the virtual PWWN feature.

## VS-1005

<b>Message</b>	Virtual PWWN config version mismatch detected.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the virtual Port World Wide Name (PWWN) configuration present on the switch is not of the same Fabric OS version.
<b>Recommended Action</b>	Converting the virtual PWWN configuration to the current Fabric OS version. No action is required.

## VS-1006

<b>Message</b>	Virtualization services failed to initialize due to lack of enough memory.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the system has run out of memory.
<b>Recommended Action</b>	No action is required.

## VS-1007

<b>Message</b>	FSS Registration failed for virtualization services.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates failure in the virtualization service daemon (vsd) startup because vsd has failed to register with Fabric OS State Synchronization (FSS).
<b>Recommended Action</b>	No action is required.

## VS-1008

<b>Message</b>	Virtualization services failed to create timer.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates failure in the virtualization service daemon (vsd) startup because vsd has failed to create a timer.
<b>Recommended Action</b>	No action is required.

## WEBD Messages

### WEBD-1001

<b>Message</b>	Missing or Invalid Certificate file -- HTTPS is configured but could not be started.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the Secure Sockets Layer (SSL) certificate file is either invalid or absent.
<b>Recommended Action</b>	Install a valid certificate file.

### WEBD-1002

<b>Message</b>	Missing or Invalid Key file -- HTTPS is configured but could not be started.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the Secure Sockets Layer (SSL) key file is either invalid or absent.
<b>Recommended Action</b>	Install a valid key file.

### WEBD-1004

<b>Message</b>	HTTP server and weblinker process will be restarted due to configuration change.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the Hypertext Transfer Protocol (HTTP) server configuration has changed.
<b>Recommended Action</b>	No action is required.

## WEBD-1005

<b>Message</b>	HTTP server and weblinker process will be restarted for logfile truncation.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates the size of the Hypertext Transfer Protocol (HTTP) log file exceeded the maximum limit.
<b>Recommended Action</b>	No action is required.

## WEBD-1006

<b>Message</b>	HTTP server and weblinker restarted due to logfile truncation.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the size of the Hypertext Transfer Protocol (HTTP) log file exceeded the maximum limit.
<b>Recommended Action</b>	No action is required.

## WEBD-1007

<b>Message</b>	HTTP server and weblinker process will be restarted due to change of IP Address.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the IP address of the switch changed and the Hypertext Transfer Protocol (HTTP) server is restarted.
<b>Recommended Action</b>	No action is required.

## WEBD-1008

<b>Message</b>	HTTP server and weblinker process cannot be started.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a rare error condition in which the built-in recovery process has failed to restore Hypertext Transfer Protocol (HTTP) services. The problem often results from invalid configuration of Secure Sockets Layer (SSL) certificates, but there can be more than one reason for such a failure.
<b>Recommended Action</b>	Verify the certification file; there may be a mismatch involved.



## XTUN Messages

### XTUN-1000

<b>Message</b>	FCIP Tunnel <VE Port (Tunnel) Number> Missed Data frame:I/T/L:<FC Initiator ID>/<FC Target ID>/<FCP Logical Unit Number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a missed frame with one or more Fibre Channel Protocol (FCP) data information units during a SCSI write or read operation.
<b>Recommended Action</b>	If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

### XTUN-1001

<b>Message</b>	FCIP Tunnel <VE Port (Tunnel) Number> Memory allocation failed tracker <Number that represents the calling source module>/<Line number in that source file>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a memory allocation failure.
<b>Recommended Action</b>	Contact your vendor's customer support for assistance.

### XTUN-1002

<b>Message</b>	FCIP Tunnel <VE Port (Tunnel) Number> Exchange timeout:I/T/L:<FC Initiator ID>/<FC Target ID>/<FCP Logical Unit Number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Fibre Channel Protocol (FCP) exchange has timed out.
<b>Recommended Action</b>	If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

## XTUN-1003

<b>Message</b>	FCIP Tunnel <VE Port (Tunnel) Number> Message Transmission failed:I/T/L/E:<FC Initiator ID>/<FC Target ID>/<FCP Logical Unit Number>/<Error return value>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a message transmission failure.
<b>Recommended Action</b>	If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

## XTUN-1004

<b>Message</b>	FCIP Tunnel <VE Port (Tunnel) Number> Exchange aborted:I/T/L:<FC Initiator ID>/<FC Target ID>/<FCP Logical Unit Number>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Fibre Channel Protocol (FCP) exchange has been aborted by the initiator.
<b>Recommended Action</b>	If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

## XTUN-1005

<b>Message</b>	FCP emulation for Tunnel/Initiator/Target/LUN:<VE Port (Tunnel) Number>/<FC Initiator ID>/<FC Target ID>/<FCP Logical Unit Number> may not be optimal.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Fibre Channel Protocol (FCP) emulation is in FastWrite mode and could also be in Tape Pipelining mode.
<b>Recommended Action</b>	For disk devices, no action is required. For tape devices, device rediscovery is required.

**XTUN-1006**

**Message** FCIP FC frame drop due to transmit timeout on slot=<FX8-24 Slot number (or 0 if 7800)> DP=<FX8-24 DP number (or 0 if 7800)> BLS=<Blaster Image Number (0 or 1)> DR=<FC Descriptor Ring Number> Frames Dropped=<Number of FC frames that were dropped>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that a Fibre Channel (FC) Send frame timeout occurred and the frames were dropped from the SW queue.

**Recommended Action** This error indicates that there is a slow draining device or a hung Blaster TX Descriptor Ring.

**XTUN-1007**

**Message** FCIP FC frame drop due to truncated receive on slot=<FX8-24 Slot number (or 0 if 7800)> DP=<FX8-24 DP number (or 0 if 7800)> BLS=<Blaster Image Number (0 or 1)> DR=<FC Descriptor Ring Number> Frames Dropped=<Number of FC frames that were dropped>.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that a Fibre Channel (FC) Received frame event was posted, but the frame was dropped due to an invalid receive length. This error occurs only on faulty hardware.

**Recommended Action** Contact your vendor's customer support for assistance.

**XTUN-1996**

**Message** FTRACE buffer <FTRACE Trace Buffer Number> on slot <FX8-24 Slot Number> DP <FX8-24 DP Number> has been cleared.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that a CLI command or **supportSave** operation freed the trace buffer back into the FTRACE free pool.

**Recommended Action** No action is required.

## XTUN-1997

<b>Message</b>	FTRACE buffer <FTRACE Trace Buffer Number> on slot <FX8-24 Slot Number> dp <FX8-24 DP Number> has been triggered.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a programmed trigger event has been detected.
<b>Recommended Action</b>	If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

## XTUN-1998

<b>Message</b>	FTRACE buffer <FTRACE Trace Buffer Number> has been cleared.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a CLI command or <b>supportSave</b> operation freed the trace buffer back into the FTRACE free pool.
<b>Recommended Action</b>	No action is required.

## XTUN-1999

<b>Message</b>	FTRACE buffer <FTRACE Trace Buffer Number> has been triggered.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a programmed trigger event has been detected.
<b>Recommended Action</b>	If there was an unexpected job failure associated with this event, contact your vendor's customer support for assistance.

## XTUN-2000

<b>Message</b>	FCIP Tunnel <VE Port (Tunnel) Number> UP.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified Fibre Channel over IP (FCIP) tunnel is up.
<b>Recommended Action</b>	No action is required.

## XTUN-2001

<b>Message</b>	FCIP Tunnel <VE Port (Tunnel) Number> DOWN (<Reason>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified Fibre Channel over IP (FCIP) tunnel has gone down.
<b>Recommended Action</b>	If the tunnel has not been administratively disabled or deleted, a possible network error or disruption has occurred.

## XTUN-2002

<b>Message</b>	FCIP Tunnel <VE Port (Tunnel) Number> Circuit <Circuit Number> UP.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified circuit is up.
<b>Recommended Action</b>	No action is required.

## XTUN-2003

<b>Message</b>	FCIP Tunnel <VE Port (Tunnel) Number> Circuit <Circuit Number> DOWN (<Reason>).
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the specified circuit has gone down, and the tunnel will also be down if this is the last circuit available.

## 5 XTUN-2004

**Recommended Action** If the tunnel or circuit has not been administratively disabled or deleted, a possible network error or disruption has occurred.

### XTUN-2004

**Message** FCIP Tunnel <VE Port (Tunnel) Number> <Priority Class>-Pri QoS UP.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified quality of service (QoS) for this tunnel is up. This applies to the data classes only. When the F-Class comes online, the tunnel itself is marked as up.

**Recommended Action** No action is required.

### XTUN-2005

**Message** FCIP Tunnel <VE Port (Tunnel) Number> <Priority Class>-Pri QoS DOWN (<Reason>).

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that the specified quality of service (QoS) for this tunnel has gone down. This applies to the data classes only. If the F-Class goes down, the tunnel itself is marked as down.

**Recommended Action** If tunnel or circuit has not been administratively disabled or deleted, a possible network error or disruption has occurred.

### XTUN-2006

**Message** FCIP Tunnel <VE Port (Tunnel) Number> CREATED (<Originator>).

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified tunnel has been successfully created.

**Recommended Action** No action is required.

## XTUN-2007

<b>Message</b>	FCIP Tunnel <VE Port (Tunnel) Number> Circuit <Circuit Number> CREATED (<Originator>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified circuit has been successfully created.
<b>Recommended Action</b>	No action is required.

## XTUN-2008

<b>Message</b>	IKEv2: <Reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the status of an IKEv2 session has changed.
<b>Recommended Action</b>	No action is required.

## XTUN-2009

<b>Message</b>	IPsec: <Reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the status of an Internet Protocol security (IPsec) association has changed.
<b>Recommended Action</b>	No action is required.

## XTUN-2010

<b>Message</b>	SPD: <Reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the status of an SPD entry has changed.

## 5 XTUN-2011

**Recommended Action** No action is required.

### XTUN-2011

**Message** FIPS: <Reason>.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the status of the module FIPS compliance has changed.

**Recommended Action** No action is required.

### XTUN-2020

**Message** FCIP Tunnel <VE Port (Tunnel) Number> DELETED (<Originator>).

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified Fibre Channel over IP (FCIP) tunnel has been administratively deleted.

**Recommended Action** No action is required.

### XTUN-2021

**Message** FCIP Tunnel <VE Port (Tunnel) Number> Circuit <Circuit Number> DELETED (<Originator>).

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the specified circuit has been administratively deleted.

**Recommended Action** No action is required.



**XTUN-2022**

<b>Message</b>	FCIP Tunnel <VE Port (Tunnel) Number> MODIFIED (<Originator>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified Fibre Channel over IP (FCIP) tunnel has been administratively modified.
<b>Recommended Action</b>	No action is required.

**XTUN-2023**

<b>Message</b>	FCIP Tunnel <VE Port (Tunnel) Number> MODATTR (<Attribute change description>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the attribute is modified. In most cases, the attribute value is modified within the specified Fibre Channel over IP (FCIP) tunnel.
<b>Recommended Action</b>	No action is required.

**XTUN-2024**

<b>Message</b>	FCIP Tunnel <VE Port (Tunnel) Number> Circuit <Circuit Number> MODIFIED (<Originator>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified circuit has been administratively modified.
<b>Recommended Action</b>	No action is required.

## XTUN-2025

<b>Message</b>	FCIP Tunnel <VE Port (Tunnel) Number> Circuit <Circuit Number> MODATTR (<Attribute change description>).
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the attribute is modified. In most cases, the attribute value is modified within the specified circuit.
<b>Recommended Action</b>	No action is required.

## ZEUS Messages

### ZEUS-1001

<b>Message</b>	Port <port number> port fault. Change the SFP or check cable.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a deteriorated small form-factor pluggable (SFP) transceiver, an incompatible SFP transceiver pair, or a faulty cable between the peer ports.
<b>Recommended Action</b>	Verify that compatible SFP transceivers are used on the peer ports, the SFP transceivers have not deteriorated, and the Fibre Channel cable is not faulty. Replace the SFP transceivers or the cable if necessary.

### ZEUS-1002

<b>Message</b>	Port <port number> chip faulted due to internal error.
<b>Message Type</b>	LOG   FFDC
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal error. All ports on the blade or switch will be disrupted.
<b>Recommended Action</b>	To recover a bladed system, execute the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands on the blade. To recover a non-bladed system, execute the <b>fastBoot</b> command on the switch.

### ZEUS-1003

<b>Message</b>	S<slot number>,C<chip index>: HW ASIC Chip error type = 0x<chip error type>.
<b>Message Type</b>	LOG
<b>Severity</b>	CRITICAL
<b>Probable Cause</b>	Indicates an internal error in the application-specific integrated circuit (ASIC) hardware that may degrade the data traffic.
<b>Recommended Action</b>	Reboot the system at the next maintenance window. If the problem persists, replace the blade.

**ZEUS-1004**

<b>Message</b>	S<slot number>,C<chip index>: Invalid DMA ch pointer, chan:<Channel number>, good_addr:0x<Good address> bad_addr:0x<Bad address>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates an internal error in the application-specific integrated circuit (ASIC) hardware that may degrade the data traffic.
<b>Recommended Action</b>	Reboot the system at the next maintenance window. If the problem persists, replace the blade.

**ZEUS-1005**

<b>Message</b>	S<slot number>,C<chip index>,A<zeus id>: Memory allocation failed.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates a memory allocation failure in the software.
<b>Recommended Action</b>	Restart the system at the next maintenance window. If the problem persists, replace the control processor (CP) blade.

**ZEUS-1015**

<b>Message</b>	Port re-initialized due to Link Reset failure on internal Port S<slot number>,P<port number>(<blade port number>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the port was re-initialized due to link reset failure.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## ZEUS-1016

<b>Message</b>	Port is faulted due to port re-initialization failure on internal Port S<slot number>, P<port number>(<blade port number>) with reason <port fault reason>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the specified port failed due to port re-initialization failure.
<b>Recommended Action</b>	When this error is observed persistently, power cycle the specified blade using the <b>slotPowerOff</b> and <b>slotPowerOn</b> commands. If the problem persists, replace the blade.

## ZEUS-1028

<b>Message</b>	Detected excessive Link resets on the port in a second. Slot <slot number>, Port <port number>(<blade port number>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the port received excessive link resets from peer port within 1 second and that exceeded threshold.
<b>Recommended Action</b>	When this error is observed persistently, change the small form-factor pluggable (SFP) transceiver or cable on the peer port to which this port is connected.

## ZONE Messages

### ZONE-1002

<b>Message</b>	WWN zoneTypeCheck or zoneGroupCheck warning(<warning string>) at port(<port number>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a zone filter or zone group check failure occurred. The frame filter logic reported a failure when creating or adding the zone groups during port login (PLOGI) trap processing. This message usually indicates problems when adding the content-addressable memory (CAM) entries before the filter setup.
<b>Recommended Action</b>	If the problem persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

### ZONE-1003

<b>Message</b>	zone(<current zone>) contains (<domain id>, <port number>) which does not exist.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the port zone member that is targeted for the local switch contains a nonexistent port. The specified port number in the effective zoning configuration (displayed in the error message) is out of range.
<b>Recommended Action</b>	Edit the zone database and change the port number to a viable value in the effective configuration.

### ZONE-1004

<b>Message</b>	Base PID: 0x<Base PID>, Port Index: <Port Index>, Port: <Slot/Port>: enforcement changed to Session-based HARD Zoning.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the zoning enforcement has changed to session-based hard zoning due to one of the following conditions: <ul style="list-style-type: none"> <li>• The zone has a mix of WWN and domain,index (D,I) members.</li> <li>• The Source Identifier (S_ID) list of the hardware-enforced zoning exceeded the S_ID limit.</li> </ul>

**Recommended Action** No action is required.

## ZONE-1007

**Message** Ioctl (<function>) in (<error message>) at port (<port number>) returns code (<error string>) and reason string (<reason string>).

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that frame filter logic reported a failure during the specified I/O Control (IOCTL) call. This is usually a programming error when adding CAM entries before the filter setup.

**Recommended Action** Avoid this problem in the following ways:

- Avoid having too many hosts zoned with a set of target devices at a single port.
- Avoid having too many zones directed at a single port group on the switch.

## ZONE-1010

**Message** Duplicate entries in zone (<zone name>) specification.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that there are duplicate entries in the specified zone object. This message occurs only when enabling a zone configuration.

**Recommended Action** Check the members of the zone using the **cfgShow** command. Delete the duplicate member using the **zoneRemove** command.

## ZONE-1013

**Message** QuickLoop not supported.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the QuickLoop feature is not supported in the current version of Fabric OS. QuickLoop zones are not supported in Fabric OS version 4.x or later. Even if the QuickLoop zoning configuration is enabled on the switch, it will not be supported.

**Recommended Action** Edit the zone database to remove the QuickLoop zoning definition in the effective configuration.

**ZONE-1015**

<b>Message</b>	Not owner of the current transaction <transaction ID>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that a zoning change operation is not allowed because the zoning transaction is opened by another task. Indicates concurrent modification of the zone database by multiple administrators.
<b>Recommended Action</b>	Wait until the previous transaction is completed. Verify that only one administrator is working with the zone database at a time.

**ZONE-1017**

<b>Message</b>	FA Zone(<zone name>) contains incorrect number of Initiator and Target devices.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the fabric assist (FA) zoning configuration has more than one initiator. This is because of incorrect entries in the FA zoning configuration.
<b>Recommended Action</b>	Edit the zone database to make sure that only one initiator is set for each FA zone configuration.

**ZONE-1019**

<b>Message</b>	Transaction Commit failed. Reason code <reason code> (<Application reason>) - \<reason string>\".
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that reliable commit service (RCS) had a transmit error. RCS is a protocol used to transmit changes to the configuration database within a fabric.
<b>Recommended Action</b>	Often this message indicates a transitory problem. Wait a few minutes and retry the command. Make sure your changes to the zone database are not overwriting the work of another administrator. Execute the <b>cfgTransShow</b> command to determine if there is any outstanding transaction running on the local switches. If the problem persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.



## ZONE-1022

<b>Message</b>	The effective configuration has changed to <Effective configuration name>. <AD Id>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the effective zone configuration has changed to the specified zone name.
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-1023

<b>Message</b>	Switch connected to port (<port number>) is busy. Retrying zone merge.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the switch is retrying the merge operation. This usually occurs if the switch on the other side of the port is busy.
<b>Recommended Action</b>	If the problem persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## ZONE-1024

<b>Message</b>	<Information message>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>cfgSave</b> command has completed successfully.
<b>Recommended Action</b>	No action is required.

## ZONE-1026

<b>Message</b>	port <port number> Out of CAM entries.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the total number of entries of S_ID CAM is above the limit while creating or adding a zone group. The maximum number of CAM entries allowed depends on the application-specific integrated circuit (ASIC).
<b>Recommended Action</b>	If hardware zoning enforcement is preferred, edit the zoning database to have zoned port IDs (PIDs) for that port.

## ZONE-1027

<b>Message</b>	Zoning transaction aborted <error reason>. <AD Id>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	<p>Indicates the zoning transaction was aborted because of a variety of potential errors. The <i>error reason</i> variable can be one of the following conditions:</p> <ul style="list-style-type: none"> <li>• Zone Merge Received: The fabric is in the process of merging two zone databases.</li> <li>• Zone Config update Received: The fabric is in the process of updating the zone database.</li> <li>• Bad Zone Config: The new configuration is not viable.</li> <li>• Zoning Operation failed: A zoning operation failed.</li> <li>• Shell exited: The command shell has exited.</li> <li>• Unknown: An error was received for an unknown reason.</li> <li>• User Command: A user aborted the current zoning transaction.</li> <li>• Switch Shutting Down: The switch is currently shutting down.</li> </ul> <p>Most of these error conditions are transitory.</p>
<b>Recommended Action</b>	Try again after some time. Verify that only one administrator is modifying with the zone database at a time.

## ZONE-1028

<b>Message</b>	Commit zone DB larger than supported - <zone db size> greater than <max zone db size>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the zone database size is greater than the limit allowed by the fabric. The limit of the zone database size depends on the lowest level switch in the fabric. Older switches have less memory and force a smaller zone database for the entire fabric.
<b>Recommended Action</b>	Execute the <b>cfgSize</b> command to view the zone database size information. Edit the zone database to keep it within the allowable limit for the specific switches in your fabric.

## ZONE-1029

<b>Message</b>	Restoring zone cfg from flash failed - bad config saved to <config file name> [ <code>&lt;return code&gt;</code> ].
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the zone configuration restored from the flash memory was faulty. This error will save the faulty zone configuration in the zoned core file directory.
<b>Recommended Action</b>	If the problem persists, execute the <b>supportFtp</b> command (as needed) to set up automatic FTP transfers; then execute the <b>supportSave</b> command and contact your switch service provider.

## ZONE-1034

<b>Message</b>	A new zone database file is created.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a new zone database file has been created.
<b>Recommended Action</b>	No action is required.

## ZONE-1036

<b>Message</b>	Unable to create <config file name>: error message <System Error Message>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Fabric OS cannot create the zone configuration file. Typically, the zone configuration is too large for the memory available on the switch.
<b>Recommended Action</b>	Reduce the size of the zone database and retry the operation.

## ZONE-1037

<b>Message</b>	Unable to examine <config file name>: error message <System Error Message>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Fabric OS cannot examine the zone configuration file. Typically, the zone configuration is too large for the memory available on the switch.
<b>Recommended Action</b>	Reduce the size of the zone database and retry the operation.

## ZONE-1038

<b>Message</b>	Unable to allocate memory for <config file name>: error message <System Error Message>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Fabric OS cannot allocate enough memory for the zone configuration file. Typically, the zone configuration is too large for the memory available on the switch.
<b>Recommended Action</b>	Reduce the size of the zone database and retry the operation.

## ZONE-1039

<b>Message</b>	Unable to read contents of <config file name>: error message <System Error Message>.
<b>Message Type</b>	LOG
<b>Severity</b>	ERROR
<b>Probable Cause</b>	Indicates that the Fabric OS cannot read the zone configuration file. Typically, the zone configuration is too large for the memory available on the switch.
<b>Recommended Action</b>	Reduce the size of the zone database and retry the operation.

## ZONE-1040

<b>Message</b>	Merged zone database exceeds limit.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Fabric OS cannot read the merged zone configuration file. Typically, the zone configuration is too large for the memory available on the switch.
<b>Recommended Action</b>	Reduce the size of the zone database and retry the operation.

## ZONE-1041

<b>Message</b>	Unstable link detected during merge at port (<Port number>).
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates a possible unstable link or faulty cable.
<b>Recommended Action</b>	Verify that the small form-factor pluggable (SFP) transceiver and the cable at the specified port are not faulty. Replace the SFP and the cable, if necessary.

## ZONE-1042

<b>Message</b>	The effective configuration has been disabled. <AD Id>.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the effective zone configuration has been disabled.
<b>Recommended Action</b>	Verify the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-1043

<b>Message</b>	The Default Zone access mode is set to No Access.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Default Zone access mode is set to No Access.
<b>Recommended Action</b>	Verify the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-1044

<b>Message</b>	The Default Zone access mode is set to All Access.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Default Zone access mode is set to All Access.
<b>Recommended Action</b>	Verify the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-1045

<b>Message</b>	The Default Zone access mode is already set to No Access.
<b>Message Type</b>	LOG
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the Default Zone access mode is already set to No Access.

**Recommended Action** No action is required.

## ZONE-1046

**Message** The Default Zone access mode is already set to All Access.

**Message Type** LOG

**Severity** INFO

**Probable Cause** Indicates that the Default Zone access mode is already set to All Access.

**Recommended Action** No action is required.

## ZONE-1048

**Message** ZONE ACA is rejected on the standby.

**Message Type** LOG

**Severity** WARNING

**Probable Cause** Indicates that the standby zoning component did not receive a syncdump command from the primary side.

**Recommended Action** Synchronize the standby control processor (CP) using the **haSyncStart** command.

## ZONE-1049

**Message** ZONE AD-DefZone conflict detected while system initialization.

**Message Type** LOG

**Severity** ERROR

**Probable Cause** Indicates that there is an Admin Domain (AD) Default Zone conflict.

**Recommended Action** Verify that the default zoning mode for AD0 is set to No Access using the **defzone --show** command. If the default zoning mode is not set to No Access, execute the **defzone --noaccess** command and then execute the **cfgsave** command to commit the default zone mode change.

## ZONE-1054

<b>Message</b>	Default Zone All Access mode is set with Frame Redirection zones.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the Default Zone All Access mode will not grant all access behavior when the frame redirection zones are defined.
<b>Recommended Action</b>	Remove frame redirection zones or set the Default Zone access mode to No Access using the <b>defzone --noaccess</b> command.

## ZONE-1057

<b>Message</b>	TI Zone <TI zone name> has domain <Domain ID of switch with version pre6.4.0> running pre FOS6.4.0 firmware. TI member (Domain <Domain ID of higher port index>, Index <Higher port index>) is not supported.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that an unsupported port index (> 511) is present in the TI zone path or the routing may not be set up correctly.
<b>Recommended Action</b>	Remove the port index from the TI zone using the <b>zone --remove name</b> command.

## ZONE-1058

<b>Message</b>	Domain <Domain ID of the switch that becomes unreachable> present in TI zone <TI zone name> became unreachable due to failover disabled mode.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the domain present in the TI zone path is unreachable. This occurs if the TI zone paths are unavailable or the TI zone is set up incorrectly.
<b>Recommended Action</b>	Verify that the paths defined by TI zones are online or remove the domain from the TI zone using the <b>zone --delete name</b> command.



**ZONE-1059**

<b>Message</b>	Unexpected TI routing behavior or a potentially unroutable TI configuration has been detected on local domain <Domain ID of the local Logical Switch where the error was detected>.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the current fabric topology and TI zone configuration may result in an unroutable condition or an unexpected routing behavior.
<b>Recommended Action</b>	Execute the <b>zone --showTlerrors</b> command on the specified switch to report the conflicting configuration details.

**ZONE-1060**

<b>Message</b>	Non-TI and TI failover-enabled traffic restricted to domain <Domain ID> due to TI failover-disabled zoning.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that only TI failover-disabled paths remain to reach the specified domain causing non-TI and TI failover traffic disruption.
<b>Recommended Action</b>	Add or restore the non-TI or TI failover-enabled inter-switch links (ISLs) to the specified domain.

**ZONE-1061**

<b>Message</b>	Some trunk members are missing from failover disabled active TI zones.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that some members in the trunk group are not added to the failover-disabled TI zone. This will result in traffic disruption if the trunk member goes down.
<b>Recommended Action</b>	If any trunk member is included in the TI failover-disabled zone path, then always add all members from that group. Execute the <b>zone --showTltrunkerrors</b> command on the switch to find the missing trunk members in the TI zone.

**ZONE-1062**

<b>Message</b>	Defined and Effective zone configurations are inconsistent.
<b>Message Type</b>	LOG
<b>Severity</b>	WARNING
<b>Probable Cause</b>	Indicates that the defined and effective configurations are different.
<b>Recommended Action</b>	Execute the <b>cfgEnable</b> command to make both the configurations consistent.

**ZONE-3001**

<b>Message</b>	Event: <Event Name>, Status: success, Info: <Zone object type> \"<Zone object member list>\" added to <Zone object set type> \"<Zone object set name>\".
<b>Message Type</b>	AUDIT
<b>Class</b>	ZONE
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a new zone object member or members have been added to the specified zone object set. The <i>zone object type</i> variable can be an alias, zone member, zone, or zone configuration. The string \"...\" appears at the end of the <i>zone object member list</i> variable if the list was truncated in the message.
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

**ZONE-3002**

<b>Message</b>	Event: <Event Name>, Status: success, Info: <Zone object set type> \"<Zone object set name>\" created with <Zone object type> \"<Zone object member list>\".
<b>Message Type</b>	AUDIT
<b>Class</b>	ZONE
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that a new zone object set was created and the specified zone object member or members were added to the zone object set. The <i>zone object type</i> variable can be an alias, zone member, zone, or zone configuration. The string \"...\" appears at the end of the <i>zone object member list</i> variable if the list was truncated in the message.
<b>Recommended Action</b>	Verify the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-3003

<b>Message</b>	Event: <Event Name>, Status: success, Info: <Zone object type> \"<Zone object name>\" deleted.
<b>Message Type</b>	AUDIT
<b>Class</b>	ZONE
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified zone object has been deleted. The <i>zone object type</i> variable can be an alias, zone member, zone, or zone configuration.
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-3004

<b>Message</b>	Event: <Event Name>, Status: success, Info: <Zone object type> \"<Zone object member list>\" removed from <Zone object set type> \"<Zone object set name>\".
<b>Message Type</b>	AUDIT
<b>Class</b>	ZONE
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified zone object member or members have been removed from the specified zone object set. The <i>zone object type</i> variable can be an alias, zone member, zone, or zone configuration. The string \"...\" appears at the end of the <i>zone object member list</i> variable if the list was truncated in the message.
<b>Recommended Action</b>	Verify the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-3005

<b>Message</b>	Event: <Event Name>, Status: success, Info: All zone information cleared from transaction buffer.
<b>Message Type</b>	AUDIT
<b>Class</b>	ZONE
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that all the zone information has been cleared from the transaction buffer.

## 5 ZONE-3006

**Recommended Action** Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

### ZONE-3006

**Message** Event: <Event Name>, Status: success, Info: Current zone configuration disabled. <AD Id>.

**Message Type** AUDIT

**Class** ZONE

**Severity** INFO

**Probable Cause** Indicates that the current zone configuration has been disabled.

**Recommended Action** Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

### ZONE-3007

**Message** Event: <Event Name>, Status: success, Info: Zone configuration \"<Zone configuration>\" enabled. <AD Id>.

**Message Type** AUDIT

**Class** ZONE

**Severity** INFO

**Probable Cause** Indicates that the specified zone configuration has been enabled.

**Recommended Action** Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

### ZONE-3008

**Message** Event: <Event Name>, Status: success, Info: Current zone configuration saved to MRAM. <AD Id>.

**Message Type** AUDIT

**Class** ZONE

**Severity** INFO

**Probable Cause** Indicates that the current zone configuration has been successfully saved to magnetoresistive random access memory (MRAM).

**Recommended Action** Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-3009

**Message** Event: <Event Name>, Status: success, Info: <Event Description>.

**Message Type** AUDIT

**Class** ZONE

**Severity** INFO

**Probable Cause** Indicates that the specified zone transaction has been successful.

**Recommended Action** Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-3010

**Message** Event: <Event Name>, Status: success, Info: Zone object \<">Zone object name>" copied to new zone object \<">New Zone object name>"

**Message Type** AUDIT

**Class** ZONE

**Severity** INFO

**Probable Cause** Indicates that the specified zone object has been copied to a new zone object.

**Recommended Action** Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-3011

**Message** Event: <Event Name>, Status: success, Info: Zone object \<">Zone object name>" expunged.

**Message Type** AUDIT

**Class** ZONE

**Severity** INFO

**Probable Cause** Indicates that the specified zone object has been expunged.

**Recommended Action** Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-3012

<b>Message</b>	Event: <Event Name>, Status: success, Info: Zone object \"<Zone object name>\" renamed to \"<New Zone object name>\".
<b>Message Type</b>	AUDIT
<b>Class</b>	ZONE
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified zone object has been renamed.
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-3013

<b>Message</b>	Event: <Event Name>, Status: success, Info: <Admin domain type> <Admin domain name> has been activated.
<b>Message Type</b>	AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified Admin Domain (AD) has been activated.
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-3014

<b>Message</b>	Event: <Event Name>, Status: success, Info: \"<AD object member list>\" added to <AD object set type> \"<AD object set name>\".
<b>Message Type</b>	AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified new Admin Domain (AD) object member or members have been added to an AD object set.  The <i>AD object set type</i> variable can be an AD alias or AD member. The string \"...\" appears at the end of the <i>AD object member list</i> variable if the list was truncated in the message.
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-3015

<b>Message</b>	Event: <Event Name>, Status: success, Info: AD configurations applied.
<b>Message Type</b>	AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the saved Admin Domain (AD) configurations are enforced.
<b>Recommended Action</b>	Verify the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-3016

<b>Message</b>	Event: <Event Name>, Status: success, Info: All AD definitions cleared.
<b>Message Type</b>	AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that all Admin Domain (AD) definitions and all zone configurations under them have been cleared.
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-3017

<b>Message</b>	Event: <Event Name>, Status: success, Info: <AD object set type> \"<AD object set name>\" created with \"<AD object member list>\".
<b>Message Type</b>	AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates the specified Admin Domain (AD) has been created.  The <i>AD object set type</i> variable can be an AD alias or AD member. The string "..." appears at the end of the <i>AD object member list</i> if the list was truncated in the message.
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

**ZONE-3018**

<b>Message</b>	Event: <Event Name>, Status: success, Info:<AD object type> <AD object name> has been deactivated.
<b>Message Type</b>	AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified Admin Domain (AD) object has been deactivated.
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

**ZONE-3019**

<b>Message</b>	Event: <Event Name>, Status: success, Info: <AD object type> \"<AD object name>\" deleted.
<b>Message Type</b>	AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified Admin Domain (AD) object has been deleted.
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

**ZONE-3020**

<b>Message</b>	Event: <Event Name>, Status: success, Info: \"<AD object member list>\" removed from <AD object set type> \"<AD object set name>\".
<b>Message Type</b>	AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified Admin Domain (AD) member or members have been removed from the AD.
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.



## ZONE-3021

<b>Message</b>	Event: <Event Name>, Status: success, Info: AD object \"<AD object name>\" renamed to \"<New AD object name>\".
<b>Message Type</b>	AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified Admin Domain (AD) has been renamed.
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-3022

<b>Message</b>	Event: <Event Name>, Status: success, Info: Current AD configuration saved to flash.
<b>Message Type</b>	AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the current Admin Domain (AD) configuration has been saved to flash memory.
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

## ZONE-3023

<b>Message</b>	Event: <Event Name>, Status: Failure, Info: AD Apply operation failed due to transaction conflict.
<b>Message Type</b>	AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>ad --apply</b> command has failed because of a transaction conflict.
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

**ZONE-3024**

<b>Message</b>	Command: <Command Name>, Status: success, Info: executed. <AD Id>.
<b>Message Type</b>	AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>ad --transabort</b> command has completed successfully in the specified Admin Domain (AD).
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

**ZONE-3025**

<b>Message</b>	Command: <Command Name> Info: executed. In AD <AD Id>.
<b>Message Type</b>	AUDIT
<b>Class</b>	FABRIC
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the <b>ad --exec</b> command was executed in the specified Admin Domain (AD).
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.

**ZONE-3026**

<b>Message</b>	Event: <Event Name>, Status: success, Info: Zone object \"<Zone object name>\" replaced with \"<New Zone object name>\".
<b>Message Type</b>	AUDIT
<b>Class</b>	ZONE
<b>Severity</b>	INFO
<b>Probable Cause</b>	Indicates that the specified zone object has been replaced.
<b>Recommended Action</b>	Verify that the event was planned. If the event was planned, no action is required. If the event was not planned, take appropriate action as defined by your enterprise security policy.