

53-1002063-03
17 December 2010



Fabric OS

Documentation Updates

Supporting Fabric OS v6.4.1

BROCADE

Copyright © 2010 Brocade Communications Systems, Inc. All Rights Reserved.

Brocade, the B-wing symbol, BigIron, DCFM, DCX, Fabric OS, FastIron, IronView, NetIron, SAN Health, ServerIron, TurboIron, and Wingspan are registered trademarks, and Brocade Assurance, Brocade NET Health, Brocade One, Extraordinary Networks, MyBrocade, and VCS are trademarks of Brocade Communications Systems, Inc., in the United States and/or in other countries. Other brands, products, or service names mentioned are or may be trademarks or service marks of their respective owners.

Notice: This document is for informational purposes only and does not set forth any warranty, expressed or implied, concerning any equipment, equipment feature, or service offered or to be offered by Brocade. Brocade reserves the right to make changes to this document at any time, without notice, and assumes no responsibility for its use. This informational document describes features that may not be currently available. Contact a Brocade sales office for information on feature and product availability. Export of technical data contained in this document may require an export license from the United States government.

The authors and Brocade Communications Systems, Inc. shall have no liability or responsibility to any person or entity with respect to any loss, cost, liability, or damages arising from the information contained in this book or the computer programs that accompany it.

The product described by this document may contain "open source" software covered by the GNU General Public License or other open source license agreements. To find out which open source software is included in Brocade products, view the licensing terms applicable to the open source software, and obtain a copy of the programming source code, please visit <http://www.brocade.com/support/oscd>.

Brocade Communications Systems, Incorporated

Corporate and Latin American Headquarters
Brocade Communications Systems, Inc.
130 Holger Way
San Jose, CA 95134
Tel: 1-408-333-8000
Fax: 1-408-333-8101
E-mail: info@brocade.com

Asia-Pacific Headquarters
Brocade Communications Systems China HK, Ltd.
No. 1 Guanghua Road
Chao Yang District
Units 2718 and 2818
Beijing 100020, China
Tel: +8610 6588 8888
Fax: +8610 6588 9999
E-mail: china-info@brocade.com

European Headquarters
Brocade Communications Switzerland Sàrl
Centre Swissair
Tour B - 4ème étage
29, Route de l'Aéroport
Case Postale 105
CH-1215 Genève 15
Switzerland
Tel: +41 22 799 5640
Fax: +41 22 799 5641
E-mail: emea-info@brocade.com

Asia-Pacific Headquarters
Brocade Communications Systems Co., Ltd. (Shenzhen WFOE)
Citic Plaza
No. 233 Tian He Road North
Unit 1308 - 13th Floor
Guangzhou, China
Tel: +8620 3891 2000
Fax: +8620 3891 2111
E-mail: china-info@brocade.com

Document History

Title	Publication number	Summary of changes	Date
<i>Fabric OS Documentation Updates</i>	53-1002063-01	New document	October 7, 2010
<i>Fabric OS Documentation Updates</i>	53-1002063-02	Added update for the <i>Fabric OS Administrator's Guide</i> .	November 10, 2010
<i>Fabric OS Documentation Updates</i>	53-1002063-03	Added updates for the following: <ul style="list-style-type: none">• <i>Fabric OS Message Reference</i>• <i>DCX Backbone Hardware Reference Manual</i>• <i>Brocade 5100 Hardware Reference Manual</i>	December 17, 2010

Contents

About This Document

In this chapter	v
How this document is organized	v
Document feedback	vi

Chapter 1 Access Gateway Administrator's Guide

In this chapter	1
Chapter 3, Managing Policies and Features in Access Gateway Mode	1

Chapter 2 Fabric OS Administrator's Guide

In this chapter	3
Chapter 14, Interoperability for Merged SANs	3
Chapter 16, Administering Licensing	3
Chapter 17, Monitoring Fabric Performance	3
Chapter 21, Using the FC-FC Routing Service	4

Chapter 3 Fabric OS Commands Reference

In this chapter	5
New commands in Fabric OS v6.4.1	5
Revised commands in Fabric OS v6.4.0	10
Command RBAC permissions and AD types	12

Chapter 4 Fabric OS Message Reference Manual

In this chapter	13
SULB System Messages	13

Chapter 5 Fabric Watch Administrator's Guide

In this chapter	15
Chapter 1, Fabric Watch notification types	15
swFabricWatchTrap severity	15
SNMP trap counters	15
Chapter 2, Fabric Watch Thresholds	16
In-between buffer values	16
Chapter 4, Fabric Watch Activation	16

Chapter 6	DCX Backbone Hardware Reference Manual	
	In this chapter	17
	Appendix D, Port Numbering Template	17
Chapter 7	Brocade 5100 Hardware Reference Manual	
	In this chapter	19
	Chapter 3, Brocade 5100 Operation	19

About This Document

In this chapter

- [How this document is organized](#) v
- [Document feedback](#) vi

How this document is organized

This document contains updates to the following Fabric OS manuals:

TABLE 1 Fabric OS Documentation Updates

Publication Title	Page Number	Publication Date
<i>Access Gateway Administrator's Guide</i>	Updates on page 1	March 2010
<i>CEE Administrator's Guide</i>	No Updates	October 2010
<i>CEE Command Reference</i>	No Updates	October 2010
<i>Fabric OS Administrator's Guide</i>	Updates on page 3	September 2010
<i>Fabric OS Command Reference</i>	Updated on page 5	September 2010
<i>Fabric OS Encryption Administrator's Guide (LKM)</i>	No Updates	March 2010
<i>Fabric OS Encryption Administrator's Guide (RKM)</i>	No Updates	March 2010
<i>Fabric OS Encryption Administrator's Guide (TEMS)</i>	No Updates	March 2010
<i>Fabric OS Encryption Administrator's Guide (SKM)</i>	No Updates	March 2010
<i>Fabric OS Encryption Administrator's Guide (TKLM)</i>	No Updates	October 2010
<i>Fibre Channel over IP Administrator's Guide</i>	No Updates	March 2010
<i>Fabric OS Message Reference</i>	Updates on page 13	March 2010
<i>Fabric OS Troubleshooting and Diagnostics Guide</i>	No updates	March 2010
<i>Fabric Watch Administrator's Guide</i>	Updates on page 15	March 2010
<i>FICON Administrator's Guide</i>	No updates	March 2010
<i>iSCSI Administrator's Guide</i>	No updates	March 2010
<i>Web Tools Administrator's Guide</i>	No updates	March 2010
<i>DCX Backbone Hardware Reference Manual</i>	Updates on page 17	March 2010
<i>Brocade 5100 Hardware Reference Manual</i>	Updates on page 19	July 2008

Document feedback

Quality is our first concern at Brocade and we have made every effort to ensure the accuracy and completeness of this document. However, if you find an error or an omission, or you think that a topic needs further development, we want to hear from you. Forward your feedback to:

`documentation@brocade.com`

Provide the title and version number of the document and as much detail as possible about your comment, including the topic heading and page number and your suggestions for improvement.

Access Gateway Administrator's Guide

In this chapter

The updates in this chapter are for the *Access Gateway Administrator's Guide*, part number: 53-10001760-01, published March 2010.

- [Chapter 3, Managing Policies and Features in Access Gateway Mode 1](#)

Chapter 3, Managing Policies and Features in Access Gateway Mode

Under the heading “Trunking in Access Gateway Mode” on page 48, add the following note at the bottom of the page.

NOTE

N_Port Trunking is not supported for HBAs connected to switches running in Access Gateway mode. This feature is only be supported for HBAs connected to switches running in Native mode.

1 Chapter 3, Managing Policies and Features in Access Gateway Mode

Fabric OS Administrator's Guide

In this chapter

The updates in this chapter are for the *Fabric OS Administrator's Guide*, part number: 53-1001763-02, published September 2010.

- [Chapter 14, Interoperability for Merged SANs](#) 3
- [Chapter 16, Administering Licensing](#) 3
- [Chapter 17, Monitoring Fabric Performance](#) 3
- [Chapter 21, Using the FC-FC Routing Service](#) 4

Chapter 14, Interoperability for Merged SANs

In the section “Zoning restrictions” on page 306, add the following item:

- The maximum zone database size is 1 MB and is a combination of the active configuration size and the defined configuration size. For example, if the active configuration size is 200 KB, then the size of the defined configuration cannot exceed 800 KB.

Chapter 16, Administering Licensing

In Table 78 on page 368, add the following entry:

Feature	License	Where license should be installed
Trunking on an HBA	Server Application Optimization and ISL Trunking	Local switch

Chapter 17, Monitoring Fabric Performance

In the section “Limitations of Top Talker monitors” on page 397, add the following item:

- Fabric mode Top Talker monitors and FC-FC routing are not concurrently supported.

Chapter 21, Using the FC-FC Routing Service

In the section “Verifying the setup for FC-FC routing,” on page 466 add the following step:

6. Delete fabric mode Top Talker monitors, if they are configured.

FC-FC routing and fabric mode Top Talker monitors are not concurrently supported. See “Deleting the fabric mode Top Talker monitors” on page 396 for instructions.

Fabric OS Commands Reference

In this chapter

The updates in this chapter are for the *Fabric OS Command Reference*, part number: 53-1001763-02, published September 2010.

- [New commands in Fabric OS v6.4.1](#) 5
- [Revised commands in Fabric OS v6.4.0](#) 10
- [Command RBAC permissions and AD types](#) 12

New commands in Fabric OS v6.4.1

Add the following new commands to the *Fabric OS Command Reference* for *Fabric OS v6.4.0*.

bufOpMode

Changes or displays the Buffer Optimized Mode.

SYNOPSIS **bufopmode --set slot -f**

bufopmode --reset slot

bufopmode --show slot

bufopmode --showall

DESCRIPTION Use this command to display or change the buffer optimized mode on a switch.

When buffer optimized mode is enabled on a slot, additional buffers are allocated on the internal ports. Use this feature, if you have slow draining devices connected to the slot and there are no long distance links on that slot. This command can provide more credit flexibility and may help with congestion. However, the full solution to traffic congestion requires the use of monitoring applications such as Fabric Watch, Bottleneck detection, and Port Fencing.

You must power off the slot before changing the buffer optimized mode. Changes take effect immediately after the slot is powered on.

Enabling buffer optimized mode removes all long distance configurations on that slot. You will be prompted if any long distance configuration is detected.

NOTES The execution of this command is subject to Virtual Fabric or Admin Domain restrictions that may be in place. For details on command availability, refer to the *Fabric OS Command Reference*, Appendix A.

This command is only supported only on the Brocade FC8-16, FC8-32, and FC8-48 blades in a DCX or DCX-4S chassis.

This command is not supported on CP and core blades.

OPERANDS This command has the following operands:

slot Specifies the slot number.

--set Enables buffer optimized mode on the specified slot. This command prompts for confirmation before removing any long distance configurations on that slot. Use the **-f** option to execute this command without confirmation.

--reset Clears buffer optimized mode on the specified slot.

--show Displays the current buffer optimized mode for the specified slot (On or Off).

--showall Displays the current buffer optimized mode for all slots.

EXAMPLES To display the buffer optimized mode for all slots in a chassis:

```
switch:admin> bufopmode --showall
Slot 1: buffer optimized mode - Off
Slot 2: buffer optimized mode - Off
Slot 3: buffer optimized mode - Off
Slot 4: buffer optimized mode - Off
Slot 9: buffer optimized mode - Off
Slot 10: buffer optimized mode - Off
Slot 11: buffer optimized mode - Off
Slot 12: buffer optimized mode - On
```

To display current buffer optimized mode for a single slot

```
switch:admin> bufopmode --show 12  
Slot 12: buffer optimized mode - On
```

To enable buffer optimized mode for a given slot:

```
switch:admin> bufopmode --set 11  
The operation is not supported when the slot is online
```

```
switch:admin> bufopmode --reset 12  
The operation is not supported when the slot is online
```

```
switch:admin> slotpoweroff 11
```

```
switch:admin> slotpoweroff 12
```

```
switch:admin> bufopmode --set 12  
Buffer optimized mode is turned on for slot 11
```

```
switch:admin> bufopmode --reset 12  
Buffer optimized mode is turned off for slot 12
```

```
switch:admin> slotpoweron 11
```

```
switch:admin> slotpoweron 12
```

To display the changes:

```
switch:admin> bufopmode --showall  
Slot 1: buffer optimized mode - Off  
Slot 2: buffer optimized mode - Off  
Slot 3: buffer optimized mode - Off  
Slot 4: buffer optimized mode - Off  
Slot 9: buffer optimized mode - Off  
Slot 10: buffer optimized mode - Off  
Slot 11: buffer optimized mode - On  
Slot 12: buffer optimized mode - Off
```

SEE ALSO [slotShow](#), [slotPowerOn](#), [slotPowerOff](#)

portCfgFaultDelay

Configures the fault delay for a single FC port.

SYNOPSIS `portcfgfaultdelay --enable [slot/]port mode`

`portcfgfaultdelay --help`

DESCRIPTION Use this command to configure the fault delay of an FC port.

In the event that the link is noisy after a host power cycle, the switch may go into a soft fault state, which means a delay of R_A_TOV. Setting the mode value to 1 reduces the fault delay value to 1.2 seconds. The configuration is stored in nonvolatile memory and is persistent across switch reboots or power cycle.

Use the **portCfgShow** command to display user-configured fault delay settings.

NOTES The execution of this command is subject to Virtual Fabric or Admin Domain restrictions that may be in place. Refer to Chapter 1, "Using Fabric OS Commands" and Appendix A, "Command Availability" for details.

This command is not applicable to non-FC ports.

OPERANDS This command has the following operands:

<i>slot</i>	For bladed systems only, specifies the slot number of the port to be configured, followed by a slash (/).
<i>port</i>	Specifies the number of the port to be configured, relative to its slot for bladed systems. Use switchShow for a listing of valid ports.
<i>mode</i>	Specifies the fault delay value for the port number. This operand is required. Valid values are one of the following:
0	Sets the fault delay to R_A_TOV (default)
1	Sets the fault delay to 1.2 seconds.
---help	Displays the command usage.

EXAMPLES To set the fault delay of a port to 1.2 seconds:

```
switch:admin> portcfgfaultdelay 2/3 1
```

To display the configuration

```
switch:admin> portcfgshow 2/3 1
Area Number:          138
Speed Level:          AUTO(HW)
Fill Word:            0(Idle-Idle)
AL_PA Offset 13:     OFF
Trunk Port            ON
Long Distance        OFF
VC Link Init         OFF
Locked L_Port        OFF
Locked G_Port        OFF
Disabled E_Port      OFF
ISL R_RDY Mode       OFF
RSCN Suppressed      OFF
Persistent Disable   OFF
NPIV capability      ON
QOS E_Port           AE
Port Auto Disable:   OFF
```

```

Mirror Port          OFF
F_Port Buffers      OFF
Fault Delay          1(1.2sec)

```

```
switch:admin> portcfgshow
```

```

Ports of Slot 2  0  1  2  3  4  5  6  7  8  9 10 11 12 13 14 15
-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----+-----
Speed           AN AN AN AN  AN AN AN AN  AN AN AN AN  AN AN AN AN
Fill Word       0  0  0  0   0  0  0  0   0  0  0  0   0  0  0  0
AL_PA Offset 13 .. .. .. ..  .. .. .. ..  .. .. .. ..  .. .. .. ..
Trunk Port      ON ON ON ON  ON ON ON ON  ON ON ON ON  ON ON ON ON
Long Distance   .. .. .. ..  .. .. .. ..  .. .. .. ..  .. .. .. ..
VC Link Init    .. .. .. ..  .. .. .. ..  .. .. .. ..  .. .. .. ..
Locked L_Port   .. .. .. ..  .. .. .. ..  .. .. .. ..  .. .. .. ..
Locked G_Port   .. .. .. ..  .. .. .. ..  .. .. .. ..  .. .. .. ..
Disabled E_Port .. .. .. ..  .. .. .. ..  .. .. .. ..  .. .. .. ..
ISL R_RDY Mode  .. .. .. ..  .. .. .. ..  .. .. .. ..  .. .. .. ..
RSCN Suppressed .. .. .. ..  .. .. .. ..  .. .. .. ..  .. .. .. ..
Persistent Disable .. .. .. ..  .. .. .. ..  .. .. .. ..  .. .. .. ..
NPIV capability ON ON ON ON  ON ON ON ON  ON ON ON ON  ON ON ON ON
QOS E_Port      AE AE AE AE  AE AE AE AE  AE AE AE AE  .. .. .. ..
EX Port         .. .. .. ..  .. .. .. ..  .. .. .. ..  .. .. .. ..
Mirror Port     .. .. .. ..  .. .. .. ..  .. .. .. ..  .. .. .. ..
Rate Limit      .. .. .. ..  .. .. .. ..  .. .. .. ..  .. .. .. ..
Credit Recovery ON ON ON ON  ON ON ON ON  ON ON ON ON  ON ON ON ON
Fport Buffers   .. .. .. ..  .. .. .. ..  .. .. .. ..  .. .. .. ..
Port Auto Disable. .. .. .. ..  .. .. .. ..  .. .. .. ..  .. .. .. ..
Fault Delay     0  0  0  1   0  0  0  0   0  0  0  0   0  0  0  0
(output truncated)

```

SEE ALSO **portCfgShow**

Revised commands in Fabric OS v6.4.0

A new configurable parameter has been added to the **configure** command under Fabric Parameters:
In Table 6 on page 133 add the following row:

TABLE 6 Configure command fabric parameters

Field	Type	Default	Range
Edge hold time	Number (seconds)	220	0-500

The description for Edge hold time is as follows:

Configures the maximum time a frame can wait after it is received on the ingress port and before it is delivered to the egress port. If the frame waits in the egress buffer for more than the configured hold time, the switch drops the frame, replenishes sender's credit, and increments the counters `sts_tx_timeout` and `er_c3_timeout` on the TX and RX ports respectively. The frame-timeout indicates a slow draining or a congestion or bottleneck in the fabric. Decreasing hold time on the Edge switches may reduce frame drop counts in the core switches. This parameter is stored persistently in the configuration file. You can configure Edge hold time only on the default switch:

Example:

To configure Edge hold time on a disabled switch:

```
Switch:admin> configure
Configure...

Fabric parameters (yes, y, no, n): [no] yes
  Domain: (1..239) [1]
  R_A_TOV: (4000..120000) [10000]
  E_D_TOV: (1000..5000) [2000]
  WAN_TOV: (0..30000) [0]
  MAX_HOPS: (7..19) [7]
  Data field size: (256..2112) [2112]
  Sequence Level Switching: (0..1) [0]
  Disable Device Probing: (0..1) [0]
  Suppress Class F Traffic: (0..1) [0]
  Per-frame Route Priority: (0..1) [0]
  Long Distance Fabric: (0..1) [0]
  BB credit: (1..27) [16]
  Disable FID Check (yes, y, no, n): [no]
  Insistent Domain ID Mode (yes, y, no, n): [no]
  Configure edge hold time (yes, y, no, n): [no]
  Edge hold time: (100..500) [220]
Virtual Channel parameters (yes, y, no, n): [no]
F-Port login parameters (yes, y, no, n): [no]
Zoning Operation parameters (yes, y, no, n): [no]
RSCN Transmission Mode (yes, y, no, n): [no]
Arbitrated Loop parameters (yes, y, no, n): [no]
System services (yes, y, no, n): [no]
Portlog events enable (yes, y, no, n): [no]
ssl attributes (yes, y, no, n): [no]
rpcd attributes (yes, y, no, n): [no]
webtools attributes (yes, y, no, n): [no]
System (yes, y, no, n): [no]
```


To configure Edge hold time on an enabled switch:

```
Switch:admin> configure
Not all options will be available on an enabled switch.
To disable the switch, use the "switchDisable" command.

Configure...

Fabric parameters (yes, y, no, n): [no] yes

Configure edge hold time (yes, y, no, n): [no] yes
Edge hold time: (100..500) [220]
System services (yes, y, no, n): [no]
ssl attributes (yes, y, no, n): [no]
rpcd attributes (yes, y, no, n): [no]
webtools attributes (yes, y, no, n): [no]
System (yes, y, no, n): [no]
```

3 Command RBAC permissions and AD types

Command RBAC permissions and AD types

Refer to [Table 7](#) for the RBAC and Admin Domain availability of new Fabric OS v6.4.1 commands.

TABLE 7 RBAC availability and admin domain type

Command Name	User	Admin	Operator	Switch Admin	Zone Admin	Fabric Admin	Basic Switch Admin	Security Admin	Admin Domain	Context	Switch Type
bufOpMode	0	OM	OM	OM	0	OM	OM	0	SwitchMember	VF	All
portCfgFaultDelay	0	OM	OM	OM	0	OM	OM	0	PortMember	VF	All

Fabric OS Message Reference Manual

In this chapter

The updates in this chapter are for the *Fabric OS Message Reference*, part number: 53-1001767-01, published March 2010.

- [SULB System Messages](#) 13

SULB System Messages

On page 620, in the SULB System Messages chapter, correct the severity level for the message SULB-1037.

- "Severity - INFO" to be changed to "Severity - ERROR"

4 SULB System Messages

Fabric Watch Administrator's Guide

In this chapter

The updates in this chapter are for the *Fabric Watch Administrator's Guide*, part number: 53-10001770-01, published March 2010.

- [Chapter 1, Fabric Watch notification types](#) 15
- [Chapter 2, Fabric Watch Thresholds](#) 16
- [Chapter 4, Fabric Watch Activation](#) 16

Chapter 1, Fabric Watch notification types

swFabricWatchTrap severity

On page 9, “SNMP traps,” a severity description for “swFabricWatch Trap severity,” is missing. For complete information about the swFabricWatch Trap severity, please refer to the following sections in the *Fabric OS MIB Reference Guide*, part number: 53-1001768-01:

- “Understanding SNMP basics”
- “Loading Brocade MIBs”
- Table 14: SW-MIB Traps

SNMP trap counters

The following SNMP information will be added in the next release of Fabric Watch:

- When a counter is in the “in-between” state, Fabric Watch sends an informational SNMP trap. (See [“In-between buffer values”](#) on page 16 for an explanation of the concepts of “in-between” boundaries and high and low thresholds.)
- When a counter is above the high threshold or below the low threshold, Fabric Watch sends a warning SNMP trap *except* for the power supply area of the environment class, CPU, and memory:
 - The severity of a Fabric Watch SNMP trap for the power supply area of the environment class will always be informational *except* when the counter value is below the low threshold. When the counter value of the power supply is below threshold, Fabric Watch sends a warning SNMP trap.
 - The severity of a Fabric Watch SNMP trap for CPU and memory will always be informational.

Chapter 2, Fabric Watch Thresholds

On page 15 and 16, the sections “High and low thresholds” have been changed to include the following expanded threshold categories:

- Above high threshold
- Below high threshold
- Above low threshold
- Below low threshold

NOTE

The *above low threshold* action applies only to the portThConfig command. It does not apply to the thConfig and sysMonitor commands.

In-between buffer values

The *below high threshold* is the term used to configure “in between” buffer values, as shown below. In this example, the high threshold value is 5 and the buffer value is 1. Therefore, the “in-between” boundary value is 4. Enter the portThConfig command using the following parameters.

```
portthconfig -set port -area crc -highth -value 4 -trigger below -action raslog
```

Above high threshold

Above action = 5

BUFFER = 1

Low action

Below high threshold

In-between

Above low threshold

Above action

BUFFER

Low action

Below low threshold

Chapter 4, Fabric Watch Activation

On page 30 “snmpConfig -set” should appear as “snmpConfig --set” .

DCX Backbone Hardware Reference Manual

In this chapter

The updates in this chapter are for the *DCX Backbone Hardware Reference Manual*, part number: 53-10000685-12, published March 2010.

- [Appendix D, Port Numbering Template](#) 17

Appendix D, Port Numbering Template

In two illustrations the port numbers have been reversed in the tables under each figure.

For Figure 42 for the FC8-32 port blade on page 133, the table under the illustration should read as follows.

- | | | | |
|---|------------------|---|--------------------------------|
| 1 | Blade Power LED | 3 | FC ports 16-31 (bottom to top) |
| 2 | Blade Status LED | 4 | FC ports 0-15 (bottom to top) |

For Figure 43 for the FC8-48 port blade on page 134, the table under the illustration should read as follows.

- | | | | |
|---|------------------|---|--------------------------------|
| 1 | Blade Power LED | 3 | FC ports 24-47 (bottom to top) |
| 2 | Blade Status LED | 4 | FC ports 0-23 (bottom to top) |

6 Appendix D, Port Numbering Template

Brocade 5100 Hardware Reference Manual

In this chapter

The updates in this chapter are for the *Brocade 5100 Hardware Reference Manual*, part number: 53-10000854-02, published July 2008.

- [Chapter 3, Brocade 5100 Operation](#) 19

Chapter 3, Brocade 5100 Operation

For Table 1 on page 19, replace the first row, with the LED Name Power Supply Status (right) with the following row.

LED Name	LED Color	Status of Hardware	Recommended Action
Power Supply Status	No light	Primary power cord is disconnected or is not actively powered, or power supply has failed.	Verify the power supply is on and seated and the power cord is connected to a functioning power source.
	Steady green	Power supply is operating normally.	No action required.
	Flashing green	A power supply and fan assembly fault has occurred for one of the following reasons: <ul style="list-style-type: none"> • The power supply or fan in the assembly has failed. • The FRU was disabled by a user. • The FRU power switch has been turned off or the unit has been unplugged. 	Take one of the following actions: <ul style="list-style-type: none"> • Replace the FRU. • Verify that the power supply/fan assembly FRU has been enabled. • Check the power switch and plug.

LED Name	LED Color	Status of Hardware	Recommended Action
Port Status	No light	No signal or light carrier (media or cable) detected.	Check transceiver and cable.
	Slow flashing green (flashing in two-second intervals)	Port is online but segmented because of a loopback cable or incompatible switch connection.	No action required.
	Fast flashing green (flashing in half-second intervals)	Port is online and an internal loopback diagnostic test is running.	No action required.
	Flickering green (steady with random flashes)	Port is online and frames are flowing through the port.	No action required.
	Steady green	Port is online (connected to external device) but has no traffic.	No action required.
	Slow flashing amber (flashing in two-second intervals)	Port is disabled (because of diagnostics or the portDisable command).	Verify the diagnostic tests are not running. Reenable the port using the portEnable command.
	Fast flashing amber (flashing in half-second intervals)	Port is faulty.	Check the management interface and the error log for details on the cause of status. Contact Technical Support if required.
	Steady amber (for more than five seconds)	Port is receiving light or signal carrier at 4 Gbps; but is not yet online.	No action required.