

# Dell System S4048T-ON 9.14(2.14) Release Notes

This document contains information on open and resolved caveats, and operational information specific to the Dell Networking OS software and the S4048T-ON platform.


**Current Release Version:** 9.14(2.14)

**Release Date:** 2022-04-15

**Previous Release Version:** 9.14(2.12)

Topics:

- [Document Revision History](#)
- [Supported Hardware](#)
- [Supported Software](#)
- [New Dell Networking OS Version 9.14\(2.14\) Features](#)
- [Restrictions](#)
- [Changes to Default Behavior and CLI Syntax](#)
- [Documentation Corrections](#)
- [Deferred Issues](#)
- [Fixed Issues](#)
- [Known Issues](#)
- [Upgrading the sub-components](#)
- [Upgrading the ONIE Package for the S4048T-ON System](#)
- [Upgrading the DIAG Package for the S4048T-ON System](#)
- [Installing Dell Networking OS on the S4048T-ON using ONIE](#)
- [Support Resources](#)

 **NOTE:** This document may contain language that is not consistent with current guidelines of Dell Technologies. There are plans to update this document over subsequent releases to revise the language accordingly.

Incorrect behavior or unexpected caveats are listed as the Problem Report (PR) numbers within the appropriate sections.

For more information on hardware and software features, commands, and capabilities, see the Dell Networking website at: <https://www.dellemc.com/networking>.

## Document Revision History

**Table 1. Revision History**

Date	Description
2022-04	Initial release.

## Supported Hardware

The following hardware is supported with this platform:

Hardware
Forty-eight fixed 10GBase-T ports supporting 1G/10G speeds

Hardware
Six fixed QSFP+ ports supporting either one port of 40G or four ports of 10G in breakout mode
Two PSUs
Four fan modules
One MicroUSB serial console port
One universal serial bus (USB Type-A) port for additional file storage
Management Ethernet interface
RS-232 Serial interface
Dual core 1.7GHz Rangeley central processing unit (CPU) system
Temperature monitoring
Software-readable thermal monitor
Real time clock (RTC) support
Two hot pluggable redundant power supplies
Power management monitoring
Four removable fans
Standard 1U chassis

The following lists the individual Dell S4048T-ON system hardware components that are available to order:

**Table 2. Hardware Components Available to Order**

Fan with airflow from I/O side to PSU side (red — normal air flow direction)
Fan with airflow from PSU side to I/O side (blue — reversed air flow direction)
AC or DC power supply with airflow from I/O side to PSU side
AC or DC power supply with airflow from PSU side to I/O side

**NOTE:** Fan modules and power supplies are field replaceable units.

**NOTE:** All fans and PSUs must have the same airflow direction. If you mix the airflow direction, the switch detects the discrepancy, issues an alarm, and may auto-shutdown to avoid heat damage to components. You must correct the mixed airflow direction.

## Supported Software

The following software is supported with this platform:

Software	Minimum Release Requirement
Dell Networking OS	9.14(2.14)

Software	Minimum Release Requirement
ONIE	3.27.1.10-0

**NOTE:** For information on non-Dell OS versions, see the Release Notes for the Hardware Platform S4048T-ON.

## New Dell Networking OS Version 9.14(2.14) Features

The following features are integrated into the Dell Networking 9.14.2 branch through this release:

None

## Restrictions

- You can use non-Dell qualified cables, adapters, and optics in a S4048T-ON switch, but Dell Networking does not guarantee their performance as the S4048T-ON does not support non-Dell qualified transceivers of 25G and above. If you insert a non-Dell qualified transceiver of 25G and above into a SFP28, QSFP+, or QSFP28 port, the switch places the interface in an error-disabled (operationally down) state and generates a syslog message, such as: %S4048TLC0640:8 %IFAGT-2-TRANSCIEVER\_UNSUPPORTED\_ERROR: Transceiver in slot 1 port 49 unrecognized, putting interface in operational-down state.

To verify the error-disabled status of an interface, enter any of the following show commands.

```
Dell# show inventory media
Slot      Port      Type      Media      Serial Number      DellQualified
-----
 1         49      UNKNOWN   UNKNOWN     USC1D6J             No**
 1         50      QSFP      40GBASE-LR4  UQ90C7B             No**
 1         51      QSFP      40GBASE-SR4  7503835V009Y       Yes
 1         52      QSFP      40GBASE-CR4  10190002            No
 1         53      QSFP      40GBASE-SR4  FE2429470007       Yes
 1         54                        Media not present or accessible
** Interface is down(error disabled) as transceiver is not DellQualified

Dell# show interfaces fortyGigE 1/49
fortyGigE 1/49 is up, line protocol is down (error-disabled[Transceiver Unsupported])
...
```

- Prerequisite steps to upgrade the Dell Networking OS from earlier version to 9.14.2.0 or later:
  1. Uninstall the older version of the Open Automation (OA) package
  2. Upgrade the Dell Networking OS to 9.14.2.0 or later version
  3. Install the following OA packages from the respective upgraded version:
    - a. SmartScripts
    - b. Puppet
    - c. Open management infrastructure (OMI)
    - d. SNMP MIB

Prerequisite steps to downgrade the Dell Networking OS from 9.14.2.0 or later to the earlier version:

1. Uninstall the OA package of 9.14.2.0 or later version
2. Downgrade the Dell Networking OS to an earlier version
3. Install the respective OA package from an earlier version

For more information about installing, uninstalling and upgrading the Dell Networking OS and OA package, refer the respective *Dell System Release Notes*.

- If you downgrade the Dell Networking OS version from 9.14.2.14 to 9.11.0.0 or any older versions, the system displays the following error message even though there is no functional impact:

```
CDB boot error:      C.cdb file format
```

Before downgrading, save the current configuration and then remove the CDB files (`confd_cdb.tar.gz.version` and `confd_cdb.tar.gz`). To remove the files, use the following steps:

```
DellEMC#write memory
DellEMC#delete flash://confd_cdb.tar.gz.version
DellEMC#delete flash://confd_cdb.tar.gz
DellEMC#reload
```

- In a VXLAN scenario, hybrid port is not supported.
- While deploying the system in the normal-reload mode in BMP configuration, use the `ip ssh server enable` command at the beginning of the startup configuration if the write memory command is used at the end of the configuration.
- The following features are not available in the Dell Networking OS from version 9.7(0.0):
  - PIM ECMP
  - Static IGMP join (`ip igmp static-group`)
  - IGMP querier timeout configuration (`ip igmp querier-timeout`)
  - IGMP group join limit (`ip igmp group join-limit`)
- You can use the `negotiation auto` command to turn auto-negotiation on or off only on fiber interfaces operating at 1G speed.
- If you use the `interface range` command to select multiple interfaces that are added to the management VRF, the `ipv6 address` command does not display the `autoconfig` option. You can configure the `autoconfig` command on individual interfaces.
- If you use the `interface range` command to select multiple interfaces that are added to the management VRF, the `ipv6 nd` command displays the following options but they do not take effect if you use them:
  - `dns-server`
  - `hop-limit`
  - `managed-config-flag`
  - `max-ra-interval`
  - `mtu`
  - `other-config-flag`
  - `prefix`
  - `ra-guard`
  - `ra-lifetime`
  - `reachable-time`
  - `retrans-timer`
  - `suppress-ra`
- REST API does not support AAA authentication.
- Do not configure the `vxlan-instance` command on the port, which is configured with the `portmode hybrid` command. Do not configure the vxlan-instance enabled port as a member of VLAN, which does not have VXLAN-VNI configuration.
- Half-Duplex mode is not supported.
- When FRRP is enabled in a VLT domain, no flavor of Spanning tree should concurrently be enabled on the nodes of that specific VLT domain. In essence FRRP and xSTP should not co-exist in a VLT environment.

## Changes to Default Behavior and CLI Syntax

The following behavior and CLI changes are applicable to the S4048T-ON switch with Dell Networking OS version 9.14(2.14):

None

## Documentation Corrections

This section describes the errors identified in the current release of the Dell Networking OS.

- The `router bgp` command allows you to configure only one L3 interface with an IPv4 address. The Configuration guide does not mention this limitation and will be corrected in the next release of the guide.

# Deferred Issues

Issues that appear in this section were reported in Dell Networking OS version 9.14(2.0) as open, but have since been deferred. Deferred caveats are those that are found to be invalid, not reproducible, or not scheduled for resolution.

Deferred issues are reported using the following definitions.

Category	Description
<b>PR#</b>	Problem Report number that identifies the issue.
<b>Severity</b>	<b>S1</b> — Crash: A software crash occurs in the kernel or a running process that requires a restart of AFM, the router, switch, or process. <b>S2</b> — Critical: An issue that renders the system or a major feature unusable, which can have a pervasive impact on the system or network, and for which there is no work-around acceptable to the customer. <b>S3</b> — Major: An issue that affects the functionality of a major feature or negatively effects the network for which there exists a work-around that is acceptable to the customer. <b>S4</b> — Minor: A cosmetic issue or an issue in a minor feature with little or no network impact for which there might be a work-around.
<b>Synopsis</b>	Synopsis is the title or short description of the issue.
<b>Release Notes</b>	Release Notes description contains more detailed information about the issue.
<b>Work around</b>	Work around describes a mechanism for circumventing, avoiding, or recovering from the issue. It might not be a permanent solution.  Issues listed in the "Closed Caveats" section should not be present, and the work-around is unnecessary, as the version of code for which this release note is documented has resolved the caveat.

## Deferred S4048T-ON 9.14(2.0) Software Issues

Issues that appear in this section were reported in Dell Networking OS version 9.14(2.0) as open, but have since been deferred. Deferred caveats are those that are found to be invalid, not reproducible, or not scheduled for resolution.

The following issues have been deferred in the Dell Networking OS version 9.14(2.0):

None.

# Fixed Issues

Fixed issues are reported using the following definitions.

Category	Description
<b>PR#</b>	Problem Report number that identifies the issue.
<b>Severity</b>	<b>S1</b> — Crash: A software crash occurs in the kernel or a running process that requires a restart of AFM, the router, switch, or process. <b>S2</b> — Critical: An issue that renders the system or a major feature unusable, which can have a pervasive impact on the system or network, and for which there is no work-around acceptable to the customer. <b>S3</b> — Major: An issue that affects the functionality of a major feature or negatively effects the network for which there exists a work-around that is acceptable to the customer. <b>S4</b> — Minor: A cosmetic issue or an issue in a minor feature with little or no network impact for which there might be a work-around.
<b>Synopsis</b>	Synopsis is the title or short description of the issue.
<b>Release Notes</b>	Release Notes description contains more detailed information about the issue.

Category	Description
Work around	Work around describes a mechanism for circumventing, avoiding, or recovering from the issue. It might not be a permanent solution.  Issues listed in the “Closed Caveats” section should not be present, and the work-around is unnecessary, as the version of code for which this release note is documented has resolved the caveat.

## Fixed S4048T–ON 9.14(2.14) Software Issues

**NOTE:** Dell Networking OS 9.14(2.14) includes fixes for caveats addressed in the previous 9.14 releases. Refer to the respective release notes documentation for the list of caveats fixed in the earlier 9.14 releases.

The following caveats have been fixed in Dell Networking OS version 9.14(2.14):

### PR# 170114

<b>Severity:</b>	Sev 2
<b>Synopsis:</b>	The switch experiences memory leaks when processing certain types of packets.
<b>Release Notes:</b>	The switch experiences memory leaks when processing certain types of packets.
<b>Workaround:</b>	None

### PR# 170232

<b>Severity:</b>	Sev 2
<b>Synopsis:</b>	The switch sends deprecated VRRP traps.
<b>Release Notes:</b>	The switch sends deprecated VRRP traps.
<b>Workaround:</b>	None

### PR# 170301

<b>Severity:</b>	Sev 3
<b>Synopsis:</b>	The <code>BN_mod_sqrt()</code> function, which computes a modular square root, contains a bug that can cause it to loop forever for non-prime moduli (CVE-2022-0778).
<b>Release Notes:</b>	The <code>BN_mod_sqrt()</code> function, which computes a modular square root, contains a bug that can cause it to loop forever for non-prime moduli (CVE-2022-0778).
<b>Workaround:</b>	None

## Known Issues

Known issues are reported using the following definitions.

Category	Description
PR#	Problem Report number that identifies the issue.
Severity	<b>S1</b> — Crash: A software crash occurs in the kernel or a running process that requires a restart of AFM, the router, switch, or process.

<b>Category</b>	<b>Description</b>
	<p><b>S2</b> — Critical: An issue that renders the system or a major feature unusable, which can have a pervasive impact on the system or network, and for which there is no work-around acceptable to the customer.</p> <p><b>S3</b> — Major: An issue that affects the functionality of a major feature or negatively effects the network for which there exists a work-around that is acceptable to the customer.</p> <p><b>S4</b> — Minor: A cosmetic issue or an issue in a minor feature with little or no network impact for which there might be a work-around.</p>
<b>Synopsis</b>	Synopsis is the title or short description of the issue.
<b>Release Notes</b>	Release Notes description contains more detailed information about the issue.
<b>Work around</b>	<p>Work around describes a mechanism for circumventing, avoiding, or recovering from the issue. It might not be a permanent solution.</p> <p>Issues listed in the “Closed Caveats” section should not be present, and the work-around is unnecessary, as the version of code for which this release note is documented has resolved the caveat.</p>

## Known S4048T-ON 9.14(2.14) Software Issues

The following caveats are open in Dell Networking OS version 9.14(2.14):

None

## Upgrading the sub-components

It is recommended to upgrade the sub-components in the following order and reload the switch where necessary, before proceeding with the next sub-component upgrade.

1. [Upgrade the BIOS or Boot-selector](#) - using the `upgrade boot bootselector-image stack-unit 1 booted` command.
2. [Upgrade the GRUB or Bootflash](#) - using the `upgrade boot bootflash-image stack-unit 1 booted` command.
3. [Upgrade the CPLD](#) - using the `upgrade fpga-image system cpld stack-unit 1 booted` command.

## Upgrade the BIOS or Boot Selector

To upgrade the BIOS or Boot Selector from Dell Networking OS, perform the following steps:

1. Upgrade the S4048T-ON Boot Selector image.

EXEC Privilege Mode

```
upgrade boot bootselector-image stack-unit [<id> | all]
```

Dell Networking OS version 9.14(2.14) requires S4048T-ON Boot Selector image version 3.27.0.0-4 or higher. The booted option is used to upgrade the Boot Selector image to the image version packed with the loaded Dell Networking OS image. The Boot Selector image version packed with the loaded Dell Networking OS can be found using the `show os-version` command in EXEC Privilege mode.

```
DellEMC#upgrade boot bootselector-image stack-unit 1 booted

Current Boot information in the system:
=====
Card                BootSelector      Current Version   New Version
-----
Unit1              Boot Selector     3.27.0.2          3.27.0.0-4

*****
* Warning - Upgrading boot selectors is inherently risky and should *
* only be attempted when necessary. A failure at this upgrade may *
* cause a board RMA. Proceed with caution !                          *
*****
```

```

Proceed upgrade Boot Selector image for stack-unit 1 [yes/no]: y

!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
Bootselector image upgrade for stack-unit 1 completed successfully.
DellEMC#

```

2. Reload the unit.

```

EXEC Privilege Mode
reload

```

3. Verify the Boot Selector image.

```

EXEC Privilege Mode
show system stack-unit <id>

```

```

DellEMC#show system stack-unit 1

-- Unit 1 --
Unit Type           : Management Unit
Status              : online
Next Boot           : online
Required Type       : S4048T-ON - 48x10G, 6x40G TE/FO G (S4048T-ON)
Current Type        : S4048T-ON - 48x10G, 6x40G TE/FO G (S4048T-ON)
Master priority     : 14
Hardware Rev        : 2.0
Num Ports           : 72
Up Time             : 1 hr, 14 min
Dell EMC Networking OS Version : 9.14(2.14)
Jumbo Capable       : yes
POE Capable         : no
FIPS Mode           : disabled
Boot Flash          : 3.27.2.10
Boot Selector       : 3.27.0.0-4
Memory Size         : 3181805568 bytes
Temperature         : 33C
Voltage             : ok
Serial Number       : NA
Part Number         : 0YVCK0      Rev A00
Vendor Id           : DL
Date Code           : 02212022
Country Code        : CN
Piece Part ID       : CN-0YVCK0-28298-6BM-0080
PPID Revision       : A00
Service Tag         : 34P0Y42
Expr Svc Code       : 681 424 632 2
Auto Reboot         : enabled
Burned In MAC       : f4:8e:38:2b:3e:85
No Of MACs          : 3

```

```

-- Power Supplies --
Unit  Bay  Status      Type      FanStatus  FanSpeed (rpm)
-----
  1     1    up             AC        up         14688
  1     2    down          UNKNOWN  down         0

```

```

-- Fan Status --
Unit  Bay  TrayStatus  Fan1    Speed  Fan2    Speed
-----
  1     1     up          up      7840   up      7546
  1     2     up          up      7840   up      7546
  1     3     up          up      7840   up      7546
  1     4     up          up      7840   up      7546

```

Speed in RPM

## Upgrade the GRUB or Boot Flash

To upgrade the GRUB or Boot Flash from Dell Networking OS, perform the following steps:

1. Upgrade the S4048T-ON Boot Flash image.

EXEC Privilege Mode

```
upgrade boot bootflash-image stack-unit [<id> | all] [booted | flash: | ftp: | scp: |  
tftp: | usbflash:]
```

```
DellEMC#  
DellEMC#upgrade boot bootflash-image stack-unit 1 booted  
  
Current Boot information in the system:  
=====
```

Card	BootFlash	Current Version	New Version
Unit1	Boot Flash	3.27.2.3	3.27.2.10

```
-----  
*****  
* Warning - Upgrading boot flash is inherently risky and should only *  
* be attempted when necessary. A failure at this upgrade may cause *  
* a board RMA. Proceed with caution ! *  
*****  
  
Proceed upgrade Boot Flash image for stack-unit 1 [yes/no]: y  
  
Bootflash image upgrade for stack-unit 1 completed successfully.  
DellEMC#
```

## Upgrade the CPLD

The S4048T-ON system with Dell Networking OS Version 9.14(2.14) requires System CPLD revision 12 and Master CPLD revision 13.

**i** **NOTE:** If your CPLD revisions are higher than the ones shown here, DO NOT make any changes. If you have questions regarding the CPLD revision, contact technical support.

## Verify that a CPLD upgrade is required

Use the following command to identify the CPLD version:

```
DellEMC#show revision  
  
-- Stack unit 1 --  
S4048TON SYSTEM CPLD : 12  
S4048TON MASTER CPLD : 13  
  
DellEMC#
```

Use the following command to view CPLD version that is associated with the Dell Networking OS image:

```
DellEMC#show os-version  
  
RELEASE IMAGE INFORMATION :  
-----  
Platform      Version      Size      ReleaseTime  
S-Series:S4048T-ON  9.14(2.14)  66927711  Feb 21 2022 17:17:19  
  
TARGET IMAGE INFORMATION :  
-----  
Type      Version      Target      checksum  
runtime   9.14(2.14)   Control Processor  passed  
  
BOOT IMAGE INFORMATION :  
-----
```

Type	Version	Target	checksum
boot flash	3.27.2.10	Control Processor	passed

BOOTSEL IMAGE INFORMATION :

---

Type	Version	Target	checksum
boot selector	3.27.0.0-4	Control Processor	passed

FPGA IMAGE INFORMATION :

---

Card	FPGA Name	Version
stack-unit 1	S4048TON SYSTEM CPLD	12
stack-unit 1	S4048TON MASTER CPLD	13

DellEMC#

## Upgrading the CPLD Image

**NOTE:** The upgrade `fpga-image stack-unit 1 booted` command is hidden when using the FPGA Upgrade feature in the CLI. However, it is a supported command and will be accepted when entered as documented.

To upgrade the CPLD image on S4048T-ON, follow these steps:

1. Upgrade the CPLD image.

EXEC Privilege Mode

```
upgrade fpga-image stack-unit <id> booted
```

```
DellEMC#upgrade fpga-image stack-unit 1 booted

Current information for the system:
=====
  Card                Device Name          Current Version      New Version
-----
Unit1                 S4048TON SYSTEM CPLD      12                   12
Unit1                 S4048TON MASTER CPLD     13                   13

*****
* Warning - Upgrading FPGA is inherently risky and should          *
* only be attempted when necessary. A failure at this upgrade may  *
* cause a board RMA. Proceed with caution !                        *
*****

Upgrade image for stack-unit 1 [yes/no]: yes

FPGA upgrade in progress!!! Please do NOT power off the unit!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!

Upgrade result :
=====
Unit 1 FPGA upgrade successful Unit 1. Please power cycle to take effect.

DellEMC#Feb 21 06:35:00: %S4048T-ON:1 %DOWNLOAD-6-FPGA_UPGRADE: stack-unit 1 fpga
upgrade success.

DellEMC#
```

2. Power cycle the system physically. Switch off the system by unplugging the power chords from the REAR PSUs and wait until the PSU FAN-REAR STATUS LED is completely OFF.

**NOTE:** Do not switch on the system with PSU-REAR LED glowing AMBER.

You can alternatively power cycle the switch using the `power-cycle stack-unit <1-6>` command as follows:

```
DellEMC#power-cycle stack-unit 1
Proceed with power-cycle? Confirm [yes/no]:yes
```

3. The CPLD version can be verified using `show revision` command output:

EXEC Privilege Mode

`show revision`

```
DellEMC#sh revision

-- Stack unit 1 --
S4048TON SYSTEM CPLD      : 12
S4048TON MASTER CPLD     : 13

DellEMC#
```

**NOTE:** Do not power off the system while FPGA upgrade is in progress. For any queries, contact technical support.

## Upgrading the ONIE Package for the S4048T-ON System

To upgrade the ONIE package you have installed, use one of the following two processes: zero touch (dynamic) update or manual update.

- Zero touch (dynamic): Copy the update ONIE installer for your system to the TFTP/HTTP server. Configure the DHCP options using the ONIE specifications shown at the following link: <https://github.com/opencomputeproject/onie/wiki/Design-Spec-SW-Updating-ONIE>.
- Manual: Copy the image onto the TFTP/HTTP servers and boot ONIE. Update the ONIE using the `onie-self-update` command, then download and run an ONIE updater image (`onie-updater-x86_64-s4048t_c2338-r0`). The supported URL types are: HTTP, FTP, TFTP, and FILE.

To upgrade ONIE, perform the following steps:

1. Reboot the system. During the reboot process, the system displays the following message prompting you to press the Esc key in order to stop the auto-boot process:

```
Press Esc to stop autoboot ... 5
Grub 2.02~beta2 (Dell EMC)
Built by root at ubuntu on Mon_Feb_21_06:23:40_UTC_2022
```

2. At this prompt message, press the Esc key. The following menu appears:

```
Grub 2.02~beta2 (Dell EMC)
Built by root at ubuntu on Mon_Feb_21_07:13:20_UTC_2022

+-----+
| Dell EMC Networking OS                               |
| Dell EMC-Boot Line Interface                         |
| DIAG-OS                                             |
| *ONIE                                              |
|                                                     |
|                                                     |
|                                                     |
+-----+

Use the ^ and v keys to select which entry is highlighted.
Press enter to boot the selected OS, 'f' to boot FTOS, 'b' to go to
BLI, 'o' to boot ONIE, 'd' to boot DIAG-OS, 'e' to edit the commands
before booting or 'c' for a command-line.
```

3. From the menu, choose the ONIE option.

**NOTE:** To choose an option from the menu, highlight one of the options using the up or down arrow key and press Enter.

The following menu appears:

```
GNU GRUB version 2.02~beta2+e4a1fe391

+-----+
| ONIE: Install OS
| ONIE: Rescue
| ONIE: Uninstall OS
| *ONIE: Update ONIE
| ONIE: Embed ONIE
| EDA-DIAG
|
|
|
+-----+

Use the ^ and v keys to select which entry is highlighted.
Press enter to boot the selected OS, `e' to edit the commands
before booting or `c' for a command-line.
```

4. From this menu, choose the ONIE : Update ONIE option.

**NOTE:** To choose an option from the menu, highlight one of the options using the up or down arrow key and press Enter.

The ONIE update mode is enabled and the ONIE prompt appears, as shown:

```
ONIE: ONIE Update Mode ...
Version : 3.27.1.10-0
Build Date: 2022-02-21T09:43-0700
Info: Mounting kernel filesystems... done.
Info: Mounting LABEL=ONIE-BOOT on /mnt/onie-boot ...
Info: Using eth0 MAC address: 00:a0:c9:00:00:36
Info: Using eth1 MAC address: 00:a0:c9:00:00:37
Info: eth0: Checking link... up.
Info: Trying DHCPv4 on interface: eth0
DHCPv4 on interface: eth0 failedONIE: Using default IPv4 addr: eth0:
192.168.3.10/255.255.255.0
Info: eth1: Checking link... down.
ONIE: eth1: link down. Skipping configuration.
ONIE: Failed to configure eth1 interface
Starting: dropbear ssh daemon... done.
Starting: telnetd... done.
discover: ONIE update mode detected. Running updater.
Starting: discover... done.

Please press Enter to activate this console. Info: eth0: Checking link... up.
Info: Trying DHCPv4 on interface: eth0

ONIE:/ #
```

5. At the ONIE prompt, to stop the ONIE discovery process, enter the following command:

```
ONIE:/ # onie-discovery-stop
```

The ONIE discovery stops, as shown:

```
discover: ONIE update mode detected.
Stopping: discover... done.
ONIE:/ #
ONIE:/ #
```

6. Configure an interface and assign an IP address to that interface using the following command:

```
ONIE:/ # ifconfig eth0 10.16.133.213/16
```

Enter the following command to upgrade ONIE:ONIE:/ # onie-self-update tftp://<tftp-server-address>/onie-updater-x86\_64-s4048t\_c2338-r0

 **NOTE:** You must copy the `onie-updater-x86_64-s4048t_c2338-r0` file to the `/tftpboot` folder in the server.

ONIE is updated on the system, as shown:

```
ONIE:/ # onie-self-update tftp://10.16.127.86/tftpboot/onie-updater-x86_64-
s4048t_c2338-r0
discover: ONIE update mode detected.
Stopping: discover... done.
Info: Fetching tftp://10.16.127.86/tftpboot/onie-updater-x86_64-s4048t_c2338-r0 ...
Eswar/onie-updater-x 100% |*****| 8561k 0:00:00 ETA
ONIE: Executing installer: tftp://10.16.127.86/tftpboot/onie-updater-x86_64-
s4048t_c2338-r0
Verifying image checksum ... OK.
Preparing image archive ... OK.
ONIE: Version      : 3.27.1.10-0
ONIE: Architecture : x86_64
ONIE: Machine      : s4048t_c2338
ONIE: Machine Rev  : 0
ONIE: Config Version: 1
Installing ONIE on: /dev/sda
Rebooting...
ONIE:/ # discover: ONIE update mode detected.
Stopping: discover...start-stop-daemon: warning: killing process 533: No such process
done.
Stopping: dropbear ssh daemon... done.
Stopping: telnetd... done.
Stopping: syslogd... done.
Info: Unmounting kernel filesystems
The system is going down NOW!
Sent SIGTERM to all processes
Sent SIGKILL tosd 4:0:0:0: [sda] Synchronizing SCSI cache
Restarting system.
machine restart
```

## Upgrading the DIAG Package for the S4048T-ON System

To upgrade the DIAG package, use one of the following two processes:

- Zero touch (dynamic): Copy the update ONIE installer for your system to the TFTP/HTTP server. Configure the DHCP options using the ONIE specifications shown at the following link: <https://github.com/opencomputeproject/onie/wiki/Design-Spec-SW-Updating-ONIE>.
- Manual: Copy the image onto the TFTP/HTTP servers and boot ONIE. Update the ONIE using the `onie-self-update` command, then download and run an ONIE updater image (`diag-installer-x86_64-s4048t_c2338-r0.bin`). The supported URL types are: HTTP, FTP, TFTP, and FILE.

To upgrade DIAG, perform the following steps:

1. Reboot the system. During the reboot process, the system displays the following message prompting you to press the Esc key in order to stop the auto-boot process:

```
Press Esc to stop autoboot ... 5
Grub 2.02~beta2 (Dell EMC)
  Built by root at ubuntu on Mon_Feb_21_13:04:17_UTC_2022
```

2. At this prompt message, press the Esc key. The following menu appears:

```
Grub 2.02~beta2 (Dell EMC)
  Built by root at ubuntu on Mon_Feb_21_13:04:17_UTC_2022
  +-----+
  | Dell EMC Networking OS                               |
  | Dell EMC-Boot Line Interface                       |
  | DIAG-OS                                            |
  | *ONIE                                             |
  |                                                    |
  |                                                    |
  |                                                    |
```

```
|
|-----+
Use the ^ and v keys to select which entry is highlighted.
Press enter to boot the selected OS, 'f' to boot FTOS, 'b' to go to
BLI, 'o' to boot ONIE, 'd' to boot DIAG-OS, 'e' to edit the commands
before booting or 'c' for a command-line.
```

3. From the menu, choose the ONIE option.

**NOTE:** To choose an option from the menu, highlight one of the options using the up or down arrow key and press Enter.

The following menu appears:

```
GNU GRUB version 2.02~beta2+e4a1fe391

+-----+
| *ONIE: Install OS
| ONIE: Rescue
| ONIE: Uninstall OS
| ONIE: Update ONIE
| ONIE: Embed ONIE
| EDA-DIAG
|
|-----+
Use the ^ and v keys to select which entry is highlighted.
Press enter to boot the selected OS, `e' to edit the commands
before booting or `c' for a command-line.
```

4. From this menu, choose the ONIE : Install OS option.

**NOTE:** To choose an option from the menu, highlight one of the options using the up or down arrow key and press Enter.

The ONIE Installer mode is enabled and the ONIE prompt appears, as shown:

```
GRUB loading.
ONIE: OS Install Mode ...
Version : 3.27.1.10-0
Build Date: 2022-02-21T09:43-0700
Info: Mounting kernel filesystems... done.
Info: Mounting LABEL=ONIE-BOOT on /mnt/onie-boot ...
Info: Using eth0 MAC address: 00:a0:c9:00:00:36
Info: Using eth1 MAC address: 00:a0:c9:00:00:37
Info: eth0: Checking link... up.
Info: Trying DHCPv4 on interface: eth0
Info: eth1: Checking link...down.
ONIE: eth1: link down. Skipping configuration.
ONIE: Failed to configure eth1 interface
Starting: dropbear ssh daemon... done.
Starting: telnetd... done.
discover: installer mode detected. Running installer.
Starting: discover... done.
ONIE:/ #
```

5. At the ONIE prompt, to stop the ONIE discovery process, enter the following command:

```
ONIE:/ # onie-discovery-stop
```

The ONIE discovery stops, as shown:

```
ONIE:/ # onie-discovery-stop
discover: installer mode detected.
```

```
Stopping: discover... done.
ONIE:/ #
```

6. Configure an interface and assign an IP address to that interface using the following command:

```
ONIE:/ # ifconfig eth0 10.16.133.213/16
```

Enter the following command to upgrade DIAG on the S4048T-ON system: `onie-nos-install tftp://<tftp-server-address>/tftpboot/diag-installer-x86_64-s4048t_c2338-r0.bin`

**NOTE:** You must copy the `diag-installer-x86_64-s4048t_c2338-r0.bin` file to the `/tftpboot` folder in the server.

The DIAG is updated on the system, as shown:

```
ONIE:/ # onie-nos-install tftp://10.16.127.86/diag-installer-x86_64-s4048t_c2338-r0.bin
discover: installer mode detected.
Stopping: discover... done.
Info: Fetching tftp://10.16.127.86/diag-installer-x86_64-s4048t_c2338-r0.bin ...
Eswar/diag-installer 100% |*****| 148M 0:00:00 ETA
ONIE: Executing installer: tftp://10.16.127.86/diag-installer-x86_64-s4048t_c2338-r0.bin
Ignoring Verifying image checksum ... OK.
cur_dir / archive_path /installer tmp_dir /tmp/tmp.a5Kpax
Preparing image archive ...sed -e '1,/^\^exit_marker$/d' /installer | tar xf - OK.
Diag-OS Installer: platform: x86_64-s4048t_c2338-r0
Found EDA-DIAG partition at (/dev/sda3)
/tmp/diag_os_install_mode does not exist, installer would run in update mode

Diag OS Installer Mode : UPDATE

EDA-DIAG dev is /dev/sda3

Mounted /dev/sda3 on /tmp/tmp.jZpckM
Update mode: Copying rootfs.....

Preparing /dev/sda3 EDA-DIAG for rootfs install
untaring into /tmp/tmp.jZpckM

rootfs copy done
Success: Support tarball created: /tmp/tmp.jZpckM/onie-support.tar.bz2

INSTALLER DONE...
Removing /tmp/tmp.a5Kpax
Rebooting...
ONIE:/ # discover: installer mode detected.
Stopping: discover...start-stop-daemon: warning: killing process 546: No such process
done.
Stopping: dropbear ssh daemon... done.
Stopping: telnetd... done.
Stopping: syslogd... done.
Info: Unmounting kernel filesystems
The system is going down NOW!
Sent SIGTERM to all processes
Sent SIGKILL tosd 4:0:0:0: [sda] Synchronizing SCSI cache
Restarting system.
machine restart
```

## Installing Dell Networking OS on the S4048T-ON using ONIE

**NOTE:** You will need the Dell Networking OS installer package, `ONIE-FTOS-SK-9.14.2.14.bin` to install the Dell Networking OS on your S4048T-ON system that has only ONIE.

To install the Dell Networking OS version 9.14(2.14) on a new S4048T-ON device, perform the following steps:

1. Reboot the system. During the reboot process, the system displays the following message prompting you to press the Esc key in order to stop the auto-boot process:

```
Press Esc to stop autoboot ... 5

Grub 2.02~beta2 (Dell EMC Inc)
Built by root at ubuntu on Mon_Feb_21_13:04:17_UTC_2022
S4048T Boot Flash Label 3.27.2.10 NetBoot Label 3.27.2.10
```

2. At this prompt message, press the Esc key. The following menu appears:

```
GNU GRUB version 2.02~beta2+e4a1fe391

+-----+
|DELL                                     |
|DELL-Boot Line Interface                 |
|DIAG-OS                                  |
|ONIE                                     |
|                                         |
+-----+

Use the ^ and v keys to select which entry is highlighted.
Press enter to boot the selected OS, 'f' to boot FTOS, 'b' to go to
BLI, 'o' to boot ONIE, 'd' to boot DIAG-OS, 'e' to edit the commands
before booting or 'c' for a command-line.
```

3. From the menu, choose the ONIE option.

**i** **NOTE:** To choose an option from the menu, highlight one of the options using the up or down arrow key and press Enter.

The following menu appears:

```
GNU GRUB version 2.02~beta2+e4a1fe391

+-----+
|*ONIE: Install OS                       |
| ONIE: Rescue                           |
| ONIE: Uninstall OS                     |
| ONIE: Update ONIE                      |
| ONIE: Embed ONIE                       |
| EDA-DIAG                               |
|                                         |
+-----+

Use the ^ and v keys to select which entry is highlighted.
Press enter to boot the selected OS, `e' to edit the commands
before booting or `c' for a command-line.
```

4. From this menu, choose the ONIE : Install OS option.

**i** **NOTE:** To choose an option from the menu, highlight one of the options using the up or down arrow key and press Enter.

The ONIE Installer mode is enabled and the ONIE prompt appears, as shown:

```
ONIE: OS Install Mode ...
Version : 3.27.1.10-0
Build Date: 2022-02-21T09:43-0700
Info: Mounting kernel filesystems... done.
Info: Mounting LABEL=ONIE-BOOT on /mnt/onie-boot ...
Info: Using eth0 MAC address: 00:a0:c9:00:00:36
Info: Using eth1 MAC address: 00:a0:c9:00:00:37
Info: eth0: Checking link... up.
```

```
Info: Trying DHCPv4 on interface: eth0
Info: eth1: Checking link...down.
ONIE: eth1: link down. Skipping configuration.
ONIE: Failed to configure eth1 interface
Starting: dropbear ssh daemon... done.
Starting: telnetd... done.
discover: installer mode detected. Running installer.
Starting: discover... done.

ONIE:/ #
```

5. At the ONIE prompt, to stop the ONIE discovery process, enter the following command:

```
ONIE:/ # onie-discovery-stop
```

The ONIE discovery stops, as shown:

```
ONIE:/ # onie-discovery-stop
discover: installer mode detected.
Stopping: discover... done.
ONIE:/ #
```

6. Configure an interface and assign an IP address to that interface using the following command:

```
ONIE:/ # ifconfig eth0 ip-address/prefix
```

7. Enter the following command to begin the installation process:

```
ONIE:/ # onie-nos-install tftp://<tftp-server-address>/ONIE-FTOS-SK-9.14.2.14.bin
```

**NOTE:** You must copy the ONIE-FTOS-SK-9.14.2.14.bin file to the /tftpboot folder in the server.

**NOTE:** After the Dell Networking OS installation completes, the system automatically reboots.

Following is the installation and boot log of Dell Networking OS:

```
ONIE:/ # onie-nos-install tftp://10.16.127.143/ONIE-FTOS-SK-9.14.2.14.bin
discover: Rescue mode detected. No discover stopped.
GRUB loading.
Welcome to GRUB!
  Built by root at ubuntu on Mon_Feb_21_07:05:39 UTC_2022
WARNING: skipping large memory map entry: 0x100000000/0x40000000/0x1
Copyright (c) 1996, 1997, 1998, 1999, 2000, 2001, 2002, 2003, 2004, 2005,
  2006, 2007, 2008, 2009, 2010
  The NetBSD Foundation, Inc. All rights reserved.
Copyright (c) 1982, 1986, 1989, 1991, 1993
  The Regents of the University of California. All rights reserved.
```

8. After the installation completes, the system displays the following DELL prompt:

```
DellEMC>
```

## Upgrading the S4048T-ON Dell Networking OS Image using the Dell Networking OS CLI

**NOTE:** If you are upgrading from Dell Networking OS version 9.9(0.0P18) or earlier, you cannot directly upgrade to version 9.14(2.14) or above. Upgrade to version 9.10(0.0) or above first and then upgrade to the required version.

### Bare Metal Provisioning

**NOTE:** If you are using Bare Metal Provisioning (BMP), see the Bare Metal Provisioning topic in the Dell Networking OS Configuration Guide or the Open Automation Guide.

### Manual Upgrade Procedure



```
!  
Feb 21 06:15:48: %STKUNIT1-M:CP %FILEMGR-5-FILESAVED: Copied running-config to  
startup-config in flash by default  
  
DellEMC#
```

6. Reload the unit.

```
EXEC Privilege Mode  
reload
```

```
DellEMC#reload
```

7. Verify the S4048T-ON has been upgraded to the Dell Networking OS version 9.14(2.14).

```
EXEC Privilege Mode  
show version
```

```
DellEMC#show version  
Dell EMC Real Time Operating System Software  
Dell EMC Operating System Version: 2.0  
Dell EMC Application Software Version: 9.14(2.14)  
Copyright (c) 1999-2021 by Dell Inc. All Rights Reserved.  
Build Time: Mon Feb 21 21:22:46 2022  
Build Path: /build/build02/SW/SRC  
Dell EMC Networking OS uptime is 1 hour(s), 34 minute(s)  
  
System image file is "system://A"  
  
System Type: S4048T-ON  
Control Processor: Intel Rangeley with 3 Gbytes (3181805568 bytes) of memory, core(s)  
2.  
  
8G bytes of boot flash memory.  
  
 1 48x10G, 6x40G TE/FO G (S4048T-ON)  
48 Ten GigabitEthernet/IEEE 802.3 interface(s)  
 6 Forty GigabitEthernet/IEEE 802.3 interface(s)
```

## Uninstalling Dell Networking OS from the S4048T-ON

To uninstall Dell Networking OS version 9.14(2.14) from the S4048T-ON device, perform the following steps:

1. Reboot the system. During the reboot process, the system displays the following message prompting you to press the Esc key in order to stop the auto-boot process:

```
Version 2.17.1245. Copyright (C) 2021 American Megatrends, Inc.  
BIOS Date: 02/21/2022 16:23:50 Ver: 0ACBZ028  
Press DEL or F2 to enter setup.  
  
GRUB loading.  
Welcome to GRUB!  
  
Grub 2.02~beta2 (Dell EMC)  
Built by root at ubuntu on Mon Feb 21 13:04:17 UTC 2022  
S4000 Boot Flash Label 3.27.2.10 NetBoot Label 3.27.2.10  
  
Press Esc to stop autoboot ... 0
```

2. At this prompt message, press the Esc key. The following menu appears:

```
+-----+
| Dell EMC Networking OS
| Dell EMC-Boot Line Interface
| DELL-DIAG
| ONIE
+-----+
```

3. From the menu, choose the **ONIE** option.

**NOTE:** To choose an option from the menu, highlight one of the options using the up or down arrow key and press **Enter**.

The following menu appears:

```
+-----+
| ONIE: Install OS
| ONIE: Rescue
| *ONIE: Uninstall OS
| ONIE: Update ONIE
| ONIE: Embed ONIE
| ONIE: Diag ONIE
| DELL-DIAG
+-----+
```

4. From this menu, choose the **ONIE : Uninstall OS** option.

**NOTE:** To choose an option from the menu, highlight one of the options using the up or down arrow key and press **Enter**.

The uninstall process begins. Following is the log generated by the system while Dell Networking OS 9.14(2.14) uninstalls:

```
Version : 3.27.1.10-0
Build Date: 2022-02-21T09:43-0700

Info: Mounting kernel filesystems... done.
Info: Mounting LABEL=ONIE-BOOT on /mnt/onie-boot ...
Info: Using eth0 MAC address: 00:a0:c9:00:00:36
Info: Using eth1 MAC address: 00:a0:c9:00:00:37
Info: eth0: Checking link... up.
Info: Trying DHCPv4 on interface: eth0
DHCPv4 on interface: eth0 failed
ONIE: Using default IPv4 addr: eth0: 192.168.3.10/255.255.255.0
Info: eth1: Checking link... down.
ONIE: eth1: link down. Skipping configuration.
ONIE: Failed to configure eth1 interface
Starting: dropbear ssh daemon... done.
Starting: telnetd... done.
discover: Uninstall mode detected. Running uninstaller.
Erasing internal mass storage device: /dev/sda4 (32MB)
  Percent complete: 100%
Erase complete.
Deleting partition 4 from /dev/sda
Erasing internal mass storage device: /dev/sda5 (300MB)
  Percent complete: 100%
Erase complete.
Deleting partition 5 from /dev/sda
Erasing internal mass storage device: /dev/sda6 (300MB)
  Percent complete: 100%
Erase complete.
Deleting partition 6 from /dev/sda
Erasing internal mass storage device: /dev/sda7 (5854MB)
  Percent complete: 100%
Erase complete.
Deleting partition 7 from /dev/sda
Installing for i386-pc platform.
Installation finished. No error reported.
Uninstall complete. Rebooting...
discover: Uninstall mode detected. No discover stopped.
Stopping: dropbear ssh daemon... done.
Stopping: telnetd... done.
Stopping: syslogd... done.
```

```
Info: Unmounting kernel filesystems
The system is going down NOW!
Sent SIGTERM to all processes
Sent SIGKILL to all processes
Requesting system reboot
sd 4:0:0:0: [sda] Synchronizing SCSI cache
Restarting system.
machine restart
```

5. After the installation completes, the system displays the following ONIE prompt:

```
ONIE:/ #
```

## Installing a Third Party Operating System

Apart from the Dell Networking OS, you can also install a supported third party operating system on the S4048T-ON system. For more information on installing a third party operating system, refer to the third party OS vendor's website for OS installation instructions.

## Support Resources

The following support resources are available for the S4048T-ON system.

### Documentation Resources

This document contains operational information specific to the S4048T-ON system.

For information about using the S4048T-ON, refer to the following documents at <http://www.dell.com/support>:

- *Installing the S4048T-ON System*
- *Quick Start Guide*
- *Dell Networking Command Line Reference Guide for the S4048T-ON System*
- *Dell Networking Configuration Guide for the S4048T-ON System*

For more information about hardware features and capabilities, refer to the Dell Networking website at <https://www.dellemc.com/networking>.

For more information about the open network installation environment (ONIE)-compatible third-party operating system, refer to <http://onie.org>.

### Issues


Issues are unexpected or incorrect behavior and are listed in order of Problem Report (PR) number within the appropriate sections.

## Finding Documentation

This document contains operational information specific to the S4048T-ON system.

- For information about using the S4048T-ON, refer to the documents at <http://www.dell.com/support>.
- For more information about hardware features and capabilities, refer to the Dell Networking website at <https://www.dellemc.com/networking>.
- For more information about the open network installation environment (ONIE)-compatible third-party operating system, refer to <http://onie.org>.


## Contacting Dell

 **NOTE:** If you do not have an active Internet connection, you can find contact information on your purchase invoice, packing slip, bill, or Dell product catalog.

Dell provides several online and telephone-based support and service options. Availability varies by country and product, and some services may not be available in your area. To contact Dell for sales, technical support, or customer service issues:

Go to [www.dell.com/support](http://www.dell.com/support).

## Notes, cautions, and warnings

 **NOTE:** A NOTE indicates important information that helps you make better use of your product.

 **CAUTION:** A CAUTION indicates either potential damage to hardware or loss of data and tells you how to avoid the problem.

 **WARNING:** A WARNING indicates a potential for property damage, personal injury, or death.