

# Dell Wyse ThinLinux Version 2.2 Operating System and Add-ons

Release Notes



## Notes, cautions, and warnings

 | **NOTE:** A NOTE indicates important information that helps you make better use of your product.

 | **CAUTION:** A CAUTION indicates either potential damage to hardware or loss of data and tells you how to avoid the problem.

 | **WARNING:** A WARNING indicates a potential for property damage, personal injury, or death.

© 2019 Dell Inc. or its subsidiaries. All rights reserved. Dell, EMC, and other trademarks are trademarks of Dell Inc. or its subsidiaries. Other trademarks may be trademarks of their respective owners.

# Contents

<b>1 Overview</b>	<b>6</b>
<b>2 Version matrix</b>	<b>7</b>
<b>3 ThinLinux version 2.2.1.00</b>	<b>8</b>
Release summary	8
Version	8
Release date	8
Compatibility	8
Supported platforms	8
Supported imaging solution	8
Supported VDI brokers, browsers, and terminal emulation applications	8
Application details	9
New and enhanced features	9
Webcam	9
Keyboard functions	9
Docking station	9
Display capability	10
Power management	10
Suspend system	10
General features	10
Known issues	11
<b>4 ThinLinux version 2.2.0.01</b>	<b>12</b>
Release summary	12
Version	12
Release date	12
Compatibility	12
Supported platforms	12
Build information	12
Supported VDI brokers, browsers, and terminal emulation applications	13
New and enhanced features	13
Citrix RTME 2.8	13
VMware Horizon View Client 5.0	13
Fixed issues	13
Samba vulnerability fixes	14
Known issues	14
<b>5 ThinLinux version 2.2.0.00</b>	<b>15</b>
Release summary	15
Version	15
Release date	15
Priority and recommendations	15

Compatibility.....	15
Supported platforms.....	15
Previous version.....	15
Wyse App details.....	16
Supported imaging solution.....	16
New and enhanced features.....	16
Domain join using Active Directory.....	16
Preserve User Settings.....	17
Quick Start.....	17
Suspend mode.....	18
Bluetooth functionality.....	18
System Performance Improvement.....	18
Web browser updates.....	18
Multidisplay support on Wyse 5070 Extended thin client.....	19
Fixed issues.....	20
Known issues.....	21
Limitations.....	22
Multidisplay support on Wyse 5070 extended thin client.....	22
Upgrading firmware.....	22
Upgrade ThinLinux 2.0 or 2.1 to 2.2 on Wyse 3040 thin client.....	22
Upgrade ThinLinux 2.0 or 2.1 to 2.2 on Wyse 5070 thin client.....	23
Upgrade ThinLinux 1.0.4 to 2.2 on Wyse 3040 thin client.....	24
Upgrade ThinLinux 1.0.71 to 2.2 on Wyse 3040 thin client.....	24
<b>6 VMware Horizon View Client version 5.0 add-on.....</b>	<b>26</b>
Release summary.....	26
Version.....	26
Release date.....	26
Priority and recommendations.....	26
Compatibility.....	26
Supported platforms.....	26
Previous versions.....	26
Supported operating systems.....	27
Add-on details.....	27
New and enhanced features.....	27
Known issues.....	27
<b>7 Installing add-ons.....</b>	<b>28</b>
Downloading the installation file.....	28
Install add-on using Wyse Management Suite.....	28
Install add-on using Wyse Device Manager.....	29
Install the add-on manually using ThinLinux.....	29
Install the add-on manually using ThinLinux INI parameter.....	30
<b>8 Resources and support.....</b>	<b>31</b>
Accessing documents using the product search.....	31
Accessing documents using product selector.....	31

Additional resources.....	31
<b>9 Contacting Dell.....</b>	<b>32</b>

# Overview

Wyse ThinLinux combines the security, flexibility and market-leading usability of Ubuntu Linux with Dell's optimizations in management and user experience. It is ideal for organizations that want to run server-based, web-based, or local applications without the deployment and security concerns of a non-standard Linux distribution.

① **NOTE:** For details about the previous versions, if applicable, or to determine which version of the operating system you need to select for your thin client, see [Version matrix](#).

## Version matrix

The following section lists the platforms that are supported in each ThinLinux release, and the add-ons required for ThinLinux.

**Table 1. ThinLinux 2.2.x version matrix**

Release version	Release date	Supported platforms	Release Notes
2.2.1.00	August 2019	Wyse 5470 Thin Client	<a href="#">ThinLinux version 2.2.1.00</a>
2.2.0.01	August 2019	<ul style="list-style-type: none"> <li>• Wyse 3040 Thin Client</li> <li>• Wyse 5070 Thin Client</li> <li>• Wyse 5070 Extended Thin Client</li> </ul>	<a href="#">ThinLinux version 2.2.0.01</a>
2.2.0.00	April 2019		<a href="#">ThinLinux version 2.2.0.00</a>

**Table 2. VMware Horizon View Client version matrix**

Release version	Release date	Supported platforms	Release Notes
5.0	May 2019	<ul style="list-style-type: none"> <li>• Wyse 3040 Thin Client</li> <li>• Wyse 5070 Thin Client</li> <li>• Wyse 5070 Extended Thin Client</li> </ul>	<a href="#">VMware Horizon View Client version 5.0 add-on</a>

# ThinLinux version 2.2.1.00

## Release summary

ThinLinux version 2.2.1 is released to support the Wyse 5470 thin client.

## Version

ThinLinux version 2.2.1

## Release date

August 2019

## Compatibility

### Supported platforms

**Table 3. Supported platforms**

Hardware	Memory configuration (eMMC / RAM)	UEFI BIOS
Wyse 5470 thin client	16 GB / 4 GB	1.0.0 and later

### Supported imaging solution

**Table 4. Supported imaging solution**

Imaging Solution	Version
Dell Wyse USB Imaging Tool	3.2.0
Wyse Management Suite	1.4 and later

### Supported VDI brokers, browsers, and terminal emulation applications

- Citrix Receiver 13.10
- Citrix RTME 2.7
- VMware View Client 4.10

- Wyse RDP 8.01.05
- Firefox Web Browser 60.4.0
- Google Chrome 72.0.3626.81
- Ericom Power Term 12.3.0

## Application details

Table 5. Wyse 5470 thin client application details

Package name	Size (Bytes)
all-addons_TL-2.2.1.00-Wyse.tgz	347,444,754

## New and enhanced features

### Webcam

The Wyse 5470 thin client has an integrated HD webcam. You can access the full functionality of the webcam during Citrix and VMware sessions.

### Keyboard functions

The Wyse 5470 thin client has a laptop layout keyboard. The following short-cut key functions are supported:

- **Fn+F1**—Mutes Audio
- **Fn+F2**—Decreases volume
- **Fn+F3**—Increases volume
- **Fn+F10**—Adjusts keyboard backlight brightness and toggles backlight on/off
- **Fn+F11**—Decreases LCD brightness
- **Fn+F12**—Increases LCD brightness

### Docking station

The Dell Docking station WD19 is compatible with the Wyse 5470 thin client. ThinLinux supports all the ports on the docking station and you can connect up to two external displays to the WD19 docking station.

### Merlin imaging using docking station with MAPT

MAC Address Override or MAC Address Pass Through (MAPT) uses a system-unique MAC address that is entered in the system BIOS. The unique MAC address overrides the dock or dongle MAC address every time when you connect to the network. For more information about MAPT, see the *What is MAC Address pass through?* KB article at [www.dell.com/support](http://www.dell.com/support).

ThinLinux supports Merlin imaging through the docking station with MAPT enabled. By default, the MAPT feature is enabled in BIOS on the Wyse 5470 thin client. You must connect the thin client to the docking station and the network cable is connected to the network connector (RJ45) on the docking station. This feature is applicable only for imaging using Wyse Management Suite or using INI parameters.

## Display capability

- Wyse 5470 thin client supports up to two external displays with 4K resolution.
- Wyse 5470 thin client supports one display with 4K resolution over the docking station.
- Wyse 5470 thin client supports up to two displays with non-4K resolution over the docking station.

## Power management

The following are the power management features on the Wyse 5470 thin client:

- You can set functions such as screen brightness, keyboard brightness and blank screen using the **Advanced Power Settings** option.
- You can enable or disable Wi-Fi using the Power-saving mode.
- The battery icon on the task bar displays the battery status.
- The **Automatic Suspend** option is added to support the **On Battery Power** and **Plugged In** modes.

## Suspend system

- You can use the Suspend System option to suspend the thin client after a specified idle time. This option enables your device to enter the S3 power state (low-power), and you can resume your work without rebooting the device.
- You can enable the suspend mode from either **Power button** or **Power module** in the **System Settings**. You can also use the INI parameter to enable the suspend mode feature.

## General features

Below listed are the general features of the Wyse 5470 thin client:

- UEFI BIOS support
- Custom GUI
- VDI broker connections such as Citrix Receiver 13.x, Citrix RTME 2.x, VMware View 4.x and RDP 8.1.05
- Network and wireless modules
- Energy star certification
- Imaging solutions using Merlin Imaging
- 802.1x & SCEP using HTTP and HTTPs enhancement feature
- Configuration using INI parameters
- Multilanguage support in English, Spanish, French, German, Dutch, Portuguese, Simplified Japanese, Chinese and Korean
- Firefox and Chrome browser
- Browser settings and customization control
- Custom connection
- SSH connection
- VNC Viewer connection
- VNC Server
- Add-on packages such as **.deb**

# Known issues

Table 6. Known issues

Issue number	Description	Workaround
TL-142	Volume cannot be increased or decreased using the sound bar in an RDP session.	There is no workaround in this release.
TL-192	You cannot answer or reject a call using the headset controller.	There is no workaround in this release.
TL-121	The RDP session does not launch when you connect two external displays in extended mode.	There is no workaround in this release.
TL-79	The drop-down option is not available in the <b>Desktop Wallpaper</b> window.	There is no workaround in this release.
TL-120	Dell AE 515 Sound Bar is not displayed in the <b>Sound</b> window.	There is no workaround in this release.
TL-156	Left and right buttons on the touch pad do not work correctly.	There is no workaround in this release.
TL-132	The <b>Sound</b> window is not displayed when you connect the Plantronics USB headset to the thin client.	There is no workaround in this release.
TL-51	After you disconnect the thin client from the domain, the domain object is not removed from Active Directory in Windows 2016 Server.	There is no workaround in this release.
TL-185	When you connect two external displays to the docking station, turning off one display turns off the second display.	There is no workaround in this release.
TL-157	When you disable the on-board LAN MAC from the BIOS setup, the device identifier is changed to AUX_MAC or Dock MAC.	Do not disable the on-board LAN in BIOS.
TL-176	External SSD fails to redirect in a Citrix session.	There is no workaround in this release.
TL-164	Docking station connected to the thin client is listed twice in the <b>Connect to USB Deviced</b> drop-down list in a VMware session.	Select one of the options from the list.
TL-146	When you set <b>Full screen</b> in mirror mode on a three-display setup, the Citrix session fails to launch in full screen.	There is no workaround in this release.

# ThinLinux version 2.2.0.01

## Release summary

ThinLinux version 2.2.0.01 is the maintenance release that incorporates the latest connection brokers and software fixes for ThinLinux - based platforms.

## Version

ThinLinux version 2.2.0.01

## Release date

August 2019

## Compatibility

### Supported platforms

**Table 7. Supported platforms**

Platform name	Memory configuration (RAM/Flash)	BIOS version
Wyse 5070 Celeron Thin client	16 GB / 4 GB	1.1.4 and later
Wyse 5070 Pentium Thin client	16 GB / 4 GB	1.1.4 and later
Wyse 5070 Extended Thin client	16 GB / 4 GB	1.1.4 and later
Wyse 3040 Thin Client	16 GB / 2 GB	1.2.5 and later

## Build information

**Table 8. Build Information**

Platform name	Build file name	Size (Bytes)
Wyse 3040 Thin Client	2.2.0.01_3040_16GB_merlin.exe	1,693,148,068 bytes
Wyse 5070 Thin Client	2.2.0.01_5070_16GB_merlin.exe	1,694,190,538 bytes

# Supported VDI brokers, browsers, and terminal emulation applications

The following are the major components in ThinLinux 2.2 MR1:

- Citrix Receiver Client 13.10
- Citrix RTME 2.8
- VMware View Client 5.0
- Wyse RDP 8.01.05
- Ericom Power Term 12.3.0
- Firefox Web Browser 60.7.2
- Google Chrome 74.0

## New and enhanced features

### Citrix RTME 2.8

Added support for Citrix HDX RealTime Media Engine (RTME) version 2.8. The following are the new features in Citrix RTME version 2.8:

- Audio quality in the Windows session is enhanced.
- Supports Skype for Business calls when the Edge server is unreachable.

For more information about the Citrix RTME 2.8 features, see the HDX RealTime Media Engine for Microsoft Skype for Business article at [docs.citrix.com](https://docs.citrix.com).

### VMware Horizon View Client 5.0

Added support for VMware Horizon View Client version 5.0. The following are the new features in VMware Horizon View Client version 5.0:

- Enhanced Horizon Client User Interface.
- Ability to start multiple desktops and applications within a single client session. This feature is applicable when you use the `--use Existing` command-line option to start resources.
- Enhanced support for multiple-display configurations. The full-screen display dynamically updates when you change the local display configuration during a client session.
- Changes to the domain security. Depending on the server configuration, you might need to enter a domain in the username text box when you log in to the Horizon 7 version 7.8 server from Horizon Client.

For more information about the VMware Horizon View client 5.0 features, see the *VMware Horizon Client 5.0 for Linux Release Notes* at [docs.vmware.com](https://docs.vmware.com).

For information about the VMware 5.0 and VNC server UI changes, see the *Dell Wyse ThinLinux 2.2 Administrator's Guide* at [www.dell.com/support](http://www.dell.com/support).

## Fixed issues

The following issues are fixed in this release:

**Table 9. Fixed issue**

CIR / JIRA ID	Issue description
CIR 97581/ TL-5	On the Wyse 5060 Thin Client, the 802.1x settings cannot be used for the wired network connection.
CIR 98706 /TL-6	Duplicate entries for VMware Horizon connection are displayed if you use <code>https://</code> URL prefix.
TL-8	Addressed vulnerability scan issues.
STRATUS-18746	Payload for deletion of USB COM port data from Wyse Management Suite are not getting updated on the ThinLinux-based devices.
STRATUS-18083	Add Wyse Management Suite support for system wide proxy settings.
STRATUS-18084	Add Wyse Management Suite support for browser proxy settings.
LS-607	On the thin client without a BIOS admin password, the changes made in the BIOS settings are not reflected on USB Manager UI when you use the <code>USB_Device_INI</code> parameter.
TL-97	Using the INI parameter, you can set zero seconds as the time period to wait before automatically reconnecting to an application server. However, the values for the <b>Reconnect seconds</b> option are from 1 to 3600 on the ThinLinux GUI.
STRATUS-19525	The system wide proxy is not set when you configure the central configuration settings on the thin client. This issue is observed only if the system wide proxy add-on is installed on the device.
TL-101	VMware client accepts an incorrect port number through the INI parameter.
TL-198	Addressed Firefox Browser vulnerabilities.
TL-210	Addressed the Nessus critical vulnerability scan issues.

## Samba vulnerability fixes

The following Samba vulnerabilities are resolved in this release:

- CIFS NULL session permitted: CVE-1999-0519
- Invalid CIFS logins permitted
- SMB signing disabled

## Known issues

**Table 10. Known issues**

JIRA ID	Issue Description	Workaround
TL-217	Printer redirection does not work in VMware Blast and PCOIP sessions when you use network and USB printers.	You need to install VMware 4.8 client and then upgrade to VMware 5.0.
TL-228	Occasionally, packages in the <b>System Information</b> window are not displayed when you log in as an admin user.	Restart the client and log in as administrator.
TL-238	Data Sharing feature is not working in VMware and RDP sessions.	There is no workaround for this issue.
TL-253	Home page of the Mozilla Firefox browser displays a blank page instead of the Dell home page.	There is no workaround for this issue.
TL-1256	Default Firefox Browser and created browser connection are launched multiple times when you press CTRL+N key.	There is no workaround for this issue.

# ThinLinux version 2.2.0.00

## Release summary

This release includes new features and resolved issues for ThinLinux 2.2-based platforms.

## Version

ThinLinux 2.2

## Release date

April 2019

## Priority and recommendations

Recommended: Dell recommends applying this update during your next scheduled update cycle. The update contains feature enhancements or changes that will help keep your system software current and compatible with other system modules (firmware, BIOS, drivers and software).

## Compatibility

### Supported platforms

**Table 11. Supported platforms**

Platforms	Memory configuration (eMMC/RAM)	UEFI BIOS
Wyse 5070 thin client with Celeron processor	16 GB/4 GB	1.1.4 and later
Wyse 5070 thin client with Pentium processor	16 GB/4 GB	1.1.4 and later
Wyse 5070 Extended thin client with Pentium processor	16 GB/4 GB	1.1.4 and later
Wyse 3040 thin client	16 GB/2 GB	1.2.5 and later

## Previous version

ThinLinux 2.1

# Wyse App details

Table 12. Wyse App Details

Package name	Size (Bytes)
all-addons_TL-2.2.0.00-Wyse.tgz	333,914,016

## Supported imaging solution

Table 13. Supported imaging solution

Imaging solution	Version
USB Imaging Tool	3.1.0
Wyse Management Suite	1.3 and later

## New and enhanced features

### Domain join using Active Directory

ThinLinux 2.2 supports domain join and domain login using Active Directory credentials. Active Directory allows an administrator to enable or disable the user authentication to specific domains. You can either join the terminal to the domain, or use the INI parameter to authenticate the user from Active Directory without joining the terminal.

To join your thin client to a domain, enter the following details on the **Active Directory** page:

- Active Directory Domain Name
- Organizational Unit for Thin Client (OU)
- Administrator Name
- Administrator Password

After the thin client is added to the domain, disable the **Autologon** option, and restart the thin client. The domain name is displayed on the ThinLinux login screen. You must enter the domain username and password to log in to the ThinLinux desktop. An error message is displayed if the thin client fails to join the domain.

**NOTE:** On successful login, you can view the Domain Name and Domain IP in the System information dialog box. Add user should disable the Auto login and need restart the device then able to login domain user

#### INI parameters

Table 14. Domain join parameters

INI parameter	Description
Domainjoin.name={yes, no}	This parameter enables users to connect the thin client to a domain. Default selection is no.
Domainjoin.username=<string>	This parameter specifies the name of the user who has the relevant permission to add a computer account to the active directory.
Domainjoin.password=<string>	This parameter specifies the password for the domain.

INI parameter	Description
Domainjoin.enable={true, false}	This parameter allows an administrator to enable or disable authentication against a domain, to require the thin client to formally join the domain, and configure other domain parameters, such as the name of the administrator group. Default selection is false.
Domain.ou=<string>	It specifies the organization unit within Active Directory to which an administrator can assign Group Policy settings.

## Preserve User Settings

The **Preserve User Settings** feature enables you to retain the configured user settings when you upgrade from ThinLinux 2.2. However, before you upgrade from ThinLinux 2.2, the Preserve User Settings feature needs to be enabled.

When imaging is performed using the USB Imaging tool, use the **Execute Preserve User Settings** option available on the ThinLinux UI to retain the previous settings after upgrade. If you are using the INI parameters to perform an image upgrade, use the `MerlinUpdate.Preserve_User_Setting` parameter to retain the previous settings.

**NOTE:** Imaging using Wyse Management Suite is not supported by the current Wyse Management Suite release.

### INI parameters

**Table 15. Preserve User Settings parameters**

INI parameter	Description
MerlinUpdate.URL=<string>	This parameter specifies the URL of the directory where the ThinLinux image is uploaded.
MerlinUpdate.Username=<string>	This parameter specifies the name of the user who has logged in to the server.
MerlinUpdate.Password=<string>	The password is used to log in to the server. Default selection is base-64 encryption.
MerlinUpdate.Preserve_User_Setting={yes, no}	This parameter enables you to retain any previously configured user settings in the ThinLinux build after you perform an image upgrade using INI parameters. Default selection is no.

## Quick Start

Quick Start is software that provides an overview of different features and hardware specifications of the thin client. The Quick Start v2.0 wizard runs only for the first time when you start a new thin client, or the first time after performing a factory reset on the existing thin client.

A default icon is added on the ThinLinux desktop that enables you to launch the application. You can enable or disable the desktop icon for a specific user by using the **Hide Desktop Icons** option in **Other Settings** , or the INI parameter.

### INI parameter

**Table 16. Quick Start parameters**

INI parameter	Description
Custom.HideQuickStart={yes, no}	This parameter enables you to hide the Quick Start application from the ThinLinux desktop. Default selection is no.

# Suspend mode

ThinLinux 2.2 supports suspend mode, which enables the device to enter the S3 power state (low-power), and quickly resume your work without rebooting the device.

You can enable the suspend mode using either the GUI option available in **System Settings**, or from the **Power** button. You can also use the INI parameter to enable the suspend mode.

## INI parameter

**Table 17. Suspend mode parameter**

INI parameter	Description
SuspendSystem=<value>	This parameter enables you to enter the time in seconds to suspend the thin client after the specified idle time. Default selection is 15 minutes.

**NOTE:** Suspend mode is supported only on Wyse 5070 thin client.

# Bluetooth functionality

ThinLinux 2.2 supports Bluetooth version 5.0. Administrator can enable or disable the Bluetooth function using the GUI option in the **Peripherals** settings, or through INI parameters. Normal user (thinuser) cannot enable or disable the Bluetooth functionality.

**NOTE:** When a normal user (thinuser) attempts to enable or disable Bluetooth, the following warning message is displayed:

```
Please contact Administrator.
```

The following devices are supported by Bluetooth:

- Keyboard
- Mouse
- Headset

**NOTE:** Bluetooth printers are not supported.

## INI parameter

**Table 18. Bluetooth parameter**

INI parameter	Description
DisableBluetooth={yes, no}	This parameter allows you to enable or disable the Bluetooth function on your thin client. Default selection is yes.

# System Performance Improvement

In ThinLinux 2.2, the system performance during bootup is improved.

# Web browser updates

- Google Chrome is upgrade to the latest version 72.0.3626.81-1.

- Mozilla Firefox Extended Support Release (ESR) is upgraded to the latest version ESR-60.4.0.

# Multidisplay support on Wyse 5070 Extended thin client

ThinLinux 2.2 supports up to six displays.

### Salient features:

- By default, the **Display Settings** UI is available in both user mode and admin mode. Any changes to display preferences that are made through this UI is saved for the user.
- You must select the layout for The **Display Settings** UI has an option to select the layout. The available layout options are **Horizontal** (1 x 6), **Vertical** (6 x 1), **2 Screens per column** (2 x 3), and **3 Screens per column** (3 x 2).
- A minimum of four monitors are required for **2 Screens per column**.
- A minimum of six monitors are required for **3 Screens per column**.
- VMware protocol supports only four monitors.
- Daisy chain configuration is not supported on ThinLinux 2.2.

**NOTE:** Rotation and Mirror screens options are not available for quad display.

### Port preferences on Wyse 5070 Extended thin client:

- Optional port can be used as second RJ45, SFP, or VGA.
- If wireless is enabled, the optional port cannot be used as second RJ45 or SFP.
- If front headphone is used, the back headset is disabled.
- When monitor is connected on USB-C port, DP2 becomes inactive.
- When VGA monitor is connected on VGA optional port, DP3 becomes inactive.
- Power option is available on the first serial port.
- PCIe slot is available.

**Table 19. Ports**

Ports	DP1	DP2	DP3	VGA	USB Type-C	mDP4	mDP5	DP6
Monitor priority	1	2B <sup>1</sup>	3B <sup>2</sup>	3A <sup>2</sup>	2A <sup>1</sup>	4	5	6
4K display	Yes	Yes	Yes	No <sup>3</sup>	Yes	Yes	Yes	Yes
Non-4K display	Yes	Yes	Yes	Yes <sup>3</sup>	Yes	Yes	Yes	Yes

<sup>1</sup>DP2 and USB Type-C port are mutually exclusive with USB Type-C port taking higher priority.

<sup>2</sup>DP3 and VGA port are mutually exclusive with VGA port taking higher priority.

<sup>3</sup>VGA port supports only 1080p resolution.

### Display matrix:

**Table 20. Wyse 5070 Extended thin client with AMD GPU**

Number of displays	Supported display resolution	
	4K resolution 3840 x 2160 @ 60 Hz	Non-4K resolution Up to 2560 x 1600 @ 60 Hz
One display	Yes	Yes
Two displays	Yes	Yes

Number of displays	Supported display resolution	
	4K resolution 3840 x 2160 @ 60 Hz	Non-4K resolution Up to 2560 x 1600 @ 60 Hz
Three displays <sup>1</sup>	Yes	Yes
Four displays	Yes	Yes
Five displays	No <sup>2</sup>	Yes
Six displays	No <sup>2</sup>	Yes

<sup>1</sup>For three displays, Dell recommends that you configure first two 4K displays on the main board (DP1~DP3), and the third 4K display on AMD GPU card.

<sup>2</sup>Support only four monitors with 4K screen resolution @ 60 Hz and the remaining displays with 2K screen resolution.

**Monitor priority**—The following order defines the monitor priority set on ThinLinux 2.2 for Wyse 5070 Extended thin client:

- DP1 > DP2 > DP3 > mDP4 > mDP5 > DP6
- DP1 > USB-C > DP3 > mDP4 > mDP5 > DP6
- DP1 > DP2 > VGA > mDP4 > mDP5 > DP6
- DP1 > USB-C > VGA > mDP4 > mDP5 > DP6

For more information about configuring multiple displays on Wyse 5070 Extended thin client, see the *Dell Wyse ThinLinux 2.2 Administrator's Guide* at [support.dell.com](http://support.dell.com).

**NOTE:** INI parameters are not supported on a multi-display setup with more than three displays.

## Fixed issues

**Table 21. Fixed Issues**

Serial number	Summary
1.	Resolved an issue where you can save the <b>Manage USB Port settings</b> using the GUI option after entering an incorrect BIOS password.
2.	Resolved an issue wherein after parsing the INI <code>USB_Rule=Deny_Class Class=Storage</code> in a VMware session, the VMware view Connect USB Device drop-down option is listed.
3.	Resolved an issue where the mouse blinks in Mozilla Firefox browser when a YouTube video is played.
4.	Resolved an issue where a blank screen is observed when you use multiple displays with high-resolution on the Wyse 3040 thin client.
5.	Resolved an issue where desktop artifacts and the <b>Windows Start</b> menu are not displayed in an ICA session. The issue is observed when you connect a secondary display on the Wyse 3040 thin client.
6.	Resolved an issue where the Swiss German language keyboard layout does not redirect to the Citrix session.

# Known issues

Table 22. Known issues

Issue ID	Description	Workaround
TL-1197	When you connect to a Bluetooth keyboard, the keyboard does not work for the first time.	Reboot the thin client.
TL-1290	When you select a <b>window resolution</b> in the browser connection and launch the browser, the resolution reverts to <b>Default</b> .	Create a Mozilla Firefox browser connection and set the window resolution.
TL-1313	Network proxy settings do not persist after passing the Firefox proxy settings.	Set either the network proxy settings or Firefox proxy settings.
TL-1342	By default, the domain name in <b>System Information</b> is displayed as <b>Project-Id-Version:gnome-shell.master</b> for supported language builds other than English.	No workaround
TL-1234	When you connect two displays in the L-shape orientation, the Citrix session fails to launch on the secondary display.	No workaround
TL-1303	The date and time are not preserved in the <b>Date and Time</b> settings window.	First set the Time zone and then set the date and time.
TL-1338	MMR Redirection does not work for VMware (PCoIP and Blast).	Not supported by VMware with gstreamer1.0.
TL-1329	Terminal name is not preserved after imaging.	Reboot the device after imaging.
TL-1263	Domain user can log in after deleting the entry from Active Directory.	Disjoin the thin client from Active Directory before deleting the entry.
TL-1355	Device does not receive messages with special characters <b>%</b> and <b>\</b> from Wyse Management Suite. The same issue is observed when you type a message after pressing the Enter key.	No workaround
TL-1330	When you set the output device mode as <b>Headset Headunit (HSP/HFP)</b> , the Bluetooth audio is played with disturbance.	Set the audio output mode to <b>High Fidelity Playback (A2DP sink)</b> .
TL-1374	When you press the CTRL+ALT+L key, the screen lock takes approximately 10 seconds to get locked.	No workaround
LS-588	Unable to set the <b>Custom Info</b> parameters from the Wyse Management Suite server.	There is no workaround.
LS-607	When the INI parameters for <b>USB Devices</b> are configured on the client without the BIOS administrator password, changes that are made in BIOS settings are not applied in <b>USB Manager</b> .	Set the BIOS password.
TL-1151	802.1x settings that are configured using the GUI options are not preserved across system restarts.	Use INI parameters to configure the 802.1x settings.
TL-1140	Google Chrome is opened with the <b>Set as default browser</b> option enabled.	Set Google Chrome as the default browser. The Chrome browser works without any issues.
TL-1028	CAC is not found when you log in to the VMware Horizon session using the onboard smart card reader.	There is no workaround.
TL-1119	After doing OEM branding, the services list is displayed during the system boot.	There is no workaround.

Issue ID	Description	Workaround
TL-731	Wyse 5070 thin client does not automatically connect to a wireless network once the client is connected to a hidden network.	Reconnect to the wireless network after restarting the client.
TL-980	When you connect one 4K and two non-4K displays on the Wyse 5070 thin client, the values in few drop-down lists are not displayed. This issue is observed on the <b>Display</b> settings and <b>connections</b> settings pages.	There is no workaround.
TL-1088	GDM login screen remains blank when you perform imaging on a dual-display setup.	Switch to one display.
TL-1065	When you switch to the admin mode from system settings and enter the incorrect password, the <code>incorrect password</code> message is not displayed. This is not observed on English and Korean builds.	Enter the appropriate password.
TL-722	AD PAM login takes more than 10 seconds.	There is no workaround.
TL-562	The thin client login password expiry function is not supported.	Reset the password on the server side.
TL-1044	The Citrix StoreFront connection does not launch the second time if the first attempt is a failure (when the target desktop is turned off). If the desktop is turned on, you must restart the thin client.	There is no workaround.
TL-753	When you connect the display to DP2 and change the display rotation to right, you cannot move the mouse cursor to the lower edge of the screen.	Connect the display to DP1.
TL-887	Ericom show menu bar options are not displayed with the respective system languages.	There is no workaround.
TL-1164	When the Ericom Power term connection is created using the INI parameters, the COM2 port is not displayed in the <b>Port</b> section.	There is no workaround.
TL-896	When you enter a command in the Ericom console by using the keyboard, the Ericom menu bar options are getting selected.	There is no workaround.

## Limitations

### Multidisplay support on Wyse 5070 extended thin client

When you set the 2K resolution for the primary display and open **System Settings** on the same display, the drop-down menu appears blank in all features except **Display**.

To overcome this limitation, do the following:

- 1 Drag the System Settings window to any nonprimary display.
- 2 Set the primary display to 4K resolution.

## Upgrading firmware

### Upgrade ThinLinux 2.0 or 2.1 to 2.2 on Wyse 3040 thin client

#### About this task

Use Wyse Management Suite version 1.3 to upgrade the ThinLinux build version 2.0.19 or 2.1 to 2.2.

To upgrade ThinLinux by using Wyse Management Suite for Wyse 3040 thin client:

### Steps

- 1 Go to [www.dell.com/support](http://www.dell.com/support).
- 2 Click **Product Support**, enter the **Service Tag** of your thin client, and then press Enter.  
**NOTE:** If you do not have Service Tag, manually browse for your thin client model.
- 3 Click **Drivers and downloads**.
- 4 From the **Operating system** drop-down list, select **ThinLinux**.
- 5 Scroll down the page, and do the following:
  - Download the **wda3040\_3.0.10-01\_amd64.deb**, **wda\_3.2.13-01\_amd64.tar**, and **merlin-nonpxe\_3.7.7-00.05\_amd64.deb** add-ons.
  - Download the latest ThinLinux version 2.2 image file (**2.2.0.00\_3040\_merlin\_16GB.exe**).
- 6 On the thin client, go to **Settings > Management > Wyse Device Agent**.
- 7 Register the device to the Wyse Management Suite server.
- 8 Log in to the Wyse Management Suite console.
- 9 Create and deploy app policy for **wda3040\_3.0.10-01\_amd64.deb**, **wda\_3.2.13-01\_amd64.tar**, and **merlin-nonpxe\_3.7.7-00.05\_amd64.deb** add-ons.
- 10 Reboot the thin client.
- 11 Log in to the Wyse Management Suite server.
- 12 Copy the downloaded image (**2.2.0.00\_3040\_merlin\_16GB.exe** file) to `<drive C>/wms/localrepo/repository/osimages/zipped/`.
- 13 Log in to the Wyse Management Suite console.
- 14 Go to **Apps & Data > OS Image repository > WES/ThinLinux** and verify that the ThinLinux image is available.
- 15 Go to **Apps & Data > OS Image policies (WES/ThinLinux)** and click **Add Policy**.
- 16 Update the required fields, and click **Save**.
- 17 Schedule the job.
- 18 Click **Update now** on the client to update the image.

## Upgrade ThinLinux 2.0 or 2.1 to 2.2 on Wyse 5070 thin client

### About this task

Use Wyse Management Suite version 1.3 to upgrade the ThinLinux build version 2.0.27, 2.1.0.0 or 2.1.0.01 to 2.2.

To upgrade ThinLinux by using Wyse Management Suite for Wyse 5070 thin client:

### Steps

- 1 Go to [www.dell.com/support](http://www.dell.com/support).
- 2 Click **Product Support**, enter the **Service Tag** of your thin client, and then press Enter.  
**NOTE:** If you do not have Service Tag, manually browse for your thin client model.
- 3 Click **Drivers and downloads**.
- 4 From the **Operating system** drop-down list, select **ThinLinux**.
- 5 Scroll down the page, and download the latest ThinLinux version 2.2 image file (**2.2.0.00\_5070\_merlin\_16GB.exe**).
- 6 On the thin client, go to **Settings > Management > Wyse Device Agent**.
- 7 Register the device to the Wyse Management Suite server.
- 8 Log in to the Wyse Management Suite server.
- 9 Copy the downloaded image (**2.2.0.00\_5070\_merlin\_16GB.exe** file) to `<drive C>/wms/localrepo/repository/osimages/zipped/`.
- 10 Log in to the Wyse Management Suite console.
- 11 Go to **Apps & Data > OS Image repository > WES/ThinLinux** and verify that the ThinLinux image is available.
- 12 Go to **Apps & Data > OS Image policies (WES/ThinLinux)** and click **Add Policy**.
- 13 Update the required fields, and click **Save**.
- 14 Schedule the job.

15 Click **Update now** on the client to update the image.

## Upgrade ThinLinux 1.0.4 to 2.2 on Wyse 3040 thin client

### About this task

Use Wyse Management Suite version 1.3 to upgrade the ThinLinux build version 1.0.4 to 2.2.

To upgrade ThinLinux by using Wyse Management Suite:

### Steps

- 1 Go to [www.dell.com/support](http://www.dell.com/support).
- 2 Click **Product Support**, enter the **Service Tag** of your thin client, and then press Enter.  
**NOTE: If you do not have Service Tag, manually browse for your thin client model.**
- 3 Click **Drivers and downloads**.
- 4 From the **Operating system** drop-down list, select **ThinLinux**.
- 5 Scroll down the page, and do the following:
  - Download the **Platform\_util-1.0.26-0.3.x86\_64.rpm**, **wda-2.1.23-00.01.x86\_64.rpm**, and **merlin\_nonpxe-3.7.7-00.05.x86\_64.rpm** add-ons.
  - Download the latest ThinLinux version 2.2 image file (**2.2.0.00\_3040\_merlin\_16GB.exe**).
- 6 On the thin client, go to **Settings > Management > Wyse Device Agent**.
- 7 Register the device to the Wyse Management Suite server.
- 8 Log in to the Wyse Management Suite console.
- 9 Create and deploy app policy for **Platform\_util-1.0.26-0.3.x86\_64.rpm**, **wda-2.1.23-00.01.x86\_64.rpm**, and **merlin\_nonpxe-3.7.7-00.05.x86\_64.rpm**.
- 10 Reboot the thin client.
- 11 Log in to the Wyse Management Suite server.
- 12 Copy the downloaded image (**2.2.0.00\_3040\_merlin\_16GB.exe** file) to `<drive C>/wms/localrepo/repository/osimages/zipped/`.
- 13 Log in to the Wyse Management Suite console.
- 14 Go to **Apps & Data > OS Image repository > WES/ThinLinux** and verify that the ThinLinux image is available.
- 15 Go to **Apps & Data > OS Image policies (WES/ThinLinux)** and click **Add Policy**.
- 16 Update the required fields, and click **Save**.
- 17 Schedule the job.
- 18 Click **Update now** on the client to update the image.

## Upgrade ThinLinux 1.0.7.1 to 2.2 on Wyse 3040 thin client

### About this task

Use Wyse Management Suite version 1.3 to upgrade the ThinLinux build version 1.0.7.1 to 2.2.

To upgrade ThinLinux by using Wyse Management Suite:

### Steps

- 1 Go to [www.dell.com/support](http://www.dell.com/support).
- 2 Click **Product Support**, enter the **Service Tag** of your thin client, and then press Enter.  
**NOTE: If you do not have Service Tag, manually browse for your thin client model.**
- 3 Click **Drivers and downloads**.
- 4 From the **Operating system** drop-down list, select **ThinLinux**.
- 5 Scroll down the page, and do the following:
  - Download the **merlin\_nonpxe-3.7.7-00.05.x86\_64.rpm** add-on.

- Download the latest ThinLinux version 2.2 image file (2.2.0.00\_3040\_merlin\_16GB.exe).
- 6 On the thin client, go to **Settings > Management > Wyse Device Agent**.
  - 7 Register the device to the Wyse Management Suite server.
  - 8 Log in to the Wyse Management Suite console.
  - 9 Create and deploy app policy for **merlin\_nonpxe-3.7.7-00.05.x86\_64.rpm**.
  - 10 Reboot the thin client.
  - 11 Log in to the Wyse Management Suite server.
  - 12 Copy the downloaded image (2.2.0.00\_3040\_merlin\_16GB.exe file) to <drive C>/wms/localrepo/repository/osimages/zipped/.
  - 13 Log in to the Wyse Management Suite console.
  - 14 Go to **Apps & Data > OS Image repository > WES/ThinLinux** and verify that the ThinLinux image is available.
  - 15 Go to **Apps & Data > OS Image policies (WES/ThinLinux)** and click **Add Policy**.
  - 16 Update the required fields, and click **Save**.
  - 17 Schedule the job.
  - 18 Click **Update now** on the client to update the image.

# VMware Horizon View Client version 5.0 add-on

## Release summary

This release notes contains information about the add-on to update VMware Horizon View Client to the latest version 5.0. This add-on is supported on Wyse 3040 thin client and Wyse 5070 thin client running ThinLinux version 2.2 operating system.

**NOTE:** You cannot install the add-on using Wyse Device Manager (WDM).

## Version

5.0

## Release date

May 2019

## Priority and recommendations

Recommended: Dell recommends applying this update during your next scheduled update cycle. The update contains feature enhancements or changes that will help keep your system software current and compatible with other system modules (firmware, BIOS, drivers and software).

## Compatibility

## Supported platforms

**Table 23. Supported platforms**

Platform	Memory Configuration		BIOS version
	Flash size	RAM size	
Wyse 3040 thin client	16 GB	2 GB	1.2.5
Wyse 5070 thin client	16 GB	4 GB	1.1.4

## Previous versions

4.10

# Supported operating systems

Table 24. Supported operating systems

Platform	Operating system	Version—English Standard build
Wyse 3040 thin client	ThinLinux	2.2.0.00-11.32506
Wyse 5070 thin client	ThinLinux	2.2.0.00-11.32506

## Add-on details

- Debian add-on
  - File name—vmware-viewclient\_ 5.0.0-12557422-00.02\_amd64.deb
  - File size—26,727,892 bytes
- RSP add-on
  - File name—vmware-viewclient\_ 5.0.0-12557422-00.02\_amd64.zip
  - File size—26,730,405 bytes

## New and enhanced features

- Enhanced Horizon Client User Interface.
- Ability to start multiple desktops and applications within a single client session. This feature is applicable when you use the `--use Existing` command line option to start resources.
- Enhanced support for multiple-display configurations. The full-screen display dynamically updates when you change the local display configuration during a client session.
- Changes to the domain security. Depending on the server configuration, you might need to enter a domain in the username text box when you log in to the Horizon 7 version 7.8 server from Horizon Client

For more information about the VMware Horizon View client 5.0 features, see the *VMware Horizon Client 5.0 for Linux Release Notes* at [docs.vmware.com](https://docs.vmware.com).

## Known issues

Table 25. Known issues

Issue ID	Description	Workaround
TL86	Enhanced support for multi-display configurations does not work for four displays during RDP, Blast, and PCoIP sessions.	There is no workaround in this release.
TL87	Occasionally, the Copy and Paste feature does not work during a PCoIP session.	There is no workaround in this release.
TL103	In a dual monitor configuration, a split screen is observed when you log off and log in to an RDP session.	There is no workaround in this release.
TL160	Installation fails when you deploy the add-on using the WDM server.	There is no workaround in this release

# Installing add-ons

## Downloading the installation file

- 1 Go to [www.dell.com/support](http://www.dell.com/support).
- 2 In the **Enter a Service Tag, Serial Number, Service Request...** field, type the Service Tag or the model number of your device, and press Enter or click the search icon.
- 3 On the product support page, click **Drivers & downloads**.
- 4 Select the appropriate operating system.
- 5 From the list, locate the file entry and click the download icon.

## Install add-on using Wyse Management Suite

### Prerequisites

Ensure that you download either the DEB file or RSP file of the add-on based on your preference:

- If you download the DEB file, add the file to `C:\WMS\LocalRepo\repository\thinClientApps` repository on the Wyse Management Suite server.
- If you download the RSP file, add the compressed ZIP folder to `C:\WMS\Local Repo\repository\rspPackages\zipped` repository on the Wyse Management Suite server and wait for 2-3 minutes. The compress folder is extracted automatically, and the extracted files are copied to `C:\WMS\LocalRepo\repository\rspPackages\valid`.

On Wyse 3040 thin client, you must install Wyse Device Agent (WDA) 3.2.13-01 or later versions. To update WDA to 3.2.13-01 or later versions, the thin client must have the WDA version 3.0.10-01.

### About this task

This section describes the steps to install the add-on using Wyse Management Suite version 1.2 or later:

### Steps

- 1 Log in to Wyse Management Suite.
- 2 Click **Portal Administration**, and then click **File Repository** under **Console Settings**.
- 3 Select the **Local Repository** check box.
- 4 Click **Sync Files**.  
Wait for the synchronization process to complete. The synchronization process copies the package from the repository to **Apps and Data**.
- 5 Click **Apps and Data**.  
The **Apps and Data** page is displayed.
- 6 Verify the copied package in the applications list.
- 7 To create a group in the Wyse Management Suite server, click **Groups & Configs**.  
The **Groups & Configs** page is displayed.
- 8 Click the **Plus sign (+)** button and enter the required details to register your client in the same group.
- 9 Click **Apps and Data**.  
The **Apps and Data** page is displayed.
- 10 Click **Thin Clients** under **App Policies**.
- 11 Click **Add Policy** to add the policy to the required group.
- 12 Update the required fields, and then click **Save**.  
An **Alert** window is displayed.

- 13 Click **Yes**.

The lock screen is displayed during the package installation process on all the thin clients. The package is deployed immediately.

## Install add-on using Wyse Device Manager

### Prerequisite

Copy the RSP file to the Wyse Device Manager server. The copied RSP file is included in the ZIP file.

### About this task

This section describes the steps to install the add-on by using Wyse Device Manager (WDM).

### Steps

- 1 Launch Wyse Device Manager and log in using valid credentials.
- 2 Click **Applications** in the Dell Wyse Device Manager dashboard page.  
The options **Images**, **Other Packages**, **Agent Update**, **Device Configuration**, and **PCoIP Device Configuration** are displayed.
- 3 Select **Other Packages**.
- 4 Click **Create Package Plus (+)**.  
The application prompts to download the Package Register utility.
- 5 Click **Allow**.  
The **Create Package** window is displayed.
- 6 Download the ZIP file on your local repository.
- 7 Navigate to the folder, and run the **Package Register** utility file.  
The **WDM Package Registration Utility** window is displayed.
- 8 Enter WDM server address and user credentials in the respective fields.
- 9 Select **RSP** to register, and click **Browse**.  
The **WDM Package Uploader** window is displayed with the progress status bar.
- 10 Click **Open**.  
The list of selected packages is displayed.
- 11 Select the packages that you want to register, and click **Upload**.  
The status is displayed as **Success**.
- 12 Schedule the package to the target client.
- 13 Click **Devices** and select the **Device ID** check box.
- 14 Click **Update**, and select the preferred package.
- 15 Click **Save**.  
The add-ons installation is scheduled to the device and the add-on is installed to thin client.

## Install the add-on manually using ThinLinux

### About this task

This section describes the steps to install the add-on by using the ThinLinux UI.

### Steps

- 1 Copy the add-on and the directory file to the `<root path>\add-ons` folder.
- 2 Log in to the thin client.
- 3 To enter into the **Admin mode**, click the **Switch to Admin** button.
- 4 Enter the default password.  
The default password is admin.
- 5 Click the **Settings** icon on the desktop.  
The **System Settings** page is displayed.
- 6 Click the **System** icon.
- 7 Click **Update settings**.
- 8 To enable the **Set update server manually** option, click the **ON/OFF** button.

- 9 Enter the URL address of the specified server in the **Update Server URL** box.  
You can also enter the user name and password of the specified server in the **Update Server User Name** and **Update Server Password** box.
- 10 Click **Addons**.
- 11 Click the **Plus sign (+)** button, to install the add-ons.
- 12 Select the add-ons.
- 13 Click **Save**.  
The add-on is installed on the thin client.

## Install the add-on manually using ThinLinux INI parameter

### About this task

This section describes the steps to install the add-on by using INI parameters.

### Steps

- 1 Copy the add-on and the directory file to the `<root path>\add-ons` folder.
- 2 To install the add-on, add the following INI parameter:  
`InstallAddons=<deb file>` in `wlx.ini`.
- 3 Log in to the thin client.
- 4 To enter into the **Admin mode**, click the **Switch to Admin** button.
- 5 Enter the default password.  
The default password is admin.
- 6 Click the **Settings** icon on the desktop.  
The **System Settings** page is displayed.
- 7 Click the **Management** icon.
- 8 Click **INI**.  
The **Manage INI Configuration** page is displayed.
- 9 From the drop-down list, select the configuration source and provide the server details.
- 10 Click **Save**.  
The following message is displayed:  
**System Upgradation complete. Machine will reboot now. Count down timer starts with 10 sec.**
- 11 Click **OK**.  
The add-on is installed on the thin client and the system restarts.

## Resources and support

### Accessing documents using the product search

- 1 Go to [www.dell.com/support](http://www.dell.com/support).
- 2 In the **Enter a Service Tag, Serial Number, Service Request, Model, or Keyword** search box, type the product name. For example, `Wyse 3040 thin client` or `Wyse ThinOS`.  
A list of matching products is displayed.
- 3 Select your product and click the search icon or press Enter.
- 4 Click **Manuals & documents**.

### Accessing documents using product selector

You can also access documents by selecting your product.

- 1 Go to [www.dell.com/support](http://www.dell.com/support).
- 2 Click **Browse all products**.
- 3 Click **Thin Clients**.
- 4 Click the desired category, either **Wyse Hardware** or **Wyse Software**.
- 5 Click the desired product.
- 6 Click **Manuals & documents**.

### Additional resources

**Table 26. Additional resources**

Resource	Content
Dell support website— <a href="http://www.dell.com/manuals">www.dell.com/manuals</a> .	Administrator's Guide, INI Reference Guide, and Release Notes.
Citrix support website— <a href="http://docs.citrix.com">docs.citrix.com</a> .	Documentation for Citrix software.
VMware support website— <a href="http://docs.vmware.com">docs.vmware.com</a> .	Documentation for VMware software.
Microsoft support website— <a href="http://support.microsoft.com">support.microsoft.com</a> .	Documentation for Microsoft software.

## Contacting Dell

Dell provides several online and telephone-based support and service options. Availability varies by country and product, and some services may not be available in your area. To contact Dell for technical support or customer service issues, see [www.dell.com/contactdell](http://www.dell.com/contactdell).

If you do not have an active Internet connection, you can find contact information on your purchase invoice, packing slip, bill, or the product catalog.