



# Dell P519HL SNMP Protocol Document

## Control Commands List

Name	Feature	Oid	Value Type	Read /Write	Criteria
RFC1213-system	sysDescr	.1.3.6.1.2.1.1.1.0	String	R	Dell Projector
RFC1213-system	sysObjectID	.1.3.6.1.2.1.1.2.0	OID	R	.1.3.6.1.4.1.674.10901.20018
RFC1213-system	sysUpTime	.1.3.6.1.2.1.1.3.0	Timetic ks	R	Operation hours * hours * minutes * seconds
RFC1213-system	sysContact	.1.3.6.1.2.1.1.4.0	String	R/W	If meet web management (system status)
RFC1213-system	sysName	.1.3.6.1.2.1.1.5.0	String	R/W	If meet web management (Group Name + Projector Name)
RFC1213-system	sysLocation	.1.3.6.1.2.1.1.6.0	String	R/W	If meet web management (system status)
RFC1213-system	sysServices	.1.3.6.1.2.1.1.7.0	Integer	R	DEFVAL { 72 }
RFC1213-interfaces	ifNumber	.1.3.6.1.2.1.2.1.0	Integer	R	DEFVAL { 1 }
pdmGeneral	pdmGeneralProductName	.1.3.6.1.4.1.2699.2.4.1.2.1.0	String	R	Dell P519HL
pdmGeneral	pdmGeneralSerialNumber	.1.3.6.1.4.1.2699.2.4.1.2.2.0	String	R	Check PPID number (the latter 7 yards)
pdmGeneral	pdmGeneralAssetTag	.1.3.6.1.4.1.2699.2.4.1.2.3.0	String	R/W	Range (0~63 byte)
pdmGeneral	pdmGeneralHardwareVersion	.1.3.6.1.4.1.2699.2.4.1.2.4.0	String	R	DEFVAL { "" }
pdmGeneral	pdmGeneralServicePerson	.1.3.6.1.4.1.2699.2.4.1.2.5.0	String	R/W	Range (0~255 byte)
pdmGeneral	pdmGeneralDeviceAge	.1.3.6.1.4.1.2699.2.4.1.2.6.0	Integer	R	Check display hours
pdmGeneral	pdmGeneralPowerOnCount	.1.3.6.1.4.1.2699.2.4.1.2.7.0	Integer	R	Everytime Projector power on, check if the count value is added by one.
pdmGeneral	pdmGeneralManufactureDate	.1.3.6.1.4.1.2699.2.4.1.2.8.0	String	R	
pdmGeneral	pdmGeneralLanguageTagSNMP	.1.3.6.1.4.1.2699.2.4.1.2.9.0	String	R	en-US
pdmGeneral	pdmGeneralNtpServerAddress	.1.3.6.1.4.1.2699.2.4.1.2.10.0	String	R	DEFVAL { "" }
PdmCtrl	pdmCtrlIndex	.1.3.6.1.4.1.2699.2.4.1.3.1.1.1	Integer	not-accessible	1
PdmCtrl	pdmCtrlDescription	.1.3.6.1.4.1.2699.2.4.1.3.1.1.2.1	String	R	T1 DDP4422HV
PdmCtrl	pdmCtrlHardwareVersion	.1.3.6.1.4.1.2699.2.4.1.3.1.1.3.1	String	R	DEFVAL { "" }
PdmCtrl	pdmCtrlFirmwareVersion	.1.3.6.1.4.1.2699.2.4.1.3.1.1.4.1	String	R	
PdmCtrl	pdmCtrlFirmwareUpgradeable	.1.3.6.1.4.1.2699.2.4.1.3.1.1.5.1	Integer	R	DEFVAL { 10 }
PdmCtrl	pdmCtrlUpgradeInstructions	.1.3.6.1.4.1.2699.2.4.1.3.1.1.6.1	String	R	DEFVAL { "" }
PdmCtrl	pdmCtrlPostStatus	.1.3.6.1.4.1.2699.2.4.1.3.1.1.7.1	Integer	R	DEFVAL { 2 }
PdmCtrl	pdmCtrlPostCode	.1.3.6.1.4.1.2699.2.4.1.3.1.1.8.1	String	R	DEFVAL { "" }
PdmCtrl	pdmCtrlPostStatusDefinitions	.1.3.6.1.4.1.2699.2.4.1.3.1.1.9.1	String	R	DEFVAL { "" }
PdmPower	pdmPowerIndex	.1.3.6.1.4.1.2699.2.4.1.4.1.1.1.1	Integer	not-accessible	1
PdmPower	pdmPowerIndex	.1.3.6.1.4.1.2699.2.4.1.4.1.1.1.2	Integer	not-accessible	2
PdmPower	pdmPowerIndex	.1.3.6.1.4.1.2699.2.4.1.4.1.1.1.3	Integer	not-accessible	3
PdmPower	pdmPowerIndex	.1.3.6.1.4.1.2699.2.4.1.4.1.1.1.4	Integer	not-accessible	4
PdmPower	pdmPowerIndex	.1.3.6.1.4.1.2699.2.4.1.4.1.1.1.5	Integer	not-accessible	5
PdmPower	pdmPowerIndex	.1.3.6.1.4.1.2699.2.4.1.4.1.1.1.6	Integer	not-accessible	6
PdmPower	pdmPowerImplementedState	.1.3.6.1.4.1.2699.2.4.1.4.1.1.2.1	Integer	R	11 (On)
PdmPower	pdmPowerImplmented	.1.3.6.1.4.1.2699.2.4.1.4.1.1.2.2	Integer	R	7 (Standby)

	mentedState					
PdmPower	pdmPowerImple mentedState	.13.6.14.1.2699.2.4.14.11.2.3	Integer	R	9 (Cooling)	
PdmPower	pdmPowerImple mentedState	.13.6.14.1.2699.2.4.14.11.2.4	Integer	R	8 (Power Save)	
PdmPower	pdmPowerImple mentedState	.13.6.14.1.2699.2.4.14.11.2.5	Integer	R	8 (Power Save)	
PdmPower	pdmPowerImple mentedState	.13.6.14.1.2699.2.4.14.11.2.6	Integer	R	10 (Warming)	
PdmPower	pdmPowerDescri ption	.13.6.14.1.2699.2.4.14.11.3.1	String	R	Power On.	
PdmPower	pdmPowerDescri ption	.13.6.14.1.2699.2.4.14.11.3.2	String	R	Power Off.	
PdmPower	pdmPowerDescri ption	.13.6.14.1.2699.2.4.14.11.3.3	String	R	Projector is cooling down.	
PdmPower	pdmPowerDescri ption	.13.6.14.1.2699.2.4.14.11.3.4	String	R	Low power mode.	
PdmPower	pdmPowerDescri ption	.13.6.14.1.2699.2.4.14.11.3.5	String	R	Low power mode.	
PdmPower	pdmPowerDescri ption	.13.6.14.1.2699.2.4.14.11.3.6	String	R	Warming up.	
PdmPower	pdmPowerMfrDe scription	.13.6.14.1.2699.2.4.14.11.4.1	String	R	Full power on, all components active.	
PdmPower	pdmPowerMfrDe scription	.13.6.14.1.2699.2.4.14.11.4.2	String	R	Standby State. Only network electronics remain on.	
PdmPower	pdmPowerMfrDe scription	.13.6.14.1.2699.2.4.14.11.4.3	String	R	Going down to standby mode.	
PdmPower	pdmPowerMfrDe scription	.13.6.14.1.2699.2.4.14.11.4.4	String	R	Power off. Fan on.	
PdmPower	pdmPowerMfrDe scription	.13.6.14.1.2699.2.4.14.11.4.5	String	R	Power off. Fan on.	
PdmPower	pdmPowerMfrDe scription	.13.6.14.1.2699.2.4.14.11.4.6	String	R	Power warming up. Fan on.	
PdmPower	pdmPowerTarget State	.13.6.14.1.2699.2.4.14.11.5.1	Integer	R	7 (Standby)	
PdmPower	pdmPowerTarget State	.13.6.14.1.2699.2.4.14.11.5.2	Integer	R	11 (On)	
PdmPower	pdmPowerTarget State	.13.6.14.1.2699.2.4.14.11.5.3	Integer	R	3 (No Transition)	
PdmPower	pdmPowerTarget State	.13.6.14.1.2699.2.4.14.11.5.4	Integer	R	7 (Standby)	
PdmPower	pdmPowerTarget State	.13.6.14.1.2699.2.4.14.11.5.5	Integer	R	11 (On)	
PdmPower	pdmPowerTarget State	.13.6.14.1.2699.2.4.14.11.5.6	Integer	R	3 (No Transition)	
PdmPower	pdmPowerTransit ionTime	.13.6.14.1.2699.2.4.14.11.6.1	Integer	R	120	
PdmPower	pdmPowerTransit ionTime	.13.6.14.1.2699.2.4.14.11.6.2	Integer	R	30	
PdmPower	pdmPowerTransit ionTime	.13.6.14.1.2699.2.4.14.11.6.3	Integer	R	0	
PdmPower	pdmPowerTransit ionTime	.13.6.14.1.2699.2.4.14.11.6.4	Integer	R	120	
PdmPower	pdmPowerTransit ionTime	.13.6.14.1.2699.2.4.14.11.6.5	Integer	R	20	
PdmPower	pdmPowerTransit ionTime	.13.6.14.1.2699.2.4.14.11.6.6	Integer	R	0	
PdmPower	pdmPowerCom mAvailable	.13.6.14.1.2699.2.4.14.11.7.1	Integer	R	3 (Available)	
PdmPower	pdmPowerCom mAvailable	.13.6.14.1.2699.2.4.14.11.7.2	Integer	R	4 (Not available)	
PdmPower	pdmPowerCom mAvailable	.13.6.14.1.2699.2.4.14.11.7.3	Integer	R	4 (Not available)	
PdmPower	pdmPowerCom mAvailable	.13.6.14.1.2699.2.4.14.11.7.4	Integer	R	3 (Available)	
PdmPower	pdmPowerCom mAvailable	.13.6.14.1.2699.2.4.14.11.7.5	Integer	R	3 (Available)	
PdmPower	pdmPowerCom mAvailable	.13.6.14.1.2699.2.4.14.11.7.6	Integer	R	4 (Not available)	
PdmPower	pdmPowerCurre ntState	.13.6.14.1.2699.2.4.14.2.0	Integer	R	Check if current projector status is correct.	
PdmPower	pdmPowerRequ estedState	.13.6.14.1.2699.2.4.14.3.0	Integer	R/W	Check if current projector status is correct.	
pdmDisplayCap	pdmDisplayCapR	.13.6.14.1.2699.2.4.15.1.0	Integer	R	1920	

	resolutionH					
pdmDisplayCap	pdmDisplayCapR	1.3.6.14.1.2699.2.4.1.5.2.0	Integer	R	1080	
pdmDisplayCap	pdmDisplayCapP	1.3.6.14.1.2699.2.4.1.5.3.0	String	R	DEFVAL { "" }	
pdmDisplayCap	pdmDisplayCapP	1.3.6.14.1.2699.2.4.1.5.4.0	String	R	DEFVAL { "" }	
pdmDisplaySet	pdmDisplaySetIndex	1.3.6.14.1.2699.2.4.1.6.1.1.11	Integer	not-accessible	1	
pdmDisplaySet	pdmDisplaySetAffectedsAll	1.3.6.14.1.2699.2.4.1.6.1.1.2.1	Integer	R	DEFVAL { 1 }	
					1. VGA 5. HDMI1 14. HDMI 2 16.Network 18. USB-Video 19. USB-Music 20. USB-Photo 21. USB-Document 22. USB-Settings	
pdmDisplaySet	pdmDisplaySetBrightness	1.3.6.14.1.2699.2.4.1.6.1.1.4.1	Integer	R/W		
pdmDisplaySet	pdmDisplaySetBrtMax	1.3.6.14.1.2699.2.4.1.6.1.1.5.1	Integer	R	100	
pdmDisplaySet	pdmDisplaySetContrast	1.3.6.14.1.2699.2.4.1.6.1.1.6.1	Integer	R/W		
pdmDisplaySet	pdmDisplaySetCOnMax	1.3.6.14.1.2699.2.4.1.6.1.1.7.1	Integer	R	100	
pdmDisplaySet	pdmDisplaySetRed	1.3.6.14.1.2699.2.4.1.6.1.1.8.1	Integer	R	DEFVAL { 0 }	
pdmDisplaySet	pdmDisplaySetGreen	1.3.6.14.1.2699.2.4.1.6.1.1.9.1	Integer	R	DEFVAL { 0 }	
pdmDisplaySet	pdmDisplaySetBlue	1.3.6.14.1.2699.2.4.1.6.1.1.10.1	Integer	R	DEFVAL { 0 }	
pdmDisplaySet	pdmDisplaySetRGBMax	1.3.6.14.1.2699.2.4.1.6.1.1.11.1	Integer	R	DEFVAL { 100 }	
pdmDisplaySet	pdmDisplaySetSaturation	1.3.6.14.1.2699.2.4.1.6.1.1.12.1	Integer	R/W		
pdmDisplaySet	pdmDisplaySetSatMax	1.3.6.14.1.2699.2.4.1.6.1.1.13.1	Integer	R	100	
pdmDisplaySet	pdmDisplaySetHue	1.3.6.14.1.2699.2.4.1.6.1.1.14.1	Integer	R/W		
pdmDisplaySet	pdmDisplaySetHueMax	1.3.6.14.1.2699.2.4.1.6.1.1.15.1	Integer	R	100	
pdmDisplaySet	pdmDisplaySetSharpness	1.3.6.14.1.2699.2.4.1.6.1.1.16.1	Integer	R/W		
pdmDisplaySet	pdmDisplaySetSharpMax	1.3.6.14.1.2699.2.4.1.6.1.1.17.1	Integer	R	31	
					3. Custom 4. Low 5. Mid 6. High	
pdmDisplaySet	pdmDisplaySetColorTemp	1.3.6.14.1.2699.2.4.1.6.1.1.18.1	Integer	R/W		
pdmDisplaySet	pdmDisplaySetReducedCirTmp	1.3.6.14.1.2699.2.4.1.6.1.1.19.1	Integer	R/W	DEFVAL { 50 }	
pdmDisplaySet	pdmDisplaySetGreenCirTmp	1.3.6.14.1.2699.2.4.1.6.1.1.20.1	Integer	R/W	DEFVAL { 50 }	
pdmDisplaySet	pdmDisplaySetBlueCirTmp	1.3.6.14.1.2699.2.4.1.6.1.1.21.1	Integer	R/W	DEFVAL { 50 }	
pdmDisplaySet	pdmDisplaySetClipTmpMax	1.3.6.14.1.2699.2.4.1.6.1.1.22.1	Integer	R	DEFVAL { 0 }	
pdmDisplaySet	pdmDisplaySetVideoMute	1.3.6.14.1.2699.2.4.1.6.2.0	Integer	R/W	Blank Screen 1. Muted 2. Not Muted	
					3. Original 5. Wide screen 16:9 7. 4:3 8. 16:10	
pdmDisplaySet	pdmDisplaySetDisplayMode	1.3.6.14.1.2699.2.4.1.6.3.0	Integer	R/W		
					5. Wide screen 16:9 7. 4:3 8. 16:10	
pdmLightSource	pdmLightSourceIndex	1.3.6.14.1.2699.2.4.1.7.1.1.11	Integer	not-accessible	1	
pdmLightSource	pdmLightSourceDescription	1.3.6.14.1.2699.2.4.1.7.1.1.2.1	String	R	Laser Diode	
pdmLightSource	pdmLightSourceStatus	1.3.6.14.1.2699.2.4.1.7.1.1.3.1	Integer	R	3. Okay 4. Failed	
pdmLightSource	pdmLightSourceEcoSetting	1.3.6.14.1.2699.2.4.1.7.1.14.1	Integer	R/W	ECO Mode 4. Off -> Normal	

## 5. On -&gt; Low

pdmLightSource	pdmLightSourceAge	1.3.6.14.1.2699.2.4.1.7.1.1.5.1	Integer	R	
pdmLightSource	pdmLightSourceErrorCounter	1.3.6.14.1.2699.2.4.1.7.1.1.6.1	Integer	R	
pdmLightSource	pdmLightSourceReset	1.3.6.14.1.2699.2.4.1.7.1.1.7.1	Integer	R/W	DEFVAL { 1 }
pdmLightSource	pdmLightSourceReplacementCount	1.3.6.14.1.2699.2.4.1.7.1.1.8.1	String	R	DEFVAL { "" }
pdmLightSource	pdmLightSourceReplacementTime	1.3.6.14.1.2699.2.4.1.7.1.1.9.1	String	R	
pdmLightSource	pdmLightSourceReplacementInterval	1.3.6.14.1.2699.2.4.1.7.1.1.10.1	Integer	R	DEFVAL { 0 }
pdmLightSource	pdmLightSourceReplacementPN	1.3.6.14.1.2699.2.4.1.7.1.1.11.1	String	R	DEFVAL { "" }
pdmFan	pdmFanIndex	1.3.6.14.1.2699.2.4.1.8.1.1.1.1	Integer	not-accessible	1
pdmFan	pdmFanDescription	1.3.6.14.1.2699.2.4.1.8.1.1.2.1	String	R	System fan
pdmFan	pdmFanStatus	1.3.6.14.1.2699.2.4.1.8.1.1.3.1	Integer	R	3. Okay 4. Warning
pdmFan	pdmFanSpeed	1.3.6.14.1.2699.2.4.1.8.1.1.4.1	Integer	R	DEFVAL { 0 }
pdmFan	pdmFanErrorCounter	1.3.6.14.1.2699.2.4.1.8.1.1.5.1	Integer	R	
pdmFan	pdmFanReset	1.3.6.14.1.2699.2.4.1.8.1.1.6.1	Integer	R/W	DEFVAL { 1 }
pdmFan	pdmFanReplacementCount	1.3.6.14.1.2699.2.4.1.8.1.1.7.1	String	R	DEFVAL { "" }
pdmFan	pdmFanReplacementTime	1.3.6.14.1.2699.2.4.1.8.1.1.8.1	String	R	DEFVAL { "1980-01-01T00:00:00" }
pdmFan	pdmFanReplaceInterval	1.3.6.14.1.2699.2.4.1.8.1.1.9.1	Integer	R	DEFVAL { 0 }
pdmFan	pdmFanReplacementPartNumber	1.3.6.14.1.2699.2.4.1.8.1.1.10.1	String	R	DEFVAL { "" }
pdmTempSensor	pdmTempSensorIndex	1.3.6.14.1.2699.2.4.1.10.1.1.1.1	Integer	not-accessible	1
pdmTempSensor	pdmTempSensorDescription	1.3.6.14.1.2699.2.4.1.10.1.1.2.1	String	R	Measure system internal temperature.
pdmTempSensor	pdmTempSensorStatus	1.3.6.14.1.2699.2.4.1.10.1.1.3.1	Integer	R	DEFVAL { 2 }
pdmTempSensor	pdmTempSensorStatus	1.3.6.14.1.2699.2.4.1.10.1.1.4.1	Integer	R	Describes the temperature being measured by the thermal sensor in 10ths of a degree C.
pdmTempSensor	pdmTempSensorErrorCounter	1.3.6.14.1.2699.2.4.1.10.1.1.5.1	Integer	R	
pdmTempSensor	pdmTempSensorReset	1.3.6.14.1.2699.2.4.1.10.1.1.6.1	Integer	R/W	DEFVAL { 1 }
pdmTempSensor	pdmTempSensorReplaceCount	1.3.6.14.1.2699.2.4.1.10.1.1.7.1	String	R	DEFVAL { "" }
pdmTempSensor	pdmTempSensorReplaceTime	1.3.6.14.1.2699.2.4.1.10.1.1.8.1	String	R	DEFVAL { "1980-01-01T00:00:00" }
pdmTempSensor	pdmTempSensorReplaceInterval	1.3.6.14.1.2699.2.4.1.10.1.1.9.1	Integer	R	DEFVAL { 0 }
pdmTempSensor	pdmTempSensorReplacePN	1.3.6.14.1.2699.2.4.1.10.1.1.10.1	String	R	DEFVAL { "" }
pdmTempSwitch	pdmTempSwitchIndex	1.3.6.14.1.2699.2.4.1.11.1.1.1.1	Integer	not-accessible	1
pdmTempSwitch	pdmTempSwitchDescription	1.3.6.14.1.2699.2.4.1.11.1.1.2.1	String	R	Avertronics INC.
pdmTempSwitch	pdmTempSwitchStatus	1.3.6.14.1.2699.2.4.1.11.1.1.3.1	Integer	R	3. Okay 5. Fail
pdmTempSwitch	pdmTempSwitchErrorCounter	1.3.6.14.1.2699.2.4.1.11.1.1.4.1	Integer	R	
pdmTempSwitch	pdmTempSwitchReset	1.3.6.14.1.2699.2.4.1.11.1.1.5.1	Integer	R/W	DEFVAL { 1 }
pdmTempSwitch	pdmTempSwitchReplaceCount	1.3.6.14.1.2699.2.4.1.11.1.1.6.1	String	R	DEFVAL { "" }
pdmTempSwitch	pdmTempSwitchReplaceTime	1.3.6.14.1.2699.2.4.1.11.1.1.7.1	String	R	DEFVAL { "1980-01-01T00:00:00" }
pdmTempSwitch	pdmTempSwitchReplacePN	1.3.6.14.1.2699.2.4.1.11.1.1.8.1	String	R	DEFVAL { "" }
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.1.1	Integer	not-accessible	1

	dex					
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.2	Integer	not-accessible	2	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.3	Integer	not-accessible	3	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.4	Integer	not-accessible	4	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.5	Integer	not-accessible	5	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.6	Integer	not-accessible	6	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.7	Integer	not-accessible	7	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.8	Integer	not-accessible	8	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.9	Integer	not-accessible	9	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.10	Integer	not-accessible	10	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.11	Integer	not-accessible	11	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.12	Integer	not-accessible	12	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.13	Integer	not-accessible	13	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.14	Integer	not-accessible	14	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.15	Integer	not-accessible	15	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.16	Integer	not-accessible	16	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.17	Integer	not-accessible	17	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.18	Integer	not-accessible	18	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.19	Integer	not-accessible	19	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.20	Integer	not-accessible	20	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.21	Integer	not-accessible	21	
pdmConnector	pdmConnectorIn	1.3.6.14.1.2699.2.4.1.12.1.1.22	Integer	not-accessible	22	
pdmConnector	pdmConnectorD	1.3.6.14.1.2699.2.4.1.12.1.1.2.1	String	R	VGA	
pdmConnector	pdmConnectorD	1.3.6.14.1.2699.2.4.1.12.1.1.2.5	String	R	HDMI1	
pdmConnector	pdmConnectorD	1.3.6.14.1.2699.2.4.1.12.1.1.2.14	String	R	HDMI2	
pdmConnector	pdmConnectorD	1.3.6.14.1.2699.2.4.1.12.1.1.2.16	String	R	Network	
pdmConnector	pdmConnectorD	1.3.6.14.1.2699.2.4.1.12.1.1.2.18	String	R	USB-Video	
pdmConnector	pdmConnectorD	1.3.6.14.1.2699.2.4.1.12.1.1.2.19	String	R	USB-Music	
pdmConnector	pdmConnectorD	1.3.6.14.1.2699.2.4.1.12.1.1.2.20	String	R	USB-Photo	
pdmConnector	pdmConnectorD	1.3.6.14.1.2699.2.4.1.12.1.1.2.21	String	R	USB-Document	
pdmConnector	pdmConnectorD	1.3.6.14.1.2699.2.4.1.12.1.1.2.22	String	R	USB-Settings	
pdmConnector	pdmConnectorT	1.3.6.14.1.2699.2.4.1.12.1.1.3.1	Integer	R	3 (See Note 2)	
pdmConnector	pdmConnectorT	1.3.6.14.1.2699.2.4.1.12.1.1.3.2	Integer	R	3	
pdmConnector	pdmConnectorT	1.3.6.14.1.2699.2.4.1.12.1.1.3.3	Integer	R	10	
pdmConnector	pdmConnectorT	1.3.6.14.1.2699.2.4.1.12.1.1.3.4	Integer	R	13	
pdmConnector	pdmConnectorT	1.3.6.14.1.2699.2.4.1.12.1.1.3.5	Integer	R	6	
pdmConnector	pdmConnectorT	1.3.6.14.1.2699.2.4.1.12.1.1.3.6	Integer	R	12	
pdmConnector	pdmConnectorT	1.3.6.14.1.2699.2.4.1.12.1.1.3.7	Integer	R	21	

pdmConnector	pdmConnectorType	.13.6.14.1.2699.2.4.1.12.1.1.3.8	Integer	R	20
pdmConnector	pdmConnectorType	.13.6.14.1.2699.2.4.1.12.1.1.2.9	Integer	R	7
pdmConnector	pdmConnectorType	.13.6.14.1.2699.2.4.1.12.1.1.2.10	Integer	R	4
pdmConnector	pdmConnectorType	.13.6.14.1.2699.2.4.1.12.1.1.2.11	Integer	R	9
pdmConnector	pdmConnectorType	.13.6.14.1.2699.2.4.1.12.1.1.3.12	Integer	R	22
pdmConnector	pdmConnectorType	.13.6.14.1.2699.2.4.1.12.1.1.3.13	Integer	R	23
pdmConnector	pdmConnectorType	.13.6.14.1.2699.2.4.1.12.1.1.3.14	Integer	R	6
pdmConnector	pdmConnectorType	.13.6.14.1.2699.2.4.1.12.1.1.3.15	Integer	R	12
pdmConnector	pdmConnectorType	.13.6.14.1.2699.2.4.1.12.1.1.3.16	Integer	R	6
pdmConnector	pdmConnectorType	.13.6.14.1.2699.2.4.1.12.1.1.3.17	Integer	R	6
pdmConnector	pdmConnectorType	.13.6.14.1.2699.2.4.1.12.1.1.3.18	Integer	R	20
pdmConnector	pdmConnectorType	.13.6.14.1.2699.2.4.1.12.1.1.3.19	Integer	R	20
pdmConnector	pdmConnectorType	.13.6.14.1.2699.2.4.1.12.1.1.3.20	Integer	R	20
pdmConnector	pdmConnectorType	.13.6.14.1.2699.2.4.1.12.1.1.3.21	Integer	R	20
pdmConnector	pdmConnectorType	.13.6.14.1.2699.2.4.1.12.1.1.3.22	Integer	R	20
pdmConnector	pdmConnectorEnabled	.13.6.14.1.2699.2.4.1.12.1.1.4.5	Integer	R	DEFVAL {1}
pdmConnector	pdmConnectorEnabled	.13.6.14.1.2699.2.4.1.12.1.1.4.14	Integer	R	DEFVAL {1}
pdmConnector	pdmConnectorEnabled	.13.6.14.1.2699.2.4.1.12.1.1.4.16	Integer	R	DEFVAL {1}
pdmConnector	pdmConnectorEnabled	.13.6.14.1.2699.2.4.1.12.1.1.4.17	Integer	R	DEFVAL {1}
pdmConnector	pdmConnectorEnabled	.13.6.14.1.2699.2.4.1.12.1.1.4.18	Integer	R	DEFVAL {1}
pdmConnector	pdmConnectorEnabled	.13.6.14.1.2699.2.4.1.12.1.1.4.19	Integer	R	DEFVAL {1}
pdmConnector	pdmConnectorEnabled	.13.6.14.1.2699.2.4.1.12.1.1.4.20	Integer	R	DEFVAL {1}
pdmConnector	pdmConnectorEnabled	.13.6.14.1.2699.2.4.1.12.1.1.4.21	Integer	R	DEFVAL {1}
pdmConnector	pdmConnectorEnabled	.13.6.14.1.2699.2.4.1.12.1.1.4.22	Integer	R	DEFVAL {1}
1. VGA 5. HDMI 1 14. HDMI 2 16. Network 17. HDMI 3 18. USB-Video 19. USB-Music 20. USB-Photo 21. USB-Document 22. USB-Settings					
pdmConnector	pdmConnectorVideoCurrInput	.13.6.14.1.2699.2.4.1.12.2.0	Integer	R/W	
pdmInterlockTable pdmInterlockIndex .13.6.14.1.2699.2.4.1.13.1.1.1 Integer not-accessible 1					
pdmInterlockTable pdmInterlockIndex .13.6.14.1.2699.2.4.1.13.1.1.2 String R DEFVAL {''}					
pdmInterlockTable pdmInterlockIndex .13.6.14.1.2699.2.4.1.13.1.1.31 Integer R DEFVAL {3}					
pdmLocaleChars pdmLocaleChars etIndex .13.6.14.1.2699.2.4.1.14.1.1.1 Integer not-accessible 1					
pdmLocaleChars pdmLocaleChars etIndex .13.6.14.1.2699.2.4.1.14.1.1.21 Integer R DEFVAL {4}					
pdmLocaleChars pdmLocaleChars etEnumEWS .13.6.14.1.2699.2.4.1.14.2.0 Integer R DEFVAL {4}					
pdmLocaleLangauge pdmLocaleLangaugeIndex .13.6.14.1.2699.2.4.1.15.1.1.1 Integer not-accessible 1					
pdmLocaleLangauge pdmLocaleLangaugeTag .13.6.14.1.2699.2.4.1.15.1.1.21 String R DEFVAL {en-US}					
pdmLocaleLangauge pdmLocaleLangauge .13.6.14.1.2699.2.4.1.15.2.0 String R DEFVAL {en-US}					

age	ageTagEWS					
pdmLocaleLanguage	pdmLocaleLanguage	1.3.6.14.1.2699.2.4.1.15.3.0	String	R	DEFVAL { en-US }	
pdmLocaleLanguage	pdmLocaleLanguage	1.3.6.14.1.2699.2.4.1.15.4.0	String	R	DEFVAL { en-US }	
pdmAudio	pdmAudioDescription	1.3.6.14.1.2699.2.4.1.16.1.0	String	R	DEFVAL { "" }	
pdmAudio	pdmAudioVolume	1.3.6.14.1.2699.2.4.1.16.2.0	Integer	R/W		
pdmAudio	pdmAudioMute	1.3.6.14.1.2699.2.4.1.16.3.0	Integer	R/W	1. Muted 2. Not Muted	
pdmAudio	pdmAudioTreble	1.3.6.14.1.2699.2.4.1.16.4.0	Integer	R	DEFVAL { 0 }	
pdmAudio	pdmAudioBass	1.3.6.14.1.2699.2.4.1.16.5.0	Integer	R	DEFVAL { 0 }	
pdmAudio	pdmAudioBalance	1.3.6.14.1.2699.2.4.1.16.6.0	Integer	R	DEFVAL { 0 }	
pdmAlert	pdmAlertIndex	1.3.6.14.1.2699.2.4.1.18.1.1.1	Integer	not-accessible	1	
pdmAlert	pdmAlertGroupType	1.3.6.14.1.2699.2.4.1.18.1.2.1	String	R	See Note 1	
pdmAlert	pdmAlertGroupID	1.3.6.14.1.2699.2.4.1.18.1.3.1	String	R	See Note 1	
pdmAlert	pdmAlertCode	1.3.6.14.1.2699.2.4.1.18.1.1.4.1	String	R	DEFVAL { "" } Alert's condition has lamp	
pdmAlert	pdmAlertDescription	1.3.6.14.1.2699.2.4.1.18.1.1.5.1	String	R	Fail, Lamp hours running out, Projector Overheating, Lamp Overheating and Fan Error.	
pdmAlert	pdmAlertSeverityLevel	1.3.6.14.1.2699.2.4.1.18.1.1.6.1	Integer	R	See Note 1	
pdmAlert	pdmAlertTrainingLevel	1.3.6.14.1.2699.2.4.1.18.1.1.7.1	Integer	R	DEFVAL { 2 }	
pdmAlert	pdmAlertDateTime	1.3.6.14.1.2699.2.4.1.18.1.1.8.1	String	R	DEFVAL ( "1980-01-01T00:00:00" )	
pdmAlert	pdmAlertPowerOnCount	1.3.6.14.1.2699.2.4.1.18.1.1.9.1	String	R	DEFVAL { "" }	
pdmAlert	pdmAlertSysUpTime	1.3.6.14.1.2699.2.4.1.18.1.1.10.1	String	R	DEFVAL { "" }	
pdmAlert	pdmAlertCriticalAlertsCount	1.3.6.14.1.2699.2.4.1.18.2.0	Integer	R		
pdmAlert	pdmAlertAllAlertsCount	1.3.6.14.1.2699.2.4.1.18.3.0	Integer	R		

#### Note 1:

- a) If there is no any current alert, all of the OID in the alert table will respond with the default value.  
 pdmAlertGroupType = "  
 pdmAlertGroupID = 0  
 pdmAlertSeverity = other (1)  
 The rest Object will respond default.
- b) If there is a FAN alert the table is as shown below:  
 pdmAlertGroupType = "Fan"  
 pdmAlertGroupID = "Fan Error"  
 pdmAlertSeverity = Critical (3)  
 The rest Object will respond default.
- c) If there is a Lamp Fail alert, the table is as shown below:  
 pdmAlertGroupType = "Lamp"  
 pdmAlertGroupID= Lamp Fail  
 pdmAlertSeverity = Critical (3)  
 The rest Object will respond default.
- d) If there is Projector Overheating alert, the table is as shown below:  
 pdmAlertGroupType = "ThermalSensor"  
 pdmAlertGroupID= "Projector Overheating"  
 pdmAlertSeverity = warning (4)  
 The rest Object will respond default.

#### Note 2:

1. Other
2. Unknown
3. VGA
4. DVI-D
5. DVI-I

6. HDMI
7. Component Video BNC-5
8. Component Video BNC-3
9. DisplayPort
10. S-Video
11. RJ45
12. Wireless
13. RCA Plug Video-3
14. RCA Plug Audio
15. Mini jack 2 dot 5mm Audio
16. Mini jack 3 dot 5mm Audio
17. Coax Audio
18. Fibre Audio
19. Memory Card
20. USB Memory
21. USB Display
22. Intel® WiDi
23. Internal Memory
24. HDMI2
25. Wireless Display Dongle
26. Network

**Information in this document is subject to change without notice.**

**© 2018 Dell Inc. All rights reserved.**

Reproduction of these materials in any manner whatsoever without the written permission of Dell Inc. is strictly forbidden.

Trademarks used in this text: Dell and the DELL logo are trademarks of Dell Inc.

Other trademarks and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Dell Inc. disclaims any proprietary interest in trademarks and trade names other than its own.