

DELL(TM) OPENMANAGE(TM) SERVER UPDATE UTILITY 6.3 README
#####

This readme provides information for Dell OpenManage Server Update Utility version 6.3 for Windows DVD.

Release Date July 2010.

This file also contains updated information for your "Dell OpenManage Server Update Utility User's Guide" and any other technical documentation that is included with Server Update Utility (SUU).

See the Dell Support website located at "support.dell.com" for more information and to download the latest version of SUU.

Note: For information on Dell Update Packages (DUP), see the DUP Readme files present on the SUU DVD.

This file contains the following sections:

- * Criticality
- * Compatibility/Minimum Requirements
- * Release Highlights
- * Installation
- * User Notes
- * Known Issues

CRITICALITY
#####

3 - Optional

It is recommended that you review the update procedure to determine if it applies to your system. The update contains changes that may impact only certain configurations, or provides new features that may/may not apply to your environment.

COMPATIBILITY/MINIMUM REQUIREMENTS
#####

This section provides information about the minimum requirements for SUU 6.3.

=====
SUPPORTED OPERATING SYSTEMS
=====

Microsoft Windows Operating Systems

- * Microsoft(R) Windows Server(R) 2003 R2 Web, Standard and Enterprise Editions with SP2 (32-bit x86)
- * Microsoft Windows Server 2003 R2 Standard, Enterprise, and Datacenter x64 Editions with SP2
- * Microsoft Windows Small Business Server 2003 Standard and Premium

Editions with SP2

- * Microsoft Windows Server 2008 Core Web, Standard, and Enterprise Editions (32-bit x86) with SP2
- * Microsoft Windows Server 2008 Core Standard, Enterprise, and Datacenter Editions (x64) with SP2
- * Microsoft Windows Essential Business Server 2008 Standard and Premium Editions
- * Microsoft Windows Small Business Server 2008 Standard and Premium Editions
- * Microsoft Windows Storage Server 2008 R2 Express, Workgroup, Standard, and Enterprise Editions
- * Microsoft Windows Unified Data Storage Server 2008 Workgroup, Standard, and Enterprise Editions
- * Microsoft Windows Server 2003 Compute Cluster Edition and Microsoft Windows Server 2008 HPC Edition

Virtualization Operating Systems:

- Microsoft Hyper-V Server
- Microsoft Hyper-V R2 Server

See the 'Dell Systems Software Support Matrix' for the latest list of supported Dell PowerEdge(TM) systems and operating systems. The 'Dell Systems Software Support Matrix' is available on the Dell Support website at "support.dell.com/manuals."

SUPPORTED WEB BROWSERS

SUU 6.3 supports the following Web browsers:

- * Internet Explorer 8.0, Internet Explorer 7.0, Internet Explorer 6.0 with SP2, and Mozilla(R) Firefox(R) 3.0 for Windows 2003 Professional
- * Internet Explorer 8.0, Internet Explorer 7.0, Mozilla Firefox 3.0 for Windows Server 2008 Professional
- * Internet Explorer 6.0 with SP2
- * Internet Explorer 7.0
- * Internet Explorer 8.0

SUPPORTED SYSTEMS

SUU 6.3 supports the following PowerEdge systems running the supported Windows operating systems:

PET710, PER210, PET110, PET310, PER710, PET610, PER610, PER510, PER910, PEM910, PER810, PEM710, PER410, PEM610, PET410,

PER300, PER905, PER200, PER900, PET100, PEM605, PE850, PE830, PET300, PET105, PEM805, PEM905, PE860, PE800, PE840, PEM600, PET605, PER805,

PE1955, PE1950, PE6950, PE2970, PE2950, PE1900, PE2900,

PE2800,PE6800,PE1855,PE6850, PE1850, PE2850,PE1800,
PESC1435, PESC1425,

NX3000, NX1950, DP100/NF100, DP500/NF500, DP600/NF600, DL2000

SUU 6.3 supports the following Dell PowerVault(TM) systems running on the Windows operating system:

NX3000, NX1950, DP100/NF100, DP500/NF500, DP600/NF600, DL2000

Note: Other systems and operating systems may be supported in this release. See the 'Dell Systems Software Support Matrix' for the latest list of supported PowerEdge systems and operating systems. The 'Dell Systems Software Support Matrix' is available on the Dell Support website at "support.dell.com/manuals."

Note: Running SUU 6.3 on an unsupported system may produce unexpected results.

RELEASE HIGHLIGHTS
#####

Added support to the following systems

PET110, PER210, PER510

Note: For a detailed table of supported Dell systems and operating systems, see the 'Dell Systems Software Support Matrix' available on the Dell Support website at "support.dell.com/manuals."

INSTALLATION
#####

SUU is a stand-alone application that runs directly from a DVD. For more information on installing SUU, see the "Dell OpenManage Server Update Utility User's Guide."

Note: Only users with administrator (Microsoft Windows) or root (Linux) privileges can perform updates with SUU.

USER NOTES
#####

This section provides information to help enhance your experience with SUU in specific implementations and environments.

* If you launch SUU from a command shell and then press <Ctrl><c>, the SUU procedure, as well as any running updates, will terminate.
(137862)

* When you launch SUU, the utility inventories the targeted system.

Depending on the system configuration, this process may take several minutes to complete. (138439)

* The figures and examples in the "Dell OpenManage Server Update Utility User's Guide" are used as examples only and may not be identical to the SUU GUI. (137294, 136624)

* When you verify the SUU return codes, use the operating system-specific commands to view the exit codes. (137296)

For example:

Microsoft Windows: echo %ERRORLEVEL%

Red Hat Enterprise Linux: echo \$?

```
#####  
KNOWN ISSUES  
#####
```

This section provides information about known issues with this release of SUU.

* If your CERC ATA RAID controllers are configured with the H661 firmware, SUU cannot update the firmware to the latest version. To update the firmware, use the "-force" option to manually apply the DUP with the latest firmware version. (134775)

* When updating multiple, identical devices on the same system, SUU applies the latest update to all instances of all devices. For example, if your system is configured with three controllers configured with firmware/driver versions 1.2, 1.3, and 1.4, and the repository version is 1.4, SUU applies version 1.4 to all instances of all devices. (136620)

* When you run SUU using the "-p" option, SUU reports the current instance log location ("suu -p") instead of the SUU instance log location ("suu -u") that is performing the update. (135925)

* SUU uses DUPs to update various system components. During a Red Hat Enterprise Linux update, the DUPs create a "/var/lock/.spsetup" file using the Linux lockfile utility during the initial execution procedure. Kernel panics or sudden reboots during DUP execution (reboots where TERM signals are not sent to running processes or where running processes do not have time to catch these signals) can generate a "/var/lock/.spsetup" lock file that cannot be deleted. SUU reports the update as successful and prompts you to reboot the system. When you run SUU again on the same system, the comparison reports no change in device status. If this situation occurs and no update is in progress, remove "/var/lock/.spsetup" before running another update on the system. (137287)

* If a NIC teaming application is installed on the system, SUU updates the NIC base driver only if the driver is compatible with the teaming application. To verify driver compatibility, run DUP on the system to update the driver and read the generated messages.(138648)

* Devices that are disabled in the operating system are not inventoried or updated by SUU. To update or inventory these devices, enable the devices in the operating system and then relaunch SUU. (142111)

* Do not use the RAC virtual media to run SUU remotely on a system. This procedure breaks the virtual media connection, causing the SUU update procedure to fail. (144487)

* SUU fails if it is run from a pathname that contains special characters. For example, ".,:/\,\$, etc. It is recommended to use a directory name without any special characters for running SUU. As an example, a case where you can get directory name with special characters is:

In the SUSE Linux Enterprise Server operating system, when a USB DVD-ROM or USB disk is attached, it may by default, mount to a directory name that contains special characters. For example, /media/USB:1:2/ (42279)

* If a RAC DUP package (RAC 4/P or RAC 4/i) is running and SUU is started, the RAC package may fail. To resolve this issue, run SUU only after the RAC package has completed execution. (23184)

* In Linux, if there is not enough space in the var partition or tmp folder, SUU displays the following error message:
"Not enough space available in the /var or /tmp folder. Please ensure you have atleast 100MB."
Ensure that you have sufficient space in the var partition or tmp folder and restart SUU to start the system inventory. (66118)

* In some cases where the latest Intel NIC driver (Intel(R) PRO PCIE Gigabit Family of Adapters 9.5, base driver version 9.6.31.0) is installed as part of Dell Systems Build and Update Utility (SBUU) install, SUU may not be able to inventory the respective NIC. This may happen because SBUU would not have installed the umbrella software. In these cases, install the umbrella with the umbrella installer (available at support.dell.com or in the SERVICE directory on the Dell Systems Management Tools and Documentation DVD) to get the Intel NIC inventoried by SUU (DF130363).

* SUU may fail to launch on Xenserver 5.6 if the lockfile dependency is not met. To fix this issue, install the procmail rpm:
procmail-3.22-17.1.el5.centos.i386.rpm

* If you use a Microsoft Windows Server 2003 operating system platform, you require .Net Framework 2.0 to run Dell_PV_Utills_NASDUP.exe. If .Net Framework 2.0 is not installed, 0xc0000135 error code may be encountered.

THIRD PARTY DISCLAIMER
#####

The following disclaimer applies to the "TreeTable" control code in IT Assistant:

Copyright 1997, 1998 Sun Microsystems, Inc. All Rights Reserved.

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

- Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
- Redistribution in binary form must reproduce the above copyright notice, this list of conditions, and the following disclaimer in the documentation and/or other materials provided with the distribution.

Neither the name of Sun Microsystems, Inc. or the names of contributors may be used to endorse or promote products derived from this software without specific prior written permission.

This software is provided "AS IS," without a warranty of any kind. ALL EXPRESS OR IMPLIED CONDITIONS, REPRESENTATIONS AND WARRANTIES, INCLUDING ANY IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT, ARE HEREBY EXCLUDED. SUN AND ITS LICENSORS SHALL NOT BE LIABLE FOR ANY DAMAGES OR LIABILITIES SUFFERED BY LICENSEE AS A RESULT OF OR RELATING TO USE, MODIFICATION OR DISTRIBUTION OF THIS SOFTWARE OR ITS DERIVATIVES. IN NO EVENT WILL SUN OR ITS LICENSORS BE LIABLE FOR ANY LOST REVENUE, PROFIT OR DATA, OR FOR DIRECT, INDIRECT, SPECIAL, CONSEQUENTIAL, INCIDENTAL OR PUNITIVE DAMAGES, HOWEVER CAUSED AND REGARDLESS OF THE THEORY OF LIABILITY, ARISING OUT OF THE USE OF OR INABILITY TO USE THIS SOFTWARE, EVEN IF SUN HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

You acknowledge that this software is not designed, licensed or intended for use in the design, construction, operation or maintenance of any nuclear facility.

#####

Information in this document is subject to change without notice.
(C) 2004-2010 Dell Inc. All rights reserved.

Reproduction in any manner whatsoever without the written permission of Dell is strictly forbidden.

Trademarks used in this text: "Dell", "PowerEdge", "PowerVault", and "Dell OpenManage" are trademarks of Dell Inc.; "Microsoft", "Windows", "Windows Server", and "Internet Explorer" are either trademarks or registered trademarks of Microsoft Corporation in the United States and/or other countries.

Other trademarks and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Dell Inc. disclaims any proprietary interest in trademarks and trade names other than its own.

The utilities provided with the Dell OpenManage Server Update Utility

are provided "as is". Dell disclaims any and all warranties, express, implied or statutory, with respect to the utilities, including, but not limited to, the implied warranties of merchantability, fitness for a particular purpose, title and any warranty of non-infringement. Use the Server Update Utility at your own risk. Dell shall not be liable for any direct or indirect damages incurred in using the Server Update Utility. In no event shall Dell or its suppliers be responsible for any direct or indirect damages whatsoever (including, without limitation, damages for loss of profits, loss of use, loss of data, business interruption, or other pecuniary loss, nor for punitive, incidental, consequential, or special damages of any kind, under any part of this agreement, even if advised or aware of the possibility of such damage).

April 2010