



Statement of Volatility – Dell Vostro 3591

△ CAUTION: A CAUTION indicates either potential damage to hardware or loss of data and tells you how to avoid the problem.

The Dell Vostro 3591 contains both volatile and non-volatile (NV) components. Volatile components lose their data immediately after power is removed from the component. Non-volatile (NV) components continue to retain their data even after power is removed from the component. The following NV components are present on the Dell Vostro 3591 system board.

Table 1. List of Non-Volatile Components on System Board

Description	Reference Designator	Volatility Description	User Accessible for external data	Remedial Action (Action necessary to prevent loss of data)
Embedded Flash in embedded controller MEC1418	UE1	192 KB of embedded Flash memory for keyboard controller BIOS code, asset tag and BIOS passwords	No	N/A
Panel EEDID EEPROM	Part of panel assembly	Non Volatile memory, 512 bytes.	No	Part of panel assembly
System BIOS	ICL:UC5、UC6 CML:UC3、UC11	Non Volatile memory, 128 Mbit (16 MB), System BIOS and Video BIOS for basic boot operation, PSA (on board diags), PXE diags.	No	N/A
Video BIOS	ICL:UC5、UC6 CML:UC3、UC11	Non Volatile memory, System BIOS contains Graphics system BIOS.	No	N/A
System Memory – DDR4 memory	Two SODIMM connectors: JDIMM1、JDIMM2	<p>Volatile memory in OFF state</p> <p>Two modules must be populated. System memory size will depend on SODIMM modules and must be between 2 GB and 16 GB.</p>	Yes	Power off system
System memory SPD EEPROM	TL1、TL2	<p>Non Volatile memory 512 Bytes.</p> <p>Stores memory manufacturer data and timing information for correct operation of system memory.</p>	No	N/A

Video memory – frame buffer	ICL:UV6、UV8 CML:UV13、UV15	Volatile memory in off state. ICL:2 GB/4 GB GDDR5 for NX230 discrete graphics systems. CML:256 MB GDDR5 for R610 discrete graphics systems	No	N/A
Hard drive(s)	User replaceable - one or two.	Non Volatile magnetic media, various sizes in GB. May also be SSD (solid state flash drive).	Yes	Low level format
CD-ROM/RW/ DVD/ DVD+RW/ Diskette Drives	User replaceable	Non Volatile optical media.	Yes	Low level format/erase

△ CAUTION: All other components on the system board lose data if power is removed from the system. Primary power loss (unplugging the power cord and removing the battery) destroys all user data on the memory (DDR3, 1067 MHz). Secondary power loss (removing the on-board coin-cell battery) destroys system data on the system configuration and time-of-day information.