

# Dell EMC Repository Manager 3.2 Release Notes

Topics:

- [Importance](#)
- [New in this release](#)
- [Fixes](#)
- [Known Issues on Microsoft Windows Operating Systems](#)
- [Known Issues](#)
- [Installation Instructions](#)
- [Global Support](#)
- [Contacting Dell](#)

## Release Type and Definition

The Dell EMC Repository Manager (DRM) ensures that the Dell EMC systems are up-to-date with the latest BIOS, driver, firmware, and software.

## Version

3.2 Rev.A00

## Previous Version

3.1

## Importance

**OPTIONAL:** It is recommended that you review specifics about the update to determine if it applies to your system. The update contains changes that impact only certain configurations or provides new features that may or may not apply to your environment.

## New in this release

This release of Dell EMC Repository Manager (DRM) supports the following new features:

- Enhanced user experience for OpenManage Enterprise repository creation
- Enhanced user experience for OpenManage Integration for Microsoft System Center repository creation
- Option to replace default script in Smart Bootable ISO.
- Option to replace default script in Smart Deployment Script.
- Automatic Dell EMC System Update through Smart Deployment Script and Smart Bootable ISO.
- Improved UI experience in Compare Window.
- Enhanced usability experience in manual repository creation and manual bundle addition
- Sign verification for all artifacts that are downloaded and used in the application.
- Provides support for only HTTPS protocol.

# Hardware requirements

Table 1. Hardware requirements


| Requirement              | Details                               |
|--------------------------|---------------------------------------|
| Processor                | 1 GHz Pentium processor or equivalent |
| RAM                      | 4 GB                                  |
| Hard Disk                | 1 GB of available space               |
| Display                  | 1024 x 768 high color, 32-bit         |
| Optical Drive (Optional) | CD/DVD writer                         |

# Software requirements

Supported operating systems:

- Microsoft Windows Server 2016
- Microsoft Windows Server 2019
- Microsoft Windows 10 (64-bit)
- RedHat Enterprise Linux 6.x
- RedHat Enterprise Linux 7.x
- SUSE Linux 12
- SUSE Linux 15

# Optional requirements

- **Internet connectivity** – To access, create, and work with bundles, catalogs, and repositories.  
 **NOTE: You can use the local repositories on DRM without internet connectivity.**
- **CD/DVD or USB burning software** – To create a bootable CD/DVD or bootable USB.

# Fixes

- Deletion of multiple bundles of large size (more than 1 GB) not reflecting immediately in UI
- Allow a catalog with invalid schema to be added as source.
- Copy operation that was not working from a migrated repository to an empty repository
- Partial selection and buttons enablement
- Default path not displayed in browse window for SLES operating system

# Known Issues on Microsoft Windows Operating Systems

- Few of the options for creating shortcut links for DRM are missing while interactive installation.
- Some files and copied shortcut are not deleted after uninstall, If application is not closed before uninstall process.
- DRM should not be installed on the network share.

# Known Limitations

- On Linux Operating Systems, DRM cannot be installed on a custom folder or location other than /opt/dell.
- DRM does not support multiuser execution. You cannot run DRM simultaneously on the same system with two separate remote/local sessions.
- The size of the repository that is created will not be displayed in the output if the catalog used for creation does not contain the size information for DUPs.

- DRM current version cannot discover the Microsoft Exchange Web Service URL from the email ID. User has to manually update the data for email configuration. Consult Users Guide for process for finding the Microsoft Exchange Web URL.
- Repository refresh shows dates 1–30 for all months. For February if 30 is selected, the refresh happens on the last day of the month.
- It is recommended not to launch the application from multiple user contexts. Occasionally there is certain unexpected GUI behavior because of insufficient permissions to the temp folder(C:\windows\temp or /tmp).
- Creating a repository from inventory file and with available catalog using CLI is not supported when catalog and inventory are placed in different network location.
- Comparison shows some downgrades and upgrades for DUPs incorrectly. Check the properties of DUPs in the right pane of the UI for devices supported before revising the component.
- Refresh inventory feature is not supported for any repository created using a local `inventory.xml` file.

## Known Issues

### Issue 1

You cannot downgrade to a lower version of DRM using the current DRM installer.

**Resolution-** To install an earlier version of DRM, first uninstall the newer version manually through Add or Remove Programs in Windows **Control Panel** and then run the installer of the desired version.

### Issue 2

Mapped network path for a user is not accessible in DRM as a location with Microsoft Windows. The mapped network path is only available to download the log in zip format.

**Resolution-** Provide the network path along with authentication.

### Issue 3

Access issue for user home on Linux operating system.

**Resolution-** Provide read and execution access to all users for home folder and read/write access to **drmuser** in the required folder where user wants to create repository.

### Issue 4

Random program files of DRM are deleted when Microsoft Windows goes for a hard system reset.

**Resolution-** Repair or reinstall the application to update the missing files.

### Issue 5

Some of the repositories from DRM 2.x may not be migrated to DRM 3.x, if the DRM 2.x application is up and running during DRM 3.x installation.

**Resolution-** Remove the database files, close the DRM 2.0 application, and then install DRM 3.0

### Issue 6

If the application GUI is kept open during uninstallation, a message is displayed which indicates a system restart is required but system does not reboot even after consent for the same.

**Resolution-** Uninstall DRM only after closing the application GUI.

### Issue 7

Share folders of an SMB 2 server cannot be enumerated in browse for location windows.

**Resolution-** Provide the share name along with IP or system name and the folders can be browsed.

### Issue 8

Store Clean-up job fails for an SMBv2 share if the store contains at least one file apart from folders.

**Resolution-**Delete the individual files manually and then run the store cleanup job for the rest of the content.

### Issue 9

During upgrade, the installer displays the default path even if the previous installation was on a custom path.

**Resolution-** You can upgrade DRM in default path or change it to custom path again. If you provide a different location, manually delete the old files in previous path.

### Issue 10

After repair when you chose to restart the system, the system does not restart automatically.

**Resolution-** Restart the system manually.

#### **Issue 11**

If you are using `home` path as your target location for exporting a file from DRM in Linux operating system, the browse window becomes unresponsive.

**Resolution-** Remove the trailing slash, and then export the file.

If you have already used `/home/` for exporting a file and the browse window becomes unresponsive.

**Resolution-**Delete the directory: `/var/dell/drm/config`, and then continue using DRM.


## Installation Instructions

- For installing DRM on Linux operating system, run the following command: `DRMInstaller.bin -i silent`
- For more information about installation instructions on Microsoft Windows operating system, see *Dell EMC Repository Manager Quick Start Guide*.

## Global Support

For information on technical support, contact your service provider.

## Contacting Dell

 **NOTE:** If you do not have an active Internet connection, you can find contact information on your purchase invoice, packing slip, bill, or Dell product catalog.

Dell provides several online and telephone-based support and service options. Availability varies by country and product, and some services may not be available in your area. To contact Dell for sales, technical support, or customer service issues:

1. Go to **Dell.com/support**.
2. Select your support category.
3. Verify your country or region in the **Choose a Country/Region** drop-down list at the bottom of the page.
4. Select the appropriate service or support link based on your need.

## Notes, cautions, and warnings

 **NOTE:** A NOTE indicates important information that helps you make better use of your product.

 **CAUTION:** A CAUTION indicates either potential damage to hardware or loss of data and tells you how to avoid the problem.

 **WARNING:** A WARNING indicates a potential for property damage, personal injury, or death.

© 2018 - 2019 Dell Inc. or its subsidiaries. All rights reserved. Dell, EMC, and other trademarks are trademarks of Dell Inc. or its subsidiaries. Other trademarks may be trademarks of their respective owners.